EXCLUSIVE: YAMAHA MINIDISC STUDIO

THE PROJECT RECORDING & SOUND MAGAZINE

OCTOBER 1996

STARRING:

STARRING: TONY BROWN AL KOOPEX RAV KENINEDY MIKE CLUTE BILLY RAY CYRUS DINO ELEFANTE

AES NEW PRODUCT PREVIEW

EVERYTHING TOU NEED TO KNOW ABOUT SURROUND SEX PISTOLS IN THE RAW

Tony Brown, MCA Nashville

USA 53.95 • (an. 54.95 • U.K. £2.95 • issue #10 1 0> 7 1896 47438 1

IN

REVIEW

(•)•

C

• • •

The Alesis MidiVerb[®] 4 is the best solution for full-featured, completely programmable reverb and multieffects. Its algorithms for reverb, chorus, flange, delay, rotary speaker simulation and special effects are beyond compare. It offers up to three great-sounding effects at once, and lets you change programs and parameters in real time using MIDI controllers like foot pedals or keyboards. Its incredible sonic fidelity comes from 18-bit digital converters, a 24-bit internal DSP and a professional 48kHz sampling rate.

UTH. STURE IMPUT OUTPUT

PROD

EDIT A H

But the key to MidiVerb 4's power is that every program offers dozens of detailed parameters that let you create the perfect effect for every environment. And since it's also easy to use and surprisingly affordable, MidiVerb 4 is the obvious choice for musicians and engineers looking to expand their effects processing horizons.

Start creating your space with the MidiVerb 4. It's at your Authorized Alesis Dealer now.

For more information on the MidiVerb 4, visit your Authorized Alesis Dealer or call 800-5-ALESIS. @Alesis and MidiVerb 4 are registered trademarks of Alesis Corporation. Alesis Corporation 3630 Holdrege Avenue Los Angeles CA 90016 800-5-ALESIS alecorp@alesis1.usa.com

ALCOL



CIRCLE 02 ON FREE INFO CARD

ARE YOU TAPING THE HISS?

If so you need the ultimate recording combination.

It's always been important to make sure that the front end of the recording chain is as clean and pure as possible. Today's digital technology reveals any weak link in the chain. This means you must chose a microphone that is quiet (*no self-noise*) and a monitoring headphone that will reveal the accuracy of your signal.

beyerdynamic))))

The beyerdynamic **MC 834** pure condenser with its natural frequency response, exceptional signal to noise ratio (*non existent self-noise*) and high SPL capability is the answer to digital technology.

Easily outperforming the competition, it ensures your recordings contain the original sound without any added noise or hiss. That's why it has become a regular feature in studios around the world just like some of our other products.

For example, the legendary beyerdynamic **DT 770** pro headphone, seen wherever musicians are at work. Their exceptionally wide and flat frequency response allow you to hear everything in the mix (*including the hiss*).

So next time you visit your Pro Audio dealer ask for a demonstration of beyerdynamic microphones and professional studio headphones.

Unless, of course you want to carry on taping the hiss....

CIRCLE 17 ON FREE INFO CARD

For more information or a brochure call 1.800.293.4463 56 Central Ave. Farmingdale, NY 11735






PROJECT RECORDING SOUND TECHNIQUES & VOLUME 7, ISSUE 10 OCTOBER 1996



...62









ON THE COVER: Tony Brown in Reba McEntire's Starstruck Studios. Photo by Beth Gwinn.

FEATURES

EQ GOES TO NASHVILLE

Music City USA's population is growing at a rapid rate thanks to many music industry veterans moving from the coasts to Music Row. This special section takes a look at the city and offers tips and techniques from some of its prominent citizens. Stories include:

NASHVILLE: A GUIDE FOR EQ READERS By AI Kooper	62
The legendary musician describes Nashville's music scene — warts and all.	
• TONY BROWN: NASHVILLE STATE OF MIND By C. Reeder	72
Find out what happens when the Demo Queen takes on the King of the Nashville Music Scer	ne.
• TIPS FROM MUSIC ROW: AMBIENT DRUM MIKING TECHNIQUES By Ray Kennedy	80
How to get the right sounds from your drum kit.	
• TIPS FROM MUSIC ROW: NOT SO "HARD"-DISK RECORDING By Michael D. Clute	84
Some good reasons to get into the world of hard-disk recording.	
• TIPS FROM MUSIC ROW: EASTWARD HO By Dino Elefante	90

How to easily make the transition from Los Angeles to Nashville.

EQ LIVE

TRAVIS TRITT & MARTY STUART: DOUBLE TROUBLE ON TOUR By Jon P. Armstrong	8
CLUB PROFILE: ACE OF CLUBS By Steve La Cerra	4
AES PREVIEW: NEW GEAR FOR YOUR NEXT GIG	8
ROAD TEST: ALLEN & HEATH GL3000 MIXING CONSOLE By Wade McGregor	0

TECHNIQUES / WORKSHOPS

SEX PISTOLS: FAT, FORTY, AND BACK By Kevin Hilton	
A SURROUND SOUND PRIMER By Bobby Owsinski	


COLUMNS/DEPARTMENTS

MI INSIDER: PHIX YOUR PHASE By Craig Anderton	
MAINTENANCE: ORGANIC DIGITAL SOLUTIONS By Eddie	Ciletti
FAST FORWARD: SCAMS WHAT AM By Martin Polon	
ACROSS THE BOARD: MISCELLANEOUS NOTES By Roger	Nichols
EDITORIAL	IN REVIEW: E-MU DARWIN W/ADAT-XT
LETTERS TO EQ	IN REVIEW: YAMAHA MD4 MD RECORDER
EQ&A	IN REVIEW: DSP+FX DIGITAL FX PROCESSOR
PRODUCT VIEWS: AES PREVIEW	

EQ&A	IN REVIEW: DSPOFX DIGITAL FX PROCESSOR 124
PRODUCT VIEWS: AES PREVIEW	
STUDIOWARE: AES PREVIEW	IN REVIEW: IC TOOLS IDM PLUG-IN
ROOM WITH A VU: SCREAMING WOO	IN REVIEW: TL AUDIO PA 2 DI/PREAMP
MICROPHILE: LAWSON L-47	IN REVIEW: HUGHES & KETTNER TUBEMAN PLUS 137
EQ TRACKS: BLESSID UNION OF SOULS "I BELIEVE"	IN REVIEW: GAS COOKER TUBE DI
FIRST LOOK: AES WORKSHOPS	AD INDEX

EQ (ISSN 1050-7868) is published monthly plus Buyer's Guide in October by Miller Freeman PSN Inc., 460 Park Ave. South, 9th fl., New York, NY 10016-7315, Periodicals postage paid at New York, NY and additional mailing offices. POSTMASTER: Send address changes to EQ, P.O. Box 0532, Baldwin, NY 11510-0532, SUBSCRIPTIONS: U.S. 1 yr. \$24,95, 2 yrs. \$39,95, 3 yrs. \$59,95; CANADA add \$10.00 per year for surface; other coun-tries add \$15.00 per with the surface of instanta address of the result of the U.S.A.





World Radio History

The VMP² 2 gives you three tubes for every one found in our competitors' preamps. While others create the illusion of being a tube preamp, in reality most only provide a single tube in the front end, leaving a cold transistor back end to do all the work. The VMP-2's all-tube preamp gives you true tube texture because we



use tubes EXCLUSIVELY throughout the signal path. And high-voltage power rails utilize 100% of each tube's energy for extended warmth—something you can't experience with a preamp powered by a wall wart. Many consider the VMP-2 a two-forone product because of the built-in all-tube EQ, which allows the artist to deliver crisp highs or robust lows to any track or mix. Odds are, you'll love the VMP-2: the vacuumtube power tool for the professional and the professional-at-heart.

Peavey Electronics, 711 A Street, Meridian, MS 39301 (601) 483-5365. Fax (601) 486-1278 http://www.peavey.com. AOL Keyword, Peavey CompuServe Go Peavey ◆©1996

CIRCLE 62 ON FREE INFO CARD



A Miller Freeman PSN Publication Vol. 7, No. 10 October 1996

PAUL G. GALLO

KATHLEEN MACKAY Associate Publisher

TIM WETMORE

HECTOR LA TORRE Executive Director

MARTIN PORTER Executive Editor

ANTHONY SAVONA Managing Editor

CRAIG ANDERTON Technology Editar

STEVE LA CERRA Senior Editor

LIANA JONAS Associate Editor

ROBERT GRANGER

MARSHALL MOSELEY Art Director

DAVID MILES HUBER, EDDIE CILETTI, DAVID FRANGIONI, BOB LUDWIG, WADE MCGREGOR, ROGER NICHOLS, MARTIN POLON Contributing Editors

MP&A EDITORIAL Editorial/Design Consultants

MATT CHARLES Sales Manager

ANDREA BERRIE, CHRISTINE CALI, KAREN GODGART, PETE SEIDEL, TARA ESPOSITO Advertising Soles

AMY HERRION Marketing Assistant

RIVA DANZIG

MELISSA HALKA

JOY ZACCARIA Reprint Coordinator

FRED VEGA Production Manager

Editorial Offices 939 Port Washington Blvd. Port Washington, NY 11050 Tel: (516) 944-5940, Fax: (51c) 767 1745

Administrative/Sales Offices 460 Park Avenue South, 9th Floor New York, NY 10016-7315

Tel. (212) 378-0400, Fax: (212) 378-2160



EQ 155N 1050 7868 is published monthly plus Buyer's Cruide in Septenties by Willer freeman PSNInc. 46D Park Ave. S. 9th B., New York, NY 100° 6-7315 Pariodical's postoge paid at New York, NY end additional

moning offices POSTMASTER Send oddres: change to EQ, PO hav CS32, Boldwin NY 1510-0532. SUBSCRIPTICHN: U.S. 1 yr 524 95, 2 yrs, 539 95, 3 yrs, 559 95, CANADA add S10 per yr for surface, other aountries add S15 per yr for surface, Al addr330 per yr for Armail Bock issues 55 All product information a subject b change publicher osumes no responsibilith for such changes. All isted model humbers and product nomes are manufactures ringisteral **Con Miller Freeman** tradomarks Printed in the U.S.A.

Greener Pastures

BY BEVERLY KEEL

OLD ROCKERS NEVER die, they just move to Nashville.

Scores of middle-aged pop and rock musicians have left the big cities for the more relaxed pace of Nashville, and it looks like many of their friends are still on their way.

Michael McDonald, Steve Winwood, Steve Cropper, Al Kooper, Tracy Nelson, Kim Carnes, Rita Coolidge, Bernie Leadon, Henry Gross, Janis Ian, John Prine, Felix Cavaliere, Donna Summer, Delbert McClinton, and Reese Wynans now call Nashville home, as does Tony Joe White, The Crickets' Jerry Allison, Leon Russell, Dick Wagner (guitarist for Lou Reed and Alice Cooper), Barry Tashian, Duane Eddy, producer Bob Gaudio, and Lynyrd Skynyrd's Ed King.

When new Nashvillian Peter Frampton wanted to record his track for a Hank Marvin and the Shadows' tribute album, he went to Adrian Belew's basement, where Belew also produced two songs for the platinum Jars of Clay album.

"I remember about seven years ago, it seemed to be a place where people in rock who were over the hill could come and get something happening," says Bonnie Raitt's guitarist George Marinelli, who moved to Nashville from L.A. in '91. "That wasn't true, but it was the rap. It's a more creative spot and it's not age specific. You don't necessarily have to be a 22-year-old, great-looking person to be involved in music here, whether it's country music or anything else."

Most musicians didn't so much move to Nashville as they did flee Los Angeles and New York. They moved their families South because it was safer, smaller, and cleaner. "I can be anywhere, but I choose to be in Nashville," says Peter Frampton, who invites Nashville writers over to collaborate in the music room he's built at the end of his home. "I just find it more conducive to writing here, I guess because it's so much more laid back. It might take a little longer to do stuff here, but that doesn't bother me."

Nashville doesn't have the restaurants or hotels offered by both coasts, but it doesn't have the distractions either. "I think the metaphor it uses is like when you are driving in from the airport, as opposed to L.A., where there's a traffic jam at 4 AM," says producer Don Was, who frequently records in Nashville. "You just breeze in and breathe the fresh air.

"That's metaphorical for the record-making process there," Was says. "There's less cerebral cholesterol clogging up the arteries. People go in, they're matter of fact. They're good and they're fast. In Nashville, there's an understanding that songs reign supreme. Without a good song, it's impossible to make a good record."

Songwriting is where you see the biggest integration of Nashville's traditional country music community and the transplants. Top writers like Gary N cholson and Gary Burr, both of whom write pop and country, frequently write with the newcomers. But except for the cowriting sessions and a few studio sessions, the two communities remain separate, forcing rockers to leave town to make money.

"We are hoping for something to qualify it as Music City USA," says Felix Cavaliere. "Right now, it's Country Music USA. The only thing I can do down here is write, which is why I moved here. The pop people down here, we don't work, except maybe a few studio players who have adapted their style to country."

While most wouldn't turn down a country cut, they're not at the risk of going country any time soon. E Streeter Gary Tallent has started his own label and produced acts that are definitely not country. "The funniest question I get is, 'Oh, you are producing country now?' " Tallent says. "Just because you are working and producing out of Nashville, it's assumed you are doing country music. I have to laugh."

Nashvillians appeared thrilled to welcome the new neighbors because it gives credibility and hipness to a city that has been considered the hillbilly cousin of the other music centers. Frampton has already graced the cover of *NashvilleLife*, and Kooper, Cropper, and others play annually at the Nashville Music Awards.

"These people know their music down here," Cavaliere says. "The regular folk, there's an acceptance if you've ever done anything in the music business. In L.A., it's what have you done lately?"

Beverly Keel is an assistant professor in the recording industry department at Middle Tennessee State University and a freelance writer whose work has appeared in such publications as Guitar World, New Country, Country Weekly, TV Time, and Music Row.

<text>



P.O. Box 4189 Santa Barbara CA 93140-4189 voice 805-962-6926 fax 805-962-3830 The real passion behind a hit song lies in the performance. You want all the emotion and the expression of the performance to burst onto the track and shine its way through the mix. Whether it's a truly great take or just a happy accident, you want that moment captured in all of its glory. When that inspired moment occurs, you need to have the right mic...the **RØDE**⁻⁻ **NT2**. The RØDE⁻⁻ has all the special stuff:

- Dual Gradient Transducers with Large Diaphragm and Gold Plated Membrane to warmly receive and translate the full body of the performance
- Internal **Gold Plated Connections**, insuring warmth and precise signal transitions for years to come
- Transformer-less low-noise circuitry
- Switchable Filter enabling you to change the low frequency response
- Switchable Pad enabling you to handle high gain
- Switchable Pattern providing cardioid or omni patterns
- **High SPL** (sound pressure level) allowing it to work cleanly for screaming vocals or instruments, or even soit spoken word
- It even comes with a Shock Mount, Flight Case, and Pop Filter.

The RØDE[®] large Diaphragm Condenser Mic is hand-assembled in Australia. In the tradition of the great microphones, it's designed to furnish outstanding, vintage-flavored vocal or instrumentation miking—at a truly untraditional, breakthrough price ... \$749.00.

Step on the road to recording success by seeking out your nearest EVENT Electronics dealer. Listen to the NT2 and hear the difference a great mic can make.

RØDE is a trademark of Freedman Electronic

CIRCLE 31 ON FREE INFO CARD



QUIET COMPANY

I've never written before, and this isn't really of a technical nature, but I thought you'd maybe find it interesting.

Some time back I had some expensive equipment walk down the hall and out the door from my little music studio, uninsured (then); that bit the ol' butt kind of hard. In addition to a surveillance camera and window alarms, I have also employed a full-time studio employeek who works only for an occasional change of outfit and is on duty 24

hours a day, 360 days per year. The lady in the picture is "populating" my studio, cheaply. Yeah, she's a mannequin — they're realistic and can be purchased rather cheaply, as they're rapidly disappearing from stores. They are quiet, good looking, and lightweight (about 35 lbs.).

And they do catch people off-guard in something other than a department store setting. Richard H. Millette Sunstroke Studio Englewood, OH

DUST IN THE WIND

Re: "Maintaining Your Cool," EQ July '96. This is a wonderful "starter" article about air conditioning, but (you guys knew a "but" was coming) it leaves you with the impression that cooling the studio is just a matter of money and it has no problems at all. Since we live in a profession ruled by Mr. Murphy, newcomers of the game should be aware of the following: (1) all A/C units will emit noise. Granted that a vented system is the least noise producer of all, but you still will get noise in your recordings unless you include a noise trap in your vent route. Now there is an idea for an article, right guys? (2) Dust may be a problem depending on where you live. Some basic filters just don't cut it, and we have to be especially aware in this new digital age of dust getting in the delicate components of our expensive machinery.

Let me digress for a second with a quick dust story. Our studio is located in Caracas, Venezuela, and the area is dusty and humid (I'll get to humidity in the next point). It wasn't unusual for us to dust every darn day before starting a session with the standard filters that most A/C systems provide. Then it came: the real fine filters designed to catch anything but bacteria, and it was great until we realized that it was affecting the flow of our system. We ended up using a combination of filters in different stages. (One great tip is to get those blue-type plastic filters that look like gigantic kitchen scrubbers and spray them with WD-40 or 3-in-1 oil. The amount of dust that they can gather is amazing, but be sure to clean them regularly if you have a dust problem.)

And (3) humidity is a nasty problem, especially because by the time you see it



QUIET COMPANY: Sunstroke Studio's glamourous security guard.

it may be too late and the sucker is already messing you up. This is particularly true if you have set up your studio in an old building or you live in a very humid area. For most places, a normal A/C will take care of any humidity present, but sometimes it will not be enough, and an additional dehumidifying unit must be installed to control the problem. They are not that expensive, particularly if you compare the money you can save in repairs.

Be sure that a hygrometer, which activates the unit when the humidity level exceeds the predetermined level, is connected to your A/C system so you don't have to worry anymore. (By the way, if you are having a tough day with a client and you want to end a session within the hour, crank up the hygrometer to 30 percent and you will see the musicians, especially singers, dry up in a hurry and call it quits. OK, so it's a nasty trick.)

I agree that this is a very sketchy summary of the things that can be done with A/C, but maybe other readers can give some more input.

> Miguel Gonzalez Le Garage Studio Caracas, Venezuela

SOFTLY SPEAKING

The entire staff of Midisoft would like to thank you for featuring our product, Midisoft Studio 4.0, in your July issue. We are all thrilled to have our products reviewed in such an esteemed music industry magazine. We are especially gratified because Midisoft's product line has traditionally been aimed at consumer users rather than at professional users like your readers.


With that in mind, I would like to take the opportunity to correct a couple

of oversights in the review. The reviewer states, "there are no provisions for precise control placement (of digital audio) within the sequence." Studio 4.0 does feature "to the click" resolution of digital audio events. Digital audio events are triggered at the level at a precision of 1/96th of the current 1/4-note value. Studio's internal timer is capable of time accuracy within 2 ms. Since we buffer all digital audio playback, the digital audio event begins playing at the exact click it is set to. Feedback from our users has been that this level

of precision is more than acceptable.

The reviewer also states in the "Weaknesses" section that "[Studio] cannot program time signature and tempo changes mid-song." Midisoft Studio 4.0 is capable of doing both. Tempo changes can be inserted in any location in the file via our MIDI List View. Time signature changes can be added via our Music menu, which features other notation editing features such as Key Signatures.

One last issue I would like to comment on is the review's view of Midisoft customer service and technical support. While I agree that it is always best to give support at the time a customer calls, this is not always possible when an overflow situation occurs. On reviewing our records, we found that Deborah Gerber called at 3:50 in the afternoon of March 13. Her information was taken down by our message service, as all technical support representatives were on the phone, and promised a call back within 24 hours. Deborah was called back at 8:50 the following morning by our technical support manager. A message was left on Deborah's answering machine explaining that we understood her situation and that the manager would personally be



Dedicated Stereo Tape Input No need to waste a precious stereo channel for your master recorder. Assignable to UR buss or monitor EQ on Every Input Hi (12kHz) and Low (60Hz) ±16cB on each. 2 AUX Sends Take your signals Pre or Post

THE LAPTOP YOU CAN GET FOR UNDER \$350"

No more excuses for not having a compact, full-featured utility mixer. A mixer you can plug in anywhere. Need more inputs? How about a submixer? What about audio for video or multimedia? Get a TASCAM M08. It's the perfect mixer for these applications and more Part of

the new breed of next-generation mixers from the leader in recording, TASCAM's new M08 will surprise you. You'll scratch your head trying to figure out how we can give you so much mixer for so little cash. No tricks. Just value.

Look at all those features! It's the mixer that goes anywhere to do almost anything. Use it every day — or when you're in a crunch. So whatever you do, don't scramble for more inputs, or schlep that big mixer, pull out your M08 instead. It's the world's best and hardest working compact utility mixer. And it comes with TASCAM quality and durability at no extra cost. Everybody needs one. Best part is, at \$349 anyone

can have one. They're at your dealer. Get yours today.




CIRCLE 77 ON FREE INFO CARD

©1996 TEAC America, Inc. 7733 Telegraph Road, Montebello, CA 90640 (213) 726-0303 TEAC Canada LTD., 340 Brunel Road, Mississauga, Ontario L4Z 2C2 Canada (905) 890-8008 *Actual MSRP is \$349.00. Actual prices may vary by dealer.



INFORMATION+SPECS VIA FAX 800 • 827 • 2268 DOCUMENT #6280





BBE 362NR is the answer

Combining our patented Sonic Maximizer and single-ended noise reduction in one unit allows you to cut hiss, AND, restore high-frequency detail and bass "punch".



Audition one today! 5381 Production Drive • Huntington Beach, CA 92649 FAX 714-896-0736 • 714-897-5766

CIRCLE 96 ON FREE INFO CARD



LETTERS TO EQ

available to answer any of her questions. We never heard back from Deborah.

Our goal has always been to make accessible usable software that allows anybody to create great music with their PC. We hope that professional user will keep us in mind while shopping form the right tool for the job. Our continuously evolving product line will continue to offer incredible ease of use, with an ever-growing list of professional quality features at affordable prices. My personal commitment to pur customers is that we make, and will continue to make, products that give them more usable value per dollar than any other music software product on the market.

> Joseph J. Marusak General Business Mgr., Music Products Midisoft Corporation

DIRECT INPUT

We at Demeter Amplification would like to thank you for your insightful "Three on Three" article in your August issue.

In regards to the unity/boost switch, the boost mode increases output by 15 dB, not 10 dB as stated. Also, each mode (unity/boost) has two distinct sounds. The unity/gain mode is taken from the cathode of the first stage and is flat from 10 Hz to 40 kHz with very low distortion. The boost mode signal comes from this second-stage plate output, creating a warmer, rounder tube sound. The review never stated which gain mode the direct box was used in. This would have a noticeable effect on the reviewers impression of the sound.

The Demeter VTDB-2B Tube Direct has been updated to meet IEC standards. The Tube Direct now features a grounded AC power cable. The original two-prong AC cable was installed to eliminate any ground-loop problems.

Publications such as *EQ* have been important in the further development of our company. We are proud of our achievements and continue to strive for excellence in all of our products.

> James Demeter President Demeter Amplification


CORRECTION

In the September issue's Studioware section, Kurzweil's address was listed incorrectly. The proper address is 13336 Alondra Blvd., Cerritos. CA 90703. Tel: 310-926-3200. We apologize for causing any confusion.

CIRCLE 67 ON FREE INFO CARD



Want your mixes to deliver the punch and clarity of the industry heavyweights? Now you can... thanks to the FinalizerTM, TC's new concept in dynamics signal processing. Inserted between the stereo output of your mixer and your master recording media, the Finalizer dramatically increases the volume without sacrificing fidelity or stereo imaging.



The Finalizer creates that extra energy boost that you otherwise only can get from a professional mastering house. With its powerful multiband processing it will make your mixes sound **punchier**, *louder*, **crisper**, **warmer**, spectrally balanced, more "in your face"... it's your choice!

The Finalizer's 'Wizard' function easily finds the optimum setting for your mix: Simply enter the type of music you are mixing and to what extent you want it processed... and you are done! The more experienced user may "tweak" the signal path extensively, with over 75 parameters to choose from. You will also find additional signal analysis tools including a Phase Correlation Meter, Peak-Hold Meter, Level Flow Meters, and a Digital Format Analyzer. We've even thrown in a Calibration Tone Generator. All of the Finalizer's functions are easily monitored on the graphic LCD and on the seven precision LED meters.

Now even your demos will sound like a CD. You can simultaneously:

Convert It:	20 Bit precision A/D and D/A Convertors		
Shape It:	Five band 24 Bit Parametric Equalizer		
Enhance It:	Choose between De-Essing, Stereo		
	Adjust or the Digital Radiance		
	Generator™		
Normalize It:	Real-time Gain Maximizer		
Expand It:	Variable Slope Multiband Expander		
Squeeze It:	Multi-band Compressor		
Trim It:	Variable Ceiling Limiter prevents overloads		
Fade It:	Manual or Auto Fade Tool		
Dither It:	To maintain the highest resolutions on		
	the digital AES/EBU and S/PDIF outputs		

Naturally, the Finalizer fully lives up to TC's twenty year reputation for sound quality, specifications and construction.

Try it - you'll be knocked out by what the Finalizer will do for your mix. Call I-800-798-4546 for the location of a TC dealer near you.





CIRCLE 79 ON FREE INFO CARD

TC Electronic Inc., 705-A Lakefield Road, Westlake Village, CA 91361 Phone: (805) 373-1829 Fax: (805) 379-2648 Email: tcus@tcelectronic.com WWW: http://www.tcelectronic.com



PATCH THINGS UP

Q I was wondering if there was anything available for the Mac that would aid in the construction, layout, and routing of a patchbay? For example, something like a template for Filemaker or similar program.

Mike Daane via Internet

A To the best of our knowledge, there is no software program currently available on either the Mac or PC platforms that will aid in the construction, layout, and routing of patchbays. We use a CAD program to do patchbay layout and design; however, this is for the drawing function only. The "smarts" behind the layout is done by a real, live thinking person.

The problem with doing any type of automated signal routing for patchbays PATCH BAYS. is that there is such a huge variety of patchbay designs and configurations, not to mention all the types of equipment that gets connected through these bays. Any type of autoconfigurator would Sig have to be very smart and have an ever 4 <u>r</u> growing library of products and bays from which to de-S sign. Such an Ш auto-configurator CABL would also be very expensive to develop.

At David Carroll Electronics (self-serving plug), we offer two solutions to this problem in the industry: First, we have a unique product called Project PatchTM, which is a plug-and-play TT patchbay system made up of bays and prebuilt cable sets (a lower cost, 1/4-inch TRS version of Project Patch will be introduced at the upcoming AES). As a part of Project Patch we offer a configuration service where we will provide complete configurations of a patchbay system to the customer's spec. We will also be introducing Studio Kits[™] in September '96. These are complete, preconfigured studio wiring systems that are based on Project Patch bays and cables. The customer only needs to specify what equipment he has and a match is made to a Studio Kit package. Further details are available at DC Electronics (510-528-8054 or fax: 510-526-1982. | Editor's Note: If any readers know of such a product, or if some inventive entrepreneur has just such a software program, let us know.—HGL

> Lee Pomerantz Director of Sales & Marketing Products Division David Carroll Electronics

A company called VDP, Inc., based in Las Cruces, NM, makes a software package called VidCad that allows sound contractors to develop draw-

MIXERS

ings and design layouts of sound installations. It's possible that this software may also support layouts and construction of patchbay systems. (They may not have a Mac-based version.) VDP, Inc. can be reached at: 749 Carver Rd., Suite 3, Las Cruces, NM 88005. Tel: 505-524-8959/Fax: 505-524-9669.

> Jim Hoffman Regional Manager Switchcraft

OSCILLATING RHYTHMS

Q I have enjoyed Eddie Ciletti's articles in EQ for some while. He mentioned in his August '96 column the necessity for recording a 1 kHz tone on DATs. I have heard this several times now and, as I am in the process of making the transition into composing music-for-picture, I am trying to find out all the technical aspects that will affect my marketability.

M, makes a soft-/idCad that allows o develop draw-AMPLIFIER AMPLIFIER Mackie 8-Bus, one TASCAM DA-88 with SY-88 [sync card], assorted sound modules, etc., but I haven't been able to find a tone generator in anything I currently have. Any basic books you would

2

Z

ADA

46

Any basic books you would recommend that would educate me on topics like this? I'm not likely to get down into the diodes and such, but I feel too ignorant of some basic stuff.

Gary Glover via Internet

M CTORS There are many reasons to record tone(s) at the head of any tape. (0 For an analog 0 tape, multiple-frem quency tones ensure consistent playback from machine to machine. With 1 kHz as reference, the high and low frequencies can be adjusted to all be at the same level (frequency extremes vary with head condition). The high-frequency tones are also used to align az-

whirlwind


Best Snakes

LING RD . ROCHESTER

If You're Not Recording Your Tunes at CD Quality, Your Career Could Be at Steak



The MD Data recording medium gives you 37 minutes of flawless digital audio on 4 tracks.



m

You won't find another studio-quality recorder at this price. As opposed to cassette, MD4 offers noise-free, loss-less track bouncing.

Well Done.

Introducing the Yamaha MD4 Digital Multitrack Recorder. Never before could you record, edit and mix with CD quality for only **\$1199.** Available now!

©1996 Yamaha Corporation of America, Pro Audio Products, P.O. Box 6600, Buena Park, CA 90622. Yamaha Canada Music Ltd., 135 Milter Avenue, Scarborough, Ontaro MIS 3Ri (416) 298-1311.









Call for more information.

IMPROVE AUDIO/VIDEO QUALITY



- Improves Conductivity
- Reduces Noise & Distortion
- Deoxidizes, Cleans & Protects
- Reduces Intermittents
- Reduces RFI, Wear & Abrasion

Even the finest equipment cannot guarantee noise-free operation. One "dirty" connection anywhere in the signal path can cause unwanted noise, distortion and signal loss. Considering the hundreds (if not thousands) of connections in electronic equipment today, it's only a matter of time before they begin to fail,



Available in Environmentally-Safe Spray, Wipes, Pen, Precision Dispensers & Bulk Containers

Some film deposits are effectively removed with "wash-type" cleaners such as contact/tuner cleaners, degreasers, alcohols and other solvents. Oxides and sulfides, however, become an integral part of the contact surface and <u>cannot</u> be removed by ordinary contact cleaners.

DeoxIT dissolves oxides and sulfides that form on metal surfaces, removing these sources of resistance. This restores the contact's integrity and leaves a thin (organic) layer that coats and protects the metal.

DeoxIT's advanced formula contains deoxidizers, preservatives, conductivity enhancers, arcing and RFI inhibitors and anti-tarnishing compounds that significantly increase the performance and reliability of electrical components and equipment.

DeoxIT provides long-lasting protection, reducing the expense of repeated cleaning with expensive and aggressive ozone-depleting solvents.

DeoxIT outperforms & outlasts all other contact cleaners.



Non-flammable, Safe on Plastics & Environmentally-safe.

1			
CAIG PRODUCTS USED BY THOSE WHO DEMAND THE BEST!			
Ampex Boeing Diebold Inc. Dolby Lab.	Federal Express Fluke Mfg. Co. General Electric Hewlett Packard	Honeywell McIntosh Labs Motorola Rane	Switchcraft Tektronix Texas Inst. Xerox Corp.
Image: Construction of the state o		o, CA 92127-1904 : 619 / 451-1799 : 619 451-2799 aig123@aol.com	

CIRCLE 19 ON FREE INFO CARD 14 OCTOBER EQ



imuth — a mechanical condition that positions the playback head gaps (the electromechanical "lenses" that bring high frequencies into focus) to be in the same place as the record head (perpendicular, hopefully, to tape travel).

For a digital machine, there are no frequency response adjustments, but there is still a need for both a reference tone and a safety pad at the head of the tape. You wouldn't want someone repeatedly playing your master mix while setting levels or, worst case, on a machine in poor mechanical condition.

l always print five minutes of tone to "burn" through the beginning of the tape, which is more likely to have dropouts either out-of-the-box or after frequent use/abuse. My tone of choice is 40 Hz because it is not painful to listen to during setup. One kHz remains the standard because it is in the middle of the frequency spectrum. You could also use tone to identify left and right channels, polarity (phase), and, again, to provide space to safely test a tape in an unknown machine. Five minutes constitutes a surprisingly short piece of tape. Several 30-second mixes could be swallowed by a hungry machine. Shortform mixes should be repeated several times on a tape for both safety and ease of use.

TASCAM and Fostex make oscillators as "accessories" for utilitarian purposes. MCM electronics (800-543-4330) also sells oscillators. Prices range from about \$75 to several hundred. Those in the battery-operated, under-\$100 range are more than acceptable.

Two excellent books you can look into are written by EQ contributing editors. Check out the latest versions of Craig Anderton's Home Recording for Musicians and David Miles Huber's Modern Recording Techniques.

Eddie Ciletti Contributing Editor Manhattan Sound Technicians NYC, NY

SURVIVAL OF THE FITTEST

We need help. We have a Roland A90EX and JV1080, a Mac Quadra 840 AV with Finale 3.5.1, connected with an Opcode Studio 4, and a new Emu Darwin hard-disk recorder. We want to do multitrack recording and get them in sync. Everything works perfectly, except we can not get the E-mu Darwin to start recording when triggered by either the Mac or the Roland A90 (which is the master controller triggering Finale to begin to play).

We have called E-mu and it seems Darwin will only start on command using MIDI Machine Control. Since neither the Roland A90, JV1080, or the Mac sends out MIDI Machine Control, how do we sync our multitrack recordings?

> George D. Anderson via Internet

The Darwin hard-disk recorder re-A sponds to locate commands and transport commands via MMC (MIDI Machine Control) and outputs MIDI timecode. Most computer-based MIDI sequencers, including Vision, Performer, E-Magic, Cubase, and Cakewalk, output MMC and will synchronize to MTC. By connecting Darwin's MIDI In and Out ports to your computer's MIDI interface, vou can locate, arm tracks, and even punch in and out Darwin from your sequencer. Darwin must be defined as an MMC device in the sequencer's setup, and different sequencers have different methods of doing this. Be sure that the Darwin is set to the same MMC ID# as what you've set up in the sequencer; this is adjusted in the MIDI set up page, under the system menu in Darwin.

You may want to note that while Finale is a powerful notation program, it is pretty limited as a sequencer. If sequencing is a major part of your production process, you might want to consider using a more suitable program, like the ones mentioned above, and transfer them to Finale for notation purposes.

> Matt Ward Director of Marketing Audio Products E-mu Systems

ASK US

Send your queries to: EQ Editorial Offices, 939 Port Washington Blvd., Port Washington, NY 11050 Fax: 516-767-1745



ane Corporation is shipping brand new technology at brand new prices. For over 15 years Rane has been producing the world's finest signal processing. Yet many of you have been asking for Rane quality that's even



more affordable. We give you Mojo. The new Mojo SERIES is American made, inexpensive, and built to outperform "bargain" brands in every respect. Why wait?... Get your Mojo working now!

YOU FOR WORKING

MOJOZ Mojo Fillers

A fresh twist utilizing our Constant Q technology. The MQ302 is a stereo 1/3rd octave equalizer which features a single set of faders that controls

both left and right channels! A ground breaking idea which fills a void in true stereo applications. Get hip to the MQ302.



MC 22 Mojo Squeeze In a word..... innovative! Rane's own Acousticlear technology will

help improve your system's overall performance. No compressor/ limiter can compete with the MC 22's superior design and sonic quali-

ties. Destined to be the number one choice of our music industry. The MC 22, at a Rane dealer mear you.





Mil 4 Mojo Cans Amp You won't believe the performance you'll get from the MH 4, designed by the company that pioneered headphone amplifier technology. You will agree that this is the finest 4-channel cans amp out there. Play it loud! Hear the MH 4 now.

CIRCLE 52 ON FREE INFO CARD

RANE CORPORATION Phone: 206-355-6000 • Fax: 206-347-7757 • Home Pager http://www.rane.com

MORE THAN MUSI Ground Radio History'S AN ATTITUDE!



Divider

You'll love this easy-to-operate, extremely accurate stereo 2-way, 24 dB per octave crossover. It incorporates an additional mono sub output. The MX 22 out-performs other brands that cost much more! The MX 22 will work for you.

ZANI

MX 23 Mojo Divider

You'll find no other brand of stereo 3-way crossover that can outperform this gem. Like the MX 22, the MX 23 offers a mone sub output, and uses Rane's popular 24dB per octave technology to assure that your system remains in phase! Cross over to the MX 23.



MORE BUSES, MORE PREAMPS, INTRODUCING THE NEW 16-CH.,

Four submix buses, swept mid EQ, AFL/PFL, new materials, new technologies and the soul

he original CR-1604 defined the modern compact mixer. Now we've "raised the standard" by adding over 20 new features like true 4-bus design with assign switches on every

EW TRIM control

for line inputs.

at 12kHz

SWEEPABLE

to BkHz range.

±15dB range.

and acoustic

at BOHz.

FO

1

.ca

AN .

(on the channel strip)

& -10dB "virtual pad"

pre/post. Aux 3 &4

with 60dB total mic gain

6 AUX SENOS per ch. Aux 1 & 2 switchable

(post-fader) become 5 & 6 via Shift switch.

MIDRANGE. Wide, musical pe king EQ with 100Hz

LO EQ. +15dB shelving

a must for live sound

(microphone) recording. Sharp, 18dB/octave @ 75Hz high-pass filter

lets you add Low shelving EQ to wocals

thumps. stage rumble, wina noise, P-pops, etc.

constant loudness to

without boosting

undesirable mic

PAN control with

maintain stereo

perspective.

MUTE switch.

DVERLOAD LED.

-20dB SIGNAL

Subs 1-2, 3-4 3

60mm FADER with

Main L/R.

material.

PRESENT & SOLD LED.

SGLD. In-place AFL or PFL (pre fade listen).

MEEN BUS ASSIGN for


true log taper, special lip seal & long-life wiper

MUTE 'S

LOW CUT FILTER is

HED. ±15dB shelving

channel, 16 highheadroom/low noise mic preamps, separate stereo Control Room/ Phones bus, effects return to monitors for just ^{\$}100 more* than the original CR-1604! No matter where you mix or what you mix, you'll find a lot to like on the new CRI604-VLZ. Call for a free 40-page brochure and applications quide today.



MORE THAN JUST SWEPT MIDRANGE. Most mixers

(except very expensive ones) have narrow EQ bandwidths - OK for drastic corrections but not very useful for gentle tonal changes. The CR1604-VLZ has wide, midrange EQ bandwidth that is far more musical-sounding and can be used more generously than narrow mid EQ.

5-WAY PHYSICAL CONFIGURATION via our

famous rotating input/ output "pod." Out of

the box the CR1604-VLZ comes in with jacks to back. Use on a tabletop () or rack-mount it with the free rack rails included 2. In minutes, with just a screwdriver, you can rotate the pod for an ultra-compact 8-rack space configuration (). Optional RotoPod-VLZ bracket places the input/output jacks on same plane as the controls (rackmount () or tabletop ()).

Stereo AUX RETURNS-1 & 2 with 20dB gain above Unity for boosting weak effects

NEW AUX SEND 18 2 MASTERS. NEW AUX SEND 18 2 SOLO switches with LEDS.

ARR ARRA & NEW Aux Return 3 ASSIGN SWITCHES to Main Mix, Subs 1 & 2

or Subs 3 & 4. NEW Aux Return 4 ASSIGN to Control Rm/Phones

NEW PHANTOM POWER LED. NEW CONTROL -ROOM/PHONES level control.

NEW TAPE INPUT LEVEL control and TAPE TO MAIN MIX switch.

NEW CONTROL ROOM/PHONES SOURCE MATRIX. Just like our 8.Bus

monitoring system, this creative feature lets you route any combination of Tape, Subs 1 & 2, Subs 3 & 4 or Main Mix to Control Room/Phones bus. Lets you create custom headphone mixes (press MAIN

MIX and let performers in the studio hear what you're hearing in the control room), run simultaneous broadcast or live 2track recording mixes, monitor 2-track tape deck output (if you're doing commercial production, press TAPE and share it

in the studio), route a cue/click track to phones or create a second stereo main output with its own level control.

*THE BIG ASTERISK: Suggested U.S. retail for the CR1604-VLZ is \$1199. This is actually LESS than the combined price of the old CR-1604 and XLR10 mic preamp expander (needed to get a full 16 mic preamps). Priced higher in Canada.



power supply.

switch.

PHANTOM POWER

BNC lamp socket. **NEW EFFECTS TO** MONITORS controls fold Aux Return 1 &

2 back into Aux Sends 1 & 2 50 that on-stage performers can hear outboard effects.

Stereo AUX RETURNS 3 & 4 with 20dB gain above Unity for boosting weak effects

Global AUX RETURN SOLO with LED.

LED METERS with -30 to +28 range.

NEW LEVEL SET LED. In conjunction with individual channel Solo lets you quickly and accurately set input levels to Unity Gain, minimizing noise and maximizing headroom.


Global SOLD level control.

RUDE SOLO light. NEW Global AFL/ PFL SOLD switch.

HEAOPHONE output NEW BUS

ASSIGN to Left and/or Right Main Mix.

NEW 60mm SUB-MASTER & MAIN L/R faders with accurate, 8.Bus log taper.



with VO talent


4 sub buses • AFL/PFL • swept mid eq • bow cut filters • 16 mic prea

MORE EQ, MORE FEATURES, MORE EVERYTHING. 4-BUS CR1604-VLZ MIC/LINE MIXER. JUST ^{\$}1199.

of our 8=Bus...we packed the new CR1604-VLZ with a 5-year "wish list" of the most-requested mixer features.



CIRCLE 51 ON FREE INFO CARD World Radio History



ABSOLUTE SPIRIT

pirit By Soundcraft has introduced the biamplified Absolute 4P monitor system. Both transducers are driven by separate power amplifiers, with 100 watts RMS delivered to the woofer and 50 watts to the tweeter. The amplifiers feature full thermal protection



and an intelligent driver system to provide the maximum possible undistorted acoustic output. A deep 30 mm edge-wound voice-coil with Kapton former offers optimum power handling. The Absolute 4P also utilizes a large-area port to maintain the bass extension even when driven hard. The soft-dome HF tweeter is driven by a 25 mm ferrofluid-cooled coil. For more information, contact Spirit By Soundcraft, Inc., 11820 Kemper Boad, Auburn, CA 95603. Tel: 916-888-0488. Circle EQ free lit. #101.



GET ON TRAC

Soundtracs recently introduced a new range of Topaz mixing consoles. The new rack-mountable Topaz 12-4 features 3-band EQ, two aux sends, four mono mic/line inputs, and an additional two stereo FX returns to make a total of 16 inputs available for mixing. All the inputs have solo and mute and can be routed to a stereo bus with output fader control, or to the LR mix bus. The Topaz 12-4 has a suggested retail price of \$449. The Topaz 14-4 has all the features of the Topaz 12-4 plus ten premium phantom-powered mic preamps with 3band EQ, two aux sends, and a solo. mute, group assign, and fader. The two stereo inputs and two stereo effects returns make the Topaz 14-4 equally at home in live sound, recording, and fixed installations. The Topaz 14-4 has a suggested retail price of \$599. The Topaz 24-4 pro-

vides all the features of the 14-4, with the addition of ten more ultra-low distortion mic preamps. The 24-4 also features four main mix busses, solo and mute functions, switchable pre/post on aux 1, XLR balanced mix outputs, and a total of 28 inputs to mix, including the two stereo effects returns. The Topaz 24-4 has a suggested retail price of \$1099. For more details, contact Korg USA, 316 South Service Road, Melville, NY 11747. Tel: 516-333-9100. Circle EQ free lit. #102.

PEAK YOUR INTEREST

ummit Audio's MPC-100A mic preamp/ comp-limiter is a single-channel unit that features a tube preamplifier section followed by a separate tube compressor/lim-



iter section. The MPC-100A offers microphone, Hi-Z (for musical instruments), or line inputs preamplified by the first vacuum stage. A switchable front-panel VU meter accurately reads input, output, and gain reduction. The MCP-100A also offers an input pad, which is a stepped attenuator and clip indicator with support for both XLR and 1/4-inch jacks. Suggested retail price is \$2400. For more details, contact Summit Audio Inc., P.O. Box 1678, Los Gatos, CA 95031. Tel: 408-464-2448. Circle EQ free lit. #103.




TALE O' THE TAPE

ncased in a unique shell that incorporates a three-piece design molded from ultra-rigid materials, BASF Magnetics' Reference Maxima TPII analog reference cassettes have been designed to meet the needs of professional recording studios and production houses. A special control element and newly developed azimuth pins help to minimize high-frequency losses due to azimuth errors. The tape consists of a ferro-cobalt formulation that provides for better recording level headroom with minimum distortion. The super smooth back coating reduces modulation noise. BASF Reference Maxima tapes come in lengths designed for studio use including C-10, C-20, C-60, and C-100. In addition, the hubs are specially marked to make in-cassette editing or cueing easier. For more information, contact BASF Magnetics, 9 Oak Park Drive, Bedford, MA 01730-1471. Tel: 617-271-4000. Circle EQ free lit. #104.

STRAIGHT FROM THE SOURCE

B ruel & Kjaer has introduced the HMA 4000 dual-channel, 130-volt power supply for 4003/4004 and 4012 microphones. The HMA 4000 features both electronically balanced and single-ended line-level outputs. The 130 volts delivered to the microphones' built-in amplifiers gives them enhanced SPL handling capabilities and increases preamplifier headroom by 10 dB. Input signal in either channel can be independently amplified or attenuated by +20 dB, 0 dB, or -12 dB with channel separation of up to 90 dB. The HMA 4000's operational amplifiers achieve very low self noise and




have a dynamic range of up to 140 dB with a frequency range of 10 Hz–200 kHz (±0.5 dB). For added versatility, the HMA 4000's impedance converter can drive up to 300 meters of line-level cable, so you can us the amplifier as a line driver in fixed installations or for live applications. For more details, contact Bruel & Kjaer/TGI North America Inc., 300 Gage Ave., #1 Kitchner, ON N2M 2C8. Tel: 519-745-1158. Circle EQ free lit. #105.



MEDIA'S MESSAGE

he HV-3C mic preamp from Millennia Media features an integrated Apogee 20-bit A/D converter that employs the Apogee UV-22 process. Optionally, the Millenia HV-3C reads and writes 20 bits directly to two combined tracks of ADAT or DA-88

and accepts any external 20-bit digital audio for stand-alone UV-22 processing. The HV-3C locks to master clocks, including AES, S/PDIF, and word clock. The HV-3C also employs Millenia's HV-3 high voltage microphone preamps and buffered line inputs. The mic preamps and A/D converters may be used independently, while the analog or digital insert point can also be realized between preamp and converter. The HV-3C mic preamp has a suggested retail price of \$2995. For further information, contact Millennia Media, Inc., 9624-C Kiefer Blvd., Sacramento, CA 95827. Tel: 916-363-1096. Circle EQ free lit. #106.



GRACE UNDER PRESSURE

he Model 201 2channel microphone preamplifier from Grace Design is based on its flagship Model 801. Each channel is equipped with phantom power, phase



reversal, and a 20-dB attenuator. The gain controls are 24-position gold contact switches accompanied by a 10-dB output attenuator knob. Like the Model 801, the Model 201 is designed to deliver clarity, subtlety, and detail to tape or hard disk with no coloration. For more details, contact Grace Design, P.O. Box 204, Boulder, CO 80306-0204. Tel: 303-443-7454. Contact EQ free lit. #107.

REV ON

amaha's REV500 offers more power using the first application of the Yamaha 3rd generation DSP chip. This same DSP chip is also used in the high-end ProR3 reverberation unit and in the mixing functions of the Yamaha 02R digital console. The REV500 features 20-bit A/D-D/A converters for high dynamic range and extremely low noise, built-in sound source for snare



drum, cross stick, and pulse, enabling reverb parameters to be set without an external source. The MSRP is approximately \$500. For more details, contact Yamaha Corporation of America, Professional Audio Products, 6600 Orangethorpe Avenue, Buena Park, CA 90622-660. Tel: 714-522-9011. E-mail: Info@yamaha.com; Web: www.yamaha.com. Circle EQ free lit. #108.

Sound better than you ever imagined...







Bigger, deeper, fuller bnss. Extended, natural highs and greater presence. Get more sound from your system without increasing penks. Individual tracks or an entire mix will 'jump' from the speakers. **105:** The Logic Assist makes this gate the most accurate and excisest to use in the world - no false triggering, clicking or chattering. The proprietary Aphex VCA 1001 ensures total audio transparency. **106:** Invisible This automatic compressor is so transparent that some people think it isn't working! Effortlessly maintain perfect levels without having to constantly adjust ratio, attack, release and threshold.

107: The award winning, #1 selling Tubessence mic preamp is the perfect marriage of solid state and vacuum tube circuitry. Upgrade the sound of all your mics with uncolored detail, presence and warmth.

These products are covaried by one or more of the following U.S. Patent numbers: 4150253, 5359665, 5334947, 5450034, 5424488, 5483600.

IN SYNC

HB Communication's new PORTADAT, the PDR1000TC/Master Sync, provides accurate jam sync'ing with timecode film cameras, ensuring that the drift will not be more than one frame in ten hours. The PDR1000TC/Master Sync also gives the user the ability to pull up at 29.97 fps drop to 30 fps drop via a single switch, and it is fully compatible with Aaton cameras via standard LEMO sockets. LEDs indicate the operational status of the 30 fps drop. Suggested retail price is \$7495. For more information, contact HHB Communications Inc., 43 Deerfield Road, Portland, ME 04101-1805. Tel: 207-773-2424. Circle EQ free lit. #109.



THE BIG SQUEEZE

phex Systems' Model 661 tube compressor/limiter, is a single-channel compressor/limiter that provides three compression curves (hard knee, soft knee, and no knee). The Model 661 also features Aphex's exclusive, patented Tubessence tube circuitry that utilizes a 12AT7 to provide a "tube sound." The 661 also features the patented High Frequency Expander (HFX).



the selectable Spectral Bass Refractor (SPR), and selectable link modes that include stereo link, master/slave link, and unlink. Nominal operating level is switchable, -10 dB or +4 dB, with a bargraph output level meter on the front panel. For more details, contact Aphex Systems, 11068 Randall St., Sun Valley, CA 91352. Tel: 818-767-2929. Circle EQ free lit. #110.

...at a price you won't believe



In the second se

Improving the way the world sounds*"

11068 Raildall Streef, Sun Valley, CA 91352 U.S.A. 818-767-2929, Fax: 818-767-2641


Foreign patents issued or pending. Aphex, Aurol Exciter, Big Battom, Logic Assist and Tubesance are trademarks of Aphex Systems Ltd. CIRCLE 04 ON FREE INFO CARD World Radio History

Is there really a tube in there?

When Tubessence was first introduced with the Model 107, some people had trouble believing that it was a real tube gain stage. Skeptics say. 'It's a tube simulator', or 'It's a starvedplate amplifier', or 'The tube's not in the audio path'.

The "Reflected Plate Amplifier" (US Patent #5450034) is a true vacuum tube circuit which has the desired characteristics without the heat, weight, fragility, sonic variability, short life and high frequency roll-off of conventional tube designs.

1011: The Wave Driphindent Compression simultaneously controls arrange and peak levels for the hottest tracks possible without the arritacts of other compressors. Finally, an "motificanteesor that sound's better.



FROM THE REFERENCE SECTION

tilizing a newly developed 6.5-inch injection-molded low-frequency transducer and a 3/4-inch fluid-cooled material dome tweeter, Tannoy's SBM studio reference loudspeaker has been designed specifically for the project studio maven. The new system features a front-loaded slot port delivering linear extended low frequency down to 45 Hz without the bloating often found in other designs. For further information, contact Tannoy/TGI North America Inc., 300 Gage Ave., #1, Kitchner, ON Canada N2M 2C8. Tel: 519-745-1158. Circle EQ free lit. #111.





RACK YOUR BRAIN

onstructed of a high-density particle board with a fused, melamine surface, RAXXESS Metalsmiths' Elite Series racks are available in two finishes — black fleck and mahogany. All edges are trimmed with solid hardwood for a rich, attractive finish. Shipped disassembled, Elite Series racks can be put together in just a few minutes with a simple screwdriver. RAXXESS's Elite Series racks are available in 4-, 8-, 12-, 16-, 20-, and 24-space models with straight fronts and in 16-, 20-, and 24-space rack models with slanted fronts. For further information, contact RAXXESS Metalsmiths, 261 Buffalo Avenue, Patterson, NJ 07503. Tel: 201-525-5105. Circle EQ free lit. #112.

BACK TO THE FUTURE

he MD421 II cardioid dynamic microphone from Sennheiser incorporates all of the classic characteristics of the original 421 while offering several improvements. The MD421 II combines advanced materials and modern manufacturing techniques, making it a more rugged microphone that is less sensitive to dust and humidity. The mic's five-position bass rolloff switch makes it ideal for most applications ranging from on-air broadcasting to vocal recording and instrument miking. The MD421 II utilizes a pressure-gradient dynamic transducer with a cardioid pick-up pattern and offers a frequency response of 30 Hz–17 kHz as well as a 175 dB SPL rating. For more details, contact Sennheiser, P.O. Box 987, Old Lyme, CT 06371. Tel: 203-434-9190. Circle EQ free lit. #113.





REAL BOSS, MAN

esigned to be the ultimate floor-type multiple effects unit, Roland's BOSS GT-5 incorporates Roland's COSM (Composite Object Sound Modeling) technology into its architecture for creating a variety of computer-generated amplifier "models" as well as a slew of cutting-edge guitar effects. Roland's Harmonic Restructure Modeling (HRM) provides many new synth-like sounds with guitar-based dynamics, while 28 other effects — including chorus, tap tempo delay, reverb, as well as harmonist and a "humanizer" feature — and an acoustic guitar simulator make it a practical unit. The fully MIDI-compatible GT-5 is housed in a rugged metal casing and features a rotary encoder for quick editing, a built-in expression pedal, a built-in tuner, and 150 presets and 100 user patches. For further information, contact Roland Corporation U.S., 7200 Dominion Circle, Los Angeles, CA 90040-3696. Tel: 213-685-5141. Circle EQ free lit. #114.



RADAR VIEW™ Highlights

Fully self-contained, no external computer

Zoom-in, Zoom-out and locate to project names

Random access, non-destructive, playlist editing

Superior sonics with the highest quality converters

Optional 48 track capability

OTARI.

http://www.otari.com

Otari Corporation USA

Phone: (415) 341-5900 Fax: (415) 341-7200 L.A. Sales: (818) 972-3687 S.E. Sales: (615) 255-6080

Otari Singapore Pte., Ltd. Phone: (65) 284-7211 Fax: (65) 284-4727

Otari, Inc.

Japan Phone: (81) 4-2481-8626 Fax: (81) 4-2481-8633

Otari Oeutschland GmbH

Germany Phone: (49)2159-50861/62-63 Fax: (49)2159-1778

 ≈ 1996 Otari Corporation. All rights reserved RADAR <code>VIEW</code> is artrademark and the Otari logo is a registered trademark of the Otari Corporation.

RADAR's Point of View

Replacing your analog 24 track can be a tough decision. All these formats, multiple units, synchronization and computers with mice. We at Otari feel that we have a far more simple solution. The RADAR with RADAR VIEWTM.

The RADAR acts just like your multitrack. Punch in and punch out, no scrolling through menus. Just hit play or record on its familiar feeling, dedicated remote. You won't even know you are using a hard disk recorder, unless of course, you want to edit. Even then the RADAR is a pleasure to use. And the RADAR VIEW screen gives you all the information you need to know about your session, in large, easy to read graphics.


We invite you to contact your local RADAR dealer or call us, at Otari, for a free demonstration video. We're certain you'll see things our way.

CIRCLE 59 ON FREE INFO CARD World Radio History




MAKING WAVES

aves Ltd. has announced the addition of the PS22-StereoMaker to their family of Waves processing plug-ins for the Digidesign TDM/SD II system. PS22-StereoMaker creates a wide stereo image from mono sources and also enhances the



spread of stereo sources. It can be used on single tracks of a mix, such as lead instruments or backing vocals, or for stereo enhancement of full mixes or old recordings. The PS22-StereoMaker plug-in is now available at a suggested retail price of \$1169. It's also available at a special price of \$919 to registered owners of Waves S1 plug-in until November 30th, 1996. For further information, contact Waves, 6716 Central Ave., Ste. 8, Knoxville, TN 37912. Tel: 423-689-5395. Circle EQ free lit. #115.



TOOLS TIME

pogee Electronics Corporation has released a new PCI-compatible version of its popular MasterTools TDM plug-in for Digidesign's Pro Tools. The new version runs under PCI versions of Pro Tools on PCI-based machines as well as NuBus configurations. MasterTools brings an array of mastering tools to the TDM environment, including Apogee's award-winning UV-22 mastering process for capturing maximum detail in 16-bit signals. In addition, DC offset removal, channel muting and reversal options are also available. The MasterTools 3D metering system indicates peak and average level, "overs," and DC offsets, with a unique history feature that shows peak levels and phase over time. A fullfeatured time-limited copy of the latest version of MasterTools can be downloaded from the Apogee Web Site (www.apogeedigital.com). Retail price is \$795. For more details, contact Apogee Electronics Corporation, 3145 Donald Douglas Loop South, Santa Monica, CA 90405. Tel: 310-915-1000. Circle EQ free lit. #116.

PUT IT ON THE CARD

ntex Electronics has introduced StudioCard, the first PCI-based digital audio adapter with four tracks of studio-quality, 16-bit sound, and real-time digital mixing capability. The Antex StudioCard is a 32-bit memorymapped board that delivers less than 0.003 percent total harmonic distortion and a 92 dB dynamic range. The StudioCard boasts high-quality components, including: a programmable 32-bit 40 MHz DSP and pro-quality connectors such as four independent balanced 1/Os (+4 dBu or -10 dBv) and AES/EBU or S/PDIF digital I/O. StudioCard also offers a standard MIDI port. Multiple adapter capability, unique to StudioCard's design, allows the user to install multiple StudioCards in a single computer for up to 16-track recording. StudioCard is plug-and-play



compatible and includes drivers for Windows NT. For more information, contact Antex Electronics Corporation, 16100 S. Figueroa St., Gardena, CA 90248. Tel: 310-532-3092. Circle EQ free lit. #117.



WHAT A VIEW

kai Digital's SuperView SVGA interface and V2.0 upgrade for the DR8 and DR16 operating systems provides a comprehensive display and enhanced operation of both of hard-disk recorders. By installing a SuperView SVGA board, the user can connect a standard SVGA monitor along with a computer keyboard directly to the DR8/DR16 to provide an intuitive user interface, however, no computer is required. The SuperView display provides a detailed waveform with zoom in/out capabilities and the keyboard also allows you to name your tracks, takes, and clips. All transport functions, as well as edit functions such as cut, copy, paste, and undo, can be controlled remotely from the keyboard. The V2.0 upgrade provides support for the SuperView interface plus other enhancements to increase the functionality of the DR8 and DR16. The SuperView upgrade board is available with an MSRP of \$699, and the DR8/DR16 V2.0 System Upgrade is available at an MSRP of \$39.95. For more information, contact Akai Digital/IMC, 1316 E. Lancaster, Ft. Worth, TX 76102. Tel: 817-336-5114. Circle EQ free lit. #118. Removable one-gig disks, unlimited space, fast as a hard drive.

als a jamini

For the nearest dealer, call: 888-2-IOMEGA, ext. j24 Or see us at: www.iomega.com



Laying down some silky-smooth tunes? Hey, the Jaz[™] drive can handle it. Just connect it to your Mac, PC, or keyboard and its onegig cartridges give you room for all your music stuff: demos, mixes, jam sessions. It's smokin' fast. And baby, the price tag won't leave you singing the blues.




The Unlimited Personal Hard Drive. Encless storace apart. Load mit clit projects in amb Goc any hilles of po.



1GB disks for as low as \$99.95. Compact one-gigabyte cartridges. Great for graphics, sound, and video. Portable files. Fast, easy backup.



CIRCLE 42 ON FREE INFO CARD







The 168RC is the first truly affordable, fully digital, 8 bus recording console. Use it with your ADAT or other digital recorder equipped with the ADAT optical interface to create the best sounding recordings you've ever made.

168RC Digital Recording Console The heart of a new, component-based Digital Recording System from Soundlink

The 168RC is the first

digital console to feature two ADAT optical interfaces (yielding 16 channels of digital input) and eight analog inputs as standard equipment. It makes the creative control and sound quality of an all digital, fully automated recording system an affordable reality.

Powered by Korg's proprietary MSP processor, our SoundLink DRS 168RC offers instantaneous control, processing and routing of all 24 inputs, 16 channels of mixing and 8 bus outputs.

With its combination of analog, ADAT optical and S/PDIF I/Os, the 168RC easily functions as the hear of a fully digital recording system while interfacing with any of your existing analog gear.

The 168RC is equipped with three-band EQs



SoundLink DRS brings the reality of all digital, fully automated, component based recording to everyone working on the next great recording. For more information about the 168RC Recording Console or any of the SoundLink DRS components, just call (516) 333-8737.

featuring semi-parametric high and low bands, fully parametric mid bands and 30 memories for EQ setups.

The 168RC also boasts two internal effects processors that run some of the finest algorithms available. Choose from 32 effects types and 50 preset programs.


The 168RC even provides automation functionality that lets you save and recall console settings or record and playback dynamic parameter changes.

Affordable, fully integrated digital recording is finally here. So check out SoundLink DRS and the 168RC today. You cau't beat this system.



Altordable, fully integrated digital recording Down to a System.

SoundLink DRS 1212 I/O Multi-Channel Audio Interface



The SoundLink DRS 1212 VO, along with Deck II software, brings the price of full-function, multi-channel computer based recording to a point that just about anyone can afford. And since the 1212 VO conforms to the new PCI format, your investment will last longer than just a few months!

With the power of advanced

personal computers, full-function multi-channel recording and editing is possible without the addition of costly, specialized hardware. The only true limitation has been in the area of multi-channel I/O. With the introduction of the SoundLink DRS 1212 I/O Multi-Channel Audic Interface, that limitation no longer exists.

The 1212 I/O features 12 inputs and 12 cutputs configured as two analog I/Os, an S/PDIF I/O and an eight channel ADAT optical I/O. All the I/Os can be used simultaneously. For even more control and flexibility: the 1212 I/O connects to Korg's 168RC Recording Console, or to the Korg 880A/D and 880D/A interfaces.

The new 1212 I/O even offers a Word Clock input and output, plus an ADAT time code input, for system synchronization. Between the 1212 I/O with Deck II



software, the 168RC Recording Console, an ADAT and a Trinity Music Workstation DRS, the combinations and configurations can meet the needs of just about any music production application.

All of the devices will interface with your existing analog equipment and form the basis for a completely digital system that will give you sound and creative control that simply isn't possible in the analog world.

Attordable, tully integrated digital recording **DOWN to a System.**

CIRCLE 44 ON FREE INFO CARD

C1996 Korg USA • 316 South Service Road, Melville, NY 11747 • ADAT is a registered trademark of Alesis Corporation. KORG

SoundLinkdr

STIUETS BETA 58A

VOCAL

SHURE

BETA 87

Just what is it that makes Beta microphones the world's most respected for live performance? Ask a professional performer and you'll hear about Beta's remarkable response to vocals and instruments. While an engineer will talk about



their tight, uniform supercardioid pickup patterns which allow exceptional gain-before-feedback. And how Beta's technical precision turns every live performance into a studio-quality sound experience.

Is It Art Or Engineering

be Premium Performance Shure Beta Microbone Family

If you're miking an entire stage, you'll want the full Shure Beta Line. It includes the

improved Beta 57A and 58A with smoother



SHURE BETA 56 response and lower handling noise. The premier Beta 87 brings accuracy and detail to vocals. And to drive it all home, complete your stage with the exciting new Beta 52 for your kick drum and the unique Beta 56 for drums and other instruments.

Is it art or engineering? With Shure Beta, it's one and the same.

Call 1-800-25-SHURE for the Shure Beta dealer nearest you.

SHURE

THE SOUND OF MOFESSIONALS... WORLDWIDE CIRCLE 95 ON FREE INFO CARD World Radio History



SHURE BETA 52

Woo and Initia

Billy Ray Cyrus leaves a *Trail of Tears* at this project studio

STUDIO NAME: Screaming Woo Music LOCATION: Kingston Springs, TN KEY PEOPLE: Terry Shelton (engineer, owner); Mike Sagraves (assistant engineer on Billy Ray Cyrus project); Melinda Shelton (client assistant)

PROJECTS RECORDED: Billy Ray Cyrus *Trail* of *Tears*; currently recording Don Von Tress (a.k.a. the "Achy Breaky Heart" man) debut solo album; vocal segments on Billy Ray Cyrus's *Storm in the Heartland* album; numerous custom projects **CONSOLE:** Mackie 32-8 with Mackie Ultramix automation

RECORDERS: TASCAM DA-88 [3], TSR 8, and DA-30 [2]; Sony TC K615S

MICROPHONES: Audio-Technica 4050 and 4033; Sennheiser 421 [5]; Shure SM57 [6] and 58 [2]

MONITORS: Yamaha NS10

AMPLIFIERS: Crown DC 300; Sony D590 COMPUTERS AND SOFTWARE: Compaq PC running Twelve Tone Cakewalk Pro Audio for PC; Mackie Ultramix on an Opcode Systems Music Quest MIDI card

OUTBOARD GEAR: ADL tube compressors; Aphex 661 compressor; dbx 160xt [2]; ART MDC; Rocktron Intellifex; Roland DEP 5 [2]; Eventide H3000; Lexicon LXP 15 [2]; Aphex 107 mic pre; Alesis Quadraverbs

MIDI GEAR: Roland XP 50 keyboard; Alesis DM 5; Roland GI 10; JLCooper MSB REV2 STUDIO NOTES: Owner Terry Shelton states: The setup in my studio is basically audio on one side and MIDI on the other. I've got all the equipment I use to record onto tape on one side of the room, while the MIDI equipment is on the other side. I have it set up this way simply because it's convenient. It's easier than stacking all the gear together; I can roll my chair to where I need to go.

The studio is actually located in my basement, which was supposed to be a bedroom. I put up hardwood walls that are soundproofed in the control room.



For Billy Ray's disc, I recorded the live parts in the living room next to the studio — that's where I've got 1/4-inch thick furniture pads for sound-deadening purposes. They're actually moving blankets that you'd use for, well, moving. They make great wall pads. I went to a tent and camping shop and had grommets installed in them, making them portable. I can hang them up and take them down as I need to.

In the middle of cutting the *Trail of Tears*, I had to rearrange the studio becontinued on page 160



Lawson L-47 Gold Tube

A new mic that may

look familiar

MIC NAME: Lawson L-47 Gold Tube PRICE: \$1695 TYPE OF MIC: Tube condenser POLAR PATTERN: Cardioid ACOUSTIC OPERATING PRINCIPLE: Pressure gradient transducer TUBE: 6072 FREQUENCY RESPONSE: 20 Hz to 20,000 Hz SENSITIVITY AT 1 KHZ: 17.7 millivolts @ 1 Pascal (94 dB SPL) RATED IMPEDANCE: 150 ohms PLATE CURRENT: 1 mA (nominal) HEATER CURRENT: 175 milliamps EQUIVALENT NOISE LEVEL: 20 dB SPL

MAXIMUM INPUT SPL: 127 dB SPL (1 kHz @ 3% THD)

POWER REQUIREMENTS: Regulated 6.3 volts DC and 130 volts DC via outboard power supply

DIMENSIONS: 9-3/4 inches (length) x 2-3/8 inches (diameter)

WEIGHT: Two pounds

MIC NOTES: The one-inch capsule used in the Lawson L-47 is a design based upon the M7 capsule used in those "famous German-made U 47 and M 49" microphones. But the L-47 capsule employs a three-micron diaphragm instead of the original seven-micron diaphragm; this departure was made to improve the resolution of transients and extend the high-frequency response of the mic.

Gene Lawson designed the L-47 to be a modern-day marriage between the M7 capsule and vintage vacuum tube circuitry, enabling the L-47 to simultaneously achieve classic tone and low noise. Lawson uses a low-loss tube socket with heavily gold-plated contacts and a high "grip" factor to reduce resistance and increase contact pressure.

A multipattern version — L-47MP has a continuously variable pickup pattern and can achieve omnidirectional, cardioid, and figure-eight patterns as well as all patterns intermediate to those standard ones. Construction of the L-47 body is brass with a 24-karat gold plating. **CONTACT:** Lawson, Inc., 2741 Larmon Drive, Nashville, TN 37204. Tel: 615-269-5542. Circle EQ free lit. #119.



HAVE YOU HEARD THE NEWS ABOUT CAKEWALK PRO AUDIO?

"The results and underlying technology are astounding"

-Recording

"The unchallenged reign of the Mac in the pro audio world may be ending."

-Electronic Musician

"Awesome! Cakewalk Pro Audio takes top honors for its excellent all-around feature set and easy learning curve."

--- New Media

"Cakewalk (Pro Audio)'s groove facilities are some of its most impressive features"

-Future Music

"Cakewalk Pro Audio...un produit fabuleux pour les musiciens"

-PC Loisirs (PC Leisure, France)

"A very good choice for professionals who work on a deadline and demand top performance"

—Electronic Musician

"Excellent—and user friendly—results."

-Musician


"A very powerful sequencer of MIDI data and audio that now makes hard disk recording a cakewalk"

-EQ

"The #1-Selling Music Software"

-Music and Sound Retailer, April 1996

CIRCLE 16 ON FREE INFO CARD MU



Pro Audio

Cakewalk Pro Audio¹¹⁴ is now the leading MIDI and digital audio workstation for Windows PCs. Cakewalk Pro Audio provides you with a unique balance of

power, stability, and ease-of-use, letting you concentrate on *creating music*. (It's a quality you won't find in music software that is merely "ported" from the Mac platform.)

PIBRA Mint

This News Just In.

Cakewalk Pro Audio 5.0 is now available. It includes both a native Windows 95 version and a Windows 3.1 version on a single CD-ROM. Plus 40 new instrument definitions, improved editing functions, new MIDI+audio song files, on-screen Cakewalk tutorials, JAMMER Hit Session™ accompaniment software, support for the Digidesign Audiomedia III™ card and Soundscape SSHDR1™ hard disk recorder, and more.

And, oh yes— *still* no copy protection. Unlike some software manufacturers, we don't treat our customers like suspected criminals.

SO SPREAD THE NEWS.

If you need integrated MIDI and digital audio recording, rock-solid SMPTE synchronization, and high-quality notation, then ask for the industry leader— Cakewalk Pro Audio.

Did we mention affordability? Cakewalk Pro Audio is only \$399. (Deluxe edition \$479; includes Musician's Toolbox CD-ROM.) For the name of a Cakewalk dealer near you, call 800-234-1171, or fax 617-924-6657



WORLD WIDE WEB: http://www.cakewalk.com

Man Sues International Manufactuer: False Advertising!

Harvey Rubinesky, of Climax, Ga. filed suit with a large professional audio manufacturer for false advertising. He contends that the Yamaha ProMix Ol was advertised as a "smart" mixer, but, in reality, it can't answer even the simplest question! "For example, the ProMix OI does not even know the capital of New Jersey", stated Harvey!

Rubinesky freely admitted that one might be "smart" and not know the capital of New Jersey. "However", continued Harvey. "how about an opinion? When I ask the ProMix for its favorite color it just sits there!"

Yamaha, when asked to comment, pointed out the ProMix was extremely smart when compared to other mixers.

ProMix 01



It is Yamaha's position that no audio mixer knows state's capitals or can offer an opinion of any kind. Where the ProMix is really smart is in the area of MEMORY - this mixer remembers every setting of all 18 input channels. This means at the touch of a button you can store and instantly recall the position of faders, mutes, aux sends, pan pots, eq. at any

> time, to allow you to return precisely to a previous mix. When connected to a MIDI sequencer or data recorder, real-time moves (such as actual movement of faders, pan, eq and aux send controls) can also be stored and replayed with precision. With 20 bit A/D converters, 3-band true parametric eq on every

> > VAMAHA

VOICE

channel. and 3 internal compressor/limiter/gates, sonically the ProMix 01 is a giant - and has performed impeccably on top film scoring sessions, classical recordings, in high-end professional sound reinforcement and broadcast applications. As a digital mixer, the ProMix can connect directly to digital recorders like RDAT and other devices, keeping signals in the digital realm. At a suggested price of \$2,199 the ProMix 01 competes with the finest mixers, replaces a ton of outboard gear and allows you to get back to your favorite settings in a snap.

Rubinesky was asked for comment after hearing Yamaha's response. Harvey maintained that having a good memory did not necessarily make one smart. When we asked Rubinesky what the capital of New Jersey was he said he couldn't remember.

P50-M Piano Tone Generator

.....

FOR MORE INFORMATION ABOUT ANY OF THE PRODUCTS SHOWN IN THIS ISSUE PLEASE Call (800) 291-4214 ext.830 or visit us at www.yamaha.com.

YAMAHA

© 1996 Yamaha Corporation of America, P.O. Box 6600, Buena Park, CA 90622. All other products or services mentioned are trademarks of their respective owners.

Surfing Tragedy

Reeve O'Neal, a popular local surfer, was sucked into the falls and knocked flat by the laptop on his longboard. Friends report that O'Neil had wanted to surf to the new Yamaha guitar internet site,

www.yes a guiturs.com, which features a complete guitar "catalog," artist information, news and cutting edge graphics.

Yamaha is dedicating the site to Reeve. "He was a cool dude and he had guts, but he wasn't very bright" remembered a close friend.

Evil Spirits Inhabit New Yamaha PianoTone Generator

VERB NATE MINICA

บานกา

• TOUCE

Beelzebub. Mephisto. Satan. Gossip says Yamaha must be selling out to this dark source-how else could it take over 100 years of keyboard manufacturing and shrink it into an 8 inch box.

Yamaha sources say their P50-m piano tone generator is simply a matter of advanced electronics and acoustic piano know-how. But who believes those corporate types anyway.

No. this reporter is witness to some peculiar activity outside the Yamaha plant late at night. Deep, evil laughs have accompanied frenzied plano solos emitting from the Yamaha R&D lab. While Yamaha claims that it has compressed over 11MB of wave ROM into 6MB of space and added 3-band EQ and 40 types of effects, this newspaper has evidence suggesting that by using the P50-m's simple panel switches. you are actually awakening the undead who would just as soon steal your soul as play your music.

Gorilla Musicians Get Mega Record Deal

Record execs from the newly formed Banana Records last week gave a family of gorillas a \$10 million recording contract after hearing their demo, "Unga Rap." Gerry O Shaunessy, director of Banana Records says: "These primates are GOOD! We are sending our best talent scout to Rwanda to find more musical apes."

Anders Olygok. an anthropologist, discovered the family's talent purely by accident. "I came to study the gorilla's mating habits. I brought some musical gear to help soothe the animals and record their mating sounds-the Yamaha SU10 hand-held sampler and CBX-K1XG controller keyboard/tone generator. Between the two I have an entire MIDI studio pow-ONTO DINUILINA NO TOTIONIO way. one night 1 awoke to this bizarre music. This family of six gorillas had gotten hold of the gear and the Silverback, the family patriarch, was crooning away."

Olygok's companion. Olga Nsygd, observed the mother gorilla working the SU10 sampler. "She took to it like a fish to water. After all, it's very easy to use. She gathered about 30 samples of the Silverback-the SU10 lets you record and replay up to 48 in stereoand then she used the ribbon controller to scratch out all kinds of wild effects."

Nsygd and Olygok then witnessed the gorilla editing the sounds by changing the playback direction, loop type and loop points. She also utilized the scale function to play samples at incremental pitches. Banana Records mega-producer Tony Romono said, "She's a born musician. Her mastery of this device is incredible."

Romono was also impressed with the youngest member of the family. Chip. "He's quite adept at the CBX-K1XG keyboard. And he loves to explore the CBX-K1XG's 727 XG and GM voices and 11 drum kits. He has no preconceived notions of what music should be. But the drums are especially prominent in his music."

At Banana Studios. Chip demonstrated his talents for the Inquisitioner using the CBX-K1XG's built-in stereo speakers. Happy with his performance, he then saved it to disk via MIDI bulk dump using his Yamaha MDF2 MIDI data filer, much as his mother did in the jungles of Rwanda with the SU10.

The only hitch in the arrangement so far is that Banana Records just can't seem to keep enough bananas around. CBX-K1XG





REGULAR GUY BUYS DIGITAL MULTITRACK RECORDER!

"It cost the same as some 4-track cassette recorders!!" Guy exclaims.

It's unbelievable, but true. This reporter has uncovered evidence that regular musicians — not just cashencrusted music moguls — can now afford digital recording. Yamaha, those same crafty devils famous for their technological know-how, now brings digital to the masses. Yamaha's MD4 is the lowest cost digital multitrack recorder available anywhere. According to Regular Guy, musician, "I got my MD4 for around a thousand bucks while most digital multitracks are going for \$2400 and up?"

Eager to blow the lid off this story, we visited Guy as he recorded a demo with his band, Psychic Poodle. We verified the facts... using the MD4 4-track multitrack. Guy's audio quality was incredible (even if the Poodles don't have the best licks). With digital audio storage, there's no audible noise. 0% wow and flütter and full range frequency response. The MD4 recording was so good, it could be used as final product — not just a scratch pad — even for professional composers.



MD4 4-Track Multitrack

FREE NS10M Speakers

It gets even juicier. Because the MD4 is digital, the sonic performance doesn't degrade with track bouncing. And you can even bounce to the same track — you don't have to keep an open track like you do with cassette recording. And

get this. You can locate an exact (and we mean exact) place in your tune easily. According to Guy. "That means you can find, hear, and re-record even a short passage without erasing any of the good stuff. If only Nixon had had this instead of tapes."

Still, we were skeptical. What was the secret of the MD4? Our inquiring minds found out when Guy popped a MiniDisc out of the MD4. That explains why he could record for 37 minutes per track instead of the 22 maximum that's normal with cassettes. Those MiniDiscs are small and portable, but then again, so is the entire MD4 system. After revealing his story, Guy packed up his Poodles, his MD4 and left (*Cont. on Page 24*)

"I'VE LIVED THE SAME DAY 500 TIMES"

Friday seemed like a normal day to Joseph. But instead of being followed by Saturday, he woke up to Friday again, 500 times! "Every day was exactly the same. I stepped in the same puddle. I heard the same song on the radio. I left my fly open. Everything."

02R

Scientists blamed sunspots for this bizarre occurrence but a recording engineer had a different idea. "It must be the Yamaha 02R Digital Recording Console. It saves every aspect of a mix, including EQ, fader positions and effects and recalls them precisely and instantly. I guess it's moved beyond music now." The embarassed scientists agreed.

CONSUMER ADVOCATE WARNS, "DON'T BUY YAMAHA RM800!"

The Inquisitioner

"I went to the local dealer to buy one and was shocked by what I found!"

Getting a free pair of Yamaha NS10M Studio speakers with the purchase of a Yamaha RM800-16 or RM800-24 (free with the possible exception of the postage to return the coupon claiming the above-we know he'll read this), was more than well known consumer advocate, Ralph Rubinesky, could take. Ralph warned that consumers should be careful in considering the purchase of the Yamaha RM800 Mixing Console. Ralph admits he is suspicious by

nature and that Yamaha's latest offering has got him spooked. "I have learned over the years." commented Rubinesky, "that if something seems too good to be true, it probably is."

Ralph explained. "I decided to start taping my nationally syndicated show at home. This required that I purchase a lot of gear, including a mixing console. Being a consumer advocate, I read all the reviews on various mixers and found the Yamaha RM800 to be just the value and performance I needed. In fact, it was almost too good to be true:

"Sound... is exceptional (particularly the low noise and sensitive EQ) for a board in this class." "Inexpensive, great sound, very versatile," says EQ Magazine.

"As the first eight bus recording mixer to come in under \$2,000...it offers the home studio market more features per dollar than any other mixer in its class," states Electronic Musician.

"I went to the local dealer to buy one and was shocked by what I found! I was

offered the RM800 at a great price. I said I'd take it. But the salesman insisted that I fill out a coupon to receive a pair of Yamaha NS10s, the world standard for recording monitors—a \$478.00 value—free of charge! This was after I had already agreed to buy the mixer. The salesman said that all I had to do was fill out a coupon and send it to Yamaha and they would ship the free NS10s directly to me!"

Nobody Expects The Inquisitioner. Vol. 18 Issue 1284

Ralph seemed clearly shaken. "Then, to put the final nail in the coffin, they offered to finance the deal, for six months, same as cash!"

When asked if he bought the Yamaha RM800, Ralph said ...

"Yes! What, are you crazy? I wanted to buy before they changed their minds, ran out, or discovered their mistake. For the smart shopper, timing is everything!"

When asked to comment. Yamaha stated that the deal was legitimate but that it was available at participating dealers only, while quantities last, and that it was a limited time offer.

"See." said Ralph. (call 1-800-291-4214 ext. 830 for your closest participating dealer).

BM800-16

Blessid Union of Souls "I Believe"

Engineer Jerry Lane discusses recording the string section for this hit tune

EQ: What stands out in your mind about recording the strings for this song? Jerry Lane: This was the first time I ever recorded real strings. The way the whole thing worked was that the original demo was recorded with just synthesizers and a sequenced piano. For the record, we thought we'd get a real piano and real strings. So we brought real string players in and they played along with the sequenced piano that we had from the demo. So the piano sequence from the demo actually made it to the record... Yes. Actually most of the parts from the demo wound up on the record.

Does that include the vocals as well? Yes. Everybody thought we'd re-record some of the parts to make them better, but it turned out that nobody really liked the newer stuff better than the original demo. The piano is a Roland W-30 sampler piano. We tried recording a real piano, then we sampled a real piano and tried sequencing it. We even tried one of those MIDI grand pianos, but the original Roland W-30 sounded the best, so that's what went on the record.

So the string players were listening to the piano sequence while they were recording their parts. Were the string parts charted out?

C.P. (Charly) Roth — who is in the band and was also the associate producer —



WHERE THE HEART IS: Blessid Union's hit song is from the album Home.

did all of the string arrangements. The string arrangement that was on the demo is the same arrangement as on the record. C.P. wrote it out and played it on synthesizers for the demo. He'd play the first violin part on one track and then we'd go to the next track and do the next violin part...He had the parts written out so we just had the players to come in and perform them.

How many string players were there? Ten altogether. Three first violins, three second violins, two violas, and two cellos. They all played together at the same time. We recorded a lot of tracks maybe two or three passes — to double all of those parts.

So their parts were layered to fatten them up?

Yes, so it would sound more full. Then we would also do a separate pass to record the entire string section on the two room mics we had up. The parts are actually tripled.

How did you go about miking the room?

We recorded the tracks at Ligosa Sound in Cincinnati. The room that we have there is kind of a weird room. We actually just redid it, but at that time it had concrete block with slots and sound deadening material in it, like they use in factories. We rented some B&K 4006 omnidirectional mics and we had two of those up in the room. Charly was conducting and the mics were behind and right on either side of him about three or four feet apart, like a spaced pair.

What did you do for the other passes? Were the strings miked in sections?

Yes. We were using Neumann TLM 170's for the violins and violas. For the cellos we used some mics custommade in Nashville by Gene Lawson of Lawson, Inc. He makes several different mics based on the capsule used in the Neumann U 47. There's a solid state and a tube version of the mic. The tube version is the L-47 [see this issue's MicroPhile] and the solid state is the L-47S.

How did you position the mics? continued on page 140

- Dual path architecture provides 80 inputs in the standard 40-channel chassis
- Extremely easy to use and especially suitable for project and production environments
- Comprehensive 4-band AMEK Eq on every input
- Fader and Mute automation on every input
- 8 Auxiliary and 24 output buses with Master level controls on all buses

CARDER CONTRACTOR

- Proven AMEK SUPERTRUE automation with extensive onand off-line mix operations
- 40 channels of AMEK VIRTUAL DYNAMICS provides a range of computercontrolled Compressors, Gates and other devices
- AMEK Visual FX provides remote operation via MIDI from the console of effects devices by major manufacturers such as LEXICON, TC and YAMAHA*
- Solo-In-Place and fully automated Solo-In-Place systems with automation-controlled Solo Defeat
- Integral onboard jackfield
- Magnificent design and first class ergonomics

Head Office, Factory & Sales: AMEK Systems & Controls Ltd Tel: 0161 834 6747/ 0161 950 8767 Fax: 0161 834 0593 E-Mail:amek@console-city.com In the USA: AMEK US Operations, Inc. Tel: 818 508 9788 Fax: 818 508 8619 in Germany: Mega Audio GmbH Tel: 06721 2636 Fax: 06721 13537

AMEK

Angela II

In Singapore: AMEK Systems & Controls Asia Tel: 65 251 1629 Fax: 65 251 1297

CIRCLE OS ON FREE INFO CARD

AES '96: Workshop Preview


Audio's show of shows is more than just products BY STEVE LA CERRA

hile every AES show brings the favorite of things — new gear — to our attention, even the most die-hard of gear sluts must recognize that the show is also an exchange of ideas that includes new technologies and techniques that we can apply while using all that wonderful equipment. This year's AES, taking place in L.A. from November 8–11, is no exception. It therefore makes sense to build into your AES schedule time to attend some of the show's many workshops and technical papers.

Since low-cost digital recording equipment is now a reality, the problem of synchronizing digital audio has become an everyday consideration. If you're having trouble sync'ing, swim over to workshop W-2 (November 8): "Digital Audio Sync Issues," which will explain methods for getting your 0s and 1s to happily line up. Addressing similar issues in the postproduction environment will be workshop W-15, "Audio Sweetening" (November 11). And speaking of digital audio, if you're struggling over the decision of whether to go with tape or hard disk (or both), don't miss workshop W-5 (November 9), "Multitrack Digital Recording: From 8 to 48-Track Machines." This session will discuss applications, techniques, and the strengths and weaknesses of various formats.

Chaired by Russ Berger (Russ Berger Design Group, Dallas, TX) workshop W-11, "Studio Design For The Project Studio," is a must for *EQ* readers. Discussion will include scheduling, budgeting, and design criteria for the project room. Three case studies will be presented from the perspectives of the studio owner, design team, and contractor. Once you've got that room up and running, you'll want to be recording some great sounds. Any successful engineer will tell you that it's all in your mic technique. Check out workshop W-1, "Microphones and Microphone Techniques" on November 8. Featuring experts in the sound reinforcement, classical, and pop/rock areas, this session will focus on how to make intelligent decisions about your microphone selection and placement.

Those of you who are die-hard tube heads will want to catch workshop W-3, "Tube Technology" (November 8), which will explore the in's and out's of every engineer's favorite studio heater. While "Loudspeaker Technology" (W-



START PLANNING: The AES Convention is quickly approaching.

14, November 11) will focus on the latest developments in loudspeaker engineering and application, it will also offer attendees the opportunity to question industry leaders in an open exchange about the future direction of the products we are using. Loudspeaker tech heads will also want to attend Session C of the technical papers, which includes "What's Really New In Loudspeakers," to be presented by Drew Daniels of Sound Path, LTD. at session A on November 8.

Engineers particularly interested in the future of the compact disc will be most interested in several workshops. The first, "Audio For DVD" (W-4, November 8), will deal with the problems of getting audio onto new media such as the Digital Video Disc (DVD). In addition to the audio/video synchronization issue involved with DVD this session will also examine "total bit budget," audio compression, and techniques such as "branching," which might be new to many audio engineers.

"CD-ROM Techniques: A Software Developer's Workshop" (W-8 November 9) will explore sample-rate conversion versus audio quality, aliasing and quantization, and digital artifacts. Emphasizing the equipment and processes used to manufacture optical discs including DVD — will be W-10 "The CD Manufacturing Process" (November 9). Chaired by David Rabideau of US Optical Disc, Inc., discussion will also include a debate of single versus double-speed (and higher) glass mastering and its effect on the audio quality of the program material.

Anyone with an interest in the mastering process (and that really should include all of us since our efforts usually go through it at some point) will want to attend workshop W-7: "A History Of Mastering." Chaired by one of the true Masters, Bernie Grundman, this session will take a comprehensive look at mastering from its humble beginnings through its present status. James A. Moorer of Sonic Solutions will present a mastering-related tech paper: "Breaking The Sound Barrier: Mastering At 96 kHz and Beyond" during Session I on November 10.

These are just some of the technical papers and workshops that are slated for the '96 AES in Los Angeles. Of course, it would be impossible to attend all of them (and even if you could, your brain might fry), but try to make time to catch some of them; your AES directories will provide the details as to where and when they'll be. Remember: the gear is great, but you've got to know how to use it. Make this year's AES a learning experience that will serve the rest of your engineering career.

For more information, contact the Audio Engineering Society, 60 East 42nd St., New York, NY 10165. Tel: 212-661-8528. Web: www.aes.org.

What's a Vocoder and a "smart" Rotary Speaker effect doing in a studio processor? Sure, the new 1204 has plenty of spacious Hall, Room, Plate and Ambience Reverbs. Distinctive Chorus, Flanger, Gate, Delay and Pitch Shift effects (a total of 512 variations) with MIDI control and 100 memory locations for edited programs. Plus a front panel mic input for vocalists and DIs. But we also thought you'd want stuff no one else has.

All for a really scary \$249.


The Zoom Studio 1204 features 18-bit, 44.1 kHz digital audio for superior studio performance.

THE ZOOM 1204 STUDIO EFFECTS PROCESSOR



Every cool ZOOM processor is distributed in the USA by Samson Technologies Corp., P. O. Box 9031, Syosset, NY 11791-9031 Phone: (516) 364-2244 • Fax: (516) 364-3888 ©1996 SAMSON

CIRCLE 99 ON FREE NIFO CARD



48-track capability and punch-on-the-fly are only part of the many professional features which make Pro Tools the best selling digital audio workstation in the world.

Putting the Pieces Together

for a totally integrated studio ...



Recording

With Pro Tools it's not just recording. There's nondestructive recording. There's loop recording. Try it over and over until you get the take you like. And do it in the digital domain. Clean, crisp, or cutting edge.



Editing

On-screen waveforms let you see what you've been bearing. Sophisticated editing tools let you cut with precision, without affecting the original audio. Piece together dozens of takes to create the ultimate performance. Be precise. Get creative.

If you spend enough time and enough money, you can put together a bunch of gear to do a bunch of things. But no matter how many things you piece together, they will never equal a Pro Tools system.

Pro Tools provides you with the best tools to accomplish every important task involved in music production, from concept to finish. Right here, right now, right on your desktop.

But great tools and great ideas are not the end of the story, they are the beginning. With the functionality that Pro Tools offers, you'll be able to create music in ways you've never imagined before. Experiment. Assemble a knock-out solo. Triple the vocals. Undo. Fly them in backwards. Re-do.



Not only will you be mixing in the digital domain, you'll bave relative fader grouping and dynamic automation of virtually all parameters. Expand your mixing capabilities with powerful Plug-Ins from over 100 Digidesign Development Partners.





With MasterList CD software, you can prepare your project for CD mastering. It's the recommended software with the necessary features for professional CD-DA creation. No need to worry about how a cassette will sound. Think about how the CD jackets will look.

Putting the pieces together is easy when the pieces are all there. And with Pro Tools, the whole is greater than the sum of its parts...and then some.

Find out how Digidesign can provide you with the solution for a totally integrated studio. Call **1-800-333-2137**, **ext. 269** for more information or our **free** Pro Tools video.

Digidesign provides complete solutions for music production, audio post production for film and video, multimedia, and radio broadcast production.



www.digidesign.com




#1996 Digidesign, a division of Avid Technology, Inc. All features and specifications subject to change without notice. Digidesign and Pro Tools are registered trademarks of Digidesign or Avid Technology, Inc.

CIRCLE 24 ON FREE INFO CARD

MI INSIDER

Phix Your Phase



Weak sounds may be more than just a phase you're going through. Here's how to fix them.

BY CRAIG ANDERTON

hen a drummer hits the beater on a kick drum, a rush of air pushes outward and we don't just hear it, we *feel* that "thud." In theory, if we record that kick drum and play it back, then the speaker will push air out and re-create the sound.

But what happens if somewhere along the line, the signal phase (or polarity, if you want to be more precise in your terminology; see sidebar) becomes flipped? This can happen in many ways, from a miswired XLR connector where hot and neutral are reversed, to a design flaw in a piece of gear (some products produce out-of-phase outputs), to a reversal of the wires going to your speaker.

Theoretically, the ear is not responsive to phase and doesn't hear any difference whether an output signal is inphase or out-of-phase compared with the input. However, many people feel that the ear *can* discriminate absolute phase with certain types of signals. This isn't too hard to believe. For example, with the kick drum example given above, it makes sense that our brain would say "something's wrong" when it hears a kick drum that sucks air away from you rather than pushes air toward you. On the other hand, with cymbals you don't hear much of a difference because the sound is more diffused anyway.

In any event, phase changes are certainly audible when mixing in-phase and out-of-phase signals together. For example, suppose two mics pick up an instrument sound with one properly phased and the second miswired so it's out-of-phase (fig. 1). As the waveform from one mic reaches maximum, the other reaches minimum, so combining the two causes cancellation that results


in a thinner sound (in practice, the output usually won't be exactly the same as the input, so the signals won't cancel completely). This is why consoles have phase switches. If you mix two in-phase signals, the result is a stronger signal.

M o s t d e s i g n engineers realize that phase consistency is important and therefore design p r o d u c t s whose outputs are inphase with the inputs. Unfortunately, this was not the case with some older devices (particularly signal processors), and even today some newer devices have phase inconsistency. So how do we correct an out-of-phase signal?

With balanced lines, you can simply reverse the hot and neutral wires. With unbalanced lines, you need an electronic adapter called a phase inverter. By inserting it in the out-of-phase signal line (fig. 2), it reverses the phase again and restores everything to normal. As to how you obtain this kind of adapter, the best way is to build it yourself.

ABOUT THE CIRCUIT

Building a phase inverter is neither difficult nor time-consuming. The Phase Switcher in fig. 3 costs next to nothing, adds virtually no coloration, and ac-



America's Fastest Growing Music Retailer ... for the third straight year!


– Source: Inc.Magazine Top 500

Sure, any dealer can sell you the latest MIDI instruments and recording equipment. Call them — they'll be glad to take your order (and your money), But only Sweetwater offers the kind of old-fashioned, per-

sonalized service you deserve from a sales staff that really knows their stuff. You also get dependable on-time shipping and technical support other dealers can only dream about, plus the industry's largest inventory in stock in our giant warehouse.



You've seen our informative, full color ads for years. Now check us out on the Internet. It's the most comprehensive music site on the planet: "www.sweetwater.com"!





Over 100,000 musicians world-wide already get a copy of our exclusive Sweet Notes newsletter. Call us today to receive your free subscription!



Sweetwater Sound first opened its doors in 1979. A whole lot of other music dealers have come and gone since then, but thanks to our innovative customer communications, affordable prices and friendly, knowledgeable sales engineers, we've grown at an astounding rate. We offer thousands of products from the



best names in the industry, like Korg, Roland. Kurzweil, Alesis. Digidesign and Tascam, to name just a few. So if you're shopping for equipment, why not make the right call and find out why thousands of other musicians have made Sweetwater Sound their first choice for all their hardware and software needs?

THE ULTIMATE

MUSIC RETAILER!



CALL NOW! YOU MAY BE PRE-APPROVED FOR OUR LINE-OF-CREDIT ACCOUNT! (Amount may vary up to \$50,000 depending upon individual credit history)

CIRCLE 81 ON FREE INFO CARD




FIGURE 3

cepts -10 or +4 signals. Its frequency response goes down to DC; the upper limit depends on which op amp you choose, but typically goes up to at least 40 or 50 kHz (that should be enough).

This circuit can produce an output signal that's either in-phase or out-ofphase with respect to the input, depending on S1's setting. With S1 in the (+) position, IC1 acts like a noninverting, unity-gain buffer. In the (-) position, IC1 becomes an inverting amp with a gain of 1. There is no output level change when you switch phase.

IC1 can be any op amp that doesn't require unity-gain compensation; a lowly 741 op amp will work or, for improved performance, a TI 071 or LF351. Half of a 5532 is also a good choice, although the pinout is different than shown on the schematic. Power can be provided by two batteries (the circuit draws very little current), or a bipolar DC adapter (as described in the book Do It Yourself Projects for Guitarists, published by Miller-Freeman). The greater the supply voltage, the greater the headroom; ±15 V to ±18 V is recommended for +4 applications. If you use an adapter, eliminate the batteries and S2. Feed the positive supply voltage to the circled +, the negative supply voltage to the circled -, and power supply ground to ground.

2

2

USING THE PHASE SWITCHER

The Phase Switcher has many applications: reversing phase of individual effects in parallel effects systems, flipping mic phase with mixers that don't have phase switches (patch the switcher into the insert jacks), and repairing improperly recorded samples (like kick drums that "suck" instead of "blow"). Having everything in-phase really does make a difference in the final mix check out this simple circuit and see if it helps make your mixes stronger and clearer.

Acknowledgment: I'd like to thank A&R veteran George Daly (and CEO of Power Entertainment) for sharing his work regarding phase anomalies with me; our conversations are why I decided to write up this circuit for EQ. Incidentally, George notes that one common symptom of phase problems is that no matter how much you turn up your mixes, they never seem quite loud enough.

Craig Anderton's latest book, a from-the-ground up revision of the classic book Home Recording for Musicians, is now available. For more info, check out his AOL site (keyword SSS).

PARTS LIST

Part10k resistors, 1/4-watt,
5% or 10% toleranceInternally compensated op amp (see text)SPDT (single pole, double throw) switchMono, open circuit, 1/4-inch phone jacks
±9 to ±18V DC bipolar power supplyDPST or DPDT on-off switch
required for battery operation)9V batteries (required for
battery operation)

PHASE VS. POLARITY

It happens all the time: you're talking about phase changes to some gorgeous creature at a cocktail party, when some nerd with a pocket protector arrogantly corrects you and says that you should use the term "polarity." So what's the difference?

It's a complex topic, but here's the short answer. Polarity affects all signals regardless of frequency. What is commonly referred to as "out-of-phase" generally means flipping the polarity so that positive-going signals now go negative, and vice-versa. Phase often implies that frequency is a factor in the situation. For example, suppose you delay a signal by 0.5 ms and recombine it with the straight signal. A 1 kHz signal will be precisely out-of-phase (the period of a 1 kHz signal is 1 ms, so starting it 0.5 ms later means the two waveforms will cancel), but signals at other frequencies will be out-of-phase to a greater or lesser degree. ----CA

COME SEETHEUSA GO SEETHEUSA

Two Tickets plus backstage passes (if available), to any concert, installation or event in which QSC Audio Products are used, including round trip airfare for two, limousine, two nights accommodations...and much more! **5 First Prizes** New USA 900 power amplifiers

900

How to Enter

Come and see the new USA Series of power amplifiers from QSC Audio at any participating retailer. Let them show you why the USA Series has beccme the best-selling amplifier in the world. Then, fill in the entry card and drop it into the mail to QSC to be entered in our contest. Other Prizes 3 Second Prizes: QSC Wool & Leather Baseball Jacket

50 Third Prizes: QSC Denim Shirt

and and the second of Sold and a

CIRCLE 65 ON FREE INFO CARD

QSC AUDIO PRODUCTS, INC. 1675 MacArthur Blvd., Costa Mesa, CA 92626 USA Ph 714/754-6175 Fax 714/754-6174 Web http://www.qscaudio.com E-mail info@qscaudio.com No purchase necessary. Contest runs 9/1/96-12/1 96 at participating retailers. Open to entrants 18 or older. Vinners will be selected in a random drawing on or about 1 1.97 and be not led by mail Prices (1) Grand Price Two (2) Ticles (p us bentaring example a participating retailers. Open to entrants 18 or older. Vinners will be selected in a random drawing on or about 1 1.97 and be not led by mail Prices (1) Grand Price Two (2) Ticles (p us bentaring example a participating retailers. Open to entrants 18 or older. Vinners will be selected in a random drawing on or about 1 1.97 and be not led by mail Prices (1) Grand Price Two (2) Ticles (p us bentaring example a city, two (2) nights accommodations, plus two (2) QSC baseball-style jackets (combined azv. 52,500); (5) 1st prices QSC USA 900 Power Amplifier (azv. \$765); (3) 2nd prizes QSC Wool. Leather Baseball Jacket (arv. \$200); (50) 3rd prizes QC C Audio Products, Inc., 1675 MacArthur Bivd. Cesta Mesa CA 92626 Onds of wining depend on number of example a final retaining depend on number of example a price of QSC Audio Products, Inc., 1675 MacArthur Bivd. Cesta Mesa CA 92626 Onds of wining depend on number of example a final retaining depend on number of example a final retaining members and on number of example a final retaining depend on number of example a final retaining depend on number of example a retaining depend on secure a final retaining depend on secure a final retaining a companies of advertising and trade without further compensation, unless prohibited businesses, aversioning and promotion agences, and their immediate family members and on number of example a final retaining depending retaining a companies of advertising and trade without further compensation, unless prohibited by law. No substitution or transfer of pice permitted All applicable Federal State and every a retaining a retaining

TECHNIQUES RECORDING

Fat, Forty, and Back!



It's been 20 years since the shock of punk, and The Sex Pistols have reformed for a tour and a live album

BY KEVIN HILTON

hey couldn't quite conjure up the same hype and media attention as 20 years ago, but the reformed Sex Pistols were sure going to try. At a carefully chaotic press conference that was broadcast over the Internet, John Lycon, the former Johnny Rotten, sneered that the band was only doing it for the money. When they came to play their first UK gig on the reunion tour, the fans - and a bemused recording crew - were confronted by posters advertising the upcoming new single and album of the show. without a single note played or a reel of tape unwrapped. The Sex Pistols wouldn't have had it any other way.

The band's recorded oeuvre is not massive — one complete album (the defiantly classic *Never Mind The Bollocks*), the soundtrack to *The Great Rock & Roll Swindle*, a couple of cobbled import efforts, and a few additional singles, many of them collector's items — but it was felt that there was enough to tour with. Virgin Records decided to record a new product, but without the hassle of going into the studio and producing something

new. As Lydon observes on the record, they're fat and 40, but the fans are glad that they're back — no matter how bad the advance reviews were.

The reformed Pistols is comprised of Lydon on vocals and tart comments, Steve Jones on guitar, Paul Cook on drums, and original bass player Glen Matlock, the man who actually said the "f" word on the *Today* show and was later booted out of the band


in favor of the doomed Sid Vicious, who couldn't play the instrument, but at least looked the part.

LUCRE-TIVE TOUR

Armed with the songs from their first album, the Pistols kicked off their world tour at a beer festival in Finland. Nobody except the press seemed to take much notice, but this didn't daunt Lydon: "We're the Pistols, nobody likes us and we don't care," he warbled in between songs. The gigs continued with more outdoor shows in Munich, Germany, and Finsbury Park, London (fittingly, the area where Lydon was brought up), followed by an indoor show at the Paris Zenith.

These last three concerts were recorded as the basis for a live album. The aptly titled *Filthy Lucre Live* was released during July to almost universal acclaim and is a record of the Finsbury Park concert only; the intention


is to release an alternative version at a later date featuring recordings from the Zenith show. *Filthy Lucre Live* shares an almost exact track listing (plus a cover version) with the now re-issued *Never Mind The Bollocks*. Like its 1976 equivalent, the new album was produced by Chris Thomas (who, unfortunately, proved unavailable for comment), who has re-created the raw, spare, aggressive sound that spat in the face of the record-buying public 20 years ago.



DECISIONS, DECISIONS: The Sex Pistols' SADIE EDL.

The single, "Pretty Vacant," preceded it, coming into the record shops only a few weeks after the London show.


World Radio History



INTRODUCING THE AMAZING DTH® S AND DTH® SF FLYING ENCLOSURES.

he DTH[®] S/SF series marks the beginning of a new era of sound reinforcement for Peavey Electronics. These highperformance enclosures have propelled us into the pro-touring market with stratospheric expectations. Equipped with 44T[™] high-frequency compression drivers, durable high-precision Black Widow[®] woofers with fieldreplaceable baskets, the DTH S/SF

series minimizes down time and keeps your tour running on schedule, night after night. And for added convenience, we've



So if you're looking for maximum sonic performance with minimum effort, check out our new act: The DTH S and SF Pro Touring Enclosures.



ne MONITOR Magazine is a publication filled with the latent information musicians want to know. To receive 4 issues for only \$5 (price good in U.S. only) send check or money order to; Monitor Magazine,Peavey Electronics, 711 A Street, Meridian, MS 39301 • (601) 483-5365 • Fax (601) 486-1278 http://www.peavey.com • AOL Keyword: Peavey • CompuServe: Go Peavey • ©1996



CIRCLE 64 ON FREE INFO CARD

TECHNIQUES

Both the Finsbury Park and Munich concerts were recorded on digital Sony multitrack to accommodate the length of the performances, which ran to one and a half hours. This running time was achieved despite their relatively small back catalog and comprised the whole of Never Mind The Bollocks plus a suitably punked-up version of the Boyce-Hart Brill Building semi-classic "(I'm Not Your) Stepping Stone," a hit the first time around for another managementcreated band, The Monkees.

The German gig was recorded in the Dirks Mobile, but Thomas and the band decided not to use the tapes, mainly due to the show being washed out by bad weather. Explaining the reasoning behind the decision, recording and mixing engineer Pete Lewis says, 'We didn't use the Munich recording because the band went on in torrential rain and the audience was covered in mud, so they weren't particularly happy. When we got to London the next day it was brilliant - the weather was good, the crowd was vibed up and there were lots of other

NEVER MIND THE RUMORS

Never Mind The Bollocks (Here's The Sex Pistols) has become a punk classic. Leaving aside the clouding issues of the money, the swearing, the choreographed outrage, and what happened to the band afterwards, the album is a tight, raw example of a different type of rock 'n' roll, all tied up by Chris Thomas's straightforward production.

The album was recorded at Wessex Studios, where the band had been putting down demos, with Bill Price engineering. Thomas was contacted by the Pistols' Machiavellian manager, Malcolm McLaren, and invited to produce the album proper, which he agreed to do, not so much for the sociocultural significance but because he felt he could make a good rock 'n' roll record with them. "I thought they were fantastic," he told John Tobler and Stuart Grundy, "especially on 'Anarchy In The UK,' there was the most incredible atmosphere in the studio."

One thing that has dogged the record is the persisting rumor that the Pistols did not play everything on it. In particular, legend has it that it was Chris Spedding, a leading session player of the time, and not Steve Jones who produced the barbed wire guitar sound that is so identified with the band. Thomas has said of this, "Despite all the rumors, Chris Spedding didn't play anything on their records." Spedding himself recently said that he was involved with the Pistols by supplying equipment for their rehearsals and by giving early encouragement, but confirms that he didn't play on Never Mind The Bollocks. Thomas added that the only substitution came with Sid Vicious, whose bass work was largely played by Steve Jones.

The discussion rumbles on, but engineer Pete Lewis hopes that Filthy Lucre Live will dispel any doubts. "If you listen to this and then to Never Mind..., you can tell that it's the same guitar player," he says. The album itself is more than just a live rehash of the studio original; even though it is 20 years on, and has the additional pleasure of the boys thrashing through "(I'm Not Your) Stepping Stone." Tongue in cheek? Coming out the other side ...



Finally there's a quality UHF wireless microphone system, at a reasonable price.

The heart of our new system is the 411UDR, PLL synthesized, dual conversion superheterodyne, true diversity UHF receiver, with 63 user-selectable channels, balanced and unbalanced XLR and 1/4" outputs, tone squelch, output volume control, status LEDs and an optional rack mount kit. The 41HT handheld and the 41BT bodypack transmitters are frequency agile and utilize surface-mount technology for superior reliability. For under \$1000 Azden redefines the parameters by which cost effective high-band wireless will be judged. For literature, and specifications, write to:



CHARGE IT! The 41HT handheld can be used with either 2 AA alkaline, or, our exclusive rechargeable NiCad battery, and you can charge it with our optional (AMC-2A) charging station.

Distributed in Canada by Erikson Pro Audio

World Radio History

147 New Hyde Park Rd., Franklin Sg., NY 11010 (516) 328-7500 · FAX (516) 328-7506

CIRCLE 13 ON FREE INFO CARD

BRUB MULTITRACK DIGITAL RECORDING

Now you can record 8 tracks simultaneously at CD-quality on a removable hard drive with no compression and no compromise!

SLAVE D-80s for 16 & 24 TRACK RECORDING The D-80 can be slave or moster to other D-894 DMT-8s and the outside world via its standard built-in MTC, and is sample accurate with Word Clock (optical SIP-DIF). inally, you can have an expandable IDE-based digital removable hard disk system which offers up to 40 minutes* of true *multitrack* recording, nondestructive 'cut. copy, move & paste' editing, instant locate & search, five 'virtual reels', digital and analog inputs/outputs along with a removable front panel which acts as a full function remote control—all in a package which is a snap to use and incredibly affordable. So much so, you might want to buy two or three for 16- or 24-track recording capability. Visit yourFostex Dealer today! Now free software TrackManager a new professional track sheet database for both the MAC and PC Windows \$59.00 value.

D-80 Digital Multitrack

For further information contact. Fostex Corp. of America · 15431 Blackburn Ave. · Norwalk, CA. 90650 · Voice: (310) 921-1112 Fax:(310) 802-1964 http://www.fostex.com

Using optional 1.71GB Hard Disk. 850Mb supplied as standard. All trademarks acknowledged

Foste

CIRCLE 33 ON FREE INFO CARD World Radio History good bands from the same era on the same bill."

SORT OF STUCK IN THE '70S

As well as the now standard CD release, *Filthy Lucre Live* has been pressed onto vinyl as a "throwback" to the '70s, but this intention didn't stop the show being recorded in the digital domain. "It's just the convenience of digital," explains Lewis. "It would have been great to have recorded it all on analog, but it's just too risky, what with continual reel changes and so on. And if anything had gone wrong, then we wouldn't have known with analog, but with digital, it either works or it doesn't."

The two Sony 3324's were loaded into a transit van and driven on site, located next to a SSL-equipped BBC radio outside broadcast truck, which was relaying the concert live to air on BBC Radio 1FM. "We recorded in 24-track," says Lewis, "running a master machine and a safety, starting the second recorder five minutes after the main to get a good overlap. This meant that we had 90 percent of the show for



Patch around limited console EQ's when tracking or mixing.

Use the five fully overlapping bands as creative or corrective tools.

Enjoy barely measurable noise & distortion.

Use wide bandwidths to enhance clarity.

Bask in the sunshine of affordability and buy a new mic with the money you save on this EQ. Infidelity or hi-fidelity? <u>You</u> make the decision by choosing an outboard EQ that stands out from the rest. A product of meticulous engineering and exacting craftsmanship.....the Symetrix 551E Five Band Parametric EQ.

This is not a copycat EQ. Our proprietary filter circuits reduce high signal level THD to less than .002%. Dynamic range exceeds 114dB. Direct coupled input and output stages add minimum components in the signal path.

As for the actual sound of our new EQ? It's as good as the best and better than all the rest. Listen for yourself. Choose hi-fidelity. Choose Symetrix 551E.



TEL 800.288.8855/206.787.3222 FAX 206.787.3211 email 102102.1126@compuserve.com

CIRCLE 82 ON FREE INFO CARD

sure, which is a good safety margin."

Stage feeds came into the BBC truck, where studio manager Ted de Bono prepared the radio broadcast mix on the SSL, with the desk's mic gain faders providing the level output to the 3324's next door. "Originally we had booked another mobile to do the gig," Lewis says. "We didn't know that the BBC was going to be there as well; they approached us and it turned out to be a good idea to do both at the same time. The recordings were made flat, straight off the mic gain, because sometimes you can get caught up in the technology of things. As long as it sounds good at the time, that's all right."

As the Pistols are only a three-piece band plus vocals (we couldn't forget Johnny), there were only 19 feeds coming from the stage, which were fleshed out with three stereo pairs to capture audience reaction. "We put two mounts on the stage to hear the audience," says Lewis, "and two more at the mixing position to hear what the engineer was hearing. This gets the ambiance and the sound of the rig, so it's a live gig that's about you and 25,000 friends."

POST-SHOW WRAP-UP

The tapes were taken to The Townhouse studio complex in West London, ironically a member of the EMI Group, particularly as the Pistols' paean to the venerable record company sits smugly on the album. Thomas and Lewis decided to give themselves plenty of choice in their lay-back formats, mixing on 48track and transferring from there to DAT and 1/2-inch tape, with a back-up and comparison version made on two spare tracks of the master multitrack. The master mix was in turn laid outo DAT and 1/2-inch tape. "The 1/2-inch sounds very rock 'n' roll," explains Lewis, "but we've got both there and sometimes one wins, sometimes the other. We also mixed to two tracks on the 48-track as a back-up and a comparison."

As the transfer to DAT was made, the mixes were loaded into a Studio Audio SADiE Portable, which was used for tracking and editing out any pauses between numbers, plus making CDs for the crew and band so that everyone could hear how the project was progressing. "Everything that Chris [Thomas] does is compiled and mastered in the studio control room," explains Lewis. "Sometimes this means that everyone gets so close to something, knowing how it sounds, so it's good to be able to take a CD home and

First Impressions Can Be Deceiving

It's What's On The Inside That Counts

There's a lot of truth to the old saying "don't judge a book by its cover." This especially holds true when buying your first pair of studio monitors.

With all the glamourous looks, sizzle and hype, it's hard to know what to buy. At Tannoy, we believe in value for money spent. All the good looks in the world won't substitute for accuracy when your mix is on the line.

While many loudspeakers are fine for soloing a kick drum or listening to your keyboard, monitors are not all the same when it comes to mixing. To correctly mix and layer your creative musical ideas, your monitor must resolve fine detail, particularly in the midrange where the ear is most sensitive. It must be well balanced to transfer well down the line and get you through your mix efficiently, effectively and without fatigue.

The new SBM monitoring system takes advantage of our in house technical prowess, honed through 70 years of experience. Its' 6.5" injection moulded low frequency and new 3/4 inch linen soft dome tweeter unit are knitted seamlessly together to ensure that every move you make will be faithfully reproduced. "No Guesswork"

When buying a new pair of monitors remember, this isn't

your recreation system. These are there to work on. Try them out in a music mix and trust your ears. You be the judge. Tannoy **SBM** – one monitor that gives you back the control.

Tannoy/TG1 North America 390 Gage Avenue, Unit 1 Kitchener, Ontario, Canada N2M 2C8

519 745 1158 • Fax: 519 745 2364 Web site: http://www.tannoy.com



TOLL FREE DEALER OF DER HOT LINE (FAX): 1-800-525-7081 TO OBTAIN YOUR FREE COPY OF THE TAINNOY NEAR-FIELDS MONITOR HANDBOOK CALL OR FAX US.

> CIRCLE 83 ON FREE INFO CARD World Radio History



CIRCLE 23 ON FREE INFO CARD



TECHNIQUES

listen to it in a different environment."

The SADiE Portable was fitted with a 4 GB removable drive, which gave Lewis enough capacity for tracking the album, even though the release CD contains 15 tracks and runs to 53 minutes 38 seconds. "We never really ran out of space on the 4 GB drive," he says, "on previous projects I've had up to 9 GB. With the SADiE you don't lose anything: it doesn't go wrong and the audio quality is excellent." When it came to the final transfer for mastering, which was also done at Townhouse, the completed mixes were laid onto [Sony] 1630.

Mixing was carried out in Studio 4 at The Townhouse, using the room's SSL 4000 console fitted with E Series EQ and a G-Series computer. There were a total of 72 inputs, using only 34 faders.

THE REAL THING

As rumors have persisted that the Pistols didn't play on *Never Mind The Bollocks* (rumors that have been consistently refuted), it is perhaps natural to think that *Filthy Lucre Live* would have undergone some cosmetic touches in the mixing suite, but Pete Lewis is adamant that there were no overdubs or repairs.

"There weren't any real mistakes," he states, "it's what they played and how they got out of the mistakes that they did make. The basic brief was to make it sound like a gig, so we didn't do that much to it in the studio. We only did a few rides during the mix, mainly on John Lydon's vocals and the guitar solos. They're only a three-piece band — how many mistakes are they going to make?'

Although the recording was made flat, Lewis says that the minimum interference policy also carried over to EQ on the mix, something that was down to Chris Thomas's style of production. "Chris has the most amazing set of ears," comments Lewis, "and he can make things sound like how he wants them to. In this case it sounds like a live gig. As far as EQ went, we put a little bit of top on the vocals, rolling off the bass as well, largely because John sings very close into the mic. We brought in a lot of tube equipment to warm things up but we only used a Pultec EQ on the bass drum because the quality of the 48-track is perfect."

Perhaps this minimalist approach came about through the undoubted confidence of the reformed Sex Pistols once they got back on stage, and particularly the strutting Lydon, who remarks at one point, "Well, we're not that f****** bad after all, are we?"

World Radio History

hen we designed the PCM 80's basic complement of effects Presets, we also provided the ability to plug in hot, new Audio Software/FX cards. Simply plug in any of our cards and you've now supercharged the effects processor everybody is talking about. New effects and algorithms. Hundreds of stunning new Presets. Sophisticated PC-Card architecture that supports our commitment to functionality and continuing upgradability.

PCM 80 FX cards offer a library of over 700 new Presets — each one tailored for a particular application - with a unique Adjust Knob that lets you quickly audition variations of the effect. We put the most useful parameters of each preset into the PCM 80's "Soft Row" so you can fine tune the Preset without having to hunt for the appropriate parameters. Engineer or



musician, there's a Lexicon FX card for practically any imaginable sound. Right now, you can instantly load-up on your creative options with any of these new FX Cards:

• Dual FX – 25 Algorithms / 250 Presets deliver highest quality stereo multieffects, unprecedented routing capabilities δ a powerful new digital sub-mixer.

• Pitch FX — 6 Algorithms / 100 Presets combine Multi-Voice Pitch Shifting

Plug Into The Future

INPLO

HEADROOM

12

13

with PCM 80 Stereo Algorithms. • Harmony FX (Coming 1997) — Intelligent Pitch Shift Algorithms / 100 Presets offer Diatonic Harmonization, Automatic Pitch Correction and more.

• Scott Martin Gershin Post FX — 100 superb post-production Presets featuring Surround Delays for Film & Reverbs for Orchestras.

• David Rosenthal Music FX — 100 powerful performance Presets featuring brilliant reverbs & effects for keyboards, guitars, vocals.

And don't forget, you can use any Preset as a template to create your own stunning versions of Lexicon effects - and store up to 2,000 of those Presets using standard PCMCIA SRAM cards.

So check out the PCM 8o FX cards and experience the future today, at your Lexicon dealer!

ADJUST

POWER

SELECT

PCM 80 DIGITAL EFFECTS PROCESSOR

K0 1.2 #Major Triads

Dual-Plt

Available Effects PCM 80 (200 Standard) Algorithm Cards - Presets

 DUAL FX
 V1.0
 250

 PITCH FX
 V1.0
 100

Artist Preset Cards

Scott Martin Gershin 100 (Post FX)

David Rosenthal 100 (*Music FX*)



ory Card

Heard In All The Right Places Tel: 617/736-0300 Fax: 617/891-0340 E-Mail: 71333.434@compuserve.com

> H A Harman International Company CIRCLE 48:00 EREFILING CARD





A Surround Sound Primer

Surround sound, the future of audio, is something so dramatic that it will forever change the way we record, mix, enjoy, and listen to music **BY BOBBY OWSINSKI**

few months ago I went to the first IAMM (International Association of Multichannel Music) conference and heard some 5.1 surround sound [the playback standard that the upcoming Digital Video Disc (DVD) will use] demos and I knew that I could never listen to or make music any other way again. The sound was simply breathtaking. As a producer, it's my job to make the music larger than life, but this was far bigger than I'd ever heard it before. Since I was starting a record with blues legend Joe Houston the next week, I begged the record company (Shattered Music) to give me a few extra mixing days to mix in this format in preparation for the future. What came next was an adventure into that future.

WHAT IS SURROUND SOUND?

What is this 5.1 surround sound and why is it bigger and better than the stereo that we now enjoy? The 5.1 means that you have six discrete speaker sources: three across the front (left, center and right); two in the rear (left surround, right surround); plus a subwoofer, known as the Low Frequency Effects channel, or LFE, which is the ".1" of the 5.1 (see fig. 1). This is the same configuration that you hear in most movie theaters since 5.1 is the speaker spec used not only by THX, but popular motion picture release formats such as Dolby Digital and DTS.

A BIT OF HISTORY

Surround sound has in one form or another been with us for more than 50 years. Film has always used the threechannel "curtain of sound" developed by Bell Labs in the early '30s since it was discovered that a center channel provided the significant benefits of anchoring the center by eliminating "phantom" images (in stereo the center images shift as you move around the room) and better frequency response matching across the soundfield. The addition of a rear effects channel to the front three channels dates back to 1941 with the "Fantasound" four-channel system utilized by Disney for the film Fantasia and in the 1950s with Fox's Cinemascope, but it didn't come into widespread use until the '60s when Dolby Stereo became the surround de facto standard. This popular film format uses four channels (left, center, right,

and a mono surround, sometimes called "LCRS") and is encoded onto two tracks. Almost all major shows and films currently produced for theatrical release and broadcast television are presented in Dolby Stereo since it has the added advantage of playing back properly in stereo or mono even if no decoder is present.

In the '80s, with the advent of digital delivery formats capable of supplying more channels, the number of surround channels was increased to two and the low-frequency effects channel was added to make up the six-channel 5.1, which soon became the modern standard.

And, of course, no surround story would be complete without a brief mention of Quad from the 1970s, the music industry's attempt at multichannel music that killed itself as a result of two noncompatible competing systems (a preview of the Beta vs. VHS



NOU DOUT THE POINT OF THE POINT

"There is an added fullness and clarity. Stereo program becomes more three dimensional, more spacious. Dense textures become more pleasurable, with a more palpable space around each discrete instrument. This is powerful stuff. Maybe its voodoo?"

"As close as we've seen to a magic black box, the BBE 462 is probably the most cost-effective improvement you can add to your rig."

Listening on a variety of loudspeakers – JBL, KRK, Meyer, Tannoy, Yamaha and a few lesser-known names – I discovered that the BBE Process provided a nice punch to older recordings without being brittle or shrill. The LF contour emphasized the bottom end, without undue boominess."

ROCESS

"All of the mixes we played gained extra sparkle and clarity when processed with the BBE 462."

A 30 second demo is all you need. Call your dealer now!

5381 Production Drive

S


Huntington Beach, CA 92649 (714) 897-6766 (IRCLE 9900 FREE INFO CARD

Fax (714) 896-0736

war) and a poor psychoacoustic basis that suffered from an extremely small sweet spot.

WHY 5.1 IS BETTER THAN STEREO

When you listen to 5.1 surround you'll notice quite a few things:



1. The sonic clarity is enhanced because the center channel anchors the sound and eliminates any "phantom" image shifts that we take for granted in stereo.

2. There is no "sweet spot" per se. Actually. the whole room becomes a sweet spot in that you can move around freely and never lose the sense of clarity, dimension, and spatial continuity. One listener described it as an "audio sculpture," in that, just like when you walk

around a piece of artwork and get a different perspective of the art, when you walk around the 5.1 room, yon get a different perspective of the mix. You might get closer to the guitar player, for instance, if you walk to the left of the room. Walk to the right and you're closer to the piano. Indeed, you don't have to even be in the speaker field to get a sense of the depth of the mix. This was perfectly illustrated while we were mixing and had people sitting on a couch behind the surround speakers who thoroughly enjoyed the experience.

3. Speaker placement is very forgiving. Yes, there are standards for placement (see the sidebar entitled "A Case Study"), but I've found these to be very noncritical. The sense of spaciousness remains the same regardless of how haphazardly the speakers are distributed around the room. In fact, speaker placement is far more critical in stereo than in surround sound.

During mixing, I found several other surprising advantages.

1. Clarity of instruments. Everything sounds much more distinct as a result of having more places spatially to sit in the mix. This means that you spend a lot less time EQing, trying to get each instrument heard.

2. Added dimension. We were

SURROUND SOUND: WHEN?

Surround sound for music is currently being driven by the home-theater market, which is reported to be the fastest growing segment of the consumer-electronics industry. With a total of 20 million home-theater systems in use (10 million in the U.S. alone), these consumers now want their CDs to sound like their laserdiscs. But is that market sufficient to push the new technology? Says Tomilinson Holman, THX inventor and the one who coined the term 5.1, "I think it's already caught on in the public's eyes. It's the public's asking for sound to light up those additional three loudspeakers that is going to drive things."

And the public may have its way as soon as later this year when DTS releases its home-theater decoder (but you need their own custom CDs to use it) and next year when the Digital Video Disc (on which 5.1 will be standard) is introduced. Plus, it's been rumored that two major car manufacturers will make some form of surround decoder standard in their 1997 models. And, of course, there's also High Definition TV, and cable and satellite delivery, all of which contain 5.1 audio in the specs.

With these glowing reports, you'd think that the record labels would be falling over themselves to get surround product out there ASAP, but Mike Frondelli, creative director at Capitol/EMI, offers a dose of reality. "From what I see, the labels are supportive of any new technology that comes along, but they're unwilling to throw a lot of dollars into it until they see that there's a market for it. The problem is that the installed user base of home-theater systems is the only one that can take advantage of the technology." Frondelli, though, also sees the key to success: "Part of the problem right now is that the artists need to champion it and use it in a very creative way so the record companies are willing to put out another format. I don't think people want to buy the same record yet another time, but I think they'd be willing to buy new material that was specifically created for this market."

Holman agrees that it's essential to have the musicians and producers lead the way. "There's a number of units on the market that will take a stereo program and process it to drive signals for all those loudspeakers, but that's not under the control of the producer. Eventually musicians and producers will have to be directly involved in making these mixes for the home-theater sound systems."

And just when you were coming to grips with 6-channel mixdown and playback, Holman gives us another dose of the future. "If you think that mono to stereo is a difference everybody can hear, and two to five channels is clearly audible, the next big step is from five to ten channels." Boy, are the equipment manufacturers gonna love this. —Bobby Owsinski

World Radio History

Paranormal EQ



It's uncanny. The precision and sheer musicality of Ghost's EQ will take your breath away.

Drawing on 22 years of Soundcraft experience, Ghost's new EQ is perfectly in tune with today's music. Two fully parametric, overlapping mid bands with shelving high and

with shelving high and low filters redefine the classic British EQ. But there's much more.

Each channel strip benefits from its own dedicated circuit board and supports both the main input plus a mix B path



for tape or other input signals. Ghost's flexibility and fidelity are staggering. The signal path quiet, true and uncompromised. And the automated mutes, just part of



Ghost's comprehensive machine control and MIDI

implementation,

don't so much cut, as fade very quickly. There are no thumps and no clicks. Ghost's microphone preamplifier, ProMic, boasts a better gain to noise performance than



you'd expect on consoles costing many times more. We could go on, but to appreciate fully the ergonomic and audio integrity of Ghost you need to see and

of Ghost you need to see and hear one in the flesh. So call 818 227 1800 to find out more.

circle 60 ON FREE INFO CARD Soundcraft


H A Harman International Company

HARMAN IN ERNATIONAL INDUSTRIES ITD., CRANBORNE HOUSE, CRANBORNE RD., POTTERS BAR, HERTS, ENG 3JN, ENGLAND. TEL: +44 (0)1707 665000 FAX: +44 (0)1707 660482—AKG ACOUSTICS, BSS AUDIO, SOUNDCRAFT & STUDER, HARMAN PRO NORTH AMERICA, INC., 1449 DONELSON PIKE, SUITE #2, NASHVILLE, TN 37217. TEL: 615 399-2199; FAX: 615 367-9046. 800#5: AKG: 800 878/7571, BSS: 888 251-8351, SCI 888, F51 8352 TY



most surprised to find that even mono tracks are big and dimensional! No longer is there a need to "stereoize" a track by adding an effect. This point was pointedly brought home when a rather bland mono background vocal track was brought up in the mix and it sounded so big after we spread it across the speakers that we couldn't believe it.

3. The ambience is different. Because of the naturally increased clarity and dimension, you no longer have to spend as much time trying to artificially add space with reverb, delays, and so on. This is not to say that you won't use these effects at all, but the approach is different since surround automatically gives you the depth that



you artificially create with stereo.

There are differences between surround for picture and for music. Normally, in the theater, all of the primary sound information comes from the front speakers and the surround speakers are utilized only for ambience info in order to keep your attention on the screen. The LFE is intended to be used just for special effects such as explosions and earthquakes, and is infrequently used. One of the reasons that the surround speakers don't contain more source information is a phenomena known as the "exit-sign effect," which means that your attention is drawn away from the screen to the exit sign when the information from the surrounds is too loud.

SURROUND SOUND: A CASE STUDY

Just wanting to mix in surround sound is not enough. It takes a big commitment in extra hardware to make the grade, unless, of course, you are on a film dubbing stage or in a post room already set up for multichannel mixing.

You will need: 5 identical speakers (preferably powered), plus the amps to drive them; 1 subwoofer (plus amp with 125 Hz low-pass filter; the ability to pan the signal to five mix channels; the ability to monitor six mix channels; and c DA-88 tape machine (the *de facto* standard) to mix to.

When I decided to mix blues great Joe Houston's project in 5.1, it was initially made possible by a chance meeting with JBL's David Kim at the IAMM conference. Wanting to help facilitate the format (and what manufacturer doesn't), David offered to send us five self-powered JBL 6208's, which immensely helped the process. [See the Audition of the 6208 in the May 1996 issue.]

Once we had the monitors, the next problem was placement of the rear speakers, which is supposed to be at 120-degree angles from the listening position. In our case, placement was inhibited by the door into the control room on one side and another door into the machine room on the other. Ultimately, we found the placement to be very forgiving and not that big a deal. For the subwoofer, we used the soffit-mounted main speakers, turned off the tweeter amp, and rolled off the low-pass filter on the playback channel.

Mix channel assignment to the mixdown deck was another problem. In this case, the '70s vintage Neve 807E had a quad mix bus, which meant that we could easily pan both left to right and front to back (see fig. 2). The center channel was put on a separate aux bus and the LFE channel was accessed through multitrack bus 1. Another way to do it would have been to use six aux busses for mix assignment, but you've got to have a console with plenty of aux sends so there will be some left over for effects. Although both methods work, neither is totally satisfactory in that panning is very imprecise. This is one of the areas where the new generation of post consoles with LCRSS (see glossary) panning really shine.

Monitoring is something we always take for granted as we're used to just reaching up for the Control Room Monitor pot to turn the level up or down. In 5.1 this is no longer possible unless you have either a film-dubbing console or one equipped with a postproduction module, like a Neve VRP or Otari PicMix, that can control six channels at once. In our case, we simply routed the outputs of the DA-88 mixdown deck into six of the subgroup channels of the Neve 8078, then connected the direct outs of the channels into the powered monitor speakers to control levels (see fig. 2). This is a little awkward in that you have six level controls instead of one, but it works.

Reverb is another potential problem. Although it's possible to take just one stereo reverb and pan it to all speakers, it sounds flat and uninteresting. In our case, Steve DeFuria of Lexicon brought a prototype multichannel reverb that allowed parameter control of all five main channels. This really brought the mix to life as the multichannel ambience was elevated to new heights of depth and realism. —Bobby Owsinski

\$1,295	2001 4 Channel Valve Mic Pre Amp
0 0 10 K 0	
\$1,295	2011 2 Channel 4 band Valve EQ
\$1,395	2012 2 Channel Parametric Valve EQ
\$1,395	2021 2 Channel Valve Compressor
\$1,295	2031 2 Channel Valve Overdrive Unit
a la contra	
\$1,395	2051 Mono Valve Voice Processor

0000000 0000 1,595 EQ-1 Dual Valve EQ 2,395 EQ-2 Stereo Valve Parametric EQ 1,795 C-1 Dual Valve Compressor \$1,695 PA-1 Dual Pentode Valve Pre-amp \$595 PA-2 Dual Valve Mic Pre-amp/DI TL Que \$795 VI-1 8 Channel Valve Interface ÷ .

\$595

VI-S 8 Channel Switching Unit

TWO **SERIES** ONE PHILOSOPHY

nannin nannin nann

hoose a valve signal processor from TL Audio and you're assured outstanding quality and the acclaimed warmth which only TL Audio Valve Technology can deliver.

The question is, which series to pick - Indigo or Classic? Not an easy choice, as they both offer a combination of superb design, quality manufacture and unique sound. It's more a question of application.

The Indigo range offers intuitive, easy-to-use valve processing at an incredibly affordable price, whilst the **Classic products feature** superb on-board mic pre amps and unparalleled control of all signal parameters.

The choice is yours!

SASCOM GROUP

Canada & USA: Sascom Marketing Group Tel: +1 905 - 469 8080 Fax: +1 905 - 469 1129 WEB: www.sascom.com

> For UK sales: Tony Larking Professional Sales Ltd. Letchworth, SG6 - 1AN (UK) Tel: +44 (0)1462 490600 Fax: +44 (0)1462 490700



POWER







World Radio History

TECHNIQUES

Music-only surround sound has no screen to focus on and therefore no exit-sign effect to worry about. Take away the screen, and it's now possible to utilize the surround speakers for more creative purposes.

TWO SCHOOLS OF THOUGHT

There are two schools of thought on how surround sound for music should be mixed. The classical way puts the music in the front speakers and the hall ambience in the surrounds, just as if you were sitting in the audience of a club or concert. This method frequently under utilizes the LFE channel by not using it at all or deriving it from the five main speakers. The demos I heard at IAMM where mostly classical and jazz, and they followed the same pattern of keeping most of the main band/orchestra information in the front speakers with just ambient info in the rear.

Now I believe that rock 'n' roll (and music in general) should be bigger than life, and using the surrounds for ambience is just not big enough for me. The more dramatic the better, I say, so I lean towards **5.1:** A surround-sound system utilizing six discrete speaker sources. Three across the front (left, center, right); two in the rear (left surround, right surround); plus a subwoofer (known as the Low-Frequency Effects channel or LFE.) (See fig. 1.)

SURROUND SOUND GLOSSARY

DAD: Digital Audio Disc. An audio-only DVD that will employ six-channel 5.1 surround, and maybe even more channels, as standard.

Dolby ProLogic: The home-theater decoder needed to decode a Dolby Stereo program.

Dolby Stereo: Surround system using four channels (left, center, right, and a mono surround) but encoded onto two tracks. It has the added advantage of playing back properly in stereo or mono even if no decoder is present.

DTS: Digital Theater Systems. This company has one of the most popular digital feature film release formats. Will introduce their own home theater 5.1 decoder soon.

DVD: Digital Video Disc [the precise def-

inition is still being debated]. The upcoming video CD format that will employ 5.1 surround as standard.

LCRS: A 4-channel system using left, center, right, and mono surround speakers. LCRSS: A 5-channel surround system using left, center, right and stereo surround speakers. This becomes a 5.1 system with the addition of an subwoofer (see LFE). LFE: A subwoofer which is the ".1" of the 5.1 (see fig. 1). The LFE channel rolls off somewhere between 80 and 125 Hz (depending on the system) and has an additional 10 dB of headroom.

Phantom Images: In stereo, the image that appears to come from between the speakers. This center image shifts as you move around the room

THX: A sound system package for theaters, consisting of speakers, amplifiers, and room voicing that employs 5.1 surround as standard. It is a standard designed to make the quality of sound more consistent from theater to theater.

ATTA

-Bobby Owsinski



The Quietest Bands On Tour. The PE 17 boasts noise and dynamic range performance surpassing 20-bit digital audio quality! With both input and output level controls you can always achieve maximum headroom with minimum noise.

Clean Up Your Room. With each of 5 bands able to access the entire audio spectrum, you can aim as many guns at feedback or sweetening as the situation demands. And with a bandwidth range from 1/30 to 2 octaves there is not much that can get by the PE 17.

Handles Rejection Well. With two extra filters for high and low shelving, you can tune out entire trouble areas of the rumble and squeak variety.

"Is That All?" The typical response to learning the price of all this quality. Rane performance, Rane value. The unbeatable combination.



PARAMETRIC EQUALIZER/NOTCH FILTER

RANE CORPORATION 10802-47th Ave.W., Mukilteo, WA 98275 (206) 355-6000 Fax (206) 347-775

CIRCLE 147 ON FREE INFO CARD

NICROPHONES

• AKG • Audix • Audio-Technica

- Beyer
 C-Ducer
- CAD-Equitek
 Countryman
- Crown Electro-Voice
- Groove Tube Microtech-Gefell • Ramsa • Samson
- Sennheiser Shure Sony Vega

PLAYERS, TURNTABLES

• Denon • Gemini • Marantz Shure • Stanton • Tascam Teac • Technics

RECORDERS



• Akai • Alesis • Digidesign **Digital Audio Lab**

Fostex • IVC • Marantz • Otari • Roland • Sony Tascam • TEAC Technics
 Telex

MEAT 'n POTATOES Full Compass carries tape,

patchbays,

connectors,

chemicals

... all the audio,

video and lighting acces-

sories you need!

EADPHONES & INTERCOMS

- AKG Audio-Technica Beyer
 Clear-Com
- Fostex Koss
- RTS Shure
- Sennheiser
- Sony Telex

SPEAKERS

- Alesis Anchor
- Audix Bag-End
 - Electro-Voice - Galaxy
 - Genelec JBL Klipsch
 - KRK PAS Ramsa
 - Turbosound
 - University Sound

SOFTWARE/ELECTRONIC MUSIC

 Digidesign • Digital Audio Labs • Opcode • Roland • Sound-Forge • Waves

- Alesis Allen-Heath
- Bogen Electro-Voice
- Fostex Furman Gemini Intelix

adda and

- Mackie Designs MTX
- Radio Systems
- Ramsa Rane Rolls
- Samick Shure
- Sony Soundcraft / Spirit
- Soundtech Soundtracs Stewart
- Studiomaster Tascam TOA
- University Sound

Check out our specials on the World Wide Web at www.fullcompass.com

TV/VIDEO

Bogen • JVC • Fast

- Horita
- Lowel-Light
- Panasonic Porta-Brace
- Sony Telex
- Videonics

GNAL PROCESSING

- AB International Alesis Aphex ART Ashly
 Behringer BBE • Brooke-
- Siren dbx DOD Digitech Drawmer
- Electro-Voice Eventide Furman
- Klark-Teknik Lexicon Rane Sabine
- SPL Symetrix Tascam TL-Audlo • TC Electronics • Valley Audio
- White Zoom

· 🕤 ··

AWARD DEALER!

V/SA

Ask for our **FREE catalog!**

(608) 831-7330 Fax (608) 831-6330 8001 Terrace Ave. Middleton, WI 53562



 AB International
 Alesis • BGW • Bogen • Carver Crown • Electro-Voice • Hafler • JVC

CIRCLE 34 ON FREE INFO CARD

Audio • Video • A/V • Lights

COMPASS

- QSC Ramsa Stewart Technics • University

OŇ NEW, DEMO

the second surround mixing method that puts the listener in the center of the band and envelopes him or her with sound. In this case, the band is spread all over the room via the five speakers and the LFE is used for bass and kick, which is also spread to the other speakers as well. The result is that it's bigger than anything you've ever heard. When you listen to Joe Houston in surround, you're on stage with Joe and he's singing and playing his sax directly to you.

PROBLEMS ALONG THE WAY

Despite the dramatic improvement in sound, there are still many hurdles to cross before surround sound becomes the standard listening fare. There are currently three major barriers, all of which are rapidly falling.

The first is the delivery medium. There is currently no product on the market that can deliver 5.1 surround, although almost all upcoming technologies — including DVD, HDTV, and cable and satellite transmissions — have 5.1 as standard in the specs (see the sidebar entitled "Surround Sound: When?"). However, DTS is soon releasing a decoder along with a fair amount of their own custom multichannel encoded CDs (including the Joe Houston CD) to support it, so this can now be within the immediate reach of consumers.

The second is a standards issue. An audio-only DVD has such an immense storage capability that the sample rate can be increased to 96 kHz (the current CD is 44.1 kHz) and the word length to 24 bits (currently 16). Although this means that sonic quality will skyrocket, it also means that the number of discrete channels will be limited, and there is considerable lobbying to make that limit as high as possible for future use (see "Surround Sound: When?" sidebar again). Luckily, the Audio Engineering Society has a task force that's addressing that issue as you read this.

The last is a hardware barrier, both for the consumer and the musicians, engineers, and producers making this multichannel music. Consumers will have to have at least six speakers and amplifiers, as well as a DVD player or surround decoder to hear surround. Recording studios will have to upgrade to support six discrete channels of mixdown information and include things like multichannel panners, reverbs, and monitoring (see the sidebar entitled "A Case Study"). That's a big monetary commitment, but there's no doubt that it's going to be worth it at some point.

Despite the above roadblocks and unknowns, just about everyone who has heard the format remains wildly optimistic about it. I've done demos for people that range from engineers, recording artists, and the everyday buying public (who in the end really makes any format go), and the overriding comment has been, "How can I get this in my home *now?*" Yes, I have heard the future and it's definitely surround sound. Every project I produce from now on will be done this way!

Bobby Owsinski is an L.A.-based blues musician who spends most of his time as a TV and record producer. He also lectures at Trebas Recording Institute about his former lifetime as a recording engineer.

MICVALVE – WOULD YOU BELIEVE A 20-BIT TUBE PREAMP?



W ITH ALMOST HALF A CENTURY in the professional audio industry, it's no surprise to learn that here at Studer, we understand tubes as well as we know digital audio. So when we added a "Tube Sound" model to our D19 Series of quality mic amps with upgradable 20-bit digital conversion, we didn't simulate it: we used the real thing —a pair of 12AT's (being European, we call them ECC81s) in each channel. Unlike other preamps that can only offer one



kind of "tube" sound, the new 2-channel **D19 MicVALVE** provides every possible variation—including switching the tubes out altogether for superb direct-to-digital recording.

They say hearing is believing. So listen to our 20-bit tubes, and hear why the **D19 MicVALVE** is more than just a tube preamp.



Studer. Engineering Quality.

Los Angeles: 818/703-1100. Nashville: 615/391-3399. New York: 212/807-0377. To:onto: 416/510-1347 London: +44 (0) 181 207 5050. Worldwide Distribution: Studer, Regensdorf, Switzerland -41 (0) 1 870 75 11.

CIRCLE TS ON TREE INFO CARD

THE FREE WORLD

The new KRK K-RoK close-field monitor looks as if it's been carved out of solid granite. These bizarre-looking little monsters feature a unique box design that produces better linearity and lowend punch than any monitor in their class.

Featuring a powerful 7" long-stroke

woofen a 1" silk-composite dome tweeter and fanatical KRK engineering, the affordable K-Roks (\$495.00 per pair) deliver the smooth response and high power handling capability that have made KRK monitors legendary.


Perfect for the home studio. K-RoKs provide world-class performance without blowing your budget. Why settle for some cheaply-constructed mini-

monitor when you can own an authentic KRK reference monitor for about the same dough? Contact your local KRK dealer for a K-RoK demonstration. K-RoK, fanatical by design. COME SEE US AT AES DEMO ROOM #306B



CIRCAR CARON FREE INFO CARD

Distributed by Group One East Coast Office: (516) 249-1399 • FAX (516) 753-1020 West Coast Office: (310) 656-2521 • FAX: (310) 656-2524 E-mail: jakel groupone@aol.com KRK Systems, Inc. 16612 Burke Lane Huntington Beach, CA 92647 (714) 841-1600 • FAX: (714) 375-6496 E-mail: krksys@msn.com




A look at Music City — from the top and bottom

I TOOK MY leave of the City of Angels six and one half years ago to do whatever the opposite of carpetbagging is in Navesh-veal, Ten C as they pronounce it down here. I had had my fill of the music business per se; I had persevered for 32 years, made my little mark, and satiated most of my goal desires. It was a time of change and I knew I needed another location. I had dropped out of the biz, but I would still run into the "music biz types" at the market, the movies, or a concert. I didn't want to see these people anymore. I really wanted to drop out. I bumped into Steve Cropper in Ralph's Supermarket in the San Fernando Valley one smoggy afternoon. I never mind running into Steve. 1 asked him what he was up to and it seemed he was trying desperately to sell his L.A. house because he had just emigrated to Naveshveal.

"You'd love it down there, Al. I'm tellin' ya, check it out," he enticed.

And because I was ready to do such a thing, I took an exploratory journey. Now, mind you, I had spent a fair amount of time in Nashville in my life up till then. I first went with Bob Dylan to record Blonde On Blonde there. Charmed by that experience, I went back and cut I Stand Alone, my first solo album there. Through the mid-'70s, I returned many times to produce albums there, utilizing the various Memphis and Muscle Shoals expatriate musicians who had gathered there for good. And lo, it was good. Except for the food. But I really hadn't been back for about 15 years, so I spent a week looking around and found what I wanted. Nice weather, nice people, slightly better food, and no matter what direction you walked in for a distance of 200 miles, you were certain not to bump into anyone from Geffen Records. For this time in my life, aged 46, it seemed a wise move.

Away I went. In May of 1990, I



bought a nice house that would have sold for \$800,000 in L.A. (at that time) for less than a quarter of that. On New Year's Eve of 1990, I rescued a cute puppy from the pound, and that was the last piece of the puzzle.

Today's Nashville is radically different from that of the mid-70's. For one, there is now parity of food quality in at least half the restaurants. But don't be misled. This is *not* Music City, USA, dear readers, this is *Country* Music City, USA.

Now what does this mean, Al?

Well, for one thing, someone put some kind of curse on rock 'n' roll in this town. No rock act has ever skyrocketed out of Nashville. (No, Jason and the Scorchers doesn't count. They did *not* skyrocket.)

So, if you don't play country, don't come here to be discovered. That is to say, you may be discovered, but *the curse* will instantly befall you! Now, that said. there are some great, organic musicians and singers that live and play out here that don't play country — Johnny Neel, late of the Allmans; Jimmy Hall, late of Wet Willie; and Larry Carlton, one of the great jazz guitarists of all time, to name but three. The Queen Of Live Music in Nashville, however, is Jonelle Mosser.

Never heard of her?

She's cursed, va know.

Don Was heard her play live while having a drink here one

If you don't know who Al Kooper is, please stop reading this magazine. night and signed her right up. Now she had one of the best bands in town, called Enough Rope (how prophetic). So Don got her to vacation from her band and join one of his side trips — a band called The New Maroons with Ringo Starr on drums, Don Was on bass, Benmont Tench (from the Heartbreakers) on key-



Skyline by David Wright, Grand Ole Opry courtesy of the Nashville Convention and Visitors Bureau Wildhorse Saloon by Donnie Beauchamp



"Souvenir shops pretending to be better than that like The Hard Rock Cafe, Planet Hollywood, and the Wildhorse Saloon, smile at you as you stroll downtown looking for something to remind you that you're still in Nashville."

a like I first did), Gary's Nicholson

and Burr, Dennis Morgan, Mike Reid, and Tom Shapiro are just a handful of about 20 more who are all over the country charts on a consistent basis. Today in Nashville, 95 percent of all writing is done in "dentist appointments." These are three-to-four-hour blocks of time that are prebooked by the writer's involved. So Gary Nicholson will get a call from, say, Delbert McClinton asking Gary



boards, and Mark Goldenberg on guitar. They played at Farm Aid, cut an album for Don's own label, and Jonelle walked around town like royalty.

Silly girl: she forgot about the curse.

The next instant, Don Was folded up his label and Jonelle and fellow Nashvillian Felix Cavaliere (also signed to Was's label) found themselves in Nashville, 10 quote Maxine Nightingale "...right back where they started from ... " For Cavaliere, whose Rascals' songs sell cars and tanning oil nowadays, it was no great loss. For Mosser, it was everything. Her band had splintered while she was lovingly glancing at Was and Ringo, so she assembled a new band, albeit, not as good as the old one, and went back to being The Oueen Of Live Music in Nashville, another victim of the curse.

'Shville (as our Jewish residents refer to our town) is the songwriter's capital of the world. There are some amazing writers living here that have raised the craft itself up a few notches. If you get in the clique, you can make some large "mailbox money" (as they refer to royalty checks here) in no time. Matraca Berg, (pronounced Muh-trace-ah; so you don't embarrass yourself with a Ma-track-

Photo by Jim Herringtor

WANTED

Self-contained digital recorder/mixer combo as easy to use and durable as my TASCAM Portastudio. No hard disk systems, please! Allan 646-3035

FOR SAME

Hard Disk Recording stem. Like new. Good but difficult operate. If you're a computer progra ner this is for you. Mark 565-5791.

★ ★ FOR SALE ★

Yamaha digital recorder. No jog nuttle wheel, no digital out, no so mute and slow drive mechanism track outputs, not enough AUXes. Wi sell cheap! Make an offer. Call Dick after 5 p 0154.

Established working party rock band seeks digital multitrack recording system with 2 AUX sends and 2 stereo AUX returns, 4 XLR mic inputs, channel inserts and individual track outputs cue outputs are a real plus. Call Gasn parks 454-3651

FOR SALE

ADAT and Mackie 8-Bus. Must sell, Looking to buy an integrated system that takes up less space and easi

WANTED

Digital multitrack system with jog / shuttle wheel for easy editing. Mick 44-3169

BODY PIERCING FOR BANDS If you've got the flesh, we've got the tools. Call INTooU 258-9631.

WANTED

ADAT transports. We can use all w can get. DMR Repair Services 767-01

Smashed my hard disk record Τοο many menus made me q mad. Looking for artist who can u it in an abstract sculpture, or se captain looking for anchor. Call Tre 457-9851.

FOR SAI

Yamaha MT8X. I tho ght it was a Portastudio. It's not. N er was. Never Gary 543-1010. will be. Best offer takes

ATTENTION COLLECTORS

dition TASCAM Priceless first Portastudio, This is the multitrack recorder that revo tionized the music business and changed the face or recording. Seri I number 00001. \$12,000

NEEDED

Stereo digital outputs on a low cost digital 4-track for making digital masters on DAT. Call Ken 799-0025.

ALTERNATIVE BANDS?

Looking for a record deal? Send your demo tapes for consideration. Eddy 445-8870

Web page design & hosting for your band. Cheap. Call Scott 255-5569.

Band looking for drummer. We've been through five. Can you hang for more than a week? Roger 626-3030.

* * FOR SALE * * Mirror ball, bell bottoms, platform shoes and leisure suits. Perfect for retro bands. Call Slick 217-8414

WANTED

Digital recording system that's easy to use and uses low cost removable MiniDiscs. Call Tina 555-2598.

ompany that make There's only o Portastudios. t the details via fax 800-827-2268 et 8320.

nted. Komodo Dragon or other or lizard for ba d mascot at live Go-T 555 shov 952

Female county vocalist wanted by songwriter to develop hit records Have full arsenal of TASCAM recording gear. Call Willie 236-6665.

· Female lead, rhythm, bass guitarist and drummer wanted. Must be able to write music and be willing to tour. Recording experience a real plus.

• • WANTED!! • •

High Performance Digital Recording System that costs less than \$1500 AND uses a non-destructive editing process - must be easy to use. Kar 78-1321

★ GUITAR LESSONS ★ earn those licks. Do five takes track on a Digital Portastudio. eter 256-5584.

Wanted By Musicians **Everywhere.**

ò

0 9

The Digital Portastudio.

It's the real thing. A Portastudio. Best part is, this one's digital. And who else could deliver the best MiniDisc multitrack digital recorder? TASCAM - the only company that makes Portastudios. With more than 15 years of designing and building the best recording products, TASCAM knows

recording better than anyone. The 564 Digital Portastudio has everything you want -

powerful features, impressive flexibility and great sound. And at only \$1499, it's worth every penny. Don't settle for anything less - because your next demo may end up a master! Find out what

the 564 can do for you. Get the full Digital Portastudio

story via fax by calling 800-827-2268, request document number 8320.



Take advantage of our experience.

5 TAKES PER TRACK?

Plus capability up to 5 song sectors. 20 indexes per song and bounce forward? Need advanced editing features! Traditional Portastudio ease-ofuse preferred. Call Eduardo 777-101

Spike st bought a ortastudio. Can't wait to lav digita dow racks. Yes. You can do your times and we'll still be able to lead he first one — cause you know US always your best.

DRUMMER WANTED

by signed band. Send tape, photo & bio. POB 2928, Newport, CA 92659.

Desperatoly Seeking Digital Simplicity. le 251-4292

Looking for a digital 4-track XLR input and mid range sweep EQ. Must be built by the company that invented cost effective multitrack recording. No imitators or motorcycle manufacture uck 858-6651.

USED GUITAR STRINGS

If you want them, I've got them. Some broken, some used by the biggest stars. Electronic and acoustic.Good 555-0973 - Call Razor

WANTED

Digital recording system that is selfcontained and offers five takes per track. Must have random access and instant locate capabilities. Will pa sh 588-7462

MAKE A LOTTA NOISE

Huge rehearsal hall for rent. Open 24 ours. Call Max dB at 555-8711.

NEEDED

Sm band on the rise looking for top soun echnicians. No newcomers to the biz p dollar paid. Sid, 556-2890.

• EQUIMMENT FOR RENT •

Top of the lif recording equipment. All TASCAM o inponents. We deliver. Rent per day, v ek or month. Call us 24 hr. 556-8293.

Need a MiniDisc digital recording sys tem that does more. Will pay a little more for the extra features. Must have digital out killer-mid-range sweep. 39-9511.

Techno Rap Band Seeks Digital Recorder that does everything: MTC or MIDI clock, editing effects like bounce forward, cut, copy, move. Undo capability a must. Ask for Father Flack 8-4775.

WARNING!

Not all MiniDisc systems are created equal. Don't settle for cheap imitations. Get the new TASCAM 564 Portastudio Facts via fax. Call 1-800-827-2268. No one's ever sorry for buying the best.

1996 TASCAM

E.B. MUSICIAN S CONNECTION CLASSIFIED

CIRCLE 85 ON FREE INFO CARD

ASCAM





RECORDING You can get the practical, real-world skills needed to successfully start your career as a recording engineer, producer or studio musician. •Hands-on approach, learning by doing • Previous experience not required • Complete 300 hours of training in less than 2 months •6 studios filled with the latest equipment •Small classes, excellent personal attention • Job placement assistance • Financial aid available ·Low cost, on-campus housing

For free brochure, call or write today 1-800-848-9900 1-614-663-2544



THE RECORDING WORKSHOP 455-Q Massieville Rd WorkShop Chillicothe, Ohio 45601 ard of Proprietary School Registration #80-07-0696T



to hold Tuesday at 2 PM for him. On Monday at 10 AM, Del will write a song with Writer A until 2 PM. Then at 2 PM he will write with Writer B until 6 PM. By the time he gets to Gary, he will have written three songs with three other writers in a two-day period. That's why I call 'em dentist appointments. Personally, I feel it's demeaning and uninspired, but that's how it's done here in the '90s - and it works quite well for them. What do I know?

Another peculiarity is Nashville's famed numbers system. This is a simplified way of reading music that is commonly used by studio musicians at every session. The chords are replaced by their musical numbers (e.g., if you're in

> THE GREENING OF NASHVILLE WORDS & MUSIC BY **AL KOOPER**

You used to be able to park on a slant down Broadway You could even take a stroll along Second Avenue And we used to love Centennial Park In the daytime or in the dark Before the carjackers and the muggers all came through

THE GREENING OF NASHVILLE The influx of cash will drag our city on down

My baby and me bought a house right here in Green Hills The house is still here but my baby is long since gone Then some stores disappeared one day and Became the entrance to the Hard Rock Cafe Now there's no music --- just a tour bus Comin' outa Bradley's Barn

THE GREENING OF NASHVILLE The influx of cash will tear our city on down

Li'l ole church on the corner Been here for so many years Gonna have a big arena next to it Gotta sell that hockey beer Wildhorse Saloon Gonna build Planet Hollywood soon Hope they leave some room for BB King's

If ya don't want a buncha people movin' here from California Stop tryin' to make this place the next L.A. What happened to democracy Why can't they just let things be ? In politics I guess every dog has got to have his day

THE GREENING OF NASHVILLE It seems that the cash will Take away our small town

1995 Rekooped Music BMI

the key of C, C is 1, F is 4, A minor is 6m, etc.). They are written in 16-bar phrases on the paper (e.g., 6M 2 5 4 | 1 3m 4 5 etc.; each number represents one bar). As far as I know, this is an aberration common only to Nashville. At any rate, any musician worth his salt can translate this system in a matter of moments.

The studio scene is hard to break into. The musicians on the A list are some of the most amazing ones l've heard in any city. Eddie Bayers on drums, Glenn Worf on bass, Brent Rowan on guitar, and Matt Rollings on keyboards could scare the pants off any L.A. or NYC musician. And then wouldn't they look silly sitting around in

their underwear?

The bars are filled with either songwriter-in-theround shows or R&B bands. There are very few country bands playing the bar circuit. Ergo, it's easy to hear non-country live music if you go clubbing. The musicianship level in the clubs is the highest of any city in the U.S. Even the so-called local punk bands are <mark>compa</mark>ratively more musically literate than any of their contemporaries in any city. For instance, the best blues band in town consists of studio guys, who are blues historians, blowing off steam one or two nights a week. The only city that could give them competition is Chicago, and they'd probably only open a few eyes there. The Bluebloods, together six years, are releasing their first CD on the local Dead Reckoning label this month.

If you just know a few chords, you're good looking, and have a stage attitude, Nashville is not the

CIRCLE 26 ON FREE INFO CARD

"The Next Level In Sonic Quality" "Vastly Improved Transport" "Amazing Technology"

In every case, the XT demonstrated a noticeable improvement in sonic detail over the original ADAT." George Petersen, Editor, MIX Magazine

ALEEL

"The XT's improvements in sound quality, transport speed, and lock-up time alone are worth the price. I believe that the XT makes recordists an offer they just can't refuse." *Michael Molenda, Editor, Electronic Musician Magazine*

The Experts On adai Xt

"The XT has new A/D and D/A converters, and the improvement in sound quality is unmistakable. If you are looking to take your ADAT-based studio to the next level in sonic quality, features and raw speed, the ADAT-XT lives up to its hype." Loren Alldrin, Reviewer, Pro Audio Review Magazine

> "When you use the machine, the first thing you notice is the vastly improved transport." Paul J. Stamler, Reviewer, Recording Magazine

"This review of the ADAT-XT can be summed up in three short lines: I used it. I loved it. I'll take it." Greg Rule, Assistant Editor, Keyboard Magazine

"The bottom line, as Casey Stengel used to say: 'Amazing, amazing, amazing.' That is, amazing technology, amazing functionality, and amazing price." Howard Massey, Technology Editor, Musician Magazine

CIRCLE 03 ON FREE INFO CARD

ESIS

For more information on the ADAT-XT, see your Authorized Alexis Dealer or call 310-841-2272. Alexis and ADAT are registered trademarks, ADAT-XT is a trademark of Alexis Corporation. Alesis Corporation 3630 Holdrege Avenue Los Angeles CA 90016 310-841-2272 alecorp@alexis1.usa.com

Photo of riverfront buildings by Robin Hood

"If you just know a few chords, you're good looking, and have a stage attitude, Nashville is NOT the place where you have a chance of succeeding."



If you think professional automation is too D expensive..... A



Think again! Optifile DRAX for 8-bus has arrived







Optifile Drax prices start as low as \$2,995 for 32 channel system. Installed inside your console. Uses existing faders and mutes. No external fader pack required. TimeCode based.

68 OCTOBER EQ CIRCLE 58 ON FREE INFO CARD COME SEE US AT AES BOOTH #763 place where you have a chance of succeeding. And, of course, there's still *the curse* to overcome.

Adrian Belew and Jill Sobule felt the curse and had to move away to achieve success. Adrian has now moved back, no longer concerned about it. Jill's gonna see how her third album does first.

Nash Vegas has its share of noncountry, veteran musical residents. Michael McDonald, Ed King, Pelix Cavaliere, Leon Russell. Larry Carlton, Tony Joe White, John Prine, Steve Winwood, and Donna Summer are but a few of the immigrants. But Nashville has begun to change in an inevitable, ugly way.

I always thought the city fathers here were geniuses. The whole tourist business was set up on the outskirts of town by the airport at Opryland. A giant theater. hotel, and theme park attracted people from the world over. They would mostly never leave the Opryland complex during their stay in our fair city. Locals could easily circumnavigate the downtown area, even at the height of tourist season.

Those days are over, my friends.

Some new "geniuses" decided to gentrify the downtown area and began with some pretty bold strokes. A huge 20.000-seat arena juts out onto Broadway at 5th Avenue now. Second Avenue, which remained unchanged from its '50s look, is a whole new tourist trap thang now. Souvenir shops pretending to be better than that like The Hard Rock Cafe, Planet Hollywood, and the Wildhorse Saloon, smile at you like rapists as you stroll downtown looking for something to remind you that you're still in Nashville. When the arena opens, a whole new set of horrors will take place when 20,000 people try to park their cars and then exit the arena later. I'll read about that carnage in the local paper. I'll be in my basement studio (Subterranean Homesick Sound) non-stop on weekends from then on.

Presenting some of the best things ever heard on our studio tapes.

"In our search to find a replacement for 996, we found something better. The BASF SM 900 runs clean and is transparent-everything else is an effect. It's our new house tape."

- Joe, Bruce, Dee Robb Cherokee Studios

"SM 468 is really clear, sounds closest to my console, and has been my favorite for 10-15 years. Now, though, everyone wants the elevated levels. SM 900 gives me the compression at the harder levels, plus the clarity of the 468."

- Joe Chiccarelli

"I've tried everything else. Once."

- John Jennings

"It created a whole complete area of sound that did not exist before."

- Michael Beinhorn

"I had to look to see if the band was in the control room or playing live, because this stuff has so much dimension to it."

- Don Smith



"The music sounded better coming off the tape than it did going on it."

- - Skip Saylor

"It's simple. I use it because I like it. I like it for the way it sounds."

Richard Dodd




CIRCLE 12 ON FREE INFO CARD

To hear the tape that's causing all the talk call; USA 1-800-225-4350; FAX: 1-800-446 BASF; Canada 1-800-661-8273; Europe (49) 621-59 20-366 World Radio History If I didn't have that wonderful home studio (TASCAM 3500 console, TASCAM DA-88's, Electro-Voice 802 nearfields, Korg synths, Rane outboard gear, Lexicon JamMan, and Audio-Technica, Sennheiser, and E-V mics), I wouldn't have a lick of trouble finding a suitable place to record. I love smallish dead rooms. All the Skynyrd albums and the first Tubes album I produced were all cut in rooms like that.

When I first arrived, I found a great room two blocks (walking distance) from my house. However, within two years they rebuilt the room to be live and the fun was over. I still mix all my stuff in the control room there,

but, sadly, the room don't work for me no more. However, most studios in town have huge A rooms and similarly small B rooms with a wide price range. Digital mastering (the way to go today) is readily available, and people are making great-sounding records here. Mark Knopfler cut a lot of his recent solo album in town. Most folks use their home studios for great demos and still pay the big boys when the serious shit goes down. I've cut about four tracks and a filmscore in my home studio that have been commercially released, but I've cut 60 demos that are just demos as well. When I make my own albums, I book



the real studios. The rule-of-thumb down here is, usually, MIDI demos and real-live musician masters.

The music stores in town still have a lot to learn. Prices are higher than the real big cities and the staffs are bloodthirstily on commission and comparatively incompetent. There are exceptions, but there's no Manny's or Guitar Center vibes or prices down here. I tried to shop here unsuccessfully, so my business usually goes to NYC with a quick phone call. This will hopefully change real soon.

There are some great places to hang out here. The Sunset Grill is a fine restaurant and bar unlike its L.A. namesake. Every Monday night, The aforementioned Bluebloods play at the usually "kempt" Bluebird Cafe. Monday nights it goes from being the premiere quiet listening room to a rowdy, mainstream blues club where Sam, the bartender, slides the longnecks continuously down the bar. John Prine, Gatemouth Brown, Joe Ely, and Billy Gibbons have all been Monday visitors in awe of Michael Henderson's guitar individualism. 328 Performance Hall is host to the visiting headliners like The Band, Son Volt, Everclear, The Subdudes, Little Feat, and John Hiatt (another local). The Exit/Inn handles most of the alternative bookings mixing local talent with visiting MTV bands. The Ace of Clubs plays an eclectic mix of music during the week and turns into a dance disco joint (replete with go-go girls) on weekends. [See the Club Profile on page 1041

My pet peeves are no New York serious delicatessen and no Chinese food of any repute. Then there's the home hanging factor. Everyone is so focused on making it, on their agendas and priorities, that the little home gatherings I am used to from living on both coasts don't really exist here. Two or three people rarely come over to your house or invite you to theirs, preferring the ambience of a local bar instead. At first, I took it personally, but then I realized, hey nobody is doing this - it's not just me! Maybe twice a year, under the pretense of a "party," do the guys come over to watch my funny video collection. Even NBA games are perused in sports bars. I'm over it - I'm used to it. I do sneak off to NYC quite a bit though; I hang out at Barbara, Nancy, or Mookie's house and order matzo ball soup or Peking duck and then all my friends come over and we watch the Knicks game and shoot the shit. Who knows? Maybe this will be Nashville 2000...but meanwhile check out the sidebar/song "The Greening of Nashville." EØ

70 OCTOBER EQ

CIRCLE 56 ON FREE INFO CARD

Roadworthy and Streetwise

Once again Peavey raises the ante for playing in the Sound Reinforcement game...

The world's most rugged and reliable sound reinforcement enclosures just got better. Having experienced substantial feature improvements, the SP[™]enclosures still maintain their highly competitive prices.

The full-range PA enclosures now feature trapezoidal cabinets, the SP[™] 2G and SP[™] 4G offer improved performance Black Widow[®] woofers, and each enclosure is equipped with the revolutionary new high-frequency driver protection, the Sound

Guard[™] circuit.

Sound Guard, Peavey's innovative protection circuit, is





not just a series bulb, but a high-tech switching mechanism that doesn't affect the original signal until excessive power is introduced into the system. Only then does the signal see the protection circuit that offers a more linear approach than the usual light bulb.

New to the SP line are two new floor monitors, the SP[™] 112M and SP[™] 115M. Both monitors feature the 22XT[™] and Black Widow high-

performance components, as well as the trend-setting Sound Guard driver protection circuit.

Visit your authorized dealer for a demo of these incredible sounding, high-performance enclosures from Peavey.



The MONITOR Magazine is a publication filled with the latest information inusicians want to know. To receive 4 issues for only \$5 (price good in U.S. only), send check or money order to: Monitor Magazine, Peavey Electronics. 711 A Street, Meridian, MS 39301 • (601) 483-5365 • Fax (601) 486-1278 • http://www.peavey.com • AOL Keyword: Peavey • CompuServe: Go Peavey • ©1996



Nashville State of Mind

WHAT WAS A nice guy like Tony Brown, president of MCA Records Nashville, doing in Nice, France last week? Could be he was following the lead for an undiscovered talent hiding out in the hills of the Alpes-Maritimes? Not. The award-winning producer of quality songs and tasty tracks was taking a well-deserved break.

The helm of the MCA flagship is charting right on course with Brown steering the creative wheel. MCA generates the largest piece of the two-billion-dollar (gross sales) country music pie, and Brown served up half a billion of those sales.

This year alone, Brown is delivering first-class product from Vince Gill, George Strait, Wynona, Bobbie Cryner, Todd Snider, David Lee Murphy, and Tracy Byrd, as well as tracks for a Mark Chestnutt "greatest hits" release. He has

Y

C

B

The Demo Queen takes on the King of the Nashville Music Scene straight from Music Row

> also produced hit albums for Reba McEntire, Lyle Lovett, Trisha Yearwood, Marty Stuart, Rodney Crowell, Patty Loveless, and Steve Earle.

> With 62 number one singles and 50 million units circulating around the globe with his name as producer, Brown knows his way around a session and a studio. James Burton, of Elvis, Jerry Lee Lewis, & Rickie Nelson fame — not to mention the coolest paisley guitar around — worked with Brown on early Mark Collie sessions. "Tony had an easy way of explaining his ideas to mu-

> > R

Photos by Beth Gwinn

World Radio History

sicians and a sharp ear," Burton says. "He took care of biz."


"I like being around talented people," Brown, dripping with executive vibe, confessed to the Demo Queen during a recent interview in his plush corner office overloo cing Music Row in Nashville. "Working with

Emmy Lou Harris, Cash, and Crowell represented the 'hip' factor, and when I got a chance to work with Reba, I thought everyone's going to think I've sold out." Brown explained, "But guess what: Reba is cocl, too. If somebody is esoteric and I think they are really good, I will stand up and fight for them, and if somebody is mainstream and they reach me, I'll do the same. It was eye opening to me, the art of mainstream and the art of left of center, and the sooner that's understood the more fun you have."

Such focus and love of music led

E

R



Brown to what he calls "my greatest moment" when he played keyboards with the Cherry Bombs, a band spearheaded by Rosanne Cash and Rodney Crowell. It was this gig that introduced Brown to a then unknown guitarist who sang backgrounds by the name of Vince Gill. Following the Bomb stint, Brown took a job in A&R for RCA and signed Gill, but left three months later for greener pastures at MCA. He still believed in the laid-back tenor, and hooked Gill for MCA after he was dropped, sailing on to produce seven albums with Gill, two of those triple platinum. Defending his signing of Gill and the deal with it to an L.A. co-worker that asked, "Who do you think you are signing...Elvis?" Brown responded, "Maybe!"

Vince Gill has gone on to win more CMA awards than any other entertainer, including vocalist of the year for the past five years. Reminiscing about signing Gill, Brown says, "Every A&R person's dream is to sign one of your friends."

Sporting a green malachite ring Elvis gave him from his early days of playing plano in Elvis's gospel group. The Voice, Brown spoke in a slightly Southern, yet sonorous baritone. "What I have going for me is my gut, and I love to work with engineers who are on the leading edge like a Roger Nichols or a George Massenburg. Any technical advantage I have comes from the engineer I work with."

Gene Eichelberger, early audio pioneer and famous for wearing T-shirts that said, "When You're Good, You Don't Have To Be Friendly," was one of the first engineers Tony worked with when he hit town. They recorded Shirley Caesar, a Grammy-nominated gospel project, at Quadraphonics Studio on the Quad 8 console with 2-band EQ or, as Eichelberger put it, "hi and low."


These days Brown has a bigger budget and says, "If I have my way, I cut on a Neve console and mix on SSL. Engineers love SSL consoles because it's a user friendly format and easy to remix on. I initially worked on SSL because of [Jimmy] Bowen. To work with Bowen was a career making move for me."

Jimmy Bowen, who was a successful leader in the push to put country music on the profit ledger sheets, now lives in Hawaii, but maintains an office in Nashville. The unorthodox Bowen took a technologically stunted Nashville by storm and is

credited with bringing state-of-the-art recording to Music City. Brown labels Bowen "The Great Professor." Bowen started in the music business as a singer

on Roulette Records in the '50s, and went on to work with Sinatra and Dean Martin before the Nashville years. "He taught me how to do a lot of things at once," Brown continues, "and at the end of the day, nine times out of ten, the artist is right." [Jimmy Bowen was profiled in our April '92 cover story.]

Described in his own words as a benevolent dictator, Jimmy Bowen is finishing up his biography, tentatively titled, *Roughmix*, (Simon & Schuster). When asked about Brown, who he recruited to



the A&R staff at MCA in the mid '80s with a promise to let him produce, Bowen said, "The key to Tony is he knows a quality product. I believed in him and his ability to help the artist do the music."

Doing the music can be a subjective call, and Bowen was notorious for recording several projects at once. Brown has a different approach. He elaborated with, "Bowen would cut tracks and let engineers do overdubs and vocals, then he would check in for the mix, starting another project during overdubbing. I found that I can only start another project during the mixing process because


during the overdubs I want to be there for every note that's struck and I want to do every vocal comp myself.

"At the end of the day nine times out

"What intrigues people is how fast country music can be recorded, but when I listen to interviews with the Stones and Eric Clapton they talk about the great recordings they've done in two

days. George Strait and Reba McEntire record tracks in four days, start at noon and end at seven." Brown continues, "And after each song I send the musicians out and do four vocal tracks. I once asked George, who likes to get back to his home in San Antonio, what do I do if I don't get vour vocal in those four days? George said, 'Have I ever let you down?' After five albums, I had to say no."

"Tony doesn't twiddle with the knobs," said Chuck Ainlay, an engineer who works closely with Brown. When



"I want to be there for every note that's struck and I want to do every vocal comp myself."

World Radio History

GET MORE. EQ's NOW WITH CONSTANT Q

> 63 80

• Constant Q filtering

• THD: 0.003% @ 1kHz

• Signal to Noise: >90dB

• Internal Power Supply

• Affordable Price

• Made in USA

• Impedance

XLR Inputs

and Outputs

Balanced 1/4"

and Balanced

• Low Cut Filter

CHANNEL 1

CHANNEL 2

1K 125K 1.6K 2K

100 125 160 200 250 315 400 500 630 800

+18 +10 0 -10 GAIN OUT 2 すすけと言 +12 +18 +10 0 -10

OUT 1

PAY LESS.

The new DOD SR series EQ's will surprise you with features you thought could only be found in EQ's costing \$100's more. Constant Q filter technology ensures stable bandwidth and response at any slider setting. Impeccable THD and noise specs make your job easier by keeping your sound clean and the switchable low cut filter offers instant protection against sudden low frequency overloads. DOD delivers these and other professional features that today's sound engineers demand. Check out the new SR EQ's at your DOD dealer today and let your ears and your budget be pleasantly surprised.


30

.

A Harman International Company

8760 South Sandy Parkway, Sandy Utah USA 84070 (801) 566-8800 (801) 566-7005 Fax • Int'l Fax (603) 672-4246 Visit us on the World Wide Web at http://www.dod.com

CIRCLE 90 ON FREE INFO CARD



14 NEW! Professional Power Amplifiers



The **WORLDTM** is a series of 5 amplifiers designed with versatility for a multitude of applications from Recording & Live Sound to the Sound Reinforcement arena. TEC award winning technology. Power outputs from 250W, 600W, 1200W 1.6K & 2.1K at 4 ohms bridged. Stable at 2 ohms.



The **CONTRACTOR SERIESTM** features two of the most powerful 70Volt models in the marketplace with two additional models for 4 and 8 ohm fixed applications. Complete with remote turn-on capabilities. Selectable High Pass Filter for each channel and front detented level controls with security covers.

KEY FEATURES

- TEC Award Winning Class H Amplifiers
- Ultra Efficient Switch Mode Power Supply
- Harmonic Shift CorrectionTM
- Ultra Flat Response
- In Rush Current Limiting[™]
- World Class Reliability
- Crystal Clear High Frequency
- 7 Stage Circuitguard Protection™
- Unsurpassed Low Frequency Response

Made in the USA

The HPA-1000 is THX® licensed for home theater

use. Rated @ 350 x 2 @ 4 ohms and capable of 1000 watts in bridged mono. Seven Stage Circuitguard ProtectionTM and low amperage draw



PRO REFERENCETM features two amplifiers that are perfect for Professional Recording Studios, Broadcast and Project Studio applications. Polished chrome face plates and gold plated input and output connectors.



MONDO™ is touring sound at its best! Power output ranging 4200W to 8400W (a 4 Ohms Bridged, XLR + Barrier Strip Unbalanced/Balanced inputs, 6 Gauge 5-way Binding Post outputs and highly efficient low AC amperage draw.



120 Blue Ravine Road, #2 • Folsom, CA 95630 Tel: 916 985.7200 • Fax: 916/985.7600 asked about recording specifics, Ainlay went on to say the team usually mixes one tune a day through the HDCD Box (20-bit) to a Sony PCM 9000 and does not EQ. Recording great vocals is another thing they do well, and, according to Ainlay, it's easy to do with a "good mic and a good environment."

Brown, being a self-proclaimed "dig" (digital) man, uses his gut feeling to pick microphones, sometimes going against the status quo. For picking gear, Brown offers, "If someone says you can't use this mic with this voice, then I say, why not? Let me hear it." On a recent Tracy Byrd project, the Audio-Technica (4050) caught Brown's ear. For Gill he prefers the AKG C12, and on Wynona the Neumann U47.

As far as a good environment goes, there is no shortage of great studios in Nashville. The newest entry (and location of our photo shoot) is Starstruck, affectionately known as Reba's World by the locals, since McEntire et al funded the complex. Designed by Grant and Associates, the same company that brought us Peter Gabriel's Real World Studio and all five rooms at the Hit Factory, Starstruck stands out on Music Row with crisply modern architecture, unique privacy windows that can switch from translucent to opaque, and no corners cut in the gear department.

Both studios in the complex are 100-percent linked together with MIDI, SMPTE, digital, analog, and video, and fully stacked with outboard gear, much to the dismay of the rental companies. If that doesn't phase you, each room contains the SSL 9000 J series console sharing the 48-channel DiscTracker. Being a Demo Queen, the elevated platform in "The Gallery" tracking room for those performers who want to "feel high" won my vote in the "something new" category.

Speaking of demos, Brown was not impressed when asked if mastered

76 OCTOBER EQ

CIRCLE 76 ON FREE INFO CARD

DON'T LET ANYTHING COME BETWEEN YOU AND YOUR MUSIC.

Introducing the quietest* and most transparent 8-bus console in the industry, the new Dual Input 48/24 EURODESK MX 8000 from Behringer.



Your Ear is Our Judge

Suggested retail price for the EURODESK MX 8000 is \$2795.

*The EURODESK, like all Behringer mixers, is the only one in its class using 4580 operational amplifiers which provide 30% quieter performance overall.

Also available with optional meter bridge and CYBERMIX automation for PCs running Windows. For a free EURODESK brochure, please call 1-800-328-2882 and ask Behringer Sales, fax (516) 364-3888 or write to Behringer Sales, Samson Technologies Corp., P.O. Box 9031, Syosset, NY 11791-9031. Behringer is exclusively distributed in the U.S. and Canada by Samson Technologies Corp. ©1996 SAMSON

> CIRCLE 09 ON FREE INFO CARD World Radio History





"What I have going for me is my gut, and I love to work with engineers who are on the leading edge. Any technical advantage I have comes from the engineer I work with."

demos caught his attention when looking for material. Songwriters, grasping for anything that might get their material a listen by the right ears, spend money mastering demos, hoping to attract attention to their better sounding tapes.

For Brown, "What makes me like something is the song — the demo could be done on a boom box. Sometimes I copy licks from the demo, but if I like the song, I can hear the band playing it in my head."

Sounds like music to the Demo Queen, and Brown angled in one last important point. "Working with musicians is not unlike talking to a woman. You have to be nice." Nice.

Hey ho...

EQ

94 State Street • New London, CT 06320 USA • Fax: 860-442-0463 • E-mail: sales@carusa.net • http://www.carusa.net

you can't expect.

...engineering this revolutionary, design & build of this quality...

sound this clear.

Focustu

FOCUS ED

...distortion this low, bandwidth this wide...



at this price... ...can you?

DUAL MIC PRE

Two channels of the latest Focusrite microphone preamplifier with +48V phantom power, phase and 75Hz hi pass filter, plus overload LED. Balanced line output will drive long lines without signal deterioration.

FOCUS EQ

New Green Range Mic Preamp plus balanced line input and high impedance instrument input, followed by enhanced four band parametric EQ with hi and lo pass filters. Output fader; balanced line output.

VOICEBOX

\$ 1.349 U.S.*

\$ 1.249U.S.*

New Green Range Mic Pre followed by compressor, de-esser, 3-band EQ. Downward Expander. Balanced line output. Output fader. The ultimate input stage for vocals recording, live & post production voiceovers.

* suggested retail price



Focusrite GREEN RANGE

CIRCLE 28 ON FREE INFO CARD

Affordable Excellence through Revolutionary Engineering.

Made in the United Kingdom by: Focusrite Audio Engineering Ltd. 2 Bourne End Business Centre, Bourne End, Bucks. SL8 5AS England. Tel +44 (C) 1628 819456 Fax: +44 (O) 1628 819443 e-mail: sales@focusrite.com USA: Group One Ltd. 201 Wilshire Blvd. #A18 Santa Monica CA 90401 Tel (West): 310 656 2521 (East): 516 249 1399

\$ 1.099U.S.*

Nashville

Ambient Drum Miking Techniques

Tips from Music Row: How to get your microphones in the right place

A MIC CAN be compared to different lenses for a camera, with each taking its own unique picture of the sound. Although there are so many variations when painting a sonic landscape, my particular taste has always been toward capturing the most real and precise representation of each and every instrument. If the sound isn't happening, the first thing to check is the instrument itself to determine if it is the right choice, if it needs some work, or maybe just replacement.


In order to get into more specific usage of this approach to recording, let's choose a particularly troublesome subject: drums. It is

hoto by Michael Gomez

possible to get a really good drum sound whether using two mics on two tracks, or 24 mics on 24 tracks. The most practical solution lies somewhere in between.

Of course, the first step is to make sure the entire kit is tuned and tweaked to its most musical state — or at least one appropriate for the kind of track being recorded. The job of placement comes next, and usually some experimentation is required to find the best spot in a room to put a drum kit. I usually favor having the backside of the kit to be closer to a reflective surface and not just out in the middle of a room.

As far as the close-miking of the



kick, snare, toms, hihat, etc., it's a fairly straight-ahead subject. I still swear by Shure SM57's on snare top and bottom (with the phase flipped on the bottom), Sennheiser MD421's on the toms, an AKG D112 on the kick, and a condenser such as an AKG C452 or C460 on the hihat. But I do believe the real magic to getting a great drum sound is in the overhead and room mics. This will be my primary focus from here on out.

HEAD'S UP

My own personal overhead technique is actually a stereo picture of the whole kit that includes some room ambience.

Many large-diaphragm condenser mics work well, but by comparison the new CAD E-300 condenser is at the top of my list. It captures the richness, the depth perception, and the dynamics, as well as the more subtle reflections. The mics are mounted at a 45-degree angle from the vertical axis behind the kit, about seven-feet high and one foot behind the drummer's stool. The capsules are then pointed away from each other at approximately 90 to 110 degrees and 12 to 20 inches apart, depending on the spread of the kit. If the cymbals are set really high, I recommend raising the

mics up to eight feet. This technique usually works best with the pickup pattern set to cardioid. Flipping the phase from the rest of the close mics also helps make for a much bigger sound.

It is always good to have phase checkers and know your absolute phase because mics and preamps vary. [Editor's note: In spite of the IEC standard pin 2 hot, a lot of gear is still designed with pin 3 hot.] This can cause cancellations and loss of fidelity. When recording the overhead mics to tape on an analog machine 1 usually go straight across through Telefunken or API preamps. Compression sounds good, although 1

The Rules have Changed We've Just Leveled the Competition



We warmed your microphones and instruments with the TUBE MP family. You've made it the overwhelming choice in realizing that classic tube sound. Now with the LeVeLAr Family, we're giving you the the next link for maintaining that sweet, classic sound.

Don't "squeeze" your signals with sterile VCA's. Manage your levels and maintain your personality with the gentle leveling of Vactrol®-based dynamics processing. The A R T LeVeLAr is your key to consistently classic sound. LeVeLAr \$159.¹⁰ msrp

> The LeVeLAr's Vactrol@based circuitry utilizes classic Electro-Optical Leveling Amplifier design for gentle, music-friendly compression...no "squeezed" signal!

VCA-less design yields compression characteristics found in classic leveling units like the renowned LA Series...without the noise and unpredictability!

Genuine 12AX7A tube utilized for make-up gain and "overshoot" transient leveling...a perfect match for tube mic preamps!

1/4" and XLR ins/outs

Gain Reduction metering with Threshold indicator

Variable Threshold and Output controls

Switchable Auto/Fast Attack and Release

Switchable Compression Ratio

>100dB Dynamic Range

DUAL LEVELAR ONLY: Two LeVeLArs in a single rack space

Stereo Link switch

Internal power supply, front-panel power switch

DUAL LEVELAR \$329.¹⁰ msrp



X

2

Professional Vactrol® Leveling Amplifiers by,

APPLIED RESEARCH AND TECHNOLOGY

R

APPLIED RESEARCH AND TECHNOLOGY, INC., 215 TREMONT STREET, ROCHESTER, NY 14608 Phone 716/436-2720, Fax 716/436-3942, http://www.artroch.com

For complete information on the LeVeLAr or Dual LeVeLAr, please contact A R T at the above address, Department 129. Flease List the publication in which you saw this advertisement. Wactrol fills a registered trademark of EGBG VACTEC INC., St. Louis, MO, USA



WE HATE NOISE !

The Radial JDI direct box brings together 'real-world' solutions to noise with a remarkably straight forward design.



The JDI is laced with all the right features: flat to 80kHz, virtually zero phase deviation, de-couples source & destination eliminating common mode noise and incorporates a 60kHz filter to protect against residuals from computers & keyboards that cause overheating of amps and drivers. Since the JDI is completely passive, no worries about 48 volts of phantom ending up in your mains, no half-juice batteries to degrade the sound, just the warmth and detail available only from a Jensen.

Built for touring, ready for broadcast, made for studios, the JDI delivers. It even has a full non-slip pad so that it won't scratch your SSL! Contact the professionals at Cabletek for more information.

Cabletek Electronics Ltd. Tel: (604) 942-1001 - Fax: (604) 942-1010

> en are registered trade marks of Cabletek Electronics & Jensen Trasnic CIRCLE 18 ON FREE INFO CARD



In stock for immediate shipment	
AMPEX 3M BASF Po	max ell. ⊛⊤⊃k Diyline [™] DIC DIGITRL
0	
hubs and reels	cassettes and DATs
boxes, albums an	d mailers labels
CDs and packaging	
Quality Service - Quality Products for over 20 years	
Ask for our free	Polyline QA catalog
Chicago (847) 390-7744 fax 390-9886	Los Angeles (818) 969-8555 fax 969-2267
Polyline Corp. 1233 Rand Rd. Des Plaines, IL 60016 96Q/A1	

CIRCLE 68 ON FREE INFO CARD

82 OCTOBER EQ

prefer to do it on the monitoring end with a UREI 1178 or two UREI 1176's.

When recording to a digital format I always print some compression to tape and mush it together before it gets turned into 0s and 1s. For this particular overhead technique, compression in the mix allows for a lot of flexibility in the amount of room sound being sucked in and the "splashy-ness" of the cymbals. When using very heavy compression I call it my "Ringo filter." The cymbals can be very loud but still warm and musical.

It is always interesting to solo the overheads and experiment with variations on mic height to find the optimum placement — which is ultimately affected by ceiling height. When the ideal spot is found, it can be quite amazing how good of an overall sound can be recorded with just the overhead and the kick mics alone.

MAKE ROOM FOR MIKING

The other area of focus I want to cover is room miking. Even though so much of this depends on the room size and characteristics, I have a technique that minimizes all of that. This application works well in stereo or in mono with one mic. Large-diaphragm condensers are placed as close to the floor as possible, at a 45-degree angle pointing up towards the bottom of the kit. Distance should be at least six fect, but can go out to 16 feet if the room allows.

The secret is in finding the sweet spot. When using two mics, they should be three to four feet apart. Aim the capsules away from each other by about 120 degrees. You can experiment with both omni and cardioid patterns to see which works best in your room. The main reason that this odd arrangement works is because it increases bottom-end response, stays clear of middle-room boxiness, and makes for a very tight response to tape. Again, the same principles about compression apply just like the overheads. So have fun and magnetize those little particles!

Ray Kennedy is chairman of the board at Room And Board studio in Nashville. He has worked with artists including Steve Earle, The V-roys, Waylon Jennings and Willie Nelson, Bob Woodruff, and Willie DeVille.

HEAD FOR DRUMS

In addition to being a co-owner of The Money Pit recording studio in Nashville and one of that area's busiest session drummers, Eddie Bayers has worked on projects ranging from McDonald's commercials to the most recent Mark Knopfler CD. And because we here at EQ get many questions on drum miking, we asked Eddie to give us a bit of insight into getting good drum sounds even before the mics are involved.

If there's one thing you need to get good drum sounds, it's good-sounding drums! And obviously the choice of heads that you put on those drums is very important. Although head selection is not quite as sensitive as the type of wood used to make the drum, it is sensitive enough that any head you put on a drum — even heads of the same type — can give a different characteristic to the tone of the drum.

I have been using Remo heads for many years, the reason being that Remo is the guy that invented the plastic head (and has been innovating it ever since) and I know of their consistency. Even still, there are times when you could, for example, try two 12-inch coated Ambassador heads and they might sound different. But I'd have to say it's very minimal that this happens. While you're changing heads, make sure to tighten all the bolts that hold on the lugs and other fittings.

I did a lot of experimenting to try and find the best combination for the top and bottom heads. My latest for the toms is a clear Ambassador on the bottom and a coated Ambassador on the top. For snare, it's a coated Ambassador on top and an Ambassador snare on the bottom — that bottom head is just a regular, thin, snare-bottom head. On the kick I have been using a clear Remo Master Series head and, after testing a lot of different heads, it seems to be the one. The kick drum has a front head on it with a 10-inch hole cut out so that you can get packing or weights and a microphone in there and position them the way you want.

Believe it or not, I pack the kick drum with sandbags. The good thing about sandbags is that they are heavy and flexible at the same time. If you were using a packing blanket in the drum, you would get some movement and the tone of the drum would change. You can position a sandbag and it will stay where you put it even if you slam the drum. —Eddie Bayers

World Radio History

Hafe PROFESSIONAL amplification

at a death + accuracy + tamapatenc



"My mixes start in the basement...That's where the bottom end lives. And then, all of a sudden like magic, the sun comes up and the top end is born. 'Hafler Amplifiers are Fat from the bottom up:"

Gary Lux Recording Engineer/ Producer Gcry uses 3 Trans+nova D.I.A.B.L.O. 9505's "Hafler Amps: Mare powerful than a 2 day old diaper!"

Carlene Scovi.l with favorite engineer, producer, dad, Robert MusiCanvas, SAG Inc.. Eldon's Boy Records





"At Spotted Pecca'y Studios, we have found no other amplifier that even comes close to the Hafler Trans+nova for its depth-of-field and definition, smoothness and clarity, and warmth and musicality. The Hafler Trans+nova is understatedly outstanding in a class of its owm."


Howard Givens Spotted Peccary Studios



Nona Hendryx Recording Art st Producer Free Records



Another Hitl New Mo Jazz release "In the Zone" Wayman Tisdale





"The new Trans•nova, regardless of power rating, out performs any other amplifier in the industry."

> Michael Jones, Conservatory of Recording Arts and Sciences



"Real world training on industry standard equipment Hafler Trans•nova, the only amplifier in our racks."

> Kirt R. Hamm, President Conservatory of Recording Arts and Sciences



at 996 Rockford Corporatio


HAFLER PROFESSIONAL, A DIVISION OF ROCKFORD CORPORATION • TEMPE, ARIZONA 85281 USA 1-800-366-1619 • INTERNATIONAL FAX 602-967-8132 • IN CANADA, CONTACT CABLE TEK 604-942-1001

CIRCLE 72 ON FREE INFO, CARD



Not So "Hard"-Disk Recording Tips from Music Row: Why you should give hard-disk recording a chance

I'VE BEEN asked why I decided to stop using tapebased multitrack recorders and switch to hard-disk systems. This is a very good question. In fact, it is the very same one my wife asked me since I own an Otari MTR-100 24-track analog machine with Dolby SR and an Otari DTR-900 32track digital. I think the answer I gave my wife was a pretty lame: "Cause I...ah...need it!" But after using my Fairlight MFX-3 and Otari RADAR hard-disk systems



for over a year now, I can definitely improve my answer. As a producer, studio owner (maybe studio *owe'er* is more accurate), musician, and engineer, I see definite benefits to hard-disk recording from several perspectives. And, yeah, it's just plain cool to use, too.

One of my favorite descriptions of

a producer was something I heard Quincy Jones say — that the primary function of a producer was to be the artist's first audience. The implication of that is helpful in many ways to creating a great recording, but you probably don't think using hard disks is one of them. But let me expound...

An audience reacts to and supports an artist's performance, but doesn't limit it. Several aspects of hard-disk recording apply in this regard. The first is speed: practically no rewind time, no changing reels every four to six takes (I have 12 GB of hard-disk space for my system), easy splicing of different 24-track takes to compile a master in minutes, and the ability to quickly and accurately comp and/or fly parts between or within takes.

The next advantage is one of minimizing limitations: unlimited tracks due to the ability to layer tracks without erasing the prior recording, the ability to correct minor timing or performance errors without endangering the integrity of the original performance, and the freedom for both the artist and the engineer

THE NEW SOUND FORGE 4.0 BUILT ON A SOLID FOUNDATION

SOUND FORGE', the most comprehensive digital sound editor for Windows', produces audio-processing effects, creates loops and regions, generates playlists, and provides an expandable architecture for power-enhancing plug-ins.

SOUND FORGE 4.0 NOW FEATURING

 Overall improvements in audio quality and speed - AVI File Support - Direct Edit Mode (fast open/save) - Vertical and Honzontal Zoom - Unlimited Undo - Quickresponse Reactive Previewing - Sync Support for Record and Playback - Dynamics (Graphic/Multi-Band) - Crossfade Loop - Paragraphic EQ - New Reverb - Improved Time Compression/Expansion - Redesigned Pitch Shift - Flanger/Phaser/Wah-Wah - Faster Graphic EQ

EXTENSIVE EFFECTS

• Noise Gate = Envelope Editing = Resample

- Delay/Echo = Distortion Fade In/Out
- Multi-Tap Delay Vibrato FM Synthesis
- And, of course, the basic editing tools

Sound Forge includes native versions for Windows 95, all Windows NT^{*} platforms, and Windows 3.1 on one CD ROM.



SOUND FORGE 4.0 NOW SHIPPING 1 800 57 SONIC (577 6642)

http://www.sloandry.com

100 Soviet Samerin Lote 2 vs. Machine Ministres 33/07 Tel 1000 Stat 1111 Fac (1919 Ser 100 Grandbar Tel 1000 Stat 1111 Fac (1919 Ser 100 Grandbar Second Second Finge at Second III Second Second Second Second Finge at Second III Second Second Tel Photogrammeria at Second Second Second Tel Photogrammeria at Second Second Second Tel Photogrammeria











CIRCLE 74 ON FREE INFO CARD World Radio History to experiment with arrangements or performances without the fear of losing what is already there.

My last point from the producer's perspective is budget. Having worked with acts ranging from multiplatinum-selling artists to ones who flip burgers to finance their career, they all have one thing in common: a budget. Tape costs, studio rates, and time spent in studio are all lowered using harddisk systems. This is a very good thing unless you really enjoy those phone calls from the business affairs office.

THE BOTTOM LINE

I already mentioned recording budgets, and, if you haven't noticed, they don't exactly have a cost-of-living increase or ad-

iustment for inflation built into them. Over the years I've been making records, budgets haven't changed and may even be lower in some cases due in part to the increased competition and quality of project studios. The 48-track machine has practically become the standard at the top end of the industry, and to compete you have to ante up about \$200,000. Or maybe not.

An Otari RADAR 48-track system will run you about 50 grand. A Fairlight MFX-324-track with a Fairlight Digital Dubber 24-track (essentially a 24-in, 48-out system with waveform

editing, a ton of DSP power, including EQ, time compression, pitch change, cross fades, level, and gating just to mention a few) will run a little over 80 grand. Either way, it's a huge savings. And both systems kick butt functionally and (in my opinion) sonically compared to any tape-based machine. There is the perception of a large learning curve required to use a hard-disk system. Nav, nav, I say. If you can run a normal multitrack remote, the Otari RADAR literally takes an extra 10 minutes to learn. And the Fairlight doesn't require much beyond that unless you get into more intense editing and DSP functions.

MUSIC TO MY EARS

What are we really trying to do in the studio? Besides basking in the glamour of the music industry and impressing the opposite sex, we are probably doing

our best to capture a great performance to be enjoyed for years. So how do hard-disk systems affect musicians?

One way is by freeing up players to "go for it" during tracking without needing to be nearly as cautious since it's easy to use the most inspired parts from multiple takes to quickly compile a master performance. This may not be as necessary if you are using the "A" team session players, but if you work with bands that actually perform on their own record like I do (and you'd be surprised at how many don't), it can make an incredible difference. Being able to let a guitarist take as many shots at the solo as he wants without having to erase a single performance is a very

killer. They are quieter and have better specs than my tape machines, so even if they only had basic tape deck functions, I would prefer them. It seems the analog/digital debate never ends, but I would rather have the lower noise floor and the knowledge that my recording will sound the same in six months as it does the first time I listen back to it (garbage in, garbage out...but it's my garbage).

Another thing about a new tool is that you learn to do things you weren't able to do before or learn to do what you did before quicker or better. Let's see, where do I start? Nondestructive editing is a good place. Besides literally saving hours, if it bites, just undo it. How about flying chorus vocals around? I can finish an entire

> song before you get the sampler plugged in and the levels set. Anybody love sibilance or "p" pops out there? Just find the "s" or "p" in the waveform and turn it down or EQ the little culprit. Done. And the singer doesn't sound like they have a speech impediment throughout the whole song.

Maybe you have done 24-track punches on a tracking date (one of my least favorite things): set that autopunch, rehearse it at least once, cross your fingers, let 'er rip, and hope the musicians play the same phrasing. With hard disk, just punch early or set it for a little prerecord handle and go

HARD (DISK) WORKIN' MAN: Mike gets to work on the Fairlight system.

liberating feature for the player - just ask one sometime!

The same thing applies for the vocalist. Besides the fact that their headphone mix stays the same without repatching, they can keep working on an idea without all the "dead air" caused by rewind time. And there is the ability to comp performances with the accuracy of a surgeon. I can also fix that late kick drum, pitch correct that third note of the 64th-note triplet in the guitar solo, slide the acoustic back to the beat, and (don't tell anyone) I can pitch correct that lead vocal in the bridge.

IT'S TOOL TIME

If I were a carpenter (and you were a lady...sorry I couldn't resist), I would use the best tools to do the best job I could. The same is true of an engineer. First of all, both of these systems are sonically for it. If you or the band blows it, undo it. Say the crash cymbal is decaying over the punch — just slide the edit point on the tracks that didn't have a clean punch-in point to an earlier or later one. Slick!

Ever had a vocalist who is a little dullsounding in the verse but when they punch out the high lines in the chorus they are so ripping your teeth hurt? Well this can be dealt with by EQing the dull parts with a little top-end boost and making an upper-mid cut on the brash phrases, or even just the offensive word. I feel that a large part of the craft of engineering is being able to keep problems from happening, but if they do, you have to deal with them in such a way that they actually enhance the final product.

NOTHING UP MY SLEEVES

Now for a few of the "tricks" I've come up with. Most of these are done with the





Get 20/20 Vision.

Visualize this

A monitoring system so good that it's easy to recognize the perfect detail of each sound.

Introducing the 20/20 bas system from Event Electronics.

20/20 bas BIAMPLIFIED MONITOR SYSTEM

- DIAMPLIFICD MUNITOR SISTEN
- Internally B:Amplified: 200W Total Power
- An Active Asymmetrical Fourth Order Crossover that separates the line level frequencies prior to amplification
- A 130 Watt Amp that receives only the low frequencies and is designed to perfectly match the 8" Mineral Filled Polypropylene Low Frequency Driver
- A 70 Watt Amp that receives only the high frequencies, designed to perfectly match the 1" Natural Silk Dome Tweeter
- A Large Diameter Low Air Restriction Front Mounted Bass Port for full, accurate bass response
- An intelligent combination XLR or #4"Input
 Connector
- Continuously Variable Precision Low and High Frequency Trim Controls
- Input Sensitivity Control and Clip LED
 Indicator
- Circuit Breaker (no looking for fuses in the middle of the night)

It's easy to put the puzzle together when you can clearly see each piece. Seek out your nearest **Event Electronics** dealer and start your next mix with perfect sonic vision.

> \$1000 per pair* *Unoowered 20/20's available for under \$400 per pair.



Fairlight MFX-3, but they may also work with other systems.

The "perfect" gate: Not that it ever happens with my tracks (ha ha), but let's say you have tom tracks with as much cymbal as tom on them (this also works for a snare track with too much hat on it). Copy the original track to an open track and use the gate function with a one-frame handle in front of the tom (or snare) "hit." The Fairlight will create a track of separate "clips" — little blocks of audio with silence in between the events. Then go to the original track and turn its level down 9 to 12 dB. Copy the gated "clip" track on top of the original and write cross fades at the front and tail of the "clips." You now have a tom track with all the attack on the hits and four times the 'tom-sound-to-bleed ratio' without losing the ambience!

Now, for "big" kicks and snares. I like acoustic drums: the ambience, the feel, the tone, and so on. But when it comes time to mix, I may want to alter the sound. Maybe I want more strainer on the snare, a longer decay to the kick, or maybe I want to add some ringing to the snare (layering sounds like a keyboard player does with a rack of synths). Totally replacing sounds is a breeze (although a little sterile) and can be done with a lot of devices. Just trigger a sound and offset it for the trigger delay, MIDI delay, and so on. But if you want to combine that sound with your original



track, you'll find that your sound is changing (or flamming) on practically every hit. Use a sequencer locked to SMPTE and it's even worse (plus have fun with the offset). Because the slope of the transient is not identical on every hit, it effects the trigger point. Then there's the accuracy of the trigger device's gate, and anything chasing SMPTE has a small amount of jitter as it keeps itself locked and corrects its position.

You say, "Mike, what do I do?" Again, use the gate function. Copy the original audio and gate the copy with a one-frame handle in front of the "hit." Then record in the sound you want to add to the original. Next, line up the transients of the two sounds and trim the front of the new sound to have the same oneframe handle as the gated original. Write a macro to jump from clip to clip, and paste the new sound over the gated clip. Then either write in the dynamics or run the track through an envelope follower to follow the original track's dynamics. Bring the new track up on another fader or digitally bounce them together in the right combination onto a single track.

One last tip: Save your effects for other stuff and use the hard disk to double parts, pitch shift/chorus vocals, or for dramatic echoes. I'm sure you'll think of more.

SAY UNCLE

By now you may gather that I'm sold on hard disk, but I should add a few more thoughts. I am not a fan of most PC- or Mac-based systems. A single-screen interface is where it's at (forget a ton of windows) and a dedicated controller is mandatory (hit a button, do a function). In my experience, dedicated systems such as those from Fairlight and Otari have been much more solid, faster to use, quicker to learn, and dependable. And Roger Nichols is right, get a master clock for the whole studio (atomic, buddy!).

Remember, we are making music and the song is the heart of it. Most of the time, what you don't do is often more important than what you do. This is the evolution (not revolution) of a tool. You might be able to build a house with a Swiss army knife, but then again we're not all McGyver!

In addition to being a studio owe'er, Mike Clute is a producer, engineer, and musician based at Midtown Tone And Volume in Nashville, TN. He has worked with acts such as Diamond Rio, BlackHawk, Duane Steele and Royal Wade Kaimes. He recently produced Diamond Rio's Grammy-nominated IV album {completely on hard disk, of course}.

CIRCLE 50 ON FREE INFO CARD World Radio History



Now add 600 more.

If you've bought one or more ADAT's or DA-88s, you've made a smart investment in the digital future. But there's so much more that can be done with the digital medium. **The Roland DM-800 disk-based Digital Audio Workstation** can exponentially increase the power of an ADAT-based recording system. Or, if you're just getting started, you can skip tape and plunge right into the DM-800. Either way, you'll get creative freedom tar beyond the reach of tape-based digital.

ADATs have opened the door to high-quality 8-track digital recording. **The DM-800 opens the doors of your creativity**. Using Roland's DIF-800 interface, you can digitally transfer any of your ADAT tracks to the DM-800 for some serious editing power. Fix the pitch of notes or cut out a breath in a vocal track. All edits are completely non-destructive, so you can experiment without worry.

Loop your best drum part, or use time compression to correct the timing of a drum fill. Or, you can sync the DM-800 via SMPTE or a MIDI sequencer. Synchronization is instant. A hundred alternate takes can be stored for any given track. Choose the best parts from up to 600 total takes and then edit them into one killer track. Using a tempo map, compiled and edited parts can be flown anywhere in a song.

Imagine making 10 digital copies of your song and then trying out different arrangements: extra choruses, different endings, alternate vocal takes with different lyrics. Then prepare for mastering using the dynamic level and EQ automation. The built-in video output lets you keep track of different song versions on a large screen.

You'll get all this creative freedom, plus the DM-800's **incredible sound quality**: wide imaging, warmth and punchness, and a well-defined bottom end. And you'll be ready to do film and videc projects, too. Just bring the portable DM-800 and DIF-800 to the video house and use an RS-422 to control your audio for layback or assembly.

Visit your Roland dealer for a trip on the fast track. Or call us now at (213) 685-5141, ext. 756, for your free DM-800 promotional video.

Powerful, Non-Destructive Editor

500 Virtual Tracky Time Compression and Puch Correction: Cut Cop. Erace slove Waveforms, Proview and Scrub Preview for last accurate chiling

Instant, Accurate Synchronization

Reads and writes all SV PT__lor_ict_with fully resolved #ame-_lite lock; MTC, STP, MMC sync caj ible

Storage and Backup Options

2 internal 540 Mcg drives. Record to 1 Gig Ionnega Jaz crives: Back up to audio DAT, d DA Jaz drives, 4____

Full MIDI Implementation

Trigger mode for instant firing of audio: Ten po maps for SPP yenc and has eduing by lars, and beats and 560 ticks. MIDI purch in and out

DIF-800 Interface Option for

Modular Digital Multi-tracks and Video 8 tracks of digital audio transfer and sample-accurate sync with ADAT_DA-88;

Video cuts; R = 112 as master or slave with capable v deo decks and video editors

Dedicated Hardware Platform

Exceptional editing and syncing speed; Completely stable; Easy to learn: Weighs or V-12 pounds: Completely self-contained; 18 bit Ab/DA conversion with 24-bit internal processing

Multi-channe. Digital Mixing

Fell onboard dynamic and snapshot automut on of all mixer functions 16 bands of 1.0.12 channels of digital mixing. Fellfect ared ligital patch bay with direct outs stereo tus busises and digital bouncing

Roland DM-800 Digital Audio Workstation

Reduz Corporation U.S. 7200 Dominion Circle Les Angeles. CA 90040 (213) 685-5141 COMPL SERVE : GO ROLAND Fax-Back Information: (213) 685-5141, ext. 271 http://www.rolandon.com


Nashville

Eastward Ho Making the move from Los Angeles to Nashville

RELOCATING YOUR FAMILY and business from California all the way to Nashville, TN is quite a move — not only physically, but also in terms of a way of life. When we were out in California, my brother John and I were producing between seven and ten records a year, and more than half of our clients were Nashvillebased. We were working with bands like Guardian, Petra, and Greg Long, and my brother was also signed to a Nashville-based company.

Doing as much gospel work as we were in California,

we felt very isolated because most of the record companies we were dealing with were down in Nashville. So we came here wanting to have access to the musicians and wanting to have a closer creative collaboration with the record companies. That's



what triggered our interest in Nashville. When we actually came and saw what it would be like to raise children here, have a family, and exist in an everyday atmosphere, it became more and more attractive. Plus we felt like there was still ground-floor opportunity and there really wasn't anymore ground-floor opportunity in California for our industry.

There is tremendous growth in Nashville right now and lot of people are coming here expecting to find work. But unless people bring work with them ---which creates opportunity for the entire community - then it just makes life harder for the people already here in good standing. We were welcomed with open arms by the Nashville community, but we also came here to make an investment in that community. We did not come to the area to set up shop and

steal other people's gigs, and that :s an important aspect of the relocation process.

MOVIN' ON DOWN

The physical logistics of the move were absolutely overwhelming. We moved five

World Radio History

Focus on the Details

Like precise visual images you get from a high quality professional camera and large lens, the CAD E-300 produces unparalleled aural imaging of the audio environment.

A unique combination of CAD's exclusive Equitek Servoed head amplifier and a classically designed large capsule provides...

- Precise Signal Reproduction
- Extraordinary Ballistic Integrity
- Extended Low -end Response
- Unmatched Transparency

<u>The E-300 Servo-Condenser Microphone</u> <u>from CAD</u> <u>'A Revolution In Resolution'</u>

- 1.1" gold sputtered dual diaphragm externally biased capsule
- Multi-pattern-cardoid, omni, figure 8
- 20dB non-capacitive pad
- Internal stainless steel EMI / pop filter
- Ni-Cad supported power supply delivering unmatched ballistic stability & allowing remote operation without phantom power.
- · Available in matched pairs





E-300 Shown with optional ZM-1 Shock Mount

• CAD, a division of CTI Audio, Inc. • P.O. Box 120 • Conneaut, OH • 44030 • 800-762-9266 •

CIRCLE 21 ON FREE INFO CARD

Sound Deals

Digital 8 Track Recorders

- Mixing Consoles
- Signal Processors
- Studio Monitors and Amplifiers
- Synthesizers and Samplers
 - Drum Machines
 - PA Systems
 - Microphones
 - Computer Software and

Hardware

Tape and Cabling

All major brands from A-Z

250 Old Towne Road Birmingham, AL 35216 205-979-1811 Fax 72662.135 @ Compuserve.Com



families, sold six houses, and brought out five 72-foot transport semi's full of recording equipment, furniture, and personal effects. We uprooted two 2500square-foot studios! Do you realize how much junk accumulates in a studio? There's gear, mics and stands, pictures, refrigerators, couches, and even wiring. It sounds easy - like you just pick up the board and the machine and go, but I'll never forget one day when I was helping load the van line from my house. I was so weary from packing and helping the movers direct what goes where that I started handing bricks to those guys to put into the moving van - common little bricks. And finally one guy turned to me and said "Hey, you can't get these in Nashville?" I was so weary from doing nothing but packing and moving for seven weeks that I wasn't thinking clearly.

In California, John and 1 were mainly producing a lot of projects, some of which 1 mentioned earlier. The studio was used probably 80 percent for us to produce records and 20 percent as a commercial venture. That ratio has been flopped here at Sound Kitchen. We have two rooms, both with Neve consoles (in an otherwise SSLfilled region), and we are building three more to meet the demand.

The interesting thing is that it's not just country acts. My brother and I were bumped this week for Barry Manilow. Recently, we have had Michael Mc-Donald and even Julio Iglesias here, and often find ourselves having to book studio time elsewhere. As a result we're building a 60-by-65-foot tracking room and two resident production suites, one of which will be occupied 100 percent by Michael Omartian.

What I find here that is much different from California is that producers will start a new project while finishing another. So now we are looking to provide a facility for producers where they can actually do their programming and overdubbing across the alley from the three main studios. A guy like Michael Omartian could walk across the alley, check on how a mix is going, walk back to his production room, and continue to work on something else. In California, this just didn't happen because the proximity was so different - everybody was so spread out. In Nashville, we are all within about 25 minutes of each other. At a multiroom facility, it's exciting and stimulating when there's five or six producers and engineers, all the rooms are pumping, and there's a lot of music going on. People are conversing in the lounge and trading ideas, and it's a place that people want to hang out.

Nashville records are being made differently than records in California.

We have three major genres: pop, which is growing; country, which is dominant; and gospel, which is just under dominant. (There's probably more records being put out in the gospel genre, but at a lower budget.) Due to this, the studios run differently and are outfitted differently. I remember running into (drummer) Mike Baird one time and he said, "Hey - 90 percent of my work is coming in and doing cymbal overdubs." Everybody was programming drums and bass either on Fairlight or on a sequencer. That was six or seven years ago and then everything came back to live. Suddenly nobody could facilitate a rhythm section in a house in L.A. or didn't have the live room for a real drum kit. Down here, the records are cut live and there's about 20 studio musicians making the majority of the records.

GET A CUE

Technically speaking, I had never heard of a Cue 8 system until I came here. This is one of those cue systems whereby every musician can do his own mix. The engineer feeds subgroups of instruments out to the musicians in the studio and each musician has his own small mixer for the headphone mix. We cannot work without that system here, but in California, John and I were the studio's biggest client and we didn't need it - so we didn't have it. In Nashville, this system is essential because the players need to get on to the next session, and everybody records at once. We didn't even have an iso booth in California because we didn't need it, but our newest room at the Sound Kitchen is going to have six: a vocal iso, grand piano iso, and four more 10 x 13 isos, plus a main room as well.

We're building a rock and roll room — very ambient — because a lot of the rooms that exist here are nonambient. In one of our big rooms we have curtains (which open and shut) and behind those curtains are 21-foot floor-to-ceiling mirrors so you can liven the room way up. For a lot of sessions they are shut, but when the pop and rock sessions come in, we even roll up the carpets.

LOUNGING AROUND

Interestingly, one of the most important aspects of the studio is the lounge. You have to have a comfortable place for people to hang out. The way a lot of the sessions run is that everybody records their tracks and the producer finds one take comfortable for all of the musicians. Then each musician comes in to do their fixes. This is usually about a two-hour process, so we've put in satellite dishes and cappuccino makers — very elabo-

Award Winning Eight Channel Dynamics Processor with Automation & MB-8 Optional Meter Bridge

SQUEEZE ME WHELE I KISSTHE SKY...



" HAVE MIXED TWO RECORDS IN THE PAST YEAR ON AN SSL-E SERIES, VCA-BASED AUTOMATED CONSOLE AND I DON'T PARTICU-LARLY LIKE THE HARSH EDGE THE CONSOLE'S VCA'S ADD TO THE SOUND. SO I WAS EAGER TO SEE HOW THE VCA'S IN THE DCP-8 COMPARE TO THE GAZILLICN-DOLLAR SSL. I LIKE THE DCP-8 VCA'S BETTER."

Electronic Musician

IDE THE SOUND WAVE! ...ASK YOUR DEALER FOR PRESONUS PROCESSORS RIGHT NOW!

fax: 504-344-8881 In Canada call: 416-234-1226 email: presonus@presonus.com website: www.presonus.com

YOU'D BE STUPIO NOT TO HAVE

Bob Doiron (Big Bob D.) of World Audio & Lights on tour in Texas with Candlebox

AN ACP-8 IN YOUR RACK.

Eight Channel Compressor/Limiter with Noise Gates TOTAL DYNAMICS CONTROL. DCP-8

Eight Crystal Clear Analog Compressor / Limiters. Eight Gates. Eight Automated Facer Channels (level). Eight Mutes. Snapshot M:x Automation. Digitally controlled: 4,096 steps of resolution the best in the adust-y!

Built-ir Software Features Include:

- Full MIPI Control
- Nan ing, Loading & Storing
- · Assumment of up to

PreSonus

PreSonus

· Pro to Line Leves

Just plug the DCP-8 into your inserts, before or after you" mu ti-track. You'll have a compressor/ limiter on every channel, a noise gate on every channel, automated faders (level), a itomated has eight of the most musical compressors you will ever hear!

ACP-8

Eight Compressor/Limiters. Eight Full Featured Gates. Side Chain on Every Channel. Gate Key Inputs on Every Channel. Balanced or UnBalanced I/C. Comprehensive Linking via Unique Power Summing Bus.

Takes the place of multiple processors. Crystal Clear Compression & Gating For Mult -Tracking & Live Sound. ALows Spectral Processing & Gate Keying Via Separate Jacks. All the dyr unics piocessing you will over need in 2 rack spaces!



World Radio History

Call Today: 1-800-750-0323



rate things — to keep musicians happy and comfortable while they are waiting. We work very hard on our hospitality. In fact, my parents — having been in the restaurant business — cook some amazing seven-course Italian meals. We feed clients like Michael McDonald and Julio Iglesias and they flip out.

These are not the kind of sessions where you are tracking the rhythm section to keep just the bass and drums. You are going for keeper parts on all of the instruments and a lot of times I have seen scratch vocals end up on records. As a result, we also need to have a more substantial investment in equipment. We have two 32-track digital machines, two 24-track analogs, a 48-track, 1/2inch Sony digital, DAT, analog 2-tracks, and PCM9000 MO recorders to mix down to, and tons of outboard gear. Each room has two dedicated racks with a couple of GML EQs, some UREI LA2A's and 1176's, and Focusrite EQs - pretty elaborately supplied rooms.

To accommodate sessions like this, you need bigger consoles, more inputs on the mic panels, and the ability to access different things on mic panels such as SMPTE, speaker leads, and line-level leads. We'll track vocals in the control room and the vocalist has a choice of monitoring either through the speakers or through headphones. If need be, we can use portable baffles, eight feet high with windows in them, to actually build a little iso room in the control room. And having that variety of gear works to our favor. I have noticed that a lot of producers are going back to analog tape again. We are currently doing a Michael McDonald album, some of which was recorded on a 25-year old (MCI) JH16 analog 2-inch. The bass, drums, and vocals were recorded on the IH and then transferred to Sony 48-track digital for additional overdubs.

Here's another interesting thing 1 have found: most of the producers in the area are on staff at a record label, either in the capacity of A&R or in some cases vicepresidents like Mark Wright and Emory Gordy Jr. They can't leave Music Row because they have a certain responsibility to the record company as well as their responsibilities as a producer. Since they have to get back to their offices, they do not want to start traveling too far. We came up with an interesting idea to help them with that problem. We've just installed ISDN lines and we have a digital transmitter. This allows us to install a box in anybody's office and they can hear the mixes from there without leaving their office. So it's like our ad for Sound Kitchen says: "Now you can be in our Kitchen without leaving your living room. But too bad you didn't get to taste the sauce." EC

CIRCLE 40 ON FREE INFO CARD

Your Work is only As good as your reference monitors. That's why so many of the Best put their trust in Ours.

It is not coincidence that more and more top professionals everywhere are using Dynaudio Acoustics monitors. Inderstanding the science of acoustics and development of ransducers is an art form at Dynaudio Acoustics. All components are built and tested at the Dynaudio factory in Denmark who, unlike many pro monitor companies, design and manufacture their own drive units.

Along the way they've developed patented naterials and manufacturing technologies that are unmatched by any speaker company, however esoteric. Inquire and you'll find Dynaudio drivers are ndeed the finest to be had. Many prestigious speaker companies have used drivers with the Dynaudio name on them. We're flattered.

We must admit a home court advantage here. Only through the unique relationship with dedicated Danish designers and manufacturers can chief designer Andy Munro (and his Dynaudio Acoustics staff) create he only complete product line of ultra-high resolution ow distortion monitoring systems available for the professional market today. From the general purpose 3M15 mid-field monitor and the application specific M1

console-top reference device o the flagship M4 active main nonitors, Dynaudio Acoustics delivers sonic accuracy you an trust. Try a pair today. When your work sounds more balanced, more dynamic simply better - you'll know vhat top professionals vorldwide have already discovered.

)ynaudio Acoustics reference.

Name drop list: Mark Knopller, London . Emerald, Nashville - Seni, LA - Chuck Alniny, Neshville · Garth Fundia, Nashville The Tracking Room, Nashville C&C Music Factory, NYC . Hit Factory Mastering, NYC - MCA Music Media Studios, N. Hollywood, CA Georgetown Mesters, Nashville Eillot Scheiner, NY & LA · Walter Atamaniaff, SF - Crawford Communications, Atlanta + American Gramophone, Omaha - Motown, NYG -Rooket Records, NYC. . Mercury Records, NYC - Battery Studios, London - Air Studios, London





Model BM15 mid-field monitor



NRG Recording Services, N. Hollywood, CA



Worldwide Sates Office: Dynaudio Acoustice UK Ltd Uml 21. Riverside Weisstiops 28 Park St London SET 9EQ UK T (+44) 171 403 3001 F (+44) 171 403 0057

dynaudio acoustics USA Distribution: Mhat you want. Giku 14Wolid Radio History SARD

True Concenser Studio Microphone





The Electro-Voice RE1000 is a monumental breakthrough in studio condenser microphone performance and value. Its sound quality and performance rivals many of the worlds finest microphones, recordless of price. One listening test will reveal that this serious audio tool belongs in your studio.



Electro Voice, Inc. a MARK IV company 600 Cecil St Hickanan, MI 49107 800/234-6831 16/695-6831 In Canado 613/382-2141 CIRCLE 36 Off FREE INFO CARD




DOUBLE TROUBLE ON THE ROAD

World Radio History

F CLUBS



TOUR DIARY: DOUBLE TROUBLE '96



Last summer, EQ spoke with engineer Jon P. Armstrong regarding the Travis Tritt tour. Well, Tritt is at it again. this time on a co-headline tour with Marty Stuart, and Armstrong has once again been called on to mix monitors. Since it is a co-headline, there are quite a few set changes each show includes an electric set by each artist individually (during which members of the other act make guest appearances), an acoustic set with both of them, and then a final set where members of both bands play together. The nature of the show requires that any audio channel be ready to go at any time - and that applies to monitor land as well as front-of-house. In this article, Jon takes us through "three days in the life" of the Double Trouble '96 tour.

DAY ONE: WALLINGFORD, CT/JULY 12, 1996


"There is absolutely no way that we'll get any rain tonight," John Boy smiled wide and looked suspiciously confident. "The weather channel says this stuff is a separate system and Bertha won't get here 'til tomorrow morning." As stage manager, it's his job to help me believe that fantasy. "No worries Mr. Chapman," I said. We'd been running ahead of this hurricane since we left Nashville and everybody was already set before this particular round of showers hit. The RARoth Lighting (Atlanta, GA) crew made plastic booties for the truss spots and the everpresent wiggly-lights they'd flown. Their trussing was left in the truck, as they were augmenting the three-truss rig

that was already at the venue. There wasn't anywhere to hang their mid-stage drape (which hides a set change), however, so we knew that morning we'd be scratching the acoustic set.

There were local vendor's racks and stacks ready with tarps piled behind them, some kind of Martin system. We didn't have an opener that day, and we had some time we could squeeze out of the bands. Travis's house guy, Jon Suskin, said the rig sounded okay. The monitor rig was the Clair system we carry with us, so we decided to relax and wait out the rain for a half hour.

The tent we'd requested for monitor world turned out to be a lean-to-type tarp stretched through the scaffolding that supported the roof over the stage. We crammed our two Yamaha PM4000m's between the scaffolds, but that tarp was more for shade than shelter. Usually those outdoor dates find me and Marty's monitor guy (and Clair guy) Brent Carpenter mixing under a tent we've prepped with plastic walls. This just isn't practical in scaffolding, however. We had to cover all the monitor gear with separate pieces of plastic sheeting. In order to be able to set up scenes and send audio signals back and forth between the two monitor consoles when Travis and Marty guest in each other's sets, we chain the console inutes and VCAs together. The PM4000m's are great with their linking and routing capabilities, but it takes

The best engineered wireless in the world comes from Lincoln, Nebraska?



BEST WORLD'S THE HOME OF

The Telex engineers in Lincoln have been designing wireless systems for over two decades. They know what works and what doesn't. They also know your real world from small clubs to outdoor festivals - and how to give you the best wireless performance in any situation.

So when they set out to design the latest Telex ProStar® Wireless. they gave it features like Posi-Phase[™], a patented auto-diversity circuit that reduces drop-outs to zero.

> Headquarters: 9600 Aldrich Ave. So., Minneapolis, MN 55420 • Manufacturing: 8601 E. Cornhusker Hwy. Lincoln, NE 68505 Tel: (612) 887-5550 • Fax: (612) 884-0043

And Posi-Squelch[™], an autosuppression circuit that keeps stray signals out of your music.

Telex wireless systems are the only systems in the industry to be backed by a limited lifetime warranty. Plus, if you ever need factory service, you won't have to send your unit across an ocean to get it.

The best engineered wireless is designed and built in Lincoln, Nebraska, but it's available at a music store near you. Try one today.

Exactly what you'd expect from a sound company like Telex. World Radio History

Telex ProStar® Systems - Engineered for the best vocal

and guitar performance



a bunch o'plastic to cover two of them (not to mention the processing racks and the ear-monitor equipment).

Clair's crew chief Joe Ravich had the FOH pair of '4000's similarly wrapped. At about 4:30, the sun came out and John Boy declared the rain over. We carefully uncovered everything and went about our abbreviated soundchecks. By 6 PM we'd covered

all the gear again and gone for dinner. I ate mine on a road case while watching the sun set into a massive cloudbank. The bank rolled in while the show started and everyone knew it was coming. Marty's rockabilly riot went well with the wind picking up and darkness falling quickly. The crowd was rowdy and in the hooting mode - usual for that point in the show.

The acoustic set normally starts as soon as Marty's Rock-n-Roll Cowboys stop the vamp that ends their set. The missing mid-stage drape would hide the set change while Marty, Travis, and Jon Bonnett and Wendell Cox (from Travis's Country Club Band) play downstage. Instead there was a 15-minute change while we set Travis's stage. (The acoustic set is 15

minutes long, so the set change is a snap when they don't have to do it quietly in the dark.) Fifteen minutes was also just enough time for the clouds to brew into a full storm. Clair's other stage guy, Mark Gould, was scotting one of the Clair P-2's we use for sidefills when a kid in the audience asked, "What happens if it rains?" "You get wet," he said. And wet they did get.

Ten minutes into the set

the rain was dumping on the crowd so hard they gave up on staying dry. There was concern for everyone's well being, but standard operating procedure dictates we play until we see lightning. Travis was getting wet as well. Production manager (and tour rigger) Ralph Perkins asked, "Is he okay out there?" "He's as safe as any of us on this gigantic lightning rod," I said pointing to the scaffolding, "if not, more so. None of his stuff will explode." Travis uses wireless FutureSonics AEM's® and the groovy new Shure UHF wireless for vocals (which kept working even though it was drenched with rain). Bud Phillips (Travis's guitar tech) uses Nady 950GS wireless units for all of Travis's guitars. Travis was totally wire-free and the band was staving (mostly) dry --- so

they played right on through the downpour. The rain let up and let loose several times before the

first lightning was spotted miles away. Travis got the high-sign and gave the band the "last song" signal they'd been expecting. The set was a little over an hour. After 50 minutes of continuous rain. the only casualty we suffered was the drum sampler getting a bath. But that happened late during load-out and it had had a long, full life anyway.

DAY TWO: COLUMBUS, OH/AUGUST 7, 1996

I was standing on top of my toolbox lid so I could see downstage. This room was

SOMETIMES BIG **THINGS COME IN** SMALL PACKAGES

We proudly announce the MQX-Series, featuring all the performance and great sound of our legendary GQX models in an uniquely compact package. The same exacting filter design and summing circuitry is utilized, with each filter exhibiting true constant "Q" response. The center detented position of every fader acts as an on/off switch for that filter (to ensure the quietest operation). Instead of the 20mm plastic faders typically used by the competition, ASHLY has selected a custom-manufactured 25mm slide fader device. This component allows us to offer up to 15 dB of boost or cut adjustment on each individual filter. Each MQX model features balanced XLR and 1/4" phone jacks, while the third-octave models also feature barrier-strips (with full ground lift provisions). Internal power supplies are standard in all ASHLY products (no "wall warts") as is our exclusive Five Year Worry Free Warranty. Finally, a

truly professional graphic equalizer in a smaller rack space package.

THE NEW MQX SERIES FROM ASHLY



Ashly Audio Inc., 847 Holt Road, Webster, NY 14580-9103 Toll Free: 800-828-6308 • TEL: 716-872-0010 • FAX: 716-872-0739 Canada: Gerraudio Dist. Inc. 416-696-2779 • International Agent: E and E Exports Inc. 714-440-0760 Internet: http://www.ashly.com

100 OCTOBER EQ

CIRCLE 07 ON FREE INFO CARD

d Radio History

THE BIG WINNER IN AFFORDABLE 8 BUS MIXING CONSOLES!

"The classic 8's EQ is totally brilliant!" ---Michael Molenda, Electronic Musician Magazine, January 1996

> hen it comes to choosing the right 8 bus mixing console, certain things need to be carefully considered. It may start with features and price, but sound quality and performance will most certainly be the deciding factors. The award-winning Mixdown Classic has all the features you want plus superb audio specifications, proven reliability and the performance you need. All this at a groundbreaking price for consoles in this class.

> o prove our point, the Mixdown Classic 8 recently ran away with Electronic Musician Magazine's Editor's Choice Award for Best Recording Console for 1996. It was also nominated for a TEC Award and has received nothing but critical acclaim worldwide. The Mixdown Classic 8 provides features not found on consoles in this price range, such as its comprehensive MIDI MUTING system, internal modular design and an optional meter bridge.

MIXING WITH THE BESTI

"In a side by side contrast, the Mixdown Classic blew the Brand 'X' 8 bus away in sonic quality!" ----Michael P. Barton, Appleton, WI "Great *&#@#*^ board...just great!" "Great *&#@#*^ board...just great!" ---Sean Nolan, Denver, CO ---Sean Nolan, Denver, CO

- 16, 24 and 32 channel versions
- Midi Muting
- 3 band EQ w/mid & bass sweep
- 6 aux sends per channel
- Balanced mic inputs on every channel
- Channel direct outputs
- Optional full-width meter bridge
- Rackmount external power supply

Studiomaster IT'S ALREADY A CLASSIC!

3941 Miraloma Ave., Anaheim, CA 92807 • 714-524-2227 Fax: 714-524-5096 Internet: http://www.studiomaster.com Studiomaster House, Chaul End Lane, Luton, Beds, LU4 8EZ UK • Tel: 1582 570370 Fax: 1582 494343

CIRCLE 80 ON FREE INFO CARD



odd — a long hall with the 7foot tall stage running down the side. It was quite unexpected, but welcome for us to find an arena on this run. The previous few shows had been bearable but the local vendor PA's were sufficient at best. Both Suskin and Marty's FOH guy, Les Banks, were wrestling every usable decibel they could from the provided systems. This day promised to be more of the same. Brent and 1 have different banks of EQ presets in the TC Electronic 1128 system to handle the monitor changes from indoors to out — one button and you're roughed in. Unfortunately, without a soundcheck, one can't really prepare for the way the stage sounds when the PA gets to running volume, especially if you've not been inside lately. Guesswork aside, the sound crew was anxious to make noise.

The 60-foot traveler track that hangs the drape was rigged and the acoustic set was green-lighted. We set about soundchecks as usual with Marty's gear in place — a 95-input line check, then the Country Club band followed by Marty and the Cowboys. The only real gremlin we had

CDs IN 3 WEEKS 300 CDs \$1,590 with black & white inserts Includes FREE design! 66 The outstanding artwork. friendly staff, great sound quality, and quick hirnaround just can't be beat. Disc Makers, you are the best. I will be back 99 – Diana Starr Columbia. IL Only Disc Makers offers all these benefits: • FREE Deluxe Graphic Design • FedEx shipping of finished Insert film and printing product at UPS Ground rates Proof Positive® Reference CD Major-Label-Quality No-Fine-Print Guarantee · Tests and proofs sent via FedEx Call today for your FREE, 1996 full color catalog: 1-800-468-935 24 HOURS TOLL FREE 609-663-9030; FAX 609-661-3458 http://www.discmakers.com

was a buzz in the video feed to drummer George Stalling's drum rack (George follows a track to sync the band to video during the Travis set). We eventually realized the video rack was normally AC ground-lifted at its home on stage right. The hall couldn't accommodate the video trussing, however, so Chris Hobbs (Tritt's video tech) set up on stage left near the house video gear he was feeding instead. Five minutes and a 49-cent AC adapter later, and we were eating dinner.

The show that night went fairly well. What the audience didn't hear was the mush we got on stage during the acoustic set. Jon and Wendell needed more volume than usual, and their live wedges began to wash out Travis's and Marty's Ear Monitor mix. While the set change in the dark behind the drape was a little slow, nobody seemed to notice.

DAY THREE: MERRILLWILLE, IN/AUGUST 24

Finally, another chance to do the acoustic set. We'd done a string of shows without the acoustic set. In fact, for this particular run of shows we'd left the rigging truck in Georgia and the drape with it. Theaters, however, are historically known to have drapes in them; this one didn't disappoint. The local lighting rig went in at 8 AM. Soun Ichecks were scheduled for 2:30 and our load-in was slated for 9 o'clock. But the venue had only a one-truck dock and no storage to speak of, so everyone emptied boxes and packed them away tight.

Space was tight on stage as well, so much that Tritt carpenter Tony Downs had to build his 4-ton hydraulic stage only two feet from the upstage wall of the theater. The set change normally starts with the drape closing and the set rising to *continued on page 142*

CIRCLE 25 ON FREE INFO CARD

World Radio History

#1 MANUFACTURER FOR THE INDEPENDENT MUSIC INDUSTRY

"hear the music thunder"

"brainliquidizing"

Now! New "fs" models with field-serviceable earpads, elements and cables.

ATH-M40*fs* ATH-D40*fs* Precision Studiophones

"excellent stereo imaging"

"The linear ATH-M40s are engineered to give you the flat, honest truth. The bass-enhanced ATH-D40s are geared toward bottom dwellers who want to hear the music thuncer. Both models do their jobs extremely well.... I'm sold. I'm keeping these cans and ordering more!"

Michael Cooper, Electronic Musician, March 1996 Excerptec from "Audio-Technica ATH-M40 & ATH-D40"

"When it comes to performance, both sets of phones produce a smooth but highly detailed sound with excellent stereo imaging and good bass extension... [They] are extremely capable and nice sounding headphones."

Paul White, Sound On Sound, August 1995

"clean and powerful"

⁴⁴The M40s exhibit an accurate blend of LF, mids and HF elements; the bass is tight and well-defined, and the highs have a nice sheen that's crisp rather than brittle. The D40s exhibit similar midrange and HF response, and...have a substantial bass boost in the 80 to 120 Hz range."

> George Petersen, Mix, May 1996 Excerpted from "Audio-Technica Studiophones"

"The D40 and M40 performed well with an excellent, clean and powerful sound, with spacious and detailed stereo imaging...The headphones are rated at a maximum input power of 1,600 mW at 1 kHz, delivening up to a brain-liquidizing SPL of 132 dB."

Christopher Holder, Audio Media, January 1996 Excerpted from "Audio-Technica ATH-IM40 & ATH-D40 Studiophones"



Audio-Technica U.S., Inc., 1221 Commerce Drive, Stow, Ohio 44224 Tel: 330/686-2600 Fax: 330/686-0719 E-mail: pro@atus.com Audio-Technica Limited, Old Lane, Leeds LS11 8AG England Tel: 0113 277 1441 Fax: 01 3 270 4836 Excerpts reprinted with the permission of the Publishers. ©1995/1996

> CIRCLE 08 ON FREE INFO CARD World Radio History



CLUB PROFILE: ACE OF CLUBS

HOW THIS CLUB DOES **DOUBLE DUTY IN** MUSIC CITY USA **By Steve La Cerra**

IN THE TOWN that has affectionately become known as "Music City USA" you'd expect to find some pretty hip clubs. And since Nashville is the center of the country music universe, you might also expect that a majority of these clubs would be host to predominantly country acts. What you might not expect to find is a place like the Ace Of Clubs, which, in addition to being one of the favorite local stops for up-and-coming and national country acts, also runs shows with just about any kind of music you might imagine. Guest artists at the near-500capacity room range from bluegrass acts like the Cluster Pluckers to Tower Of Power to borderline metal bands.



DOUBLE DUTY: Is the Ace of Clubs a live-band club or a dance hall? It's both.

block building that used to be a warehouse. The room is roughly 115 feet long by 40 feet wide. At one end of the club is the stage, measuring 24-feet across and 16-feet deep. Along either length of the room runs a balcony

that is 12-feet deep. Unlike many single-room clubs, the Ace Of Clubs runs live entertainment Monday or Tuesday through Thursday nights (depending upon how busy the season is). Then on Friday and Satur-



Ace of Clubs is in a concrete



ACE OF TECHS: Engineer Mark Phaneuf stands at the Club's PA system.

day nights, it turns into a retro-dance hall, with a DI playing music from the 1970s and early '80s (the club is closed on Sundays). An interesting aspect of the club is that instead of having separate PA systems for the stage and DJ (as is often the case), output from the DI system is fed into the house PA.

SOUNDING OFF

Jim Wakefield of Production

Services, Inc. (Nashville, TN) designed and installed the front-of-house system and describes the speaker cabinets used for the mains: "We use a proprietary box that is the same box we use for all of our shows. It's a front-loaded trapezoidal box 42-inches wide by 42inches high by 22-inches deep. Each box has a pair of RCF 15-inch woofers, a pair of RCF 12-inch drivers, and a Peavey CH4 horn on a Peavey 44T driver. At each side of the stage is one of these boxes (flown), and a sub box with two Peavey 18's in each. The sub boxes — which sit on the floor – have the same footprint as the full-range boxes, but are 46-inches tall.

"The system is four-way mono, all Crest powered and crossed over with a Peavey PC4XL. We use a 7001 for the low end and low-mids, and a 4801 for high mids and highs. The boxes are not very big, but they can play loud and get

104 REASONS WHY YOU SHOULD CHOOSE A VEGA WIRELESS SYSTEM



- Reason #1: The wireless you see on specials, award shows and live TV performances is almost always Vega.
- Reason #2: Selectable receiver and transmitter provide maximum frequency agility, so you can use it anywhere.

World Radio History

- Reason #3: Dual Mode Squelch prevents interference.
- Reason #4: Vega's unsurpassed sonic quality and performance is now within your reach.


Reasons #5 - #104: An unprecedented choice of 100 UHF channels with just a few simple clicks.

For the dealer nearest you or for a free brochure, call 800/877-1771. Manufactured in the United States.



CIRCLE 84 ON FREE INFO CARD





OFF TO THE RACK: The racks can be switched between FOH and monitor land.

the system up to around 110 dB." In the previous install, the entire PA was sitting on the floor, but Jim observed that as soon as the club filled up with people, the bodies blocked the PA and the low-mids disappeared. By flying the full-range boxes, the problem was averted and the coverage of those boxes negates the need for any additional fill speakers towards the rear of the room.

For the house console. Wakefield installed a 32channel Soundcraft Spirit. Monitor mixes are done from the house mix position so he has set up the Spirit with four prefader sends for monitor and two postfader sends for effects. At the house position are five 31band equalizers: a Klark-Teknik DN30 for the house and four Peavey EO31's for the monitor mixes. House effects are a Roland SDE1000, two Yamaha SPX90 II's, four channels of Symetrix gates, and four Symetrix compressors. Also available is a dbx 160x for compressing the house (more on that later).

The Peavey EQs are in a separate rack that can easily be moved to the stage when an act wishes to bring in a monitor console. Jim notes that for engineers familiar with the room, the monitor situation isn't a problem, but it can sometimes be when a guest engineer comes in who is not used to this type of setup. "Where four mixes are enough but the engineer really doesn't want to do monitors from the house, we can bring in a small console like a Yamaha 2408 or a Peavey Mark IV, put it in as a monitor board and be able to mix from the stage area. This gives the band the diversity of having another engineer to handle monitors, but won't run the cost up a great deal. For 80 percent of the bands that come in, four mixes from front-of-house is fine."

Monitors include three Maryland Sound wedges up front (JBL-loaded with two 12's and a 2-inch horn) and a Maryland Sound drum-fill box with two 15's and a horn (also JBL-loaded). All monitor mixes are biamped (crossover is at 1.2 kHz) with SAE power amps on the low end and Peavey M4000's on the highs. Anticipating the fact that some acts would request different or additional equipment, Wakefield installed a 24channel snake with a permanent split for a monitor console. The wedges and power amps are already there, so connecting a monitor desk is as easy as patching in the monitor output of the split.

In addition to monitor rigs, some acts bring in their own console or request something bigger than the Spirit, in which case Jim can offer a Yamaha PM3000 or a Crest GT (both 40 inputs) or an eight-mix monitor rig. On occasions where more house speakers are required, the system is doubled up, but Wakefield warns that if the SPL gets much over 110 dB, "it is just too loud and the bar will not do much business. But there are shows where the idea is not doing bar business, it's just putting a band in and selling tickets. But we're prepared to bring any gear in or out needed to make a show happen." With that in mind, the available mic selection includes Shure SM57's. SM58's and SM98's. a Sennheiser MD 421, AKG C451's, and ProCo and Countryman DI's.

HOUSE OF CARDS

The PA at Ace Of Clubs really is under a rigorous schedule. In addition to the live shows and the weekend DJ thing, the club is used by acts for label showcases as well. "We do 50 to 60 label showcases a year there," explains Wakefield, "so the PA runs quite a bit. This rig has been in there for almost four years, and in that time I have replaced one 15-inch driver and one 18inch driver."

What is the secret to keeping it in such good condition? Tests and maintenance. Jim periodically checks the system for weaknesses before they become problems. He will bypass the crossovers and access the amplifiers directly, feeding a sweep tone through the drivers and listening for rattles, cones rubbing, loose screws, etc. Peavey's crossover has a limiter built-in for each band and has been carefully adjusted by the engineer to avoid problems, "We have the lim-

iters set right at the maximum output of the amplifier, before the amp starts to clip. Basically, I don't care what someone does with the dbx compressor at front-ofhouse. It is there as a convenience for compression, if they wish. It is not a protection device --- protection is at the crossover. There is no input limiting at the crossover but there is output limiting and it is set right at the point where the amps will cease delivering clean power. So we don't have to worry about damage done by driving the amps into clipping. The only problem we could have is if an engineer drives the console into the ground on an input and produces DC, but that just doesn't happen down here."

MIX TIPS

Wakefield offers this advice to engineers mixing in the room for the first time: "Frankly, this is a really nice-sounding room just the way it is. You need to remember that the room is brick and concrete block and is not all that large. So it's a loud room, and there is a great deal of stage volume. If you have a guitar player using an amp with any kind of stage volume at all, you probably won't put a lot of guitar in the PA. It's just not a necessity. Everybody in the room will already be well aware that there is guitar there. The room is small enough that the monitors feed the front-of-house and the front-of-house system feeds the monitors. After you get to a certain volume level, it just becomes a wall and nothing is going to cut through there. So you need to keep the volume level under control, starting at the stage." EC

THE FINEST LINE OF POWER TOOLS IN DIGITAL AUDIO...

Software Andio Workshop 🔓

Professional non-destructive Hard Disk Editor and Mixer for Windows. Simultaneous playback of up to 16 mono OR stereo tracks (32 tracks max). Real time effects provide parametric EQ, noise gate, limiter, compressor, normalize, echo/delay, vari pitch, reverse phase, AVI video

viewer available for video/audio scrubbing. Real time sample rate conversion. SMPTE/MIDI generate and chase lock resolve. And much more. An alternative choice to products costing thousands more... Retail list price \$999.00







Audio Editing Solution at an affordable price with the SAW Plus engine and 3D graphical interface in a 4 track environment. Live. automated splitting of L/R audio to 2 mono sound files while recording. Complete drag and

drop non-destructive editing with real time effects processing. Multiple levels of undo. Simultaneous Sync Record/Playback (soundcard dependent). SMPTE/MIDI generate and trigger. Adjustable volume pans, mutes and solos during playback without additional expensive hardware. Loop scrubbing and more... Retail list price \$599.00.

e orginal award winning audio hard disk ing software for the PC environment. Classic forms digital audio editing, mixing, sampling 1 other functions with ease, speed and cision. SAW Classic Utilities rack included

h the program, provides emulated DSP processing functions such as EQ, echo, file mat converter, gate, compressor, etc. Time savings and amazing versatility are yours... ail price \$299.00.

vailable Exclusively Through Our Manufacturer utlet. Now Offering You Great Distributor Prices nd Daily Package Specials!



Be sure to check our Web site for incredible ONE DAY SPECIALS! Get a FREE working demo: http://www.iqsoft.com

Software Audio Workshop



0 U A L I T Y S O F T W A R E 4680 S. Eastern Ave., Ste D Las Vegas, NV 89119

> Tel (702) 435-9077 Fax (702) 435-9106 BBS (702) 435-7186



INNOVATIVE QUALITY SOFTWARE BUILDING THE FUTURE IN DIGITAL AUDIO...

World Radio History



AES PREVIEW: GEAR FOR GIGS

SLICK Speakers

Housed in lightweight, vinyl-covered charcoal-gray



enclosures with interlocking corner guards and steel mesh gilles, TOA Electronics, Inc.'s SL Series loudspeaker systems are operable between 70 Hz and 20 kHz. Each of the 8-ohm enclosures houses a 90° x 40° constant directivity horn coupled with a piezo driver

at the high end. Low frequencies are passively directed to either a 12-inch (models SL-122 and SL-122M) or 15inch (models SL-152 and SL-152M) transducer. Power handling for each model is

rated at 240 watts RMS continuous program. Two parallel 1/4-inch phone jacks located on the rear panel of each SL loudspeaker facilitate multiple hook-ups. The line's two stackable models (SL-122 and SL-152) have suggested retail prices of \$414 and \$494, respectively. The floor monitors (models SL-122M and SL-152M) list at \$446 and \$530. For more information, contact TOA Electronics, Inc., 601 Gateway Boulevard, Suite 300,

> South San Francisco, CA 94080. Tel: 415-588-2538. Circle EQ free lit. #120.

QUICK CHANGE ARTIST Crest Audio's

Crest Audio's LMx mixing console is the first monitor console de-

signed to provide 100 percent multimode operation. The LMx can configure any or all of its 22 output busses for either mono or stereo pair operation. Without any patching or module swapping, the LMx provides this flexibility simply with the touch of Global Level/Pan



buttons on the corresponding output modules. The LMx's output section is comprised of ten dual Group Output modules and one Stereo L/R Output module. Each of the Group Output modules incorporates a dedicated stereo EQ section with three overlapping swept bands, sweepable high-pass filter, individual balanced insert switches, and summing inputs. The console also features a built-in microphone splitter, eight scene mute groups, a globally selectable AFL/PFL solo system, comprehensive subgrouping capabilities, separate pre/post switching for every pair of output sends, and two separate monitor outputs. For more information, contact Crest Audio Inc., 100 Eisenhower Drive, Paramus, NJ 07652. Tel: 201-909-8700. Circle EQ free lit. #121.

BAG A QUARTZ

Designed to complement Bad End Loudspeaker Systems' other entries into the highoutput, arrayable concert sound-reinforcement market - Saphhire and Crystal - the Quartz subwoofer system is loaded with four 18-inch ELF drivers and has a power-handling capacity of 1600 watts continuous sine wave. Weighing in at 225 lbs., the Quartz's compact size (27-inches wide by 40-inches tall by 30-inches deep), factory-installed wheels, and eight handles make it easily adaptable to a multitude of applications. The enclosures are constructed of 3/4-inch Finland birch plywood supported by internal bracing and are finished

in durable black, textured catalyzed urethane. The grille is vinyl-coated steel in an aluminum, extruded frame, and married to the cabinet with a heavyduty weather seal. Retail price is \$3500. For further information, contact Bag End



Loudspeaker Systems, P.O. Box 488, Barrington, Il 60011. Tel: 847-382-4550. Circle EQ free lit. #122.


Go Low

Martin Audio's new WSX subwoofer is a folded-horn subwoofer designed to complement the existing Martin Wavefront range of loudspeakers. Featuring a 600-watt, 18inch driver with magnet structure and suspensions specially engineered for very large linear excursion, the WSX features the internal "S" shaped folded horn that has become a Martin hallmark. The horn itself is over 7-feet long. The result is an efficiency typically 5 dB greater than ported direct radiator subbass systems. For more information, contact Martin Audio/T.G.I. North America Inc., 300 Gage Ave., #1, Kitchener, ON N2M 2C8. Tel: 519-745-1158. Circle EQ free lit. #123.



World Radio History





Emotional Thing

AKG Acoustics' Emotion Series has been designed specifically for live performance applications and will initially consist of two models — the D770 dynamic cardioid instrument and vocal microphone (\$90 suggested retail price) and the D880 vocal super cardioid microphone (\$99). Additional products in the Emotion Series line are planned for next year. AKG has developed the new "Doubleflex" technology, which is a two-way elastic suspension system that mechanically isolates the microphone capsule and reduces handling noise. The Emotion Series also uses neodymium magnet assemblies. For more details, contact AKG

THREE-PEAT

The Miles Technology MTI-3 incorporates a patent-pending electroacoustic imaging process called TriSonic Imaging, which takes the centerpanned sound sources in the mix and reproduces them in the center channel. Sidepanned sounds radiate unmasked from the side loudspeakers. This process results in options for even greater capacity. The MTI-3 requires no encoding process to produce 3channel sound and it adds no distortion-generating EQ or dynamic modification. With the MTI-3's SpreadSound function, mono sources can be enhanced and made to sound "bigger." The 1U MTI-3 is rackmountable and includes XLR and RCA connectors for input and balanced output. For more



Acoustics, 8500 Balboa Blvd., Northridge, CA 91329. Tel: 818-909-9748. Circle EQ free lit. #124. an increased optimum stereo listening area, as well as increased vocal intelligibility. The unit also offers two surround details, contact Miles Technology, 70 N. St. Joseph, Nile, MI 49120. Tel: 800-280-8572. Circle EQ free lit. #125.

MODEL 356AT <u>ALL</u> VACUUM TUBE PREAMP The ultimate recording and mastering tool!



4 Vacuum Tube Amplifiers (2 discrete mic preamps and 2 discrete line amps)

All world-class transformer-balanced inputs and outputs • Extremely low noise Exceptional dynamic range • Very low distortion • Wide, very flat response

"Tracked Taj Mahal's latest album, 'PHANTOM BLUES' with the Giltronics 356 mic preamp for vocals and acoustic guitar and went direct to tape (bypassing our Neve console). It sounded like I took the cover off the microphone. Incredible!" Joe McGrath, engineer (working at Sound City, Hollywood) "Exciting and clear. Solid tool for cutting vocals and instruments, maintaining the richness and depth lost in digital mastering." Russ Gary, West Coast Country Music Producer of the Year "We used the Giltronics Mic Pre for a critical cabaret scene when taping Hearts of Fire (CBS). It strengthened the singer's performance and picked up every detail, even with the Beta 58's we were using. Lots of balls." Larry LaSota, Emmy Award winning CBS staff mixer

"I'm used to Focusrite and other fine mic pre's. The 356AT is more natural, with more presence." Milan Bertoso, Producer/Engineer, with 400 album credits, Honolulu

Also Available: Model 4TMP (4-mic pre) or 4TLA (4-line amp)

Giltronics · Kauai · Hawaii · USA · CALL Gil at 800-682-2778 e-mall: gilamp@hawaiian.net





ALLEN & HEATH GL3000 MIXING CONSOLE



THE ALLEN & HEATH GL series of consoles has provided many live-sound companies with consoles that are as flexible as they are portable and are specifically designed for livesound applications. The GL3000 reviewed here offers a sensible combination of features based on the GL3 console with a few items (such as eight sub-groups) borrowed from the top of the range GL4 mixer. The result is an easy-to-use mixer suited to mixing the FOH sound at an afternoon concert in the park and then throw on top of some road cases at the side of the stage to mix monitors for an evening club gig. The switch-over between tasks is accomplished by recessed pushbuttons on the face of the mixer. The result is a mixer that has all of the most important practical requirements for each task, available whenever the need arises.

The GL3000 is based on a steel chassis that contains modules of eight mono inputs; four stereo and four mono inputs; and a master module with eight groups, left/right master, two stereo returns, two matrix outputs, and the masters for the eight auxiliary sends. The review unit also included the optional M24 meter bridge with mediumsized VU meters for the groups, L/R masters, and PFL/AFL level. The mechanical VU meters are especially appreciated by anyone who must work in direct sunlight, known to make LED meter indications virtually invisible. For those who work in less intense lighting, the basic console includes LED ladders for the L/R masters that switch to PFL/AFL. There are also four-stage LED indicators above each group fader and three-stage LED indicators above each input fader. All the frame

sizes have the master section located centrally within the chassis so that the operator can easily see and reach any control on the console.



MANUFACTURER: Allen & H ath 8760 S Sandy Parkway, Sandy UT 34070 Tel 801 566 5800

APPLICATIONS: Mixing live sound FOH or onstage monitors and one receiding uses

SUMMARY: A let ble ght bus console that quickly reconfigures to suit the FOH or monitor engineer and expands on fratures of the GL3 console that preceded it

STRENGTHS: Consistent coloring of controls simplifies operation, controls swap to suit FOH or menitor use, dedicated full function stereo inputs meter brillige option: expandable from c


WEAKNESSES: Us in must chuck status of configuration buttans care fully: no output connectors for four of eight group outputs.

PRICE: \$6444_20 mono and four stereo inputs eight groups stereo master and two output matrix with optional meter bridge (as rere-ed) \$5595, GL3000-824.2 mono and 4 error input version (without meter bridge) \$849 optional meter bridge for 24-channel chassis

EQ FREE LIT. #: 126 BY WADE MCGREGOR

ProChoice





Microtech Gefell—the professional's choice.



TEL 212 765-3415 FAX 212 581-8938

CIRCLE 35 ON FREE INFO CARD

NG

NG






FIGURE 1: The 4-band equalization of the GL3000 mono inputs covers the audio range with significant overlap between bands. The two midrange bands sweep peaks or dips from 35 Hz to 1000 Hz (low-mid) and 500 Hz to 15 kHz (high-mid), while the shelving filters are shown as gentle slopes at each end of the spectrum. The slightly flattened appearance of the low-frequency peak/dip is an artifact of the measurement.

The outputs from the console are an interesting variety of formats and compromises. The primary outputs (master L/R, mono, aux 1 to 4, and groups 5 to 8) are fully balanced; the secondary outputs (aux 5 to 8, matrix output and 2-track send) are quasi-balanced (a resistor between the "cold" connection and ground); while the inserts on the inputs and balanced outputs are all unbalanced send and return on a single 1/4-inch phone jack.

Although anyone expecting to use the console for recording to an 8-track may find the lack of group outputs 1 to 4 to be a limitation, in many live-sound applications this compromise makes sense. Aux 1 to 4 often drive the line back to the stage monitor amp rack and must be fully balanced, whereas the last four auxiliary outputs (5 to 8) are usually only going to a nearby effects rack and will usually be OK if unbalanced.

This said, balanced connections offer a greater level of confidence when everything around you can change from venue to venue. There is an option to balance the matrix output, but clearly the cost of balancing all connections on the console would place the unit out of reach for many prospective buyers. We now live in an age where the quasi-balanced connection is becoming the norm for low-cost consoles - however compromised this connection may be in less-than-ideal situations.

Allen & Heath deliver their usual good signal-tonoise ratio (90 dB with 16 ch. routed to master output) and provide the kind of gain structure and headroom that is so necessary to coping with *live* sound. The GL3000 is specified to be able to drive the balanced outputs up to +27 dBu before clipping; unbalanced outputs max out at +21 dBu. The balanced outputs are all XLR connectors. Sys-Link (an A&H standard) provides the optional capability to connect all the busses, aux; group; L/R; PFL/AFL; and DC control, between two consoles.

The auxiliary sends can be switched on each input from prefader to postfader in groups (aux 1-4 and aux 5-8), but can be permanently assigned individually by resoldering jumpers on each input circuit board. There are also jumpers to change the sends from pre-EQ to post-EQ and premute to postmute. These features combined with other jumpers for meter source and the switching assignment of group/aux masters and the Mono Master function create a very flexible design that can be adapted to suit very individual working styles.

The switches convert the console to an on-stage monitor mix console with little compromise. The auxiliary masters switch from knobs to full-size (100-mm throw) faders. The Mono output switches from a sum of the L/R masters to being fed by the PFL/AFL bus for driving a listen wedge. All the main outputs (aux 1-8, group 5-8, Master Left and Right) include inserts to allow patching in comp/limiters or EO.

The mono and stereo inputs also include inserts. These are of the tip-send, ring-return single-phone jack variety. The output matrix includes input levels from each of the eight groups and the left/right masters. This allows two (A and B) independent mixes to be compiled from these sources for productions where a simple Left and Right is not sufficient. Unfortunately, the console stops short of individual

group and master assignment or a full complement of group outputs required for many live theater applications.

The inputs feature phantom power, 20 dB (or line I/P), and high-pass filter switches at the top of the strip along with the 50 dB range input gain control. The mic preamp is clean and well behaved with an active front end that suits most situations. You will have to pay a lot more to get the truly bulletproof input transformer that sounds as good. The 4-band EQ covers the spectrum nicely (see fig. 1), with two variable-frequency midband sections (mono I/Ps only) and includes a bypass switch. The bandwidth of the mid filters are sufficient to hone in on problems and smoothly shape the tone of an instrument. Just don't expect to punch in a 40 dB notch.

After the eight auxiliary sends is a pan pot (balance on stereo 1/Ps) and the bright red Mute switch with an even brighter red LED indicator. Beside the 100 mm channel fader are an input-level meter, PFL switch, and the five stereo pairs of group and master bus assignment switches.

In addition to the mono and stereo input sections, there are two stereo effects returns assignable to the L/R master, one pair of groups, and the Matrix masters. There is a dedicated interface for connecting a DAT or cassette deck to play walk-in music and record the show. Dedicated send and return levels mean no inputs are wasted for this use, and switching allows the tape to be cued in the headphones or directly routed to house through the L/R masters. There are indi-




vidual talkback buttons for each aux send and an XLR so you can plug in a real microphone instead of using a \$3 thing buried in the metal work.

The knobs and faders are clearly colored to make it easy to identify functions, and the optional meter bridge includes the group or master reference in the lighted portion to maintain visibility even in darkened venues. The rackmount power supply includes an LED to indicate power on and is convection cooled to limit the noise to just the buzz of the transformer. External supplies, such as this one, are essential to minimize the electronic noise floor within the console. The console's solid construction offers confidence that the show will go on regardless of road or roadies between venues.

The GL series of consoles has offered a clear focus on live-sound reinforcement by a manufacturer that continues to listen to the users on tour, in rental companies, and at small venues. Everything from the contrasting colors on the controls to the very specific signal routing capabilities show that this console is built for small-to-mediumsized gigs. If double-duty is a regular job for your console, then consider trading it in for one that was built for it.

Wade McGregor is a senior consultant for Barron Kennedy Lyzun & Associates, an acoustical consulting firm based in Vancouver, BC. For more info, visit their home page at www.bkla.com.





GET A SOUND EDUCATION

At Five Towns College you can study Audio Recording Technology while earning a twoyear college degree or four-year bachelor degree. Five Towns College offers the most advanced recording facilities including a 16-Track, 24-Track and world-class 48-Track digital recording studio You will take master classes with leading professionals and our internship program will place you in one of NYC's top recording studios. Five Towns College is fully accredited and tuition is affordable. And housing is available for outof-state residents. Call or write Five Towns College and ask about our music programs.



Five Towns College 305 N. Service Road, Dix Hills, NY 11746 (516)-424-7000 ext. 110.

CIRCLE 144 ON FREE INFO CARD



CIRCLE 151 ON FREE INFO CARD

IN REVIEW

E-mu's Darwin Evolves: The ADAT Connection



MANUFACTURER: E-mu Systems, Box 660015, Scotts Valley, CA 95067-0015. Tel. 408-438-1921.

APPLICATION: Eight-track hard-disk recorder designed for stand-alone use or with ADAT systems.

SUMMARY: It's not as sophisticated as computer-based hard-disk recorders, but Darwin enhances ADAT with editing capabilities, while ADAT provides cheap backup for Darwin.

STRENGTHS: Easy-to-use, non-intimidating interface; excellent sound quality; digital routing is well-implemented and all bouncing occurs digitally; complements ADAT well; multiple levels of undo; "virtual slave reels" make 8-tracks seem like much more.

WEAKNESSES: No DSP; display doesn't show waveforms; cannot slave to MIDI systems; no automated mixing or punching; can't reference times to bar/beats/measures.

PRICE: Model 4000 (no hard drive), \$3195; model 4001 (internal 1 GB drive), \$3795; model 4002 (internal Jaz), \$3995; model 4003 (reviewed; with Jaz, ADAT sync and digital I/O), \$4374. Accessory boards: ADAT optical I/O, \$149; ADAT 9-pin sync, \$379; 4-input analog expander, \$249.

EQ FREE LIT. #: 127

BY CRAIG ANDERTON

BY NOW YOU may have read reviews of E-mu's Darwin hard-disk recorder in other publications (that's okay, we're not the jealous types). EQ didn't mind waiting on this one because we knew this product would go through changes. And Darwin has indeed evolved into a different type of product; thanks to the latest software/hardware options (optical I/O board for communicating with ADAT's "light pipe," and ADAT 9-pin sync card), Darwin is now being positioned as an adjunct to ADAT-based studios. So rather than reviewing Darwin on its own, we thought it would be best to look at E-mu's new little beast in a system context, and see if it really does improve life in the project studio when mated to ADAT. —HGL

Question du jour: Tape or hard-disk recording? If your budget allows, I've always recommended having both -tape excels at capturing and storing signals, while hard disk is great for editing. Apparently E-mu feels similarly, because they're making a case for not buying that second or third ADAT, but buying a Darwin instead. Like ADAT, Darwin provides eight tracks of digital audio, responds to the BRC and other ADATs, and is even about the same size. But it also has several tricks up its sleeve that ADAT doesn't. Have we arrived at a "best of both worlds" situation? Let's investigate.

BASIC DARWIN

For those unfamiliar with Darwin, here's an overview. This 3-rack space, self-contained 8-track hard disk recorder offers





P.O. BOX 5976 SAN CLEMENTE, CA 92673 USA TEL: 714.492.2000 FAX 714.492.4284

CIRCLE 10 ON FREE INFO CARD



several storage options: internal hard drive, no internal hard drive (use the SCSI port), and internal Jaz. I/O includes 8 analog outs, 4 analog ins (optionally expandable to 8), S/PDIF, headphones, punch/record footswitch, and MIDI in/out/thru. There's a SCSI port for additional hard drives and a computer port for future expansion (this is currently unimplemented). The display is a backlit 5- x 1.5-inch LCD; it's better than tape, but spartan compared to computer-based hard-disk recording programs.

Darwin has some fun tricks; my favorite is "virtual slave reels." You can copy a song to create different, memory-efficient "versions," which opens up many editing options. As just one example, copy a tune with stereo drums, vocals, piano, bass, and rhythm guitar (each part on its own track) to create a new version. Premix everything in the new version to 1 track as a reference. Next, record several lead guitar parts, then create a fabulous composite solo by keeping the best bits (and erasing the rest) from each guitar solo prior to bouncing them to a "composite" track. At this point you're still working with the copied version. Finally, cut (or copy) the composite track, and paste it back into the original song. This isn't quite the same as having unlimited tracks, but it sure makes eight tracks feel like a whole lot more.

Also handy: 40 autolocate points, multiple levels of undo, and a shuttle/jog wheel for scrubbing (however, it's choppier and less precise than rocking the reels on analog tape). Editing is basic — cut, copy, insert, replace, erase, insert silence, and move — but definitely functional. Darwin can output MTC, but cannot slave to MIDI (although it responds to MMC controls for start, stop, etc.). It syncs up easily with ADAT via the 9-pin card as master or slave.

Signal routing is all-digital; there are five presets and one user preset (although its settings aren't memorized when you power down). The internal digital mixer is great for bouncing, but there's no automation. Nor is there any DSP, other than the adjustable crossfade time that comes into play when doing edits. (E-mu has already anticipated many of these critiques; see the "Preview" sidebar.)

Recording is straightforward, however, you can't drop in autolocation points "on the fly," nor is there autopunch (use the front-panel controls, a footswitch, or MMC commands). I found it simplest to record the part to be punched on a separate track, copy it, and paste it over the punch zone on the track to be fixed.

What Darwin may lack in sophistication, it makes up for in ease of use. When someone buys a computer-based hard-disk system, my advice is not to use it on a session for at least a week while you learn your way around. Darwin is the opposite — I had it figured out in a couple hours, which included unpacking, installing three option boards, and reading the entire manual (which is clear and easy to follow).

DARWIN MEETS ADAT

sing the two as a team is a snap once you get used to some new concepts. For example, the two systems' rewind/fastforward times differ, so if you tell the master to rewind, the slave may rewind at a slower or faster rate, depending on whether you've selected fast or slow wind modes on the ADAT and Darwin (these are not identical and do not track each other). As a result, with ADAT slaved to Darwin, Darwin starts playing before the ADAT locks up, which can take several seconds if the two are at very different times. If Darwin is the slave, it plays back shortly after the ADAT starts, which is more predictable.

Frankly, though, this is all pretty moot because you'll end up doing most of your locating with the autolocation buttons. Autolocation is fast, simple, convenient, and works equally well whether Darwin is the master or slave. As a master, Darwin's transport Stop button can also thread/unthread the ADAT tape.

Darwin allows 44.1 or 48 kHz sampling, although ADAT was never really intended to be a 44.1 kHz system, and it's less confusing to keep everything at 48 kHz (if you run at 44.1 kHz with a BRC, MIDI sequencers fed from the BRC will play back slower compared to using the sequencer's internal clock, and the ADAT time display will read slow compared to Darwin).

Transferring parts between the two devices is simple. Although Darwin can save to an external DAT drive, it's a lot easier to just blast the eight tracks over continued on page 140

PREVIEW: VERSION 2.0 IS COMING

According to E-mu, Version 2.0 software (slated for release at the Los Ar geles AES convention) will offer:

• Support for a SMPTE card, which handles all timecode formats. It features timecode in/out on balanced 1/4-inch jacks and BNC word clock in/out.

• Support for a floating point, 32-bit processor-based DSP card. Initial functions include gain and fade control, time compression/expansion, and highquality polyphonic pitch shifting.

- Mixer levels can be controlled via MIDI
- Front-panel and ADAT 9-pin autopunch
- On-the-fly storage of locate points
- QIC tape drive support for low-cost SCSI backup

24 Bit Digital I/O

AES/EBU

Time Digital Format Conversion

Optical & Coaxial

ers, co players, orginal consoles &

Presenting Multi!Wav Digital PRO: The ultimate card for direct digital sampling & transfer in Windows.

Use Multi!Wav Digital PRO to make digital masters, digital mixdowns, sample edits, and direct transfer of audio files with NO GENERATION LOSS!

Use Multi!Wav Digital PRO for real-time digital format conversion!

Multi!Wav Digital PRO is future upgradable! Add new HARDWARE features, such as 24 bit audio, from <u>sof</u>tware!

Multi!Wav Digital PRO installs easily into your EXISTING setup - WITHOUT IRQs! Use it with any WAV editor, such as SAW, Sound Forge, Samplitude, Cakewalk PA ...

Best of all, Multi!Wav Digital PRO sounds great! Use it for your most demanding work."

Multi!Wav Digital PRO: The best in professional digital I/O for <u>Windows</u>.



18 Bit Analog Output

Professional Digital I/O for Windows

Multi Way Digital PRO/PRO 18 Features.	What you can do with Multifivery Digital PRO/PRO 18
Prof <mark>essional AES/EBU</mark> Digital I/O Capability	Direct digital sampling and transfer with any AES/EBU connection Interface to DAT machines, hard disk recorders, digital consoles, broadcast equipment
Optical & Coaxial S/PDIF Digital I/O Capability	Direct digital sampling and transfer with any S/PDIF connection. Interface to DAT machines, CD players, samplers, Macs & other computers, digital mixers
High Quality 18 Bit Analog Output	Clean 18 bit monitoring of digital output without need for "second DAT". Future upgradable to QUAD output for INDEPENDENT analog and digital outputs! (PRO 18 only)
Real-Time Digital Format Conversion	Convert Optical to Coaxial, S/PDIF to AES/EBU, or vice versa, in REAL-TIME
Software Upgradable Hardware Design	New HARDWARE features can be added from software, such as 24 bit audio & more!
Multi-Track Transfer Mode	Free up CPU time! Increase multi-track software performance! Do 24 bit simultaneous record & play. (PRO18 only)
Shielded Transformers	Reduce common-mode noise and clock phase jitter.
Flexible Ground Strapping	Achieve optimal grounding configuration.
Independent Master or External Sync Clock	Maintain sync during SRP for internal digital mixdowns Sync [analog &] digital output to an external clock.
Multiple Card Support	Use multiple Multi!Way Digital cards in one PC.
256/512 Bit Upgradable RAM FIFO Buffer	Improve performance reliability by reducing sensitivity to hardware underruns & overruns.
I/O Overload Protection	Protect against misconnection of I/O ap to 50 VDC.
LC Filtered Analog Supply	Improve receiver PLL performance by reducing noise.
Multi-Layer PCB	Improve performance by reducing "digital" noise.
► 64 Selectable Addresses	Eliminate hardware installation conflicts.
> Professional Sample Rates	48kHz, 44.1kHz, 32kHz (software selectable).

MultilWare Digital FRO Series is available in three versions: FRO 18, PRO, & SP. MultilWav Digital (all versions) requires, one 16-bit ISA bus slot; a computer that invests the hardware requirements of your WAV editing software; and digital 1 O cables, 24 bit audio functionality requires a software upgrade. Please visit our Web site for the latest specifications. Specifications may change without notice. AdB and MultilWav are trademarks of AdB International Corporations Made in USA.

NOW, bundled with Multi!Wav Digital PRO is Sound Forge XP, Winner of the 1995 Multi!Media World All-Star Competition. This offer is limited. Contact AdB International for details.



Questions? Give us a call or visit our Web site.

AdB International Corporation • 2180 Pleasant Hill Rd. Suite A-5100 • Duluth, GA 30136 Voice: 770.623.1410 • Fax: 770.623.1629 • E-Mail: info@adbdigital.com • Web: http://adbdigital.com

CIRCLE 141 ON FREE INFO CARD

IN REVIEW

Yamaha MD4 MD Recorder/ Mixer



MANUFACTURER: Yamaha, 6600 Orangethorpe Ave., Buena Park, CA 90620. Tel. 714-522-9011.

APPLICATION: "Ministudio" sketchpad for songwriting, arranging, demos, live recording, etc.

SUMMARY: The cassette multitrack recorder has finally met its digital match in this MiniDisc-based 4-track recorder/mixer.

STRENGTHS: Sound quality vastly superior to cassettes; MIDI sync doesn't require giving up a track; can bounce into already-recorded tracks; quiet operation; "Undo" function by saving copies; fast locating; variable speed option; easy to use.

WEAKNESSES: Tempo map not saved with song; mixer knobs don't feel particularly solid; no digital I/O; data compression inherent in system; limited compatibility with standard audio MDs.

PRICE: \$1199

EQ FREE LIT. #: 128

BY CRAIG ANDERTON

WHEN I FIRST heard about multitracks based on the MiniDisc (a format touted by Sony as a replacement for the analog cassette), the concept seemed like a strange match. But now that I've lived with one for a bit and had the time to put any prejudices aside, I'm quite impressed. Twenty years ago, when the dollar was worth a lot more, it cost almost \$1000 for an analog 4-track recorder. Today, a little over a grand buys a 4-track digital ministudio that runs circles around cassette ministudios, and even incorporates some hard-disk and digitaltape recording features. Yup, there's a new toy in town — and it's much more than I had expected.

BRAVE NEW WORLD

The MD4 resembles a tape-based ministudio. However, while the mixer is a traditional analog type (see sidebar), optical-based recording offers several advantages. The first time you bounce four tracks into one without needing a spare track to bounce into, or sync up a MIDI sequencer without having to stripe a track first, you'll know you're not in Kansas anymore.


The MD4 uses MD data storage discs (not MD discs intended for recording audio, although standard audio discs will play back on the MD4; see sidebar). These provide about 37 minutes in 4-track mode, 74 minutes in



stereo mode (which is not compatible with standard audio MD playback), or 148 minutes in mono. You can mix and match the various modes within a given disc, but not within a given song. A total of 254 songs can be recorded and titled, but you'll hit that limit only if you record a ton of short cues or samples.

MiniDiscs have a TOC (Table Of Contents) area that tells the machine where to find particular pieces of data or edits, and must be updated periodically. If the power goes away before updating the TOC, you could lose data. For-

THE COMPRESSOR LIMITER EXPANDER/GATE THAT WILL TURN THE WORLD ON ITS EAR. AGAIN.



You've seen and heard dbx signal processors for as long as you've been involved with audio. After all, our boxes are in daily use all over the world, with major touring companies, world class recording facilities, radio and television broadcast facilities and anywhere else audio professionals ply their trade.

Now, after over twenty years of pleasing the most finely tuned ears in the business, dbx has done it again with the new 1065. The dbx 1066 will, of course, be the standard against which all compressor/limiter/gates are judged. State of the technology VCA's, meticulous component selection, and scrupulous testing procedures are just a few reasons the new dbx1066 is the latest in a long line of

pedigreed signal processors.

So head on down to your local dbx dealer and audition this box. We're sure you'll see why the dbx1066 is destined to turn the world on its ear.

Save the Plant I I is the Oaly Market Wrive Ge

For more information contact us at: (801) 568-7660 Fax (801) 568-7662 dbx 8760 S. Sandy Parkway, Sandy, UT 84070 USA or if you prefer surfing to snailing send e-mail to customer@dbxpro.com

©1994 dbx Professional Products Jensen® and Neural Corr resident distances of Jensen Transformers Inc. and Neurak USA respectively.

tunately, an indicator lets you know when the TOC needs updating, and it's impossible to eject the disc without finalizing the TOC.

At present, finding MD data discs from a source other than Yamaha is difficult. No one even knew what I was talking about when I called large computer stores, such as Fry's. Fortunately, with TASCAM and Sony also having MDbased multitracks out in stores, the market should heat up a little bit and make discs more widely available in this country (they are readily available in Japan, where MD has been quite successful). Hopefully the price will also come down a bit from the current U.S. cost of \$29.95 per disc.

PONG & PUNCH

The MD4 can record on all four tracks simultaneously, but you can build up more tracks through clever ping-ponging (bouncing) options. Bouncing occurs through the analog mixer, not digitally. However, the quality remains

YAMAHA MD4 MIXER FACTS

Connections

- 1/4-inch phone: 4 mic/line ins, L/R aux return, mono aux send.
- RCA phono: Stereo submix in, stereo out, stereo monitor out, 4 track direct outs
- MIDI out
- Headphone out
- Input Strips (4 total)
- Gain (accommodates mic and line signals)
- EQ (3 controls: ±12 dB shelving @ 12 kHz and 80 Hz,
- ±12 dB peaking @ 1 kHz)
- Mono aux send (stereo returns)

• Group assign (1/2 or 3/4). Assigns input signal to the desired track. It works in conjunction with the panpot (e.g., if 1/2 is selected, the panpot sends the signal to group 1 or 2 at the extremes of rotation, or anywhere in between).

- Pan control
- Input select (mic/line or playback from disc)
- Fader

Master Section

• Aux return group assign. Works similarly to the input strip group assign; the return is also permanently assigned to the stereo bus for mixing.

• Aux return level. Adjusts the stereo returns level.

• Stereo submix group assign. This works like the aux return group assign, but with the signal connected to the stereo submix in (e.g., from another mixer, tape, or CD, etc.).

• Stereo submix input level. Adjusts the stereo submix in levels.

• Monitor select switches. Choose from groups 1/3, 2/4, master stereo bus, or cue bus.

- Cue level (four separate controls for each track)
- Monitor level (sets monitor out and headphone volume)
- Stereo master fader

high through multiple bounces; certainly there's no comparison to the humiliation that bounced signals endure with analog cassettes. The "feel" is just like piloting a cassettebased device, since you spend most of your time working with the mixer; when you do think about the transport, it's mostly to realize you're not waiting for rewinds or fast forwards any more.

The MD reads data from the disc before writing, so you can play back all four tracks while bouncing down to the destination track or tracks (yes, you can mix down your song within the MD4 itself by bouncing to two tracks!). Although this overwrites existing track data, a rehearse mode lets you practice the premix. Better yet, you can copy the song you're working on elsewhere in the MD as a "safety." This lets

you record with a much more secure feeling.

The concept of bouncing to a different part of the MD is a radical, and way cool, departure from tape. For example, suppose you want to premix a song with guitar, bass, drums, and piano before adding vocals. Copy the song, premix the copy, then add vocals. If while adding the vocals the guitar seems too loud, no problem: nuke the copy, recopy the original, do another premix, and try again. You can "archive" a song in various stages of completion so that if you need to "undo," you can at least go back to an earlier version and try again. Incidentally, copying a song also copies the title, location markers, and tempo map (described later), in addition to the audio.

But wait...there's more. A divide function can cut a song at any point, converting it into two new songs (songs are renumbered if needed). Songs that were divided can be recombined later on (another "undo"like function, but you cannot combine unrelated songs; they must have been joined previously).

You can also copy tracks, or parts of tracks, to other tracks. One scenario would be to record four vocals over a sequenced MIDI background, then copy the best parts of each to the fourth track to create a composite vocal. Individual tracks can also be erased. All this is done similarly to working with cassette multitrack recorders.

Punching is well-implemented. You can punch manually, with a footswitch, set up autopunch points on the fly, or set points manually while the unit is stopped. Pre- and post-roll times (times before and after punchout, respectively) are independently adjustable from 0 to 9 seconds, and a rehearsal mode lets you audition the punch before committing to it. In this mode, the machine simulates the punch, proceeds to the post-roll point, then returns to the pre-roll point so you can do another rehearsal or punch "for real." This sequence of events can also be initiated via footswitch. Punches are accurate to within ±5.8 ms, since the MD4 stores data in "frames" that are 11.6 ms long.

KURZWEIL POLOBB

THE HOTTEST THING UNDER THE SUN IS ALSO THE COOLEST

1995 TEC AWARD WINNER!!



THE WORLD'S FINEST PROFESSIONAL DIGITAL PIANO KEYBOARD CONTROLLER



THE BEST JUST KEEPS GETTING BETTER! VISIT OUR WEB SITE AT www.youngchang.com/kurzweil E-mail at kurzweil@aol.com

Kurzweil Music Systems, 13336 Alondra Blvd., Cerritos, CA 90703 Tel: 310-926-3200 Fax: 310-404-0748 Young Chang (Plano) Canada Corp., 395 Cochrane Drive, Markham. Ontario L3R 9R5 Tel: 905-513-6240 Fax: 905-513-9445

> CIRCLE 150 ON FREE INFO CARD World Radio History



TRANSPORT GOODIES

There are no standard rewind and fast forward functions, but rather 2X and 4X cue and review modes. Little fragments of the signal play back as you shuttle across the disc, so you know where you are; even when reviewing, the signal never plays "backwards.'

To locate to points in a song, it's faster and easier to use search functions. These include:

· Search for song. This works

like the buttons on CD players that take you to the next or previous song.

· Search by time. Lets you specify and go to a specific time within a song, or anywhere in the disc.

· Find most recently set record in and out points. This is also handy for checking punch points.

• Search for markers. There are ten markers: Start and End, (which cannot be edited) and eight user markers you can insert during playback and/or record. These can be edited or erased; existing markers are renumbered when you insert a new marker between existing markers. One very cute feature: when editing marker locations, the MD4 performs a temporary volume change at the marker so it's easy to hear precisely where the marker occurs. I wish all programs had this feature, it's an obvious and effective aural cue.

You can create a playlist of songs recorded on the MD, but there are also repeat (loop) and cue list (playlist) options - loop one specific song, all songs, or a user-definable portion of a song. Playlists are assembled by using marker locations and specifying the order in which cues should be played. Up to nine steps are available; each step specifies the start marker, end marker, and number of

MINIDISC BASICS

The MiniDisc (MD) is essentially a miniature, recordable magneto-optical disc that comes in two formats: Audio (designed for the MiniDisc record/playback audio devices targeted to consumers) and Data (used for computer storage and, now, multitrack recording).

To get the most out of its 140 MB storage capacity, the MD uses data compression (or more correctly, data omission), which discards portions of audio deemed unnecessary, such as silence. Although the coloration is subtle, compared to DAT, the sound seems a bit more compressed (which affects the stereo imaging somewhat) and has a more "hyped" high end. Then again, that seems to be an effect lots of people are looking for these days. However, let's put things in perspective: the coloration isn't even remotely close to what a cassette does to your sound under the best of circumstances, and the effect is subtle enough that many people don't even notice it. Given the advantages of optical over analog tape-based systems, compression is a tradeoff that's easy to accept.

> repeats (1 to 9). For example, the MD4 could play from marker 1 to marker 5 three times in a row, then marker 2 to marker 3 twice, and so on.

> One caution: If you remove a marker, even if it's not used in the cue list, you'll get an error message when you try to play the cue list. This problem does not occur if you simply edit the marker nositions

> Does this sound like the ultimate sketchpad remix machine? Close, but there's no way to crossfade between sections, and you may not be able to place a marker exactly where you want due to the 11.6 ms frame size. Still, despite a warning in the manual that there can be discontinuities during transitions, the cue list feature worked extremely well when testing out remix options on a song I'd transferred over to the MD4. After the playlist is set, you can even create a new song that glues all the pieces together in the order you specified.

> A pitch control provides a range of about ±6 percent, and the sound quality remains excellent while pitch changing. One tip: If you slow down the full amount, it's easier to find precise points when editing marker locations.

> > continued on page 140

CIRCLE 86 ON FREE INFO CARD

	P		C	E
A	Annel I Dranel 0.000 \$, Delay 0.000 Plute Display Channel 2 R	dynamic channels wi Now with full move a For Digidesign® Pro	Tools® with TDM	
C goo C 11005 C 11005	n 2.00 prrection [225 017 Rm Conter Filter O'Tools SR Convert 10'9WAL	Lasd Setup		
C 2005 C 2400 C 24000 C 24000 C 24000 C 2400 C 2400 C 2400 C 2400 C 2400 C 2400 C 240	Lano Muris with helpon in 0.0 di 0.0 di Protectione Lano Coloradi Lano Coloradi 10 lano 0.0 dia 17 Higi	Cancel	QX/TDM professional soun expands stereo main or sub findividual stereo or panne For Digidesign® Pro T	dfield enhancer nixes including d mono tracks.
	intection Dennetic (0 is 20 of 2) UStrace Part (0 - 126)	(SH - 500 Hz) 156	Tools/SF includes: ISYS/SF single-channel static nono-to-3D localizer, IX/SF stereo enhancer and ISRC/SF sample rate converter.	

When the time comes to gain control over your space, QSound 3D audio plug-ins are simply the way to go.

Whether you choose a QSYS mono-to-3D localization tool or a QX stereo expander, you'll be in command of the most effective, best-sounding spatial enhancement available for loudspeaker listening. And 3D doesn't have to come at the expense of mono-compatibility – all QSound plug-ins have advanced features to help you keep your mono in line and your low end solid and natural.

QSound 3D audio technology is based on extensive research tempered with the skill and taste of audio professionals. Accept no substitutes!

When you're ready to go beyond stereo, you're ready for QSound.

OSYS/TDM, OX/TDM, OXSDII, OTools/SF, QSYS/SF QX/SF & OSRC/SF are trademarks, and QSound & the QSound logo.are registered trademarks of QSo and Labs, Inc. Sound Designer II is a trademark, & Digressing & IPro Tools are registered trademarks of Digdesignit, a division of Avd Tectinology. Inc Sound Forge is a trademark of Sonic Foundry.



QX/SDII professional soundfield enhancer provides high fidelity stereó expansion. Perfect for mastering! For Digidesign® Sound Designer II™

bound Labs, In

2748 37 Avenue N.E. Calgary, Alberta, Canada T1Y 5L3 Tel 403.291.2492 Fax 403.250.1521 Canada/US Toll-free 1.600.315.8955 Email: proaudio@qsound.com

ON ERSE INCO CARD

2015 148



DSP·FX Digital Effects Processor



MANUFACTURER: Power Technology, 100 Northhill Drive, Building 24, Brisbane, CA 94005. Tel: 415-467-7886. Web: http://www.dspfx.com

APPLICATIONS: Very high-quality reverberation, echo, flanging chorusing, and pitch-shifting effects for studio applications.

SUMMARY: An effects device capable of clean and dense reverb and timeand pitch-shifting effects with a unique interface that brings all parameters into view at a glance.

STRENGTHS: Excellent true stereo effects; very low noise floor; hugely expandable while still very easy to use; software support for multiple DSP-cards.

WEAKNESSES: Requires a PC host that will typically have a noisy fan; currently limited to one effect per DSP-card; may require careful PC slot selection to avoid internal PC noise when using on-board analog I/O.

PRICE: \$1299, Studio System with hardware and five software modules (as reviewed); \$799, basic unit with hardware and one software module of your choice

EQ FREE LIT. #: 129

BY WADE MCGREGOR

WE HAVE SPENT so many years staring at the tiny displays of the typical effects unit that we can be forgiven in assuming that it is the only way to control our effects. Although there were a few MIDlots that used a computer and MIDI interface to enlarge their window into the world of algorithms, the rest of us developed a knack for using nudge buttons and parameter knobs. We also resigned ourselves to either spending serious money for a high-end unit or using phone jacks and 16-bit conversion as the normal connection to our mixers.

Power Technology has developed an effects system that sidesteps not only the limitations of the typical rackmount processor, but also the limitations of the DSP architecture that powers most of the current units on the market. Unlike the other effects processors, the DSP•FX is a card that is inserted into the ISA-bus of a PC. Thankfully, it doesn't suffer from the limitations commonly associated with internal cards in computers because all of the audio functions remain on the card. The connection to the computer is simply there to provide the virtual front-panel interface for the unit. This allows the DSP+FX to maintain high-quality audio in spite of the noisy and clumsy (for audio) internal workings of the IBM-compatible computer. The result is a device producing effects that are excellent in both sound quality and user interface.

The DSP•FX provides a visual interface that is extremely easy to use and shows everything you need to know about the parameters in a single glance. The ability to bring a software-based user interface onto the computer screen allows the designers at Power Technology to focus on visualizing (see fig. 1) the parameters with the full power of a VGA display instead of simple text and graphs on an LCD in the front panel of a device. By using the mouse and keyboard, it is easy to adjust the parameters, and the graphics display the results as the changes happen. The computer also simplifies the storage and recall of presets. Users will be able to add new effects algorithms or download other users presets from the Internet and immediately try them out on their processor. Power Technology has developed a scheme for upgrading that will allow users to receive the new plug-ins (\$199 each) via the Internet or on disk.




FIGURE 1: The reverberation control screen for the DSP•FX. Parameters are controlled using the mouse to adjust (surprisingly easily) the knobs. The image on the left shows the current settings of the controls through visual metaphor.

The Studio System version (as re-

FOLIO

THE FACTS (& no Bull)

At Soundcraft. designing the mixing

consoles people actually want has been a serious business for over 22 years. We've listened to our customers - from budding musicians to world-renowned artists and sound companies and we've built their wish-lists into our mixers. We don't hype our new features and we don't go in for gimmicks. When you listen to SX you'll realize we listened to you.

NO HYPE **NO GIMMICKS** NO BULL.

FOLIO SX is a powerful, multipurpose mixer with DAT quality sound, housed in a freestanding frame with carry handle.

\$769.95 Suggested Retail in USA

• 20 inputs (including i stereo channels) as standard, enough for most live and recording situations

- 12 mono inputs with UltraMic™ preamps giving 60dB of gain range and +22dBu of headroom, allowing any mic or line device to be plugged in.
- · Two sub-buses allow you to record groups of instruments to multitrack, send them to additional speakers, or sub-group to mix. SX also has a dedicated Mono Out.
- · 8 Direct Outs switchable pre/post fader, equally useful when recording in the studio or at a gig.
- · 100mm faders throughout
- · Real British 3-band EQ with swept mid
- 18dB/Octave High Pass Filter effectively reduces low end muddiness.
- · 3 Auxiliary Sends: 2 can be pre- or post-fader.
- · Custom-designed consistent controls give an even spread of control around their sweeps.
- Surface-mount technology
- Rack mount option

SX's Direct Outs on the first 8 inputs are front panel switchable prelader for live track laying or post-fader so you can massage" recording levels in the studio.



UltraMic[™] padless preamp gives 60dB of gain range with 22dBu of headroom Insert point for effects Direct Out on channels 1-8 100Hz steep slope High **Pass Filter** 3-Band "British" EO with swept mid 3 Auxiliaries configurable 2 x Pre/1 x Post or 1 x Pre 2 x Post Channel "ON" switch MIX/SUB routing switch Full 100mm fader PFL

STEREO INPUTS

13. 14, 17 & 18: simple phono inputs with Bevel and MIX/SUB routing

15, 16, 19 & 20: Balanced jack inputs with Gain, 2 band EQ. Aux levels, Channel 'ON', MIX/SUB routing, 100mm fader and PFI



APPLICATIONS

LIVE SOUND Bands, small venues, conferences, schools, places of worship STUDIO RECORDING Digital and analogue multitrack (4 & 8 track), small or home studios, pre-production, video post production SUBMIXING

LOCATION SOUND

TYPICAL **SPECIFICATIONS**

Mic EIN	-129dBu
Crosstalk (1kHz)	
Channel Mute	<95dB
Fader Cutoff	<90dB
Frequency Respo	onse
(20Hz to 30kHz)	<1dB
THD	<0.006%

URFACE MOUNT ECHNOLOGY REAKS THE EATURES/PRICE ARRIER

As one of the world's largest mixing console manufacturers, Soundcraft has invested in the most advanced production systems available. Leading edge circuit construction using

Surface Mount double-sided glass epoxy PCBs means lower manufacturing costs without any downside. The result: much more mixer for your dollar.

CIRCLE 145 ON FREE INFO CARD

Spirit by Soundcraft[™] Inc. 11820 Kemper Road Auburn, CA. 95603 Tel: (916) 888 0488



http://www.spirit-by-soundcraft.co.uk




FIGURE 2: The Multi-Tap Delay control screen displaying the individual (Edit) parameters for channel 4 (green). The image at the upper right shows the settings for all eight delays including: panning (location left to right); relative level (size of outer circle); feedback (size of inner circle); and delay (relative vertical position). A single glance provides confirmation of all settings.

viewed) includes the full set of effects, reverberation, echo/delay, flanging, chorusing, and pitch shifting. All these effects were supplied with a wide range of useful factory presets and, of course, the number of user presets are unlimited. Parameters are well chosen and provide a useful range of control that is deeply enhanced by the visual feedback of the graphic display. This graphic display incorporates sensible metaphors for each parameter that allow you to see, in a single glance (see fig. 2), all of the settings of even the most complex presets.

Note that most current effects processors use a 24-bit fixed-point DSP to manipulate the audio. This seems sufficient considering we can be quite happy with the quality of 20-bit audio. However, as signal levels decrease, such as with a reverb tail, a fixed-point DSP begins using less and less of its 24-bit path word to represent the signal. This results in a signal path that can often be far less than 24-bits - a detail that is most noticeable in the tail-out of the effects as the processing approaches the noise floor. The audible result is a grungy distorted sound to the very lowlevel audio signal.

The DSP•FX employs a new Texas Instruments TMS320C32 32-bit floatingpoint DSP to increase the dynamic range of the audio (the floating-point format always uses all 32 bits to represent the signal value) in order to eliminate the low-level distortion common in effects that depend on considerable regeneration, such as reverb and echo. The result is especially noticeable in longer reverb settings, where the sound decays smoothly and cleanly. There is also a notable lack of stuttering or pitch to the reverb. I found that it was easy to create a recital hall for piano tracks or a cathedral for a choir. The small room settings were able to create a convincing ambience for a jazz trio that gave the impression of small, smoky room without any of the hollow tube quality common to small room settings in lesser reverberation units. The DSP•FX is also capable of true stereo reverberation (input panning affects the early and late reflection localization) available in only a couple of other reverb units on the market.

The brightness of the reverb can easily be adjusted with the high-frequency decay control. (I would also like to have control over the relative decay rates of the mid and, especially, the low frequencies.) I found the density (diffusion) control to be far too subtle and would prefer far more diffuse reverberation for some applications. I also experienced some noise from the onboard I/O when the DSP•FX card was too near the video card in the computer, and some of the longer reverberation (Room Liveliness) settings had a tendency to cause low-level oscillation when left without an input signal.

The DSP•FX's echoes remain clear and even intelligible after seconds of regeneration. They are so good that you can use them with a little regeneration to create small rooms for background vocal tracks or blending horn sections. The chorusing and flanging are excellent and hearken back to the days of a finger on the reel of an Ampex AG-440. The visual interface provides not only a reference during adjustment, but allows you to remember (visually) which range of settings were suitable to a particular guitar style or drum track. The quality of the chorusing and flanging allows even excessive settings to work without obscuring the original instrument. The pitch-change algorithm sounds very clean, however, I had difficulty losing the slight vibrato quality.

The unit offers MIDI control over all parameters for each module. This allows control over the unit even when it is buried behind other Windows applications. By assigning a MIDI switch, access is even gained to the parameters in the Edit page, such as the reverberation; early and late decay; or density (diffusion). With sufficient MIDI controllers, you can remotely access all of the onscreen parameters. Power Technology offers a gold-colored version of the JL-Cooper CS-10 MIDI controller (\$999) that features dedicated knobs, switches, and faders for all the MIDI-addressable controls of the DSP•FX. The DSP•FX is compatible with any CS-10. It only took a few minutes to set up my Lexicon MRC (MIDI remote control) to achieve hardware fader/pushbutton control over the most important parameters. MIDI control requires a MIDI interface (not included) for your PC or Windows application that can produce controllers (such as Cakewalk or SoftMC) and offers potential for automation control of the effects. The clearly written and well-organized manual includes a complete listing of the MIDI control values.

The DSP•FX is part of an open-ended DSP platform. For those who do not own a Windows-based PC or don't want to open up their computer, a complete package (DSP•FX Power Pack, \$3995) is available, including a rackmount PC with room for up to six DSP cards connected on a high-speed proprietary bus. An optional rackmount 2channel interface with 20-bit A/D and *continued on page 142*

IN REVIEW

Ridge Farm Gas Cooker Tube DI



MANUFACTURER: The Home Service, 178 High Street, Teddington, Middlesex TW11 8HU, United Kingdom. Tel: 44-181-943-4949.

APPLICATION: Project and commercial studios; guitar rigs; live sound.

SUMMARY: Two-channel, all-tube DI.

STRENGTHS: Stonking sound [US translation: *real good* sound]; superbly variable; very versatile; perfect tube DI.

WEAKNESSES: Not a rackmount.

PRICE: \$649

BY ZENON SCHOEPE

EQ FREE LIT. #: 136

DESIGNED BY THE boffins [US translation not available] at Ridge Farm residential studios in Surrey, England, the Gas Cooker is based on a unit originally built in response to client requests for tube gear and which sat on the studio floor for years in a wooden box. It was tested along with two other DIs by Geoff Emerick, Alan Parsons, and John Hudson in the August '96 issue, but we felt it also deserved our typical EQ "In Review" treatment.

The Gas Cooker is now commercially available and it's an all-tube (three ECC83s) twin-channel DI box with a switchable 20-dB input pad, a buffered unbalanced output (which is pre gain-control pot), and unbalanced and balanced post gain-pot outputs (the last sporting transformer isolation with a switchable ground lift). All connections except the unbalanced output are on the front panel.

Gain is controlled on two, large, old-fashioned, gas-cooker-style knobs that are calibrated and marked for unity gain at around the number 3 on the scale and offer a maximum of X30 on the unbalanced output and a maximum of X3 on the balanced connector. The Cooker's fairly meager controls and facilities are extremely adaptable. Aside for the usual DI'ing of guitars and basses, it can be integrated into a guitar rig as a very capable front end. Keyboards get in on the act by virtue of the variable gain and you can color the sound up to taste. Plus, you can process console outputs. If you track with it, you'll end up with something that sounds distinctly different from what you would have got otherwise.

This DI sounds absolutely stupendous. It probably is the best DI I have ever used because it's so variable and because it stamps TUBE on everything it goes near — immediate resonance and thickness without any loss of quality.

This box provides the best clean DI guitar sound I have ever achieved. The sensitivity is marvelous. Driving the gain harder doesn't give you a mini-Marshall stack sound, but it does dish out a meaty chordal sound with hotter humbuckers.


Bass guitar sounds smooth and goes on forever through the Cooker, and yet it still holds everything together even if you tune the bottom E down a couple of tones.

Quite honestly, if you had one, I can't think of any good reason why you would not want to use the Cooker all the time.



Organic Digital Solutions

from this past summer



A ll summer long I had my head buried in digital tape machines. Now I wanna share some stuff with you.

REAL BASIC TIPS

• Fast-wind all tapes end to end before formatting

- Clean the heads after formatting
- Wind tapes to either end and remove from machine when not in use

• Know how to query the machine's total head hours


• Have a maintenance schedule and stick to it, *or*...

• You know it's maintenance time if the machine eats a tape, freezes up, and displays error messages.

• Get a humidity gauge (Radio Shack Part Number: 63-867)


Don't smoke

Manhattan is an island surrounded by water. It ain't "Nawlins," but it can get muggy in the summer. DAT machines are pretty forgiving, but weather extremes can make your digital 8-track more temperamental than usual. In a video machine room, temperature and humidity are kept to 67 degrees and 40 percent, respectively. Too little air moisture in-



creases static electricity. Too much moisture makes the tape stick to the heads.

The typical mid-August weather in my shop/studio is 75 degrees, 49-percent humidity with the AC on. If I turned the AC off, the temperature might only rise a few degrees, but the humidity can easily jump ten percent! Pick up a temperature/humidity gauge and take note of the changes from day to day. You may find that high humidi-



ty contributes to more than just "bad hair." Try to regulate the humidity and don't forget to change the filter in the air handler. Vacuuming is also highly recommend (be sure to change that filter, too), while smoking is not.

COOL AND CLEAN

The TASCAM/Sony digital 8-track deck has fan cooling. The fan draws air into the machine across the electronics, which is good, but it can also suck dust in through the mechanism's tape-access "port." Use the high-velocity vacuum cleaner nozzle attachment and a 1/2inch artist's brush to remove the stuff that collects in this area.

In order to bring cleaner air into the machine, it must first be filtered. The filter is available from Digi-Key (Tel: 800-DIGI-KEY, part number CR214-ND, they have a minimum), but the direction of airflow must also be changed. To do so, unplug the machine. Remove the three screws on each side of the cover as well as the single screw on the cover's top/rear/middle. There is a black plastic extension rod that links the front-panel power button with the switch in the rear (see photo 1). Pull it in the direction of the front panel until it pops off. Then remove the two screws that secure the power switch subassembly to the chassis. (Photo 2 indicates all screw locations.)

There are four screws that secure





the fan to a metal frame, which itself has two screws. After all six screws have been removed, extract the fan, disconnect its power cable (see photo 3), and vacuum the dust that has collected on the blades. Flip the fan's direction, reconnect and remount with the power connection on the "inside."

Mount the air filter to the machine's cover using pan head (the type that countersink) #6 screws (see photo 4). For extra safety, paint the threads with nail polish (preferably red or purple) so that the nuts don't come loose and get sucked into the power supply (see photo 5). Be sure to clean and/or replace the filter from time to time.

TAMING THE HOT ROD

All ADATs, regardless of brand name, are made by Alesis. This is an odd but generally good thing. Some transports are noisier than others, particularly in fastwind modes. One client described it as sort of a "hot rod" sound. The two culprits in the ADAT mechanism are white plastic rollers (see photo 6). At the top left is an "Impedance Roller" that stabilizes the tape on its way to the head. At the bottom right is a pulley on which a circular magnet is mounted. When this "Hall Effect" pulley is linked to the take-up reel table via belt, it generates a tachometer signal that corresponds to tape travel.

Noisy rollers should be replaced, but a little lubricant will shut 'em right up. Both must first be removed before lube can be applied. (Power down and unplug before removing the cover.) A white plastic cap is pressure fit over the metal shaft on which the Impedance Roller spins. Use a flat-blade screwdriver as a wedge to lift the cap. Then, *gently* squeeze the cap with a serrated-jaw long-nosed pliers, alternating clockwise and counter-clockwise while *gently* pulling (see photo 7). (Did I mention the concept of being gentle?)

Let the metal shaft enter a tube of "Lubriplate" (MCM, Tel: 800-543-4330, part number 20-1325) so that a light coating is left behind. Replace the roller and gently slip on the cap until there is minimal vertical "play" in the roller. Clean the roller with a lint-free cloth dampened with 99-percent alcohol.

To access the magnetic roller, it is necessary to power the machine and



coax it to lower the tape loading "elevator." This can be done two ways: via either software or very talented hands. The soft ap-

Press Record

and Record 7



while powering up.

• The front panel should display "ProG."

• Press Pitch Ÿ until the display indicates "CAP."

Press Auto Play to extinguish the decimal point.

• Press Pitch/to lower the elevator.

On some transports, the tape sensing latches will keep the elevator from moving, hence...



	DIGITAL	TAPE MACHINE I	HIDDEN FEATU	RES
Machine	1st Key Stroke	2nd Key Stroke	3rd Key Stroke	Function
ADAT	Set Locate & Stop			Drum "On" Time
ADAT	Set Locate & FF			Software Version
ADAT-XT	Set Locate & Stop			Drum "On" Time
DA-88	* Stop & Play			Total Drum Time
DA-88	* Stop & FF			Fast Wind Time
DA-88	* FF, Stop & Play	** Stop	Remote	Bargraph for tracks 1 & 2 will indicate errors for A & B heads when in "Play."
RC-848	While logo is displayed	Rew, FF & Stop	•First B'day	Should have v. 2.04 or highe

* The DA-88 requires the user to press these key, on Power-Up.

** Press STOP immediately after the machine is powered. The alpha-numeric display should indicate "test" mode. If so, proceed to the next keystroke.
 After installing new firmware, a "First Birthday" is required to initialize the system. Set all S1 DIP switches to On, power up, and set all S1 SIP switches to the Off position.

Come to New York City

RUT YOUR HEAD WHERE

the center of the recording industry. Learn recording engineering at the

INSTITUTE OF AUDIO RESEARCH

Our 9 month Recording Engineering and Production Program includes: Multitrack Recording, Mixdown Techniques, MIDI, Digital Audio & more. + a diploma from a world renowned school.

Call 800-544-2501 212-777-8550 (NY, CT&NJ) Your focus is music, our focus is you.



INSTITUTE OF AUDIO RESEARCH 64 University Place New York, NY 10003

WORKSHOP MAINTENANCE



The talented hand approach: As per photo 8, position the right hand and fingers as shown to disengage the latches. Power up and move the hand forward as if it were a tape. Power down as soon as the elevator is lowered. Remove power, locate the magnetic roller, and remove the belt. The roller is held in place by a split plastic washer. In years past, this type of snapwasher was made of metal and formed into the shape of a "C" or "E." Extraction typically required the user to invoke the name of a deity, especially if the washer flew off into the Irish town of O'Blivion. If you've had too little or too much Cappuccino, take the machine to a qualified service center. Otherwise ...

A jeweler's flat-bladed screwdriver can be inserted into the split. A slight twist will open the washer, while a second screwdriver keeps the washer from achieving orbit (photo 9). Fine tweezers or needle-nosed pliers can be used to safely remove the ^#\$%@ washer. Apply lubricant in the same way, replace the roller, split-washer, and belt (if the belt appears "glazed," replace it). Apply power. The elevator should automatically be returned to the "ready" position. Insert a noncritical tape, check play, and fast-wind in each direction. The machine should now be much quieter.

GENERALLY SPEAKING

DESCR

Impedo

Magne

Belt for

All tape machines suffer from transportrelated problems. As mentioned in pre-


TABLE 1	
RIPTION	PA
ance Roller with Base Assembly	y 11
tic "Hall Effect" Wheel	
Hall Sensor Wheel	

vious columns, the electronics are nearly always very stable. The keys to reliable transport operation are the "Mode" and "Load" switches. These are sensors that report transport status to the system control circuitry. Dirty and worn switches generate misinformation, a.k.a. error messages and eaten or jammed tapes. If this happens to you, don't let it happen more than twice. It's time for service.

SCHEDULING MAINTENANCE

Schedule maintenance every 250 hours. This is typical for the video transports used in digital tape machines. All digital 8-track decks have built-in counters that accumulate the time tape is on the heads. There are no buttons labeled "Total Head Hours." In all cases, a combination of magic buttons must be pressed to gain access to the digital netherworld.

The Panasonic SV-3700/3800 (which has a recessed, thermometertype hour counter on the rear panel) requires the user to press "Mode, Reset, and Pause" buttons to access such need-to-know items as status (consumer or pro) and error rate. TASCAM machines must be powered up while the magic keys are pressed. (See the table 2 for your machine.)



WARRANTY COVERAGE

TASCAM's DA-88 warranty is currently 90 days for labor and one year for parts. In August, Alesis sent a warranty upgrade to all of its ADAT XT customers. Now increased to 1 year parts and labor, it was formerly 90 days for labor/head assembly and one year "free of defects."

PART NUMBER 7-14-0024
7140024
7-14-0024
7-14-0018
7-14-0017

The XT headstack is warranted for 1 year or 1500 hours. TAS-CAM's expected head life is 1000 hours. **EC**

130 OCTOBER EQ

AD INDEX

For fast and easy information use the reader response card in this issue

PAGE	BRAND	INFO#	PHONE	PAGE	BRAND	INFO	PHONE
50	Acoustic Science Corp.	1	503-343-9727	61	KRK	46	714-841-1600
117	AdB International	141	404-623-1410	121	Kurzweil	150	310-926-3200
2, 67	Alesis	2, 3	800-5-ALESIS	146	Leatherman Tool Company	47	800-847-8665
35	Amek	5	818-508-9788	51	Lexicon	48	617-736-0300
20-21	Aphex	4	818-767-2929	16-17	Mackie Designs	51	206-487-4333
133	Apogee Electronics	216	310-915-1000	132	Manny's Mailbox Music	49	212-819-0576
81	Applied Research & Technology	6	716-436-2720	88	Markertek Video Supply	50	800-522-2025
100	Ashly Audio, Inc.	7	716-544-5191	144	Martin Audio Duplication	53	800-553-8906
103	Audio Technica	8	716-544-5191	146	Media Store	54	800-555-5551
115	Avalon Design	10	714-492-2000	145	Microboards	55	800-646-8881
95	AXI-Dynaudio Acoustics	149	617-982-2627	70	Millennia Media	56	916-363-1096
46	Azden Corporation	13	516-328-7500	92	Misson Recording	57	770-599-0681
148-151	B&H Photo	11	212-807-7474	155	Oasis	XX	800-697-5734
69	BASF	12	800-225-4350	68	Optofile	58	905-469-8080
10, 53	BBE Beathau Dava Commence	96, 91	714-897-6766	23	Otari Corporation	59	415-341-5900
145	Beatboy Drum Sequences	14	800-838-BEAT	5, 45, 71	Peavey	62, 61, 64	601-483-5365
77	Behringer Boll Electronics	9	516-364-2244	10	Peninsula Marketing	67	310-373-9129
145	Bell Electronics	15	903-784-3215	82	Polyline	68	847-390-7744
3 82	beyerdynamic Cabletek Electronics	17	800-293-4463	93	PreSonus	63	504-767-7887
82	Cabletek Electronics	18	604-942-1001	132	Pro Sound & Stage Lighting	69	
31	Caig Laboratories Cakewalk	19	714-897-6766	132	Q-Sound & stage Lighting		800-672-4128
31 78	Cakewalk Caruso Music	16	617-926-2480	43	QSC	148 65	415-842-7600
78 78		20	203-442-9600	43 15, 58			714-754-6175
50	Countryman Associates Creamware	22	415-364-9988	13, 58	Rane Corporation	52, 147	206-355-6000
50 91	CTI Audio	23 21	800-899-1939	136	Rich Music Ridao Ruppor	70	800-795-8493
119	dbx	146	800-762-9266 801-568-7660		Ridge Runner Poskford / Hafter	71	800-FRET-PRO
38-39	Digidesign	24	415-842-7900	83 89	Rockford/Hafler Roland	72	800-366-1619
102	Disc Makers	24	800-468-9353		Roland	66	213-685-5141
66	Discount Distributors	25	516-563-8326	163 28	Sennheiser Shuro Brothers	73	203-434-9190
75	DOD Electronics	90	801-566-8800	28	Shure Brothers	95	800-25-SHURE
135	E-mu Systems	142	408-438-1921	85	Sonic Foundry	74	800-57-SONIC
136	East Coast Music Mall	97	800-901-2001	92	Sound Deals	75	800-822-6434
96	Electro-Voice	36	616-695-6831	55	Soundcraft	60	818-893-4351
145	Empire Records	27	716-871-3475	125	Spirit by Soundcraft	145	615-399-2199
145	Europadisk	29	212-226-4401	76	Stewart Electronics	76	916-985-7200
7, 87	Event Electronics	30, 31	805-962-6926	60	Studer Revox	78	818-703-1100
113	Five Towns College	144	516-424-7000	101	Studiomaster	80	714-841-4227
79	Focusrite	28	516-249-3662	41	Sweetwater Sound	81	219-432-8176
136	Forge Recording Studios	32	610-935-1422	48	Symetrix	82	800-288-8855
47	Fostex	33	310-921-1112	11	TC Electronic	79	805-373-1828
59	Full Compass	34	800-356-5844	49	Tannoy America	83	519-745-1158
111	G-Prime	35	212-765-3415	9, 65	TASCAM/TEAC America	77, 85	213-726-0303
144	Geoffrey Daking & Co.	37	302-658-7003	122	Taxi	86	818-888-2111
109	Giltronics	38	302-658-7003	99	Telex Communications	87	612-884-4051
94	Grandma's Music & Sound	39	800-444-5252	142	The John Hardy Company	143	847-864-8060
94	Hohner Midia	40	707-578-2023	66	The Recording Workshop	88	614-663-2544
107	Innovative Quality Software	45	702-435-9077	57	TL Audio	89	905-420-3946
130	Institute af Audio Research	98	212-777-8550	105	Vega	84	818-442-0782
144	International Audio	41	708-734-1695	113	West L.A. Music	151	310-477-1945
25	lomega	42	801-778-3712	12	Whirlwind	92	716-663-8820
164	JBL Professional	XX	818-895-8190	146	World Records Group	100	800-463-9493
144	Klarity Kassette	43	800-458-6405	13, 32-33	Yamaha Pro Audio	93, 94	714-522-9011
26-27	Korg USA, Inc.	44	516-333-9100	37	Zoom Corporation	99	516-364-2244

EQ&A

continued from page 14

BULKING UP

QI am using a TASCAM DA-88 that sounds very thin. Am I doing something wrong? Also, how do I get wide images in my recordings with the DA-88? I have a full selection of excellent gear, including a TASCAM M-3500 mixer and DA-30 DAT; Lexicon, Drawmer, Aphex, Yamaha, and Ensoniq processors; AKG C414 mics; Genelec monitors; and Roland, Korg, and Ensoniq musical gear. What's the secret?

> Achmad Khadafi via Internet

A "thin" sounding recording, regardless of whether the recording medium is analog or digital, can be the result of numerous factors working alone or collectively. This phenomenon can result from inadequate record levels, an inappropriate microphone for any given task, improper use (placement) of the microphone during recording, excessive compression (which can make a recording sound "small") and a host of other gremlins.

You may want to do some basic technical checking before moving on to the more production-oriented tips listed below. For ex-

ample, are you placing your mics in such a way that they are receiving the same information and the resultant signals are acoustically canceling each other? This would contribute to a very thin signal (or no signal...). Adjust your mic position and check the phase on the mics by flipping the polarity switch on your console. Next, check the monitor speaker polarity by making sure the speaker wires are consistently wired. Play back a commercial CD through your system and listen for that thin sound. If it's still there, deal with the monitor/console chain first, specifically the speaker wiring. Also, listen to hear if all tracks or just one or two tracks are the thin culprits. If a single track is the problem, check your connections to the machine as you could have wiring or connector problems that could adversely affect the low end of your signals (it's unlikely every track would have a wiring problem, but don't discount it ...). -HGL]

When we listen to a finished recording, we really have no idea how many tracks were used for any given component of that recording. As an example, one trick to "fatten up" a vocal track is to record multiple takes. While each take is remarkably similar to the previous one, there are slight deviations from one performance to another that create a natural chorusing effect when played back collectively. With a clean recording console and good recording technique, you might experiment with several vocal takes and then bounce them down to one track of your DA-88.

By employing signal processing, you might consider adding some chorus to fatten up a track. Rather than returning the processor's output to an effect return, try bringing it in through a normal input channel so that you have full control over EQ and panning. Try panning the "dry" signal slightly left or right while the "wet" signal from the processor gets panned an equal amount in the opposite direction. Solo both inputs and make certain that both signals are matched in terms of level.

The real crux of the matter, however, is good recording technique and a healthy spread of your recordings various components throughout the stereo field. Make every effort to ensure optimum record levels. For a vocal recording, use the best microphone you can get — even if you must borrow or rent it — and pay particular attention to its placement. Before you begin your session in earnest, listen for any audible anomalies such as odd reflections, lip smacks (got the "pop" filter?), sibilant sounds, etc. Is your room "dead" enough? Try hanging some old blankets or towels. There is much to consider!

> Roger Maycock Marketing Support Representative TASCAM



DIGHTAL MASTERY APOGEE'S AD-1000: THE PLATINUM **EDITION**

48

1000 REFERENCE STANDARD ANALOG TO DIGITA

12 2/51 32 44

- **Full 20-Bit Resolution**
- **Digital setup oscillator**
- Digital pass-through with UV-22

12 -2/SL SOFTUMI OVERLY OVER PHANTOM

- UV-22[®] Super CD Encoding and Soft Limit
 8-channel ADAT[®] & DA-88[™] interfacing*
- Transparent mic preamps with phantom power
- PaqRat[®]-compatible 20-bit bi-directional interface
- Sync to ADAT, Video, AES, S/PDIF, Optical, Word Clock

HE AWARD-WINNING APOGEE AD-1000 20-bit analogto-digital conversion system was the result of years of development coupled with the practical, real-world experience of thousands of Apogee users.

Building on the success of the industry-standard AD-500E, the original AD-1000 included 20-bit capability; UV-22 encoding-the choice of the world's top mastering houses-to preserve 20-bit quality on 16-bit media such as Compact Disc; ADAT optical, AES and S/PDIF outputs; a digital oscillator; "analog-like" soft limiting; portable 12v operation; and transparent phantom-powered mic preamps.

Now there's the AD-1000 Platinum Edition, offering all these features, plus many more. Digital passthrough enables you to UV-22 process an existing digital signal. Full ADAT and DA-88 format inputs and outputs* enable you to hook up virtually any modular digital multitrack system.

*DA-88 interfacing available with the use of the FC-8 Interface Unit included with the Platinum Edition. Trademarks and registered trademarks are the property of their respective owners.

The new PagRat-compatible 20-bit capability allows you to record and play back 20-bit signals by using pairs of tracks on your MDM.

CONVERTER

16 U

001

SAMPLE PAT

Never before has so much digital conversion capability been packed into such a small unit.

Experience the AD-1000 Platinum Edition at your Apogee authorized dealer.




CIRCLE 216 ON FREE INFO CARD

APOGEE ELECTRONICS CORPORATION 3145 Donald Douglas Loop Scuth, Santa Monica, CA 90405. Tel: 310/915-1000. Fax: 310/391-6262 E-mail: info@apogeedigital.com Web: http://www.apogeedigital.com/

IN REVIEW

TC Tools Reverb & Chorus/ Delay TDM Plug In



The way they have presented the otherwise boring information such as "high-frequency decay time" is very easy to follow. At a glance you can get a very good picture of what is happening inside the DSP and how reverb your sound "looks." It does not take very much time at all to get used to setting up new reverbs without even looking at the numbers. "A little bit less of the light green space," becomes the kind of phrase overheard in the con-

I KNEW IT would happen sooner or later. I have this great reverb from TC Electronic called the M5000. The problem with the M5000 is that it performs so many cool functions that you can't decide which ones to use. When mixing in Pro Tools III, I usually connect my M5000 to one of the digital I/O ports and record the resulting reverb on another track to free up the M5000 for another task. The bad news is that after you decide that the reverb settings are not set exactly right, you have to re-record the reverb. In order to operate more efficiently, you need to have many M5000 reverbs.

TC Tools to the rescue. TC Electronic has announced a TDM plug-in that gives you a world famous TC Reverb and a TC Chorus insert that you can use within Pro Tools. If you need 17 different reverbs, then you can insert 17 TC Reverbs. As long as you have the DSP power available, you can use TC Tools as many times as you want. With external hardware reverbs, if you need another reverb, you have to go out and buy it.


VISUAL EFFECT INTERPOLATION

No, this is nothing like radial caratotomy. What TC has done is present a unique graphic window for setting the parameters in the reverb and the chorus. trol room. "That looks good, let's try it," is heard just as often as, "That sounds good."

LOOKIN' GOOD

I expected the TC Tools to sound just as good as the stand-alone M5000. The TDM system does use the same DSP as in the M5000, so it seems reasonable that after interface problems are worked out that the sound should match up pretty well.

In fact, it did sound the same. I was



The Power Without the Pain



$D \wedge R W I N^{2.0}$ DIGITAL AUDIO DISK RECORDER

Sound On Sound — "Friendly, familiar tape-like operation and superb audio quality."

EQ -

MUSICIAN

ELECTRONIC — "E-MU's modular hard disk recorder offers great sound and a graphic LCD that makes editing and track Recording management easy."

"Makes 8 tracks feel like a whole lot more – The Darwin/ADAT combination delivers the goods."

"Darwin appears as another ADAT to a BRC



DARWIN OPTIONS:



Seamless interface with ADATs and BRC. Adds 800 virtual tracks to an ADAT



DSP option card provides time compression, state of the art Poly-GenderTM pitch change, and gain control



SMPTE/Word Clock sync card option



Jaz drive: records to inexpensive, removable media, eliminates the need for back-up between projects

Features:

- Midi Controllable Digital Mixer
- 800 Virtual Tracks
- 16 layers of undo
- Non-destructive, playlist based editing
- Auto record, via the front panel, ADAT 9-pin or MMC
- Sample accurate audition modes
- MIDI Machine Control allows DarwinTM to be controlled by a sequencer
- Much, much more ...

E-mu Systems, Inc.

Corporate Office: P.O. Box 660015, Scotts Valley, California, USA 95067-0015 Tel: 408-438-1921

European Office: Suite 6, Adam Ferguson House, Eskmills Industrial Park Musselburgh, UK, EH21 7PQ Tel: 44 (0) 131 653 6556 http://www.emu.com





M5000 for tasks like 3-band compression and digital EQ. I was also able to have a separate TC Reverb for each instrument. Each reverb was set up with a quality that matched the instrument in question, instead of one main reverb for the whole mix with individual sends from each instrument. You can still use the "send-receive" setup if you want, but I have never seen anyone with access to a whole bag of potato chips eat just one.

TIDA

A nice solo classical guitar sounded great with a medium large room and 70 ms of predelay. Changing the absorption of the walls allows very fine adjustments to the quality of the reverb and how it ties to the guitar. Drums in a garage? How about a nice 315-car garage?

Usually you can tell about the quality of a reverb by seeing how small you can make the room before the reverb starts sounding like fingernails on a chalkboard. No matter how small you set TC Reverb, the ambience maintains a rich quality that is going to be hard to beat. [The mono-/stereo-In, stereo-Out TC Tools permits assembling ambiences from six different rooms - Club, Fan, Hall, Horseshoe, Prism, and Small.]

The TC Chorus was equally great sounding. The results were dense and smooth without strange side effects that you hear from even some rather expensive stand-alone chorusing devices. The available parameters, along with the graphic-setting display, made TC Chorus the easiest chorus to set up I have ever used. When recalling various chorus presets, the graphics display made it readily apparent what the differences were between them. Seeing all of the parameters at once made it easy to discover what sonic changes were caused by what parameter changes.

CONCLUSION

Your first question to yourself should be, "What am I going to do with all the money I save?" Yes, you have just saved thousands of dollars by not having to buy 17 TC M5000 reverbs. You just have to get one copy of TC Tools for Pro Tools TDM. It could be one of the best things you ever did with your money, except maybe sending me the 15-percent commission on the money you saved. EQ has a mailbag waiting, and has promised that they will forward all but a small handling fee.

Hughes & Kettner TubeMan Plus



MANUFACTURER: Hughes & Kettner Inc., P.O Box 2297, Des Plaines, IL 60017. Tel: 800-452-6771.

APPLICATION: Guitar preamp, with distortion, for live or studio.

SUMMARY: This well-thought out 3-channel preamp delivers a collection of great tube tones — just don't expect exceptional flexibility.

STRENGTHS: At home on stage and in the studio; rich, creamy distortion sounds; easy to use; solid construction; footswitch included.

WEAKNESSES: EQ shared by all channels; wall wart power supply; nonprogrammable.

PRICE: \$499

EQ FREE LIT. #: 135

BY CRAIG ANDERTON

I LIKE THE flexibility of multieffects, but there's much to be said for simpler boxes that pick a limited number of tasks and do them extremely well. Hughes & Kettner have that act down — their TubeMan (reviewed in March '96) is painless to use, but the sounds are wonderful. The TubeMan Plus gives more options for tweakers, and is also more oriented toward playing live.

This 1U box has a mono 1/4-inch input and two 1/4-inch outs, one for feeding a power amp (flattest response) and one with an associated switch that selects between "to mixer" (includes the H&K Red Box cabinet simulator) or "to guitar amp" (slightly less bright). You can use both outputs simultaneously.

TubeMan Plus has three basic voicings: Clean, Crunch, and Lead, each with its own output level control. For live use, a footswitch (included) lets you move instantly between the three sounds, while front-panel LEDs indicate which sound (or bypass) is selected. A single control sets gain for both Clean and Crunch, while a front-panel switch (paralleled on the footswitch) selects between the two sounds. The lead has its own gain control, in/out switch (also on the footswitch), and a "lead 2" pushbutton that gives a "meatier" timbre. A bypass function is available from the footswitch, but not the front panel.

The input stage is very well designed. Turning your guitar's volume control gives a smooth, even change in response, and any loading is negligible. A mid-boost switch located next to the input changes the master timbre for all sounds. The 4-band EQ (bass, mid, treble, and presence) affects all channels. The controls are very gentle, like what you'd expect from a '50s guitar amp. I particularly liked pulling back the presence and pushing the treble a bit with rhythm, and taking down the treble but boosting the midrange on lead. However, since you can't program different settings, for live use it's necessary to choose EQ settings that work with Clean, Crunch, and Lead sounds.

Inside, there's a 12AX7 running with 170 volts on one plate and 210 volts on the other. ICs (for the input stage, midrange boost, and outs) are 5532, TL071, and TL074 — all good stuff. Two CMOS ICs provide the switching. The box is solidly built, with the only weakness being the wall wart-style power supply.

If you need a selection of vintage tube amp sounds, TubeMan Plus is an overachiever. The timbre is creamy yet with an authoritative edge, and there's a transparent quality that provides a clean, defined tone. The footswitch is a plus for live use, and aside from the wall wart, TubeMan Plus seems ready for the rigors of the road. Overall, this is a solid performer — the more you play it, the more you appreciate just how many great sounds you can coax out of this well-designed, and very musical, box.



N REVIEW

TL Audio PA 2 Dual Tube DI and Microphone Preamp

THE TL AUDIO PA 2 combines tubes and solid-state circuitry to give two channels of mic preamp and instrument DI. All the action, including connectors, happens on the front panel of this 2U rackmount.

The mic input has a solid-state, electronically balanced input amp that passes through one-half of an ECC83/12AX7 twin-triode tube as a second stage to add tube character. Instruments get two cracks at a tube stage and impedances can be switched to match guitar (high gain and very high impedance) and keyboard (moderate gain and line-level impedance) inputs. A solid-state balanced XLR output stage completes the picture.

Mic inputs are on XLRs with switch-

able phantom power, while instruments, selected on a switch, come in on unbalanced jacks. All signals pass through a gain pot with an associated peak LED of the variable intensity type. This LED starts to glow when the tubes pass the threshold of compression and then increases in brightness until it maxes out at full intensity when 10 dB of headroom remains before clipping. For DI'ing guitar, you'll want to be working and the indicator works best as an indicator of tube condition because it's hard to judge level by.

Many people don't even own a DI for recording guitars as they're usually coming in on a mic or through some fancy guitar preamp/effects unit. Even



MANUFACTURER: TL Audio, Tony Larking Professional Sales Ltd., Letchworth, SG6 1AN. Tel: 44-0-1462-490600. Distributed in North America by Sascom Marketing Group, 34 Nelson Street, Oakville, ON L6L 3H6, Canada. Tel: 905-469-8080.

APPLICATION: Project and commercial studios; live sound.

SUMMARY: Dual-channel tube DI and mic preamp.

STRENGTHS: Tube character; can handle a variety of inputs; you get mic preamps, too.

WEAKNESSES: Peak LED difficult to judge.

PRICE: \$595

EQ FREE LIT. #: 134

BY ZENON SCHOEPE

World Radio History

fewer use DIs on keyboards, which is strange when you consider the disparity in their output. Many synths are extremely low level and don't begin to tax a console's peak light even with everything in the chain on full. DI'ing the keyboards cures this and also employs the mic circuitry of the console, which, particularly on "affordable" desks, can offer significantly better quality than its line input counterpart.

In addition to improving noise performance in the sound chain, DI'ing keyboards lets them sound their best, as they seem to "breathe" a little more freely. Guitars also benefit from DI, especially if you're after a cleaner sound, but throw in some tubes and things really get interesting because on this unit you can overdrive in a gentle or hard way.

Guitar performance is excellent smooth and rounded and infinitely better than the usual run-of-the-mill DI box. This is because you can thicken the signal with higher gain settings. (It's no fuzz box, though.)

The mic preamp is good and similar to that found on other TL Audio units. The keyboard input can also be used to process line-level inputs, so you can get the tubes working on stereo mixes.

This is a damn good guitar DI that is flexible enough to "tube" a variety of different sources. EQ

PRESENTS:

B. SOUND

REACH NEW BUYERS AND NEW BUSINESS

UDIX

1ST ANNUAL

CORDING

5 G

00

0

100000000 00000 00

each over \$5,000 ecording Sound Ausicians, ngineers, roducers


)ver 5,000 lew Products

oming in **IOVEMBER** 996!

ecturing:

HE MOST

the Year i Review



USA

EQ TRACKS

continued from page 34

For the cellos, the mics were down in front of the f-holes, about a foot and a half away from the instruments. The violin mics were up about two feet over the tops of them and the violas were miked the same way.

How did you physically arrange the players?

You could barely fit ten people in the room. The violins and violas were in the same room, but the cellos might have been in a drum booth. I have done it both ways.

Any leakage problems?

You could kind of hear a bit of the other instruments on a given track. But the "signal-to-noise" from one instrument to the other was enough that if you needed more of one part you could turn it up. The other leakage that you'd hear on a track didn't affect the sound that much. There was bleed, but the takes were performed all together, so it didn't really matter.

What mic preamps did you use?

We had a couple of API mic preamps that I used on the violins and then we had two SSL outboard mic preamps. Those were the only outboard mic preamps that we had at the time, so we ran the rest of the mics straight into the console, which was a DDA AMR 24.

What was the tape machine?

We had only one 24-track machine and it was a Sony JH24. We had to make a slave reel using the rhythm tracks from the master tape. We had Sound Tools at that time, so we sync'd Sound Tools to the master and did a mix of the tracks into Sound Tools. Then we put that onto another reel of tape and recorded all the strings on that tape.

The strings took more tracks than we had available on the master. We ended up using up around 20 tracks for the strings. After the slave reel was done, we bounced each part to a separate track on the master. All of the first violins were bounced to one track, and all of the second violins were on another. We'd put them into Sound Tools and then fly them back to the main reel. So on the master reel there was one track of first violins, one track of second violins, one track for the violas, and one track of cellos. Then we had separate tracks for the stereo rooms mics. EQ

E-MU DARWIN

continued from page 116

to ADAT. Furthermore, this is a backup you can actually play. Going in the other direction, once ADAT tracks are in Darwin, you can edit away, then bounce back to tape.

While doing transfers with a BRCbased system, it's important to set the BRC to external clock (even though the BRC is always the master in a Darwin/ADAT setup). This causes it to search for an external clock, not find it, and instead sync to its own phaselocked 48 kHz clock. Otherwise, according to E-mu, the BRC's regular variable speed clock has enough jitter to add noise to digital transfers. (This is another good reason for sticking with 48 kHz.)

SO WHAT'S THE DEAL?

If you have an ADAT and plan to expand, you could add another ADAT and BRC to gain another eight tracks, the ability to do some hard-disk-style editing (by offsetting the two machines and dropping parts into tracks), and do what Alesis calls "megatracking" (using multiple cassettes per project, such as recording rhythm tracks on machine 1, then inserting a cassette for vocals in machine 2, recording eight tracks, and bouncing them down to one track on machine 1).

For somewhat more bucks, Darwin also adds eight tracks, but the editing and "megatracking" is faster and more sophisticated than with tape. It's an attractive combination; duplicating Darwin with a personal computer-based system (e.g., Pro Tools with an ADAT interface) would be fairly expensive, and wouldn't necessarily function as an ADAT slave or work with a BRC. However, unlike computer-based editors, editing on Darwin is more at the arrangement level than the note level. If you're looking for editing precision and processing, Darwin is not your best choice.

But if you just want to set up and let 'er rip, then push tracks around and perfect things "offline," the E-mu Darwin/Alesis ADAT combination delivers the goods. If you're an ADAT owner and debating whether to convert over to hard-disk recording, marrying ADAT and Darwin produces a synergistic team that capitalizes on the strengths of both technologies: easy capture, cheap storage, undo, and hard-disk-based editing.

YAMAHA MD4

continued from page 122

MIDI MEETS MD

The MD4 transmits MTC (30 fps only) and MIDI clocks (with Song Pointer) but does not slave. Sync comes from within the MD and does not require giving up an audio track. Using MTC allows for making tempo changes at the sequencer, but with MIDI clocks you can still program tempo variations with the MD4's Tempo Map function, which allows each song up to 26 tempo and 26 meter changes. Each map is saved as a separate file and needs to be reloaded whenever you start work on the associated song.

Time signatures range from 1–99 beats per measure, with rhythmic values of 1/2-, 1/4-, 1/8-, or 1/16-note. Tempo ranges from 20 to 300 BPM. Creating a tempo map is a tedious process, but you can easily insert or delete changes.

Note that there is limited memory available for tempo maps — according to Yamaha, each disc can hold four or five maps that use all 26 steps. If you use lots of tempo changes or need to change tempo between beats, edit your sequencer's tempo track and drive it with MTC.

COOL TOOL?

MD-based ministudios have a real shot at dominating the market now held by cassette-based types. While MD models are more costly than cassettes, the superior audio quality and feature set are worth it. I'm still not convinced about MD as a delivery system for consumer audio, but it seems ideal for this application, and some may actually prefer the sound of data compression to straight linear encoding. (MD should have also been the logical successor to the 3.5-inch floppy disk, but that's another story.) Although the MD4 is not all-digital - you still have to enter, exit, and bounce with analog - it nonetheless has that distinctively clean, "digital" sound. Its high-frequency response poops out a shade before 20 kHz, but that's hardly audible (if it's noticeable at all), and, of course, compared to multitrack cassettes, the high end is far superior.

Simply stated, the MD4 is not just the lowest-cost digital multitrack studio you can buy at the moment, but a quantum leap beyond its cassette-based forebears. The MD may not have caught on with consumers, but, ironically, it appears that it will indeed replace the cassette in at least one application.



T H E · A G E · O F VIDEOGRAPHY

TWENTY YEARS That changed the way we see ourselves

1976-1996

To celebrate our industry and the contributions, VIDEOGRAPHY magazine is proud to announce the publication of *"The Age of Videography,"* a special book that commemorates the role that the professional video industry has played in altering public perceptions, broadening our visions, and pioneering new artist possibilities.

Ten percent of all proceeds will be donated to The Vision Fund.

"The Age of Videography" Editorial Director Brian McKernan Director of Sales Joe Palombo Project Coordinator Cristina Gallo

> Miller Freeman PSN, Inc. 460 Park Avenue South, 9th floor New York, New York 10016, USA

> > Tel: 212.378.0400 Fax: 212.378.2160

DOUBLE TROUBLE

continued from page 102

its ten-foot maximum. Marty's drum riser rolls underneath the Travis set and behind it, where it can be dismantled out of the way. Marty's stage left guitar/bass riser and stage-right risers then switch sides of the stage (to where they'll be used during the Travis set and the finale). The stage then lowers to its six-foot "show" position, all the lights and band gear are visually checked, and the band members take their places.

We set up the Travis set as for the fi-

nale and walked the local crew backwards through the set change, giving them the advantage they needed to strike Marty's drums quickly. Then we checked the acoustic set, with some changes. We checked with Jon and Wendell upstage, and with Marty's guitarist Brad Davis playing mandolin upstage as well. This change solved two problems, namely getting those live wedges out of the downstage picture and saving Jon and Wendell from scrambling to their risers after the set. We also closed the drape during the check. This tiny detail had somehow been ignored until Tritt backline tech Gary Mc-Murray pointed out that problems always occurred after it was closed.



(ACTUAL SIZE)

"No comparison!" "Whoa!" "Even the producer could tell the difference!" A few typical comments! The M-I is clearly superior. Here's why:

The JENSEN JT-16-B INPUT TRANSFORMER, IMPROVED! The world's best mic-input transformer, now even better!

THE 990 DISCRETE OP-AMP. The 990A-24V is far superior to the monolithic op-amps found in other equipment.

DC SERVO and INPUT BIAS CURRENT COMPENSATION eliminate all coupling capacitors and degradation they cause.

Standard equipment: illuminated push-buttons, shielded toroidal power transformer with 6-position voltage selector switch, silver plated XLRs, ground-lift switches, phantom power, polarity reverse and gain controls. Options include the Jensen JT-11-BM output transformer, VU-1 meter (shown), PK-1 meter, gold plated XLRs.



That night the sets went seamlessly one into another. Shows since have been similarly smooth. Now we check the acoustic bit religiously, drape closed and PA running. It seems what we had to do was to fall back on the basic rules of live audio, the first of which is: "Start at one end and work to the other. It works with signal flow and soundchecks." I guess the trick is knowing which end to start with.

Ion P. Armstrong is currently on the Double Trouble '96 tour mixing monitors for Travis Tritt.

DSP•FX REVIEW

continued from page 126

D/A, and AES/EBU and S/PDIF ports (\$599 and \$299 for AES and S/PDIF daughterboard, also available separately) should be shipping as this issue goes to print. However, the ease of installation should allow even the less adventurous computer owner to stick the Basic System in a PC and be up and running as quick as they can get the cover back on. The ISA card is typical of the high-quality versions of other PC products, with easily accessible address switches and clear instructions for setting them. Many PC users cringe at the thought of adding a board into their computer based on previous experience. Thankfully, the DSP•FX wasn't even a problem to install in my fully loaded Pentium. No conflicts, no software problems, and it runs fine in Windows 95 (although it is a 16-bit Windows 3.xx program).

The DSP•FX ships with a large number of presets for each of the five plug-in modules, and this will probably increase as the user base grows. The size of the preset files are very small (between 400 and 1400 bytes), and therefore practically unlimited in number. The DSP•FX is a powerful DSP engine, and we can look forward to many other applications for this hardware. The large dynamic range of the 32-bit DSP coupled with Power Technology's smart visual interface concepts should prove to be an interesting combination.

Wade McGregor is a senior consultant for Barron Kennedy Lyzun & Associates, an acoustical consulting firm based in Vancouver, BC. For more info, visit their home page at www.bkla.com

THE VIDEO HOW-TO MAGAZINE

LEARN H

Find out everything you need to know about professional video production in the #1 video production magazine — VIDEOGRAPHY. It's the only video production magazine written by video professionals for video professionals.

FILLED WITH EXPERT TIPS

Every month VIDEOGRAPHY contains all the practical, how-to information you need to design, record, edit, and mix your audio for your video customers. It offers you all the tips you need to profit from the growing demand for audio-for-video.

YOUR ESSENTIAL TELEPRODUCTION HANDBOOK

Subscribe to VIDEOGRAPHY today and receive one free issue. If you don't agree that VIDEOGRAPHY is an essential handbook for today's dynamic video production scene, there is no obligation.

VDEOC		P		RECEIVE YOUR
				REE ISSUE!
Ves, I want to subscribe to VIDEOGRAPHY				
One Year (\$30) Two Years (\$50) Payment in US\$ drawn on US bank only.				One Year Airmail Foreign (\$60)
Enclosed is my check or money order.	Bill My:	Amex	🗆 Mastercard	🗍 Visæ
Account#	والمرجع المراجع			Exp. Date
Signature		<u></u>		
Name		(Company	
Address				
City			State	Zip
VIDEOGRAPHY P.O.	BOX 05	13 BAI	DWIN NY	11510-0513
				A subject of the local distance of the



World Radio History

CIRCLE 43 ON INFO CARD

EQ SHOPPER

Beatboy Drum Sequences

noths. Excellent pro-level Waknesses NONE (EC review June 1996 by Graig Anderton)



Britist Signature Series diths 169.95 auch Nigel Disson Illion John) #191 Pap Eddle Bayers session great # 164 Country **Rod Margenstein** Doin Trais) =182/PowerFock 113 Progressure. Fock

FIRE Star certain in May 1995 Keyhoard

ILTIMO 3000 Series ap/Dance (7,081 bars) \$24.95 atin Percussion \$14,95 azz: Hock; New Rige \$19.95 co or Complete ULTIME Collection 5,279 bars only \$79,95 tel 848-838-8E81(252E) mail Brathoules \$ 101.com

CIRCLE 14 ON INFO CARD

SSETTE - VINYL LP®

CD & CD-ROM REPLICATION

Disk Price	Set-Up Cost vs Turn-Around-Days				
Quantity	Price Ea.	3 DAYS	5 DAYS	10 DAYS	15 DAYS
200 to 499	S.95	\$1,100	\$850	\$500	\$450
500 to 999	.90	1,000	775	375	350
1,000 to 1,999	.80	900	625	200	100
2,000 to 4,999	.72	725	250	no c	harge
5 000 to 25 000	65	no cl	arae	no c	horae

From your Premastered CD-R replicated CD or 1630 and label film. Prices include 2-color (D) label (1 color pr 999 or less) Premastering & Packaging are available Jewel Case & Shrink-Wrap Packaging, \$.28; \$.25 @ 5,000 & over

RETAIL-READY CD PACKAGES with Full Color Graphics					
CDs in Je	wel Case	+ Full (Color Boo	klet and	Tray Card
	300	500	1,000	2,000	5,000
1-Pane ²	S1,627	\$1,748	\$1,903	\$2,893	\$5,943
4-Pane	\$1,957	\$2,078	S2 233	\$3,353	\$6,643
6-Panel	S2.387	\$2,508	S2 663	\$3,873	\$7,093

Includes graphics layour, typesetting, graphics proofs, film and printing for booklet tray card and 2-color @ label (1-color for 999 or less), replication and packaging in shrink-wrapped jewel cuse -from your sketch, photos and premastered CD-R.

NEED CD-AUDIO PREMASTERING?

DAT to Sonic Solutions PMCD Moster Disk + Reference Disk for your approval: S125 to 25 minutes; S' 40 to 63 minutes, S150 to 74 minutes

RETAIL-READY CASSETTES with Full Color Graphics

Full-Co or	Standard	J-Card,	Norelco	Box - C	HROME!
	500	1,000	2,000	3,000	5,000
to 12 Min.	\$720	\$1,004	\$1,588	\$2,090	S2 974
13 - 29 Min.	S750	\$1,071	\$1,714	S7,267	S3 247
30 - 49 Min.	\$791	\$1,148	\$1,865	\$2,478	\$3,575
Full-Color O-Card Cassette Single - CHROME!					
to 12 Min.	S715	\$935	\$1,394	\$1,918	\$2,600
to 29 Min.	\$740	\$979	\$1,476	\$2,033	\$2 778

Includes graphics layout, typesetting graphics proofs, film, craphics printing shell printing, tes: cassette, and shrink-wrapping - from your sketch, photos and master.

VINYL RECORD PACKAGES						
	300	500	1,000	2,000		
12 " Single (to 14 Min.)	S795	\$1,015	\$1,285	\$2,195		
12 " LP (to 26 Min.)	\$895	\$1,115	\$1,385	\$2,295		
Includes Direct Metal Mastering, Ploting, Test Pressings, Label Typesetting, Label						
Printing (1) ink color) all plastic cleave, collation & cartoning in 50 count hoxes						

Black Die-cu (hole-in-the-middle) Jackets 35¢ each







Micro: dards is the Muster Distri ator of ALEA CD-R Duplication Stations

Featuring: PlayWrite 2X, 4X CD-R Systems (supported by MasterList CD) bundled with Red Roaster editing software.

Red Roaster is the first windows based package that edits PQ subcodes, and sets index/track numbers, pause, start time and emphasis.



audio Since 1968

> GIANT **INVENTORY BEST PRICES** CALL NOW

CIRCLE 29 ON INFO CARD

pro

Order 1 800 785 3099 Info 1 903 784 3215 Jax 1 903 785 2844

A Division of Bell Electronics

CIRCLE 15 ON INFO CARD



Includes: CDR: 70 mins CD, 20 marks, 2 color disc. full layout scolor separations; full color 4-page insert, full tolog may card, jewel box/maemilly, and shrinkwrag, Inte shipping Included! Ask about our cassette packages.

Call toll free for free brochure & sample 1-800-305-DISC Fax: (716) 871-9317 2635 Delaware Ave. Buffalo, NY 14216

We accest Mastercant & Visa CIRCLE 27 ON INFO CARD

Fax: 612-470-1805 CIRCLE 55 ON INFO CARD

1-800-646-8881

MICROBOARDS

of AMERICA

EG SHOPPER



LEATHERMAN® PST II™



Like the original **LEATHERMAN®** tool, the new **PST IITM** contains full-size, full-strength pliers and a lot more. New features include the strongest, most useful scissors found in any multi-purpose tool. The file has been upgraded to

include diamond coating and a unique sharpening groove. The wire cutters are engineered to cut even harder grades of wire. And a combination straight/serrated edge makes the knife blade more versatile. Add the tight tolerances, premium materials and 25-year guarantee that come with every genuine

LEATHERMAN® tool, and you have a product that will be useful in the studio or on the road for years to come.

Leatherman Tool Group, Inc. P.O.Box 20595 Portland, Oregon 97294 Phone 800-847-8665



CIRCLE 100 ON INFO CARD

EQ SHOPPER ORDER FORM

If your advertising budget does not meet your sales goals, then you should be advertising in the **EQ SHOPPER**. The **EQ SHOPPER** is a special advertising section that offers more impact than classifieds at a lower cost than display ads. Simply put, the **EQ SHOPPER** is the most effective way to market your product/service to thousands of project studio owners! To reserve advertising space, just fill out this coupon and send to: **EQ SHOPPER**, 460 Park Avenue South, 9th Floor, New York, NY 10016 or fax (212) 378-2158.

For more information, contact: Christine Cali at (212) 378-0454 or Pete Seidel at (212) 378-0457

Name			
City	State	Zip	
Phone			
Method	d of Payment: 🗆	Check or Money	Order
🗆 Ma	sterCard 🛛 🗆 Visa	🗆 American E	press
Card#		Exp. Date	
Signature			
		0	

CIRCLE 47 ON INFO CARD

X

Scams What Am

Be on the lookout for the following project studio equipment scam artists. Don't say we didn't warn you.



There was a time when commercial recording studios dominated the studio audio recording business. That time has changed is clearly identified by the existence and prominence of the project studio category. Also indicative of this trend is the current policy of record labels to support their groups in project studio ownership over using major studio session time in album preparation.

It is interesting that project studios are also sharing the bad along with the good from the world of the commercial studio operators. It seems that the scam artists who have been "working" the mainstream studio marketplace are now mining the project studio universe as well. Here are some of their 'bag of tricks' to be avoided!

1. Memory Scams: Though not exclusively the province of the audio recording studio at any level and most certainly a problem plaguing the personal-computer industry at all levels, audio operators are being stung by fraudulent suppliers of both Level Two Cache and RAM DIMMs and SIMMs.

These cyber "bunko" artists are hanging up their shingle at computer swap meets and via second-level publications serving the computer user via direct local distribution. These phony suppliers sell the processor cache needed by PowerPC chips in Macs and by "P" series Pentium chips in Wintel computers. These special chips provide the 256k, 512k, or 1 MB cache memory that the processors use to store certain instructions. They also sell main memory RAM chip sets for PCs and Macs. In almost all cases, this memory is either rejects or returns from legitimate sources or actually counterfeited dummies from Asian pirates.

The dishonest vendors avoid direct contact with their customers as well as any contact with magazines that are delivered by mail. The product that they provide is also not delivered through the U.S. Mail. So they avoid the jurisdiction of the local police and of the U.S. Postal Inspectors.

2. Microphones: This is the old "don't judge a book by its cover" scam. The microphone you buy casually at a professional meeting from a "friend of a friend of a friend" is either made from scratch in Asia of cheap materials with a Chinese cartridge in it, or it has a real case with a cheap cartridge, or it is stolen goods. In any case, you don't want it — no matter what the price!

3. Flea Markets: This is a really good place to buy a piece of studio gear with "something missing." If a piece of studio gear is intact, it can be traded in via legitimate dealers or sold via want ads in recording magazines. Someone has modified or cannibalized or "cherry picked" the best parts out of the unit in question as often as not!

4. Studio Gear Sold from the Back of Large Trucks: This is usually where you find excellent studio equipment at excellent prices. Here is where you get that professional DAT recorder you always wanted or perhaps that digital mixer. The only problem is that the units are almost always stolen directly from the maker on the way to legit dealers. The people selling are not the sort you would want to take home to your family, although they frequently belong to a different kind of "family." To buy, you become a receiver of stolen goods and risk the loss of the purloined units, not to mention criminal charges against you.

5. Same as the Above but in a Parking Lot: Just as it sounds.

6. Midnight Audio Supply: In this case, the piece of equipment you always wanted but thought you could never afford walks through your front door under the arm of a "suit" or a street person. The unit has a price tag that is so low, it seems unreal. Believe that it is! The equipment in question left one of your competitor's facilities via the "five finger discount" in most cases.

Now the bottom line here is a simple one: If the deal seems too good to be true, it probably is. Remember that there just isn't that much slack in the selling price of professional audio gear to allow deals that are half or threequarters off a specific unit's retail selling price. Buy your new equipment only via mail order using the advertisements in legitimate mainstream pro audio magazines. Patronize only retailers who are franchised to sell the products of the specific manufacturer you are interested in. When you use your credit card to pay for such equipment, you add a large financial institution to the equation that is mandated by Federal law to help you if an untoward situation develops. If you must buy used equipment, buy it from a facility or individual who is known to vou.

Scam artists cannot exist without the greed of their potential victims. In looking for that great deal, you become part of the equation that will ultimately take your money from you.

Martin Polon is the principal of the Boston-based Polon Research International (PRI). PRI forecasts the electronic entertainment industry for the financial community.



"THE PROFESSIONAL'S SOURCE

FOR ORDERS CALL: 800-947-5518 212-444-6688

OR FAX (24 HOURS): 800-947-9003 212-444-5001







Best values for musicians, studio operators and production houses the 102 km ll and the 103 consistently produce only the highest quality tape recorded output

They Feature

- 6008 signal-to-noise ratio combines with wide frequency response for high-fidelity sound reproduction using any type of cashette tape
- ndustry-standard Dolby BrC noise reduction and Oolby HX Pro sound technology extends high frequency performance up to 6dB and minimizes distortion
- Advanced bias sensing electronics automatically chooses optimal incording settings for the type of tape you load in-Norm II total or Cr02

- Normal: Instal or C702 Per ord Mirte autospace automatically inserts 4 seconds of minner bilitywen songs or broadcast segments Multi-function display clearly indicates transport mode, tape counter position. Tape type and level indicator Multi-counter with both tape counter and run-time modes I independent Land R stereo level controls and master record level control

Tascam 103 Advanced Features:

- Lascam 103 Advanced Features: 3-head system allows you to record on a tape and monitor it at the same time. without rewinding. MPX filter button eliminates pilot and sub carrier broadcast tones that can interfere with Dolby noise reduction

202 MKIII **Dual Auto Reverse Cassette Deck**



The 202 will provides high-fidelity sound reproduction and a wide frequency reconse, as well as a host of features that help you dub edit, record or playback onto/from one or two cas

- Poud dub edit, record or playback enfolvition one or two cas-settes easily and efficiently.
 Normal speed and high-speed dubbing
 Autospacer automatically inserts 4 seconds of silence between songs or broadcast segments for pro quality tapes
 Incorporates Dolby HX Pro sound technology to extend high frequency performance and minimize distortion on Mormal, Metal and Cr02 tape.
 Altows you to quickly and easily create a professional-sound-mg composite tape from several sources. Functions like Infra Check, Computerized Program Search, Blank Scan and One Program quickly find the beginning of tracks you want.
 Timm two read is sested deals in a durable rack-mount hous-ing that can be used separately or in tandem during recording and p-spice for total flexibility.

- -Record simultaneously on both decks from an external master
- -Play back both sides of one or both decks in a continuous loop five times

-Auto Reverse automatically reverses tape direction during play back and record

-Repeat re -Timer swi u s tape and allo ws infinite looping during playbac pr ynattended record/playback (timer required)

Timer switch for unattended record/pla NEW! 302

Double Auto Reverse Cassette Deck All the features of the 202 mkIII, the nev 302 adds even recording and playback flexibility. Thats because the 302

actually two fully independent cassette decks. Both decks have their own set of interface connectors, transport control keys and naise reducing functions · Auto-reverse capability on both decks

Individuals:multaneous record capability-both decks Individuals:multaneous record capability-both decks Individuals:multaneous record capability-both deck Cascade and Control IIIO tet you link up to 10 additional machines for multiple dubbing or long playing record and additional optical additional additional additional additional additional machines for multiple dubbing or long playing record and

pl, zh, ck, p **CD-601**





Frame-accurate cueing precision, extremely high-fidelity and a limited form factor make the CD-601 ideal for post-production applications where sound effects and music are "flown-in" from compact discs. The CD-601 integrates with most post-produc-tion equipment including mixers video editors and computer studio controllers. studio contri

- Balanced XLR and unbalanced RCA outputs
- Precision cueing control and Auto cue
 Linear motor-driven pick-ups eliminate dead air
 Optional RC-601 remote control adds additional leatures and
- con eniences Optional 8U-2 RAM for instant start and seamless loops up to three minutes

maran 60 PMD-101/201/221/222/430

Portable Professional Cassette Recorders The world standard for field recording, the PMD line is also the value leader. They all feature RCA line input/outputs, 1/4-inch headphone jack, built-in speaker, pause control, audible cue and review, tape counter, full auto shut-off and low battery indicator

• All models except the PMD-430 General PMD-101 PMD-201 PMD-221 PMD-222 PMD-430 have 1/2 speed playback/record capability With 1/2 speed play-Stereo/Mono Mono Моло Mono Mono Sh Heads 2 3 3 complicated passages for analy-sis And when played back at 1/2 speed, the pitch is lowered by exactly one octave so the notes are still musically correct—ideal for figuring out complications. 1/4-inch Miniplug Mini/XLB Miniplug 1/4-inch **Built-I** Buitt-1 Built-In Built Yes Yes Yes Modular Tel Jack Yes Yes Yes Yes External Speaker Jack Yes Yes solos or picking patterns solos or proking patterns. By recording at 1/2 speed, a three hour meeting can be recorded on a single tape. A built-in microphone and automat-ic level control make operation cimple activity is eacher. **Record Controls** 2 (Illuminated) VU Meter -Speed Recording Yes Yes Yes Yes Dolby B NR Yes dbx NR Mic Atten simple, and built-in speaker 0.-10dB, -20dB 0,-10dB, -20dB 0.-10dB, -20dB 0.-15dB, -30dB makes transcription convenient. Ambient Noise Cont Yes Yes 1/2 speed recording is equally ideal for churches, because 90 minutes can be recorded on a MPX Filter Yes Manual Level Contro Yes Yes Yes Limiter Yes Yes single side of tape-no interrupt ing your recording to flip the tape Yes Yes Yes Yes over Line inputs make it easy to use and connect to your existing Peak Indicator Yes Yee Playback Controls use and connect to your existing sound system Three standard 'O cell batteries provide up to 7-1/2 hours of ±20% ±20% ±20% ±20% •6° Pitch Contr Bias Fine Ad Yes operation and the optional RB430 Tone Contro Yes Yes Yes Yes rechargeable battery delivers up Half-Speed Playback Yes Yes Yes Yes Memory Rewind Yes

Telex ACC2000/4000 Series Cassette Duplicators

Designed for high performance and high production. Telex's ACC Series (ACC2000/ACC4000) and (ACC200 XU/ACC4000 XL) of expandable duplicators also offer easy maintenance and unsurpassed ease of use. The ACC2000 is a two-channel monaural duplicator, the ACC4000 is a four-channel stereo duplicator Each produces 3 copies from a cassette master al 16 times normal speed and each can expand up to 27 copy positions (with additional copy modules) With the extra copy modules, you can duplicate up 127 27 copies of a c-60 original in t<u>ess than two minutes</u> And they copy both sides at once. The XL Series feature "Extended Life' cassette heads for increased performance and wear

characteristics They also offer improvements in wow and flutter, frequency response, signal-to-ratio and bias. Additionally the ACC4000 XL allows for either chrome or ferric cassette duplication. XL- mo able in stereo (ACC4000 XL) or mono (ACC2000 XL) versions. dels are avai Fingertip Operation Easy maintenance controls • Short tape indicators alert you if a tape • Slanted work surface and unique *heads-up* cassette platform allow less oxide build up or

rewind and copy operation

ing incomplete copies caused by iam or

natic or manual selection of

· Individual rotary audio level conti

allow for an increase or decrease of audio levels as the master translates to

to 5-1/2 bours

reading LED indicators allow quick and accurate monitoring of audio fluctuations

Side A or A'B select button let you set up for duplication of either 1 side or both sides of a cassette at once

Stop all tapes instantly at any point during the copy or rewind cycle

ACC2000 Mono MasterModule

- 1/2 track two-channel monaural duplicator produces 3 copies from a cassette master at 30ips (16X normal speed)
 Expands up to 27 copy positions by adding ACC2000 copy
- Creating and the activity positions and adding activity concerns and activity positions activity and activity activity and activity activity activity and activity activit
- Includes removable power cord and protective dust cover
- ACC2000 AL Mono Master Module:
 Same features as ACC2000 *plus*-Extended Life cassette heads
 ACC4000 Stereo Master Module:
- 1/4 track four-channel stereo duplicator. Same features as ACC2000 Mono Master Module/ ACC4000 XL Stereo Master Module
- All features as ACC4000, *plus*-Extended Life cassette heads. Can be configured for chrome or ferric cassette duplication

Same as the ACC4000Copy Module, *plus*-Extended Life heads Configurable for chrome or ferric cassette duplication

Weighing only 8 lbs (36 kg), this unit has a durable impact resistant housing and includes a remov-able power cord carrying han-

ing system that provides gentle ape handling A mono version is also avail-

die and protective cover it

also has an optical, non-

reflective end-of -tape sens

Copyette EH Series Duplicators The popular Copyette series produces high quality, low cost cassettes in large quantities at nearly 16 times normal speed. This means you can reproduce both sides of a C-60 tape in less than two minutes. Available in two versions, the Copyettes are capable of duplicating either one cassette or three at a time. In addition each are available in both mono and stereo models. They couldn't be easier to use You simply insert the cassettes, press the START switch and they do the rest. They rewind all tapes to

the beginning, copy, then rewind to the beginning again before stopping. The whole process can be stopped at a ny time by pressing the CYCLE button Side Select feature allows u to set them up to copy one side of a tape or both sides at once Stereo Convette 1•2•1 able

Stereo Copyette 1-2-3

This du of three cassettes at once, yet as small as the 1•2•1. It weighs only 12 pounds (5 4 kg) and includes a hard cover to protect the unit while not in use. It uses all DC Servo motors for the ultimate in reliability



The classic 'no fulls' production workhorse, the 112 well is a 2 head, cost effective deck for musicians and production studios Extremely rugged and reliable, the 112 km II is ideal for production mastering and mixdown. It also features a parallel port for external control an and optional balanced connector kit means it is fiexible enough to integrite into any production studio Utilizes Dolby B or C noise reduction with Dolby HX Pro • Automatically selects proper bias type iso you get optimal

- recording & playbank response with Normal. Metal or Cr02 tape
- recording & piaybank response with Normal. Metal or CR2 tape Gas independent input data leftyou dal in stereo VU calibration with one dial. You can also aduat for channel specific calibration Offers two Autolocator buttons and a MEMOI IN control Thes controls allow you to select two points on any tape for one but-ton forwardiverses to wherever in the action is Additionally RT2 (return to zero) quickly spools the tape back to 6000 on the tape controls. tape counter • Rear-mounted RCA input/output jacks for easy connection to
- high-quality sources
- Optional LA-112 connector provides additional balanced or unbalanced XLR inputs and outputs Installation is simple and requires no special tool .
- · 25-pin D sub connector (parallel port) on the back, links the deck to the optional RC 134 remote control unit or for fader start from any mixer that use the same protocol

112R MKII **Bi-Directional Stereo Cassette Deck**

The 112R MkII is a sonically uncompromising auto reversing and continuous play cassette dick. It offers the finest indepen dubbing and editing features that make it ideal for long program recording dent bead auto-reverse design at this price level, plus it has extra

All the features of the 112 MK II plus-

- Three-head transport with separate high-performance record and playback heads. Manufactured from resilient Cobalt Amorphous materials, the independently-operating heads combine with precision FG servo direct-drive capstan motors to provide the highest standards of reproduction quality and performance Frequency response is 25 Hz to kHz with less than 1% total
- harmonic distortion Equipped with Hysteresis Tension Serve Control (HTSC) the

advanced servo control system that maintains consistent back tension on the tape all through the reel combatting inconsistencies brought on the extreme temperatures and humidity

- Super Acculign Rotating Haad System allows recording or playback tape direction to be changed with one button A six gle-screw azimuth adjustment makes it easy to maintain the head alignment after many hours of continuous use
- nead augment are: many hours of continuous use for unattended record/playback of material that is longer than one side of a tape, there are two features that spare you from constantly attending to the deck —Auto Reverse mode plays or records in both directions before stopping, switching sides on the fly Continuous Deverse mode clays or clays use to be the deverse.

stopping, switching sides children by —Continuous Revelse mode allows you to loop the tape dur-ing; layback up to 5 times, or record in both directions, with-out pausing to flip the tape and re-engage the record mecha-mism. Bothfeatures are accessible from the front panel, with one-button selection

122R MKIII **3-Head Stereo Cassette Deck**



The standard for production and broadcast facilities, the 122 will features smooth faultless tape handling mechanisms a three head transport with high-performance Cobalt Amorphous record/playback heads and precision servo direct-drive capstar

All the features of the 112R MK II (no reverse of course) plus-

- XLR balanced and unbalanced RCA inputs and outputs are selectable with the flip of a back-panel switch. There are 1/4-inch inputs on the front panel for simple and direct plug-in of
- line-level gear MPX filter buttow eliminates polot and sub carrier broadcast
- Hind builds in the reaction in the set of the set of the traditional to the set of lator adjustment signals to get proper VU calibration before or during each recording session
- Record/mute autoparer automatically inserts 4 sec. of silence between songs or broadcast segments for pro quality tapes

MOST ORDERS SHIPPED WITHIN 24 HOURS

CIRCLE 11 ON FREE INFO CARD

-Rewinds tapes to the beginning or end automatically (AUTO mode) or manually -in AUTO mode the copy button activates the entire rewind/copy/rewind sequence. In manual it starts copying ediately

- 1/2 track, two-c
 - 1/2 track, two-channel monaural copy module.
 Each module has four copy positions with erase heads and controls for side select.
 - LEO displays indicate end-of-tape status for each pocket
 Includes rbbon cables for connection to ACC2000 master and other copy modules.
 - tocludes removable power cord and protective dust cover
 - Additional and the power of the power o

Cassene platorin and/ess oxide build up of the heads and makes cassette loading and unloading much easier
Each cassette position has a three point tape guidance system that eliminates skew prob-lems. Plus, when a tape is inserted, each cas-ter and the system tape is inserted.

sette position is activated to prevent unreces-sary wear and tear on the tape head mechanism • Audio and bias, along with head adjustments, are made easily from the top of the unit and a switch on the back engages the head and simple mille for second adjustment along the

pinch roller for convenient cleaning

ACC2000 Mono Copy Module

1/4 track,four-channel copy module. Has all the features of the ACC2000 Copy Module ACC4000 XL Stereo Copy Module:

FOR PHOTO & VIDEO" 🔤 🐖

TO INQUIRE ABOUT YOUR ORDER: 800 221-5743 • 212 807-7479 OR FAX 24 HOURS: 212 366-3738

119 WEST 17TH STREET, NEW YORK, N.Y. 10011

Store & Mail Order Hours

Sun 10-4:45 • Mon & Tues 9-6 • Wed & Thurs 9-7:15 • Fri 9-2 • Sat Closed **BUSINESS LEASING AVAILABLE**





The 3630 provides two full-featured professional compressor/limiters in one rack space. Ideal for any application from studio recording and mixing to live sound reinforce nent and broadcast

Dual mong or linkable true stereo operation.

Chocse between RMS and peak compression styles as well as hard kin e /sch kine characteristics.
 Dual 12-segment LEDs display gain reduction and input/out-

put levels. • Each channel's mult-in noise gate has an adjustable thresh-

Each phannel's Huilt-In hoise gate has an adjustable intresti-old and close rate to ensure clean, transparent performance
 Varianie affack and release times and a sidechain function for "flucking" in broadcast applications.

t.c.electronic Wizard M2000 Studio Effects Processor

The M2H00 features a "Dual Engine" architecture that permits multiple effects and six different routing modes. There are 254

The M200 teatures a "Dual Engine" architecture than yermits multiple effects and so different routing modes. There are 254 factory programs including reverb, pitch delay, delay, chorus, flag, phase, ambience. EO, de-essing, compression, lmiting expansion, gaing and litereo enhancement. The M200M also fea-tures 20-bit analog conversion. AES/EBU and S/PDIF digital impuls/ortputs. "Witan:" help menus, 16-bit differing moles, Tap and MID1 tempo mode: and single page parameter editing. The array of mhanced pitch shift (up to 8 voices), chruns, and delay effects are characterized by their precision and versality. Everything frem the fine and suble to the wide and spectraturar is handed with equal superionity. The algorithms in the dynam-ics section (compression, limiter, expander, gate and the-esser) are unique as stami-some effects, but are particularly useful in combination with cither effects. Those might be de-eser/oom, nate chall or compression jfunction ensures semises transi-tion badjusti in best-per-iminite and sub-divided from M200 ran badjusti in best-per-iminite and sub-divided from M200 ran badjusti in best-per-iminite and sub-divided from M200 Preset "aliding" (morphing) function ensures seamless transi-tion between effects. Very useful in live and mixing situations. tion between effect . Very useful in live and mixing situations.

Control 5 **Compact Control** Monitor Loudspeaker

The Control 5 is a high per-formance, wide range control monitor for use is the prima-ry sound source in a variety of applications. It's smooth, extended frequency response combines with wide dramme combines with wide dynamic capability to provide acoustin performance that's ideal for recording studios, AV con-trol rooms and remote

trucks. • 6-1/2 inch (165inm) low frequency driver provide : solid, pow-erful bass response to 58 Hz and a pure titanium 1-inch dome

enuit bask response to 34 m2 and a pure manum ining nome handles high frequency response to 20 kHz. • Both transducers are magnetically shielded, allowing use in close proximity to video monitors. • Dividing networf- incorporates protection circuitry to privent system damage and utilizes high quality components including bypass cajavactions for outstanding transient accuracy. • Molded of dense polypropylene foam, with a choice of black, reavies which limeth.

gray or white finish. • Pleasing euclosure allow - It to easily fit into any environment. A host of mounting systems including ceiling, rack and ir pod allow positioning in exactly the right spot for best performance

4200 Series **Studio Monitors**

The 4200 Series are console-top monitor models designed specifically for use in the near field. Both the 6.5-inch (421%) and

specifically for use in the near field. Both the 6.5-inch (424%) and the 8-inch (4208) effer exceptional sonic performance, setting the standard for today's mith-inpropose studie environment? • Unique Multi-Radai sculptured baffle directs the axial output of the individual con ponents for optimum summing at the most common listening distance (approx. 3 to 5 th). • The baffle also positions the transducers to achive alignment of their acoustic centers so tial low, mid and high frequency information reaches your ears at the same point in time, resulting in superb imaging and greatiff reduce phase distortion. • Curved suffice of the ABSbaffle serves to direct possible reflections of the sonder wavelengths away from the listening justition, eliminating baffle effication distortion. • Vertical alignment of the transducers across the baffle center produces anzient immediment.

Vertical alignment of the transducers across the bathe center produces naruan mirroc-imaging.
 Pure titanium diaphragm high frequency transducer provides smooth, extended responsiv.
 Magnet assembly is shiftided, allowing placement near magneti-cally sensitive equipment like CRTs, tape recorders, etc.
 Low frequency components also feature magnetic shielding making the 4200 Series monitors ideal for use in video poer production facilitien as well as music recording studies.

FOSTEX XR-5/XR-7 Multitrackers MIDI/TAPE multi-mix

High-speed (1-3/4 ips) four-track (2-tracks simultaneously) recorder with built-in Dolby noise reduction (one had to be the second seco recorder with built-in Dolby noise reduction (can be turned off Pitch controller varies the tape speed within a range of $\pm 12\%$ off) Punch in/out function makes corrections and phrase insertions when necessary, can be done easily with optional ootswitch

Four inputs accommodate two microphones in channels one and two. Has convenient insert younts for connecting a comand two has obtained in their points to contract a contract pressor/imittle and other devices for the mic channels. • Each channel is equipped with two-point high/low shelving equalizers to help shape the sound, and an AUX send function for processing anbient system effects.

Trim function lets you switch High/Mid/Low input levels for

 Attinuition les you since in momente winput reves to channels one ind two.
 Alternate Mix mode lets you independently select the signa?
 from the input ack or the tape physicack. Prefader effect send, mine monitor & other functions are also possible using this mode. -Post foldback -monitor) send function routes the foldback sighal to the ALIX send. When the foldback is activated you can

actually mixdown at the same time you add reverb to a tape



can simultaniously mix all MIDI sound source output with tape playback sound and effect output while monitonnal

The XR-7 has all the features of the XR-5 plus-

Ine xH-7 has all the leatures of the XH-5 plus— 6 inputs, plus the ability to record four tracks simultaneously • Dolby C noise reduction plus dua, spied recording • During recording, Channels 5 and 6 are the primary inputs for microphones and accustic instruments. They have thin controls and mid-sweep EO. During mixdown, these channels act as the minimized the burn. main stereo L/R bus.

 Auto rehearsal mode let's you concentrate on the music instead of the machine



The easiest way to get into multitraik recording, the PORTA 05 is an extremely economical that lets you wverdub as

SAFE selection keins vol

over tracks you've

recorded earlier

from inadvertently recording

of multiple mono or stereo tracks onto a single empty track, leaving the orginal

submix tracks free to over

dub new material onto. You can

even add a "live" track to the submix while you're bouncing down, to squeeze in yet another

Headphone jack for com-fortable monitoring
 RCA output jacks for mixdown to calisette

XR-5 Features

- well as mixdown to standard cassettes. -4-track recorder with integrated two channel mixer Two 1/4-inch MICALINE inputs with trim control Extended dynamic range with DolFy 8 noise reduction

· 3-digit tape counter keeps track where you are on the tape

Master level control for the entire mix, and the level sent to
 LINE OUT for stereo mixdown
 Track selector indicates which of the 4 tracks you're recording to

PORTA 07 Ministudio

The PORTA 07 packs high-end features into a compact and economical package. Achieves great sound with high speel tape transport, high-low EC and DBX noise reduction. 4-track recorder with integrated to in channel mixe · "Bounce or "ping pong" a submi

- . Two 1/4-inch LINE inputs and two 1/4-inch MIC/LINE inputs
- with trim control S- parate high ai d low ED for each track provides t0dB of
- boost or cut. dbx noise reduction for improved signal-to -noise ratio.
- Punch-in/out r manually or with optional RC-30 footswitch.
 Effects send with stereo return can be applied in varying amounts to all four channels

Separate 3-band EQ section for each of the four mono

while you practice your punch-in/out and overdub moveswithout committing a single note to tape Two independent redicated AUX sends let you use more effects or use one as tape cue during tracking

424 MKII Portastudio

track

The 424 is premium Portastudio that takes multitrack recording to the next level. Features superior audio quality, traianced XLR inputs, enhanced equalization and a kig-studio style AUX section All the features of the PORTA 07 plus-

Dual-speeds, logic-controlled take transport system improves tap handling and sound quality. Select 3-3/4 inch per 4-track recorder with 8-input mixer (4 mono MIC/LINE inputs with 1/4-inch and balanced XLR jacks and 2 stereo inputs with second HIGH speed for • Auto Punch in/out with rehearsal, pl is a Repeat switch lets you set up a tape toop that goes over the same area of a tape

the best possible rei ord-ing quality or NORMAL 1-7/8 lps speed.

- Monitor output makes it easy to connect an external monitor amplifier without repatching-at mixdow
- · Tape DIRECT OUTS are provided for integration with external mixers

MLDI Musicians Take Note—I you've got MiDI keyboards, drum machines and sound modules in your set up, you van exploit the power of virtual tracking" with either the PORTA 07 or 424/464/488 Portastudio You can use a MiDI synchionizer like the Tascam MTS-30 MIDI-Tape Synchronizer to record (stripg) a code onto track 4 (track 8 with the 488), Just select STNC mode on the DBX switch and record the tone to tape. After striping the tape with FSK or Song Position Pointer commating, allyour MIMI instuments will faithfully follow the tape during playback and recording, even If you slow or speed the tape same the PICh con-trols. The big benefit is that your MIDI tracks (called virtual tracks) don't actually have to be recorded unit final mixdowi , giving the big more used tracke to record on. you lots more unused tracks to record on

464 Portastudio

The functionality of a pro recording studio in a small, lightweight uackage, the 464 Portastudin is a full-lea-fued eight input, four-track cassette recorder complete with a 12x2 internal mixer and dual buss design that less you create separate recording and cue mixes. All the teatures of line 424 wk II plus—

4-træck recorder with 12-input mixer (4 mono MIC/LINE with 1/4-inch and baianced XLR jacks. 4 stereo 1/4" jack jairs.

1/4" jacks.)

 Channels 1-4 offer High and Low shelving EOs and a sweepable Mid EO. Trzzks 5-6 and 6-7 have shelving EO only, while 9-10, 11-12 are best used with input that has its own internal FO

488 MKII Portastudio

When 4 tracks are just not enough then you need the perfect creative tool-the 488 MKII Portastudio The most cost-effective 8-tracks in corder on the market, the 488 bit of our direct additional capacity but versatile capability and intuitive operation for easy capturing & manipulation of your ideas. Whether recording accustic or electronic instruments or vocals, the 488 offs rs maximum creativ freedom to produce your best work. With all the functionality of a professional studio, the 488 may be the ultimate demo recording machine.

> SEVEN DAY CUSTOMER SATISFACTION GUARANTEE **CIRCLE 11 ON FREE INFO CARD**

All the leatures of the 464 MK II plus

 Includes phantom power for use with high-guality condenser microohones

microonones. - Bollit-in mixer features low-noise circuitry, with 12 inputs and 2 group busses. There is a separate input for your stereo master recorder. - Each of the 8 main input channels includes Individual 3-band equalitiers. You get Hi and Low shelving EOs, plus a semi-para-metrics weepable micrange EO - Lindow, mitting the canability of bandling in to 20 Unique multi-mix mode with the capability of handling up to 20

inputs at mixdown.

. The only 8-track cassette that offers a serve controlled tape transport complete with electronic braking. Equipped with a high-performance Hysteresis Tension Servo Controlled (HTSC) tape transport, the 488 ielivers better sound than the first 8track reel-to-reel machines

 HTSC maintains precise and consistent tape tension from the beginning until the end of the tape.It actually dynamically adjusts the back tension on the tape as it moves from one ento the other, allowing precise locating capability



Near Field Studio Reference Monitor

Designed by engineers with decades of experience, the award win ning Monitor One provides the last critical link in the recording studio's signal chain; giving you an accurate reproduction of what being recorded.

- Delivers excellent image and transient reproduction, powerful bass, and smooth, extended high frequency detail. Exclusive SuperPort speaker venting technology eliminates the
- "choking" effect of port furbulence for solid high-power bass transients and extended low frequency response. Ferrofluid cooled 1" silk-dome driver eliminates the harshness
- and ear fatigue associated with metal or plastic tweeters, making it easy to mix on for extended periods. Monitor One's powerful bass incorporates a proprietary 6 5" low
- frequency driver with a mineral-filled polypropylene cone and a 1.5" voice coll wound on a high-temperature Kapton former
- They come in a mirror-image left/right pair covered with a non-slip rubber textured laminate for stable mounting

Monitor Two

Mid Field Studio Reference Monitor With much of today's popular music demanding more bass at

louder volumes than a small near field monitor can possibly produce-the Monitor Two delivers-at a price no higher than many of these smaller speakers. • Utilizes a 10" three way speaker design with a unique asymmetrical



crossover to maintain the same accurate tonal balance and imaging of the Monitor One—but with a much larger sound field. 10" low frequency driver incorporates Alesis' SuperPort speaker technology to provide powerful, extended bass.

- mid frequency driver offers exceptional mid frequency detail 1° silk dome high frequency driver delivers a broad but natural
- frequency response from 40Hz to 18kHz Covered in a non-slip rubber finish, the Monitor Two comes in a
- mirror imaged pair for mixing accuracy

TANNO **PBM Series II Reference Monitors**

The PBM II Series is the industry standard for reference moni-tors. They feature advanced technologies such as variable thickness, injection molded cones with nitrite rubber surrounds and the highest quality components including polypropylene capaci-tors and carefully selected indicators. With a Tannoy monitor system you are assured of absolute fidelity to the source, true dynamic capability and most important, real world accuracy



PBM 5 II

Custom 5" injection-molded bass driver with a nitrite rubber surround for extended linearity and accurate low frequency surround for citized internet into account of the decount of the reproduction. They are better damped for reduced distortion and exhibit more naturally open and detailed midrange. Wooler blends seamlessly with the *X* polymide soft dome ferro-fluid cooled tweeter providing extended bandwidth for

extremely precise sonically-balanced monitoring Designed for nearlield use, the PBM 5 II cabinets are produced from high density medite for minimal resonance and features an anti-diffraction radiused front baffle design

PBM 6.5 II

- Transportable and extremely powerful, the PBM 6.5 II is the
- ransportable and extremely powering, the row of of its the ideal monitor for almost any project production environment.
 6.5" Iowfrequency driver and 3/4" tweeter are fed by a completely redesigned hardwired hand selected crossover providing uncom-Fully radiused and ported cabinet design reduces resonance and diffraction while providing deep linear extended bass

PBM 8 II

control and enormous dynamic capability. 8° driver is capable of powerful bass extension under extreme SPL demands

components available. • Full cross-braced matrix medite structure virtually eliminates

Ensures precise low frequency tuning by incorporating a large diameter port featuring laminar air flow at higher port velocities

cabinet resonance as a factor.

Hard wired crossover features true bi-wire capability and utilizes the finest high power polypropylene capacitors and

High tech 1" soft dome tweeter with unmatched nattem



SPIR

FOLIO LITE

Compact Professional Mixing Console



OR FAX (24 HOURS):

MIXPAD 9

Adjustable mic input trims allow use with

and the second second

Phantom powered XLR mic input connectors.
 Peak LEDs for left and right main outputs
 Extremely durable, extruded aluminum ch. ssis

To To Yo Yo Yo

FOR ORDERS CALL: 800-947-5518 212-444-6688

in-line power supply eliminates magnetically-induced hum

2 auxiliary sends for effects and two Stereo returns
 Independent 2-band shelved EQ, pan control for mono chan-

- 3 mic/line inputs and 3 stereo channels (total 9 inputs)

nels and balance control for stereo channels

4

A remarkably comp

800-947-9003 212-444-5001



E-Mail at 76623.570@compuserve.com



Newly-developed, powerful noise gate. Switchable soft knee/hard knee characteristics for varied

sound pressure levels. Bright, illuminated LEDs show gain reduction



 Integrated auto/manual compressor, expander & peak limiter · Compresses "musically" in dynamic range without any audi-

ble "pumping" or "breathing". Attack & release times are controllind automatically or manually Interactive Gain Control (IGC) combines a clipper and peak limiter for distortion-free limitation on signal peaks Servo-balanced inputs and outputs are switchable between
 +4dB and -10dB.



High frequency switch mode power supply fully charges 120,000 times per second (1000 times faster than most power supplies) requiring far less capacitance for iltering and storage
 High speed recharging also reduces power supply "sagging" that

afflicts other designs Incredibly efficient 5 PA-1i400 or PA-1400's (4 PA-1800's) can there using encloses and and 20 amp parcels to see the standard 20 amp parcels to no end for staggered turn-on configurations or other preventive measures when using multiple amp set-ups They produce smooth and uncolored sound, while offering very

full detailed low end response and tons of horsepo · Each amp carries a full 5 year warranty on parts and labor

PA-1000 weighs 9 lbs. is 15" deepand occupies one standard rack space. Delivers 1000 watts into 45. when bridged to mono PA-1400 weighs 16 lbs. is 15" deep and takes 2 standard rack

paces Delivers 1400 watts into 412 when bridged to mono PA-1800 weighs 17 lbs. is 17" deep and takes two rack spaces ers 1800 watts into 462 when br idged to mono



Performance Series Amplifiers



86

Measuring only 3.5 inch is high and weighing 26 pounds, the Series 1 delivers more than 15 I watts per channel Its welded steel chassis is unbillevably strong while a custom

has includ according as a dramatic tably along miles obsolved heat sink extension provides exceptional thermal capacity An internal fan provides quiet background noise levels for critical monitoring applications and wien pushed hard the cooling sys-tem insures continuous cool operation even in the most demanding situations

Active balanced inputs with both XLR and 1/4" phone lacks Suppled with quality 5-way bridling posts for highly reliable speaker connection
 Front panel handles are reversible for either rack mount installa-

tion or easy handling • LEDs are provided for signal presence and clip indication, the letented gain controls 'lave large knobs for easy front panel adjustment

Performance Series 2

600-Watt Power Amplifier Same as above except the Series 2 weig 32 pounds and deliv ers more than 300 watts per hannel.

Performance Series 4 1200-Watt Power Amplifier

• Same as above except the Series 4 weighs 53 pounds and deliv-ers more than 600 warts per channel • Has a switch selectable clipping eliminator that prevents damage to the speakers

sentchable pre/post fader switchable pre/post fader PFL Slolo on all inputs, dedicated tape return Headphone socket and discreteUR outputs for mo 10-segment three color bar graph metering Consistent hingh performance controls, global phan Optional rack mounting panel and PortaPower Unit

FOLIO SI

Stereo Input Mixing Console All features of Folio Life PLUS— • 16 inputs as standard (20 including stereo returns) • 3 stereo channels and 2 moin channels, with 60mm faders • Comprehensive 3-band E0 on inputs 1-14 • High pass filter on mono inputs • Oedicated tape return and control room outputs • Insert points on L, and R master outputs • 12-segment bar graph melering • Wain outputs are mound compensated and immediance balan

12 inputs as standard (up to 16 at mixdown)
 4 mono channels & 4 stereo chann Inserts on all mono inputs and mix outputs

2 Aux sends on all channels, Aux 1

Ultra low-noise (-129 dB

EIN) mic inputs Musically responsive 2-band EQ

12-segment bar graph metering
 Main outputs are ground compensated and impedance balanced
 Free standing or rackmount versions available
 Optional Porta Power unit allows battery powered operation

from various sources

FOLIO RAC PAC 4-Bus Multi-Purpose Mixing Console

12212232211

14 input channels with up to 28 inputs at mixdown
2 stereo inputs with 60mm faders and 2-band EQ ·1.0 use (-129 dB) mic

Comprehensive 3-band EQ with swept Mid_plus high pass filter on every mono

input 6 versatile Aux sends, 4 dedicated fully-fledged stereo returns plus 2 stereo effects returns

Stereo solo-in-place (PFL) on every input channel · Direct outputs on each mono channel for recording direct to multitracks

Dedicated 2-track tape return routable to mp Global phantom powering, compact 8U rack-mount design

POWERSTATION **Powered Mixer**



Studio quality mixing, with a power amp and effects prov an all-in-one solution for ive performance

8 mono and 2 stereo input

channels
 18 inputs at mixdown,

- Includ-Ing tape and effects returns Bullet-proof UltraMic pre-amps with 60 dB gain range for stunning signal handling capability High-spec 265W + 265W (RMS) power amp Bullit-In Lexiton effects mixer Consistent high performance controls. PFL solo on all channels 3-band EQ with swept mid-frequency on mono channels 2 auxiliaries for effects and foldback 7-band precision dual graphic EQ Hinb haas thire on mono inputs

- High pass filter on mono inputs
 40 Hz subsonic filter on outputs to protect speaker cabinets
- 48y phantom power

Inserts on mono channels and main outputs

Inserts on mono channels and main outputs
 Separate power amp input to amplify external sources
 Dedicated record outs and tape returns dedicated mono output
 Rugged steel chassis hinged cover for protection

PROTRACKER

In-Line Multitrack Recording Console





- ProTrackers High quality, high gain mic pre-amp (-129 dB). 5Hz-150kHz) with switchable 48v ghantom power on every input Switchable hugh pass filter on every channel Built-in limiter (300ms attack imer6 sec release) selectable on every channel Overioad and limiter indicators on each channel Insert and aus switchable between channel and monitor paths

- Aux globally switchable pre/post fader
 Monitor fader and pan control
- Monitor fader and pan control
 Balancet lape & send/return, switchable between -4d8 &-10d8
 Separate pre -fade insert and return sockets, eliminating the need for Y-cables
 Inputs switchable to mix to allow simultaneous front -of -housing mixing and recording
 Mix routable to tape sends 7/8 for simultaneous 2-track recording on a single multi-track, without effecting multitack feeds from channels 1.0.6
- from channels 1 to 6 Headphone monitoring of 2-track return, aux,7/8 or mix
- Monitor outputs follow headphone output
 Mix output & 2-track return accept +4dE XLRs or -10 dB RCA phonos

 Working S/N tatio of 90dB, distortion below 0.025% across the entire audio spectrum and +28 dB balanced me drivers 4 mono channels with discrete, balanced balanced me/bine inputs and 4 stereo channels (12 inputs total) Line inputs and outputs work with any line level. Iron instru-ment level, to semi-pro -10dB, to professional +4dB.
 Sealed rotary pots resist Switchable phantom-powered (48%) inputit for condensar mic Every input channel has a gain control, par pot, low EO at 80 Hz, high EG at 12,5 kHz and two aux sends with 2CdB gain Master section includes two stereo returms, headphone level control and metering Sealed rotary pots resist and other contaminants. **MS1402-VLZ** 14 x 2 Compact Mic/Line Mixer Mackie's fanatical engin -hand

NSON°

Ultra-Compact 9-Channel Audio Mixer

A remarkably compact 9 inhannel mover. The MIXPAD 9 offers professional audio performance and a wide range of user-intensive limitures. It boasts low noise and distortion specifications, includes wide-range gain trim controls for both mic and line inputs and provides exceptionally low group delay over the full tre quercy bandwidth for a more transparent, open sound It also has a very high slew rate—usually found only on larger, more expensive mixing consoles—allowing in to react very quickly to transients and main-tain a crisp, articulate sound. It offers phantom power (48v) for use with condenser microphones and an and an ender sound and an ender sound and an ender sound and an ender source of the so

ALL SLO

MICRO SERIES 1202-VLZ

12-Channel Ultra-Compact Mic/Line Mixer

Usually the performance and durability of smaller inwers drops in direct proportion to their price. Fortunately, Mackie's fanatical approach to pro sound engineering has result-ed in the Micro Series 1202-VL2 an affordable small inwer with studio specifications and rugged construction. It delivers no-compromise, non-stop, 24-houra-day professional du in permanent PA applications. TV and radio stations, broadcast studios and editing suitee-where nothing must all output of the duration up 005b, access the Suitebable abaption.

six studio-quality mic preamps and extra Alt 3-4 stereo bus—in less feet of space -in less th

 Studio grade mic preamps (chs. 1-6) with high headroom, low Subio grade rine preamps (ctrs 1-o) with migh nearborn, row noise and phantom power Also incorporate low cut if first so cut mic handling thumps, pops and wind noise. Lets you safely use low shelwing 60 on vocals.
 Trim controls (ch 1-6) with uitra wide range (+1010 - 40dB) handle everything from hd rdigtal multitrack feeds to whisper-ing lead singers and older, low output keyboards.

Pan control with constant loudness and high UR attenuation so you can pan hard left or right without bleed-through
 Two aux sends per channel with 15dB extra gain above Unity

• Two au

mining an 1 3 square

· 60mm log-taper faders are accurate along their whole length of

accurate along their whole length of travel and employ a new long-wearing contact matenal for longer fader life & uper resist-ince to dust, smoke vic Control room/phone matrix adds incredible tape monitor.ng, mixdown and live sound versatility. • Mute switch routes channel output to exita ALT 3-4 stereo bu ... Use if of releding multitrack recorder channels, creating a sub-group via control room/phones matrix, menitoring a signal before bringing in into the main mix or creating a" mix mixes. • Solid steel chassis instead of aluminum or plastic.

The new MS-1202, 1402 and 1604 all include VLZ (Very Low Impedance) circultry at critical signal path points. Developed for Mackle's acclaimed 8-Bus console series, VLZ effectively reduces thermal noise and minimizes crosstalk by raising current and decreasing resistance.

CR-1604 VLZ

16-Channel Mic-Line Mixer

 Localization of toxing organises, studio session players, as well as
 broadcast and sound contracting The new CR-1604 VL2 features everything you
 would expect from a larger console, and then some 24 usable line inputs with special
 headroom/ ultra-low noise Unityplus circuitry, seven AUX sends, 3-band60, constant porver pan
 controls. 10-segment LED output metering and discrete front end phanom-powered mic inputs
 "Lowest noise and highest headroom (90 dB working SN and
 108 dB dynamic range). Many drummers conserved in the only
 more capable of handling the attack and transients of acoustic
 and electronic drums.

and electronic drums Genuine studio-grade phantom powered, balanced input mic preamps on channels 1-6 All CR-1604 VLZ (and optional XLR10

preamps on channess for all other took vice (and optional ACHO) for ten more) discrete input inc. preamp stages incorporate four conjugate-pair, large-emritter geometry transistors. So whether recording nature sound effects or heavy metal miking futes or kick drums, you get the quittest, cleanest routis possible

sent indicators. New standard size channel, as well as RIA tape inputs/cutput
 New standard size channel trim pots are found at the lop of each channel Rear panel features include insert ooints and 1/4-inch /XLB con

FLEXIBLE EQ SECTION

your FO application

either without repatch

EQUIPMENT LEASING AVAILABLE CIRCLE 1 ON FREE INFO CARD

PLEABLE ED SECTION Bi-directional split EQ means you can use either or both EQ sec-tions in the Monitor or Channel path. or defeat the effect alto-gether with one bypass button. Other comparably priced nikers will lock the shelving mix into the Monitor path only, limiting

AOVANCED SIGNAL ROUTING DPTIONS

group and direct-out jacks are one and the same, you can select

ERGONOMIC DESIGN

The M-2600 has a big studio teel. Alibutions are tightly spring loaded, lock into place and accomodite even the biggest ingers. The faders and knobs have a tight, smooth "expensive" feel and are easy to see, reach and manipulate. Center detents assure zero positions for EQ and PAN knobs, Smooth ang throw 100mm faders glude nicely yet lollow you to position them secure by without fear of accidentally skpping to another position.

Direct channel input switching Assign to one of eight busses, direct to tape or disk, or to the master stereo bus Because the

each channel • Rotary input/output "pod" allowing three different positions for set-up

TASCAM M2600 MKII Series 16/24/32-Channel 8-Bus Mixers

LOW NOISE CIRCUITRY

PREMIUM QUALITY MIC PRE-AMPS PREMUM QUALITY MIC PRE-AMPS The M-2600's mic pre-amps wid an extremely low noise floor enormous headroom and an extremely flat frequency response talso increases gain control to an amzing 51dB. Plus you get phantom power on each channel Accepts balanced or unbalanced 1/4' inputs, and low-imped-ance XLR jacks. Better still, the TRIM controls operate over a etdb C.R. construction for the horizon processor and it to be

STGB input range For the holdest incoming signals, all it takes is a press of the -20 dB PAD button atop each channel strip to bring any signal down to manageable levels. Plug in anything-keyboards guitars basses, active or passive microphones,

THE BEST AUX SECTION IN THE BUSINESS

INE BEJI AUX SECTION IN THE BUSINESS Versatile AUX section has 8 sends total, 2 in stereo. Send signal in stereo or mono, pre-or post-fader. Available all at once. Return signal through any of 6 stereo paths.

• The M-2600

mplers

Combining completely redesigned low noise circuitry with Absolute
 Sound Transparency¹⁴ the N-2600 delivers high-quality, extremely
 clean sound. No matter how many times your signal goes through the
 M-2600, it won't be colored or altered. The signal remains as close to
 the original as possible. The only coloring you hear is what you do with
 creative EQ and your outboard signal processing gear
 Double reinforced grounding system eliminates any hum
 World-class power supply provides higher voltage output for
 better headroom and higher Na too.
 PREMIUM QUALITY MIC DBC sector

FOR PHOTO & VIDEO" 🔤 🥯

TO INQUIRE ABOUT YOUR ORDER: 800 221-5743 • 212 807-7479

OR FAX 24 HOURS: 212 366-3738

TASCAM DA-P1 Portable DAT Recorder

Portable DAT Recorder
 Rotary two head design and two direct drive metors for the best transport in it class.
 VIR-balanced micli ine inputs (with phantom power) accept signal levels from -50dB to 4-4B.
 Analog line inputs 3 outputs (unbalanced) pius S/rDIF (FPA) digital inputs and outputs enable direct digital transfers.
 Uses next generation A/D & D/A converters for amazingquiatily.
 Supports 32/44.1/48kt/s ample rates & SCMS-free recording.
 MiC limiter and 20dB pad to achieve the best possible some without outside disurbances.
 TRS jack & level control to monitor sound with any ieadphilmes.
 Buint togh. the DAP't is housed in a solid, well-constructed

without outside disturbances TRS jack & level control to monitor sound with any iread/ihi mer Built tough, the DA-P1 is housed in a solid, well-constructed hard case. It includes a shoulder belt, AC adapter & 1 battery

SONY TCD-D8 **DAT Walkman Player/Recorder**

Long Play (LP) motie allows 4 hours of record/playback of 12-bit audio on a single OAT casselt. Equipped with digital coaxial and optical input connector. Also hours of the optical analog Mic and Line inputs. High-speed Automatic Music Sensor search function (Indis & plays tracks, skips foreard or

Sensor search function finds & pays tracks, skips forward or back up to 99 tracks, all at 100x normal speed Objiptal Volume Limiter System increases listening :omrbrt & sound quality butomatically adjusting for souden level charges. Two-speed cue-rewew lets you hear sound while player is in fast-wind modes, up to 3x or 25x normal speed LCD display with backlit windows clearly shows record ng

level track number, operating status and 4-segment battery ator, even in low ambient light conditions. ndicator

 Optional RM-D3K Lystem Adapter Kit for complete digitall
 interface. It has input/output connectors for both the optical cable & the coaxial lable. Also includes a w less remote nontre

TCD-D10 PRO II **Portable DAT Recorder**

Hac h Has balanced XLR nput, so mic (-60dB) or line (+4dB) inputs. A 12-pin divital con nector provides interfacing with AES/EBU digital sig-nals of 32/44.1/48.0 kHz sampling rates

Comprehensive selt-diagnostics fund

comprehensive self-diagnostics func-tion constantly monitors the rotation of the head drum, capstain and reles. The tape transport mode and load/unload time are continuously checked as well
Up to 99 start IDs can be recorded in the subcode area. When the record button is pressed, the start ID is recorded auconsti-cally for 9 scoods. During recording, it can also be added manually to any position of the tape. Search for start IDs is 100x normal speed.
20-segment dig tal peak level meters include overload indicat-tors. Closely tracks input signal for accurate level and indications. During Jabyack, I'rs data and time of recording is displayed.
Has a record-level initier with a tast attack time of 300ms. Mic attenuator prevents distortion by suppressing signal leve. 20 cB.
Immediate playback is possible through a built-in gealaer.

Supplied wired remote controller also accepts a mic holder

Supplied Wheel related to the standard of the





Direct drive transpirif with 4 heads for confidence monitoring, Balanced XLR mic and line analog inputs and two RCA insign line outputs. Digital inputs and outputs include S//PDIF rom-sumer (RCA) and AES/EBU balanced XLR
 VER (VGA/PDIF) and AES/EBU balanced XLR
 VER (VGA/PDIF) and AES/EBU balanced XLR
 Vertight channel mic input attenuation selector(VGA/PDIF) and AES/EBU balanced XLR
 Vertight channel mic input attenuation selector(VGA/PDIF) and AES/EBU balanced XLR
 Vertight and AES/EBU balanced XLR
 Vertight channel micro & incremal mon tor speaker.
 Illuminated LCD display shows clock and counter, pack level
 metering, margin display, battery status. ID number, lape
 source status and machine status
 Supplied Microkel Metal Hydride rechargeable battery powers the
 POR1000 for two tours. The battery has no "meminy effect"
 Adapter/charger

PDB1000TC Additional Features

PDR1000TC Additional Features: In addition to all the teatures of the PDR1000 recorder tile PDR1000TC is equipped to record, generate and reference to time code in all existing international standards. • All standard SMPTL/EBU time codes are supported, inclucing 24, 25, 29 37 (drop trame and non-drop trame) and 30 pp. • External synconization to video, field sync and word sync



A full function workstation, the DM-800 performs all digital mixing opera-In the microri workstation, the birror boy performs an utility and imaging in the performance of the second second

HIGHEST QUALITY SOUND • Sampling rates of 48/44.1/32 kHz • 24-bit intern - I processing • 18-Bit A/D and D A with 128 and 8 times oversampling

FULL AUTOMATION

FULL AUTOMATIUN Microscope editing of automation data Dynamic and shapshot automation of level, san, 2-band EQ, including frequency select, boost and cut -Phase level editing of level, crosstade and fade in/out

MIDI FEATURES

• MtDL mar • MIDI machine control • Internal tempo mass • MIDI clock and song position pointer output • 8 MIDI triggers for instant phras- playback • MIDI trigger of record and punch involut • Tempo maps from exturnal sequences, MIDI or tap input. . nal temno

RECORDING OPTIONS

Records to standard SCSI hard drives Up to 24 hours recording time possible Uses MO, Syquest or Jazz drives for fast provect change overs

PROJECT CATALOGING

project zoom

Multi-Track Recorders

TASCAM DA-88

The first thing you notice about the eight channel DA-88 is the size of the cassette - it's a m II HI-8 vid ec cassette Y ju'll also notice the recording time - up to 120 minutes. The move of the advantages of the DA-NB simovative use of Brann technology. These are just 2 and the advantages of the DA-NB simovative use of Brann technology. ATF system ensures no tracking errors or loss of synchronization. All eight tracks of audio are perfixed y synchronized. It also **qu**arantaev perfect tracking and synchroniza-tion between all audio tracks on all bascaded de like - whether you have one deck or sixteen win to 128 tracks!)

Incoming audig is doubter by the un-board 16-bit 0/A at either 44.1 or 48KHz. The

Incoming addits organized by the in-tools of orall by at entite 44. Or 46667, the frequency response is fait from 2012 to 21%Hz while the dynamic range exceeds 92dB. • Execute warmlers Punch-ins and Punch- oits. This feature offers programmable digital crossfades, as well is the ability to insett new material accurately into hight spots. You can even delay individual tracks to generate special effects or compensate for poor fining.





POWERFUL EDITING

veform zo am • Orthonal RS-422 interface

o AUX send buss, 2 pereo AUX

reums Digital stereo input and two digit. I - tereo putputs - Direct channel cuts 4 balanci di analikg inputs with gain con-tricts and 4 balanced analog outputs

ACCURATE SYNCHRONIZATION

FLEXIBLE 1/0 STRUCTURE

Time compres ion, pitch diamp · Non-destructive cutting, erasing, popying · Faut looping for music or ambiance edit

· Si level

- Eullid

Flawless sound quality, outstanding reliability and profeliational audio interfac-ing with AES/EBU digital I/O and XLR analog I/O commetilins.
 Combines audio functions such as precise auto pumin involut digital cross fade technology, external synchronization with SMPTE/EBU time code and selec-table sampling frequencies to 44.1 and 48Hzt.
 Shuttle dial for precise tape control, variable speed glayback of 6% in 0.1% becomente and a full featuremy response free 70Hz to 70Hz

Make flawless copy/paste digital edits between machines or even within a single unit. Track Copy 'pature makes a digital clone of any track (or group of tracks' and copies it to any track (or group) on the same recorder. This allows you to

track (or group) of me same recorder. The allows you to assemble composite tracks for digitalized/ineq opposite of low multiple ADAT-XTS and Tape Offest lets you copy and paste not only irack to track, but from location tap. Offset assembles your project with a minimum of repetitive overdub-bing and changes the tape position of a slave XT to its m.ster, so you can "fly" adult of different locations on each tape. Track Delay can delay the time reference of a track by up to 170ms. Also each changes the to encous of a tune. Track Delay to the series the provide the time reference of a track by up to 170ms. Also each change step around a tune. Track Delay to the series the provide the time reference of a track by up to

170ms. Also easily change sthe groove of a tune. Track Delay is individually adjustable on each channel and is excellent for fixing

stight timing errors in recorded tracks (player lags behind or rushes the beat). In recordings with multip a microphones, you can time-align each track, precisely compensating for the spac-ing between mics with accuracy to 0,0001 seconds

an; other

nes, you

played back

toring.

functionality to the D-10.

a bind im

Dinital Editor:

MinimumShipping USA (Except AK & III) \$7.30, up to 3 lbs. Add 50c for euclyadditional lb. For lies, add 40c per \$100. 1996 B&H Photo - Video. Not responsible for typographical errors. Prices valid subject to supplier prices. CIRCLE IT ON FREE INFO CARD

Snuttle dial for precise tape control, variable speed playback of 6% in 0.1% increments and a flat frequency response from 2014 to 21kHz.
 Overate up to 15 PCM-9C0's in perfect sync with cubinal RCC's 1 sync ables for up to 128 Channels of digital audio record ng.
 Overate up to 15 PCM-9C0's in perfect sync with cubinal RCC's 1 sync ables for up to 128 Channels of digital audio record ng.
 Overate up to 15 PCM-9C0's in perfect sync with cubinal RCC's 1 sync ables for up to 128 Channels of digital audio record ng.
 Overate up to 15 PCM-9C0's in perfect sync with cubinal RCC's 1 sync ables for up to 128 Channels of digital audio record ng.
 Overate up to 18 PCM-9C0's in perfect sync with subtrame accurate citizence in the cubinal ABN synchronizes to external video reference signal.
 Optional RM-Di000 provides comprehensive remote control over all PCM-800 functions.
 The RM-D800 can control up to six units
 for up to 48 cubinels of eightal audio.

ALESIS adat xt

8-Track Digital Audio Recorder

An incredibly aftiridable tow, the ADAT-XT sets the standard in mod-ular digital multitack recording. With new features & enhanced capa-bilities, the ADAT-XT operates up to four times faster than the orgi-nal ADAT offers an intelligent software-controlled tage transport and provides unboard digital editing and "lexible autoincation. Flexible Inputs and Outputs: Flexible Inputs and Outputs: Servo-balanced S6-pin ELCO connectar operates at +4dB to interface with consoles with +4 dB barenhul inputs/outpcts. Also unbalanced -10dB inputs/output! (phi-no connectors). Has an electronic patch bay built-in s in Ican be used with stereo and 4-bus consoles. Multiple Optical Digital I/O carries up to eight tracks at onie. The digital I/O combined with the ADAT Synchronization Interface make it completely compatible with any ADAT-format recerder or other devices that use Alesis' proprietary digital protocel.

Stuoning Audio:

 Incorporates uitra-high Ili-lifty 18-idi, 128 X oversampling AD converters which praced better-hin-Do audic quality.
 For outputs, the D/A converters yrovide 21-bit, 8x versam-pling performance for a flatter frequency spectrum, improved phase response and much less low-amplitude discortion.
 20 Hz to 20/kHz ad 564 frequency spectrum, 20/83 AV ratio, crasstalk between channel: better than -900B @ 19Hz. prates u tra-high fidelity 18-bit, 128 X oversampling

Onboard Autolocator with Auto Record:

- Unbacra Autolocator with Auto Incent; Orboard Topeint autolocate system provides quica access to multiple tape liveations. Four specialized locate points make ydur recording sessions quicker and easier. Auto play the moment ang autolocation pdint is reached, Auto Return automatically rewinds at the end of a loop. Auto Return durction Histy ou automate pench-involunch-out times that are uscurate to 1/100m if a second.

- miles ma are jecuratero vi voun el a sebino. Referers Mode allows jou centro or exit recorti modes without actually laying irazkis to tape: To record on te fly, you can even use the individual Record Erable buttons io punci in and curfot tracks: Indiudes temoto control with tracsport and locate tenctions, offers a tootswinch jack for handi-free punch-in.
 - Intelligent Transport: Acvanced transport software continuously monitors autolo
 - Brances rate provide a commoday memora another account of the second seco

Roland[®] **DM-800** Digital Audio Workstation

119 WEST 17TH STREET, NEW YORK, N.Y. 10011

Store & Mail Order Hours:

Sur 104:45 • Mon & Tues 9-6 • Wed & Thurs 9-7:15 • Fri 9-2 • Sat Closed

BUSINESS LEASING AVAILABLE

A compact, stand-alone multi-track disk recorder that provides an amazing array of features at an unbelievably low price. Whether for music production post production or broadcast, the DM-800 lets your work easier and taster.

TRIGGER FEATURES

 Trigger mode to play any combination of 8 tracks for vocal ity ins or sound effects placements
 Advanced tricmer mode for live operation with preset or dial up cue of phrases to be played one after another

Up to 150 projects on line at once
Cataloging of sound effects and projects
Easy transfer of seunds from one project
to another
Up 50 out

VIDEO OUT

- Composite, S videx, digital RGB outp
 All track oversiew with infinite level of
- Views of phrase and waveform editing

Very accurate level meters
 Track status and time location

Panasonic SV-3800/SV-4100 Professional DAT Recorders

PHOTO - VIDEO - PRO AUDIO



Designed for professional applications, the SV-3800/SV-4100 have highly accurate and reliable transport systems with search speeds up to 400X normal, and 20-bit D A converters to satisfy the highest ional expectations both in terms of sound and functionality SV-3800 Features:

ecording via analog inputs offers sampling rates of 44.1 or 48kHz

- Recording via analog inputs offers sampling rates of 44.1 or 48kHz When recording through digital inputs, in automatically clocks to incoming frequencies of 3244.1 or 48kHz
 XLR-balanced adjust inputs/outputs plus consumer format cataval and optical inputs/outputs. XLR-balanced analog stereo inputs/out-puts. Output level is selectable between -4db and -104b. The input level is -4db
 Built-in shuttle wheel has two vanable speed ranges. 3 to 15x in Play mode and 172 to 3x normal speed in Pause mode
 High speed transport enables searching up to 250x normal speed scanned in Play. For REV mode. This ensures access to any point on a two-hour DAT in under 30 seconds.
 Ramped record mute and unmute with Infee aeconds lade-in and five sconds tade-out provides automatic level changes at the start and end of a recording.
- five seconds fade-out provides automatic timer charges at the second and end of a recording. Comprehensive display includes program numbers absolute time, program time, remaining time and Table of Contents

SV-4100 Has all the features of the SV-3800 Plus-

SV-atou has all the realizes of the SV-Sou Fus—: Offers enhanced performance required for professional production, broadcast and live-sound systems. Features such as instant start, external sync capability and enhanced system diagnostics make the SV-4100 the DAT quality standard



Digital Master Recorder With professional features and a



consumer prive tig the U-s satis-fies a lot of requirements. It records or play-back four hours of music includee optimal and digital input/output, and TOC functions that are as easy to use as a CD player (I's guipped with bacis pro features such as inction, GPI and XLR cosm stors and 300X each functions.

speed locate and search functions Playback/record audio with32/44 1/48 kHz sampling in SP (sta dard play) mode. Equipped with LP (long play) mode. It can play/record at 32 kHz up to 4 hrs. on a 120 minute cassette

Analog interface includes switchable (+4dB/-10dB) balanced and Analog interface includes switchable (4-doc/-100b) palanced and unbalanced XLR inputs and outputs
 AES/EBU digital interface (XLR) for professional use and optical (S/PDF) input/output/or consumer/sem-ipor connections
 -goin GPI input connector allows. Play, Stop & S-ID search to be implemented through commands from an external source Records CD-0 code sync ID, enabling precise music start up

When performing digital signal transfer from CD through it's optical input, the D5 precisely records S-IDs according to the track number and index information of the CD-Q cade. So even if there is break in the middle of a song or there isn't a non-recorded section between two songs you can locate to the S-ID location (eg

D-10

Digital Master Recorder

Switchable 44.1 and 48kHz sampling frequenus
 Analog interface includes switchable XLR-balanciud (+4dB)
 and unbalanced RCA -100B inputs and outputs
 Equipped with and XLR-balanced AES/EBU digital interface and
 optical (\$PPIP) input/vature conforming to 16C consumer
 Built-in RMB RAM (4 MB x 2) offers instant start as well as scrub-bin at Intercond accuracy

Auto Cue provides automatic locating to the exact start of audio modulation during ID search and tape loading

Universa GPI input/output enables easy and fast assemble editing based on A-time between a pair of D-10s. Switchatle 2-position reference level. 12dB-20dB. Start and Skip IDs as well as up to 799 P-NOs can be recorded and

bing at 1m/second accuracy. Advanced jog/shuttle for precision cueing and monitoring

10-digit key-pad lets you store and recall 100 cue points Continuous or peak reading level meters can display available headroom with an accuracy of ±0 1dB
 Reads and displays A-time or Pro R-time also provides PCM moni-

Optional 8333 interface card adds timecode and RS-422 (X 2)

Reads an external timecode and records on the sub-code area Reproduces and outputs the timecode from sub-code area -Switchable RS-422 and ESbus protocols Using the ESbus up to 16 D-10s can be daisy chained.

beginning of song) precisely

2222

HELP WANTED

AUDIO BENCH TECH NEEDED

Atlanta GA. CTG a pro audio/video service shop seeking audio bench tech with 2 yrs experience. Must be able to repair at component level. ADAT & DA88 experience a plus. FAX RESUME: 404-352-2962

AUDIO UPGRADES

LA-2A LA-3A OWNERS Before you by a new T4B optical attenuator, have it rebuilt at a fraction of the cost. Also stock OPTO's. ANTHONY DEMARIA LABS 914-256-0032 ************

INFORMATION GUIDES



SONGWRITERS

NGWRI T ERS Have you been searching for these items *Contracts, Copyrights, Business Books, Blank Cassettes *Blank, Color & Laser Printed Labels, B&W or Color J-Cards *8X10 Bio Photos, 100 Oty. Duplication Packages B&W/Color *Directories for Major Labels, Publishers, Radio Stations, Media *Artist/Mgr/Producer Contracts, Critique Forms & Post Cards Call Now!......(800) 487-SPIN "Free Catalog" Songwriter Products Ideas & Necessities



REPAIR SERVICE

and Panasonic Specialists.

recorder brands and models.

Compare our rates!

TRAINING / TUTORIALS



World Radio History

San Francisco, CA 94188

ACOUSTICAL PANELS

ALL NEW, MUCH IMPROVED CLEAR-SONIC PANELS



A tough, light weight, and portable <u>solution</u> to your loudness problem! Now more transparent!

NEW LOWER PRICES!

Call for our free brochure!

ACCUSONICS MFG. (800)-888-6360

ACOUSTICAL CONDITIONING

MICRO ROOM Silent Speaker System

Record Guitar, Bass or ANY amplified inst. thru you amplifier SILENTLY. MICRO ROOM's isolated sound chamber contains: Shure SM57, Speaker and Auralex acoustic treatment. Like adding another room to your studio. Contact: Folded Space Technologies 770 427 8288 fspace@mindspring.com



Would you like to learn how to get into the Jingle Business?

I've been doing it for 17 years. My complete Jingle Course shows you exactly how you can do the same. Part-or-full time. Locally-or nationally. CALL NOW! This information will save you years of trial and error. Make the money you want with your music TODAY. If you are already in the Jingle business. Check out our new syndication division. It's changing the industry.

Call 1-800-365-8688 or write to RSM-Direct 4542 E.Tropicana #211 - Las Vegas, NV. 89121 IN A BIG HURRY? Check out our Webb page http://www.jinglebiz.com



ACOUSTICAL FOAM

For over 13 years our acoustic foams & sound barriers have been making rooms sound worldclass at affordable prices. Well, now we've changed our name & branched out with even more cool stuff that'll help you sound better. New items: T'Fusor™ & MiniFusor™ Full Bandwidth Diffusors (you won't believe how good the testing data & prices are!), LENRD™ Bass Traps, U-Boat™ Floor Floaters, Active & Passive Studio Monitors, Mic Windscreens, NS-10M Tweeter Protectors & more. Not only that, our new expanded catalog is packed full of even more great acoustical advice you can't get anywhere else! The catalog & sample kit are FREE, so call us today. Your room & wallet will be very glad you did!

Clients: AT&T, NASA, Sony, General Dynamics, Shure, Warner Bros., 20th CenL Fox, ABC Radio Network, Ensoniq, '96 Democratic Convention, Ford, Hitachi, Dennis DeYoung (Styx), Toshiba, Universal Studios, Maury Povich Show, NPR, Skid Row, Community, US Gov't, Bootsy Collins, Manley Labs, ShowCo, Dick Ervasti (Voice of NFL on Fox), Pat Duke (Voice of McDonalds/Miller Brewing), KC Royals, MTX-Soundcraftsmen, etc...

Auralex (formerly USAFoam) \star 11571 E. 126th Street \star Fishers, IN 46038 Samples & Questions (317) 842-2600 \star (800) 95-WEDGE \star Fax (317) 842-2760

EQUIPMENT FOR SALE



EQUIPMENT DEALERS

SOUND PRODUCTIONS Dallas, Texas

We Sell the MAJOR BRANDS of NEW & USED SOUND EQUIPMENT as Used by TOURING SOUND COMPANIES and LIVE MUSIC VENUES

We Have WHAT YOU WANT at DISCOUNT PRICES

Our SALES ENGINEERS are EXPERIENCED SOUNDMEN and can RELATE TO YOUR NEEDS

If you are a SOUNDMAN, get on our MAILING LIST for your SPECIAL DEALS

Call Today and Find Out Why We Are #1 In Sound System Sales





ODYSSEY PRO SOUND NEW, USED & VINTAGE QUALITY RECORDING EQUIPMENT Competitive Prices Satisfaction guaranteed Consoles*** Tape Machines*** Outboard Microphones***Vintage*** and MORE! We buy, list, and trade quality audio equipment

Tel: (508) 744-2001 Fax: (508) 744-7224 VISA E-Mail: odyssey@pcix.com MC

154 OCTOBER EQ

RECHARGEABLE POWER SUPPLY

PROBLEM SOLUED.



The Pro's agree! Eco Charge rechargeable power sources make even the most demanding recording situations a breeze. The ECS line of rechargeable battery systems is extremely reliable, easy to use, and maintenance-free. Systems are available for all portable



DAT recorders, analog recorders, and portable mixers. Battery/case systems are available in a variety of voltages and sizes and can be custom designed for specific requirements. Make power problems a thing of the past! Call Eco Charge today.

P.O. Box 956 • Boulder, CO 80306 • TEL 303.449.5761 • FAX 303.449.1545 ORDERS 800.361.5666



Visa, MC, Discover & AmEx. "Dealer Inquires Welcome World Radio History

DUPLICATION/REPLICATION SERVICES

CRUCIAL STEPS DUPLICATION *PRESENTS:* **CRUCIAL STEPS FOR THE SUCCESS OF YOUR CD RELEASE**

1. Work with a Reputable Duplication Company

Oasis has several worthy competitors, but not all duplicators are reputable. Things to check:

Financial stability of the company. (Caution: there has been a recent rash of duplicator bankruptcies. Make sure your duplicator won't collapse while it has your masters!)
Is the price too LOW? If a deal seems

too good to be true, it probably is.
Consider the quality of the company's

clientele--does it work with professionals--names you recognize? Ask for references.

• Consider how knowledgeable & helpful the company's staff is on the phone: do they know the music business? Are they interested in your project's potential?

2. Work with a Qualified. Independent Graphic Artist

If you want your product to compete with the major labels, you have to look as good as they do. One-stop "chopshop" duplicators who offer one-sizefits-all graphics aren't going to cut it.

This is your project: you need to sit down and work with your own graphic artist-- face-to-face. Resources for finding good graphic artists in your local area include local ad agencies, fellow musicians, or a free referral from the Oasis graphic artist database. (You can e-mail or call Oasis & we'll locate a good graphic artist for you in or near your hometown.) **3.** Think Backwards--Plan Your Promotion First

What good is a CD release if nobody hears it? Make sure you get your music to radio. Try to get onto a radiooriented sampler CD program, such as the OASISALTERNATIVE[™]. OASISACOUSTIC[™], OASISROCK[™], & OASISJAZZ[™] sampler CDs. which go to every radio station in their genres.

Be sure to also take advantage of the inexpensive promotion and distribution opportunities available on the World Wide Web. You can set up your own Web "homepage," or you may want to consider joining the Oasis-sponsored Musicians on the Internet program, which promotes your CD online & distributes it via the CDnow superstore.

If you are in need of CD & cassette duplication, Oasis offers its assistance: Call (800)697-5734 or e mail to oasiscd@clark.net for more information

> And check out "A Musician's Guide to CD Manufacturing," http://www.oasiscd.com for a more thorough discussion of the topics we've touched on here.



\$1 79 Cassette Copies Includes High Bias Chrome Tape Laser Labels, Norelco Boxes and Duplication. <u>NO JOB TOO SMALL !!</u> Also CD Packages and Recording Supplies — Call (718) 768-4723

Duplication Systems RELIABILITY DURABILITY EASE OF USE

That's what you get with a Marantz duplication system from Full Compass. Marantz has totally integrated real-time analog cassette duplication systems that will be custom designed for you. For complete information and a price that's too low to advertise call Full Compass.



IT PAYS TO ADVERTISE IN EN MAGAZINE

WHITEWATER RECORDING 9 Busbee View Road Ashevills, NC 28803 Retail-Ready Packages! Call brow five 1995-16 calabag 500 CD's B/W \$1389 Full Color \$1669 1000 CD's B/W \$1389 Full Color \$2147 300 TAPES Full Color \$589.00 Real-Time \$759.00 CD packages include mastering, design, film, label, box, & wrap

> *300 CD Special: \$849 *500 CD Special: \$999 *with client provided CD-R or 1630 and artwork. Digital Mastering, CD-Rom & Graphic Design Available

Silicon Graphics Digital Printing Full color inserts from \$275 10 Free Posters w/ complete package Call (800) DIGIDOC

DUPLICATION/REPLICATION SERVICES



156 OCTOBER EQ


DUPLICATION/REPLICATION SERVICES



World Radio History

EQ OCTOBER 157

DUPLICATION/REPLICATION SERVICES



Sponsored by Pro Sound Menus in cooperation with Synergetic Audio Concepts

Live Sound Reinforcement Workshop

The Live Sound Industry's Premier Educational Event! Eighth in a Successful Series



anuary





Where: Chapman University, Orange County, CA When: January 13-15, 1997 (preceding Winter NAMM in CA) Fee: \$695.00 (Includes workshop material and meals)

Back to the Basics



Program Highlights:

High-level presentations on computer control Mixing console fundamentals, including hands-on instruction Increased opportunities to mix a band on multitrack tape Complete sound system set-up, gain structure and equalization The 'business' of live reinforcement business

Workshop Staff:

Albert Lecesse of Audio Analysts Howard Page of Showco David Scheirman of Concert Sound Consultants and IED Mike Whelan of Crown International David Robb of Jaffe Holden Scarbrough

For more information, contact: Synergetic Audio Concepts 8780 Rufing Road, Greenville, IN 47124

🕿 800 796 2831 • Fax: 812 923 3610 • E mail: patb@synaudcon.com • http://www.synaudcon.com

ACROSS THE BOARD

continued from page 162

ed up cutting 18 times. Six that night, eight Wednesday, and four Thursday morning. Thursday afternoon 1 had two studios going at once. We needed to finish up some overdubs and fix some vocals, but if I didn't start mixing, we wouldn't make our deadline of mixed, mastered CDs in L.A. by Monday afternoon. So my assistant (Jason Lavine) worked on the overdubs while I started mixing.

I mixed Thursday, Friday, and Sunday. Don't ask me about Saturday - I can't remember Saturday. I finished mixing the last tune about 10 PM Sunday night, packed up my gear, went home, and started compiling and mastering mixes. I then had to cut six CDs for delivery to John, his manager, and the record company. I finished the last CD at 5 AM, packed my bag, and left at 6 AM to catch my flight to L.A. I dropped the CDs off on time Monday afternoon. We did it. With a lot of team work and little sleep, we pulled off what started out to be an impossible task. I attribute this successful project to all I

have learned by reading my columns in *EQ* magazine.

Attached To Plane Ticket: "NARAS Meeting Tuesday 11:30 AM." | am on the NARAS Technology Planning Committee with guys like Bruce Swedien, Lee Hershberg, Jac Holzman, Murray Allen, Les Paul, and John Eargle. The meeting is about identifying, acquiring, and preserving a definitive collection of recording equipment, technical instruments, and other relevant associated technology used throughout the history of the recording industry. This is going to be a fun project. I want to be the guy who goes up to George Massenburg's house, knocks on the door, and says, "Excuse me, George. NARAS Technology Police. I have a warrant to search your garage for technical artifacts for the NARAS Museum. I'll need to take a few of these GML mic preamps and a couple of these GML limiters if you don't mind. We need them for evidence."

On Bathroom Mirror: "Turn in EQ Column By Friday...Last Friday." Well, because of the time crunch, I didn't get into the bathroom much last week. This is Tuesday morning, I am on my way to the NARAS meeting, and I will let you know next month if I need any equipment out of your garage.

ROOM WITH A VU

continued from page 29

cause we were physically and musically outgrowing everything. I bought more gear and I upgraded from a Mackie 24.8 to a 32•8 - we just needed more room. So I dismantled the whole studio. I rewired the patchbay and spaced everything around. I bought an Argosy desk for the Mackie; you need something to slump over after a 12-hour session and this is great for that! EQUIPMENT NOTES: Shelton continues: My secret weapons are the Mackie Ultramix and the ADL tube compressors. The Ultramix automation is just a dream come true, and Greg Mackie didn't leave anything out on the 32•8 board - it's the best deal on the planet for the money. The ADL compressors makes the mics more open and sweeter; almost any mic l use gets plugged into an ADL. The Cakewalk sequencing program is also something that I could not do without. It's got all the necessary features for sequencing and is easy to learn. And, of course, it's all nondestructive editing, which is very important. The JLCooper MSB REV2 MIDI patchbay lets me fly in any other MIDI gear that I may need for any particular session. EO

COMING UP IN **EQ NOVEMBER**

EQ'S AES SPECTACULAR. It's finally here — the audio industry's show of shows! Get the inside scoop on many of the new products that will keep you drooling throughout the upcoming year. Plus, the tales of Los Angeles's recording history as told by Chris Stone.

EXCLUSIVE: DIGIDESIGN'S PRO TOOLS 4.0 IN REVIEW. Roger Nichols puts the latest version of the hard-disk recording standard to the test — and you'll read it here first.

ON THE ROAD AGAIN. In addition to the latest sound-reinforcement products from the floor of the AES Convention, EQ LIVE presents road stories from Mary Chapin Carpenter's and Dave Matthews current tours.

NEW COLUMNS. Two new columnists have joined Craig Anderton, Martin Polon, Eddie Ciletti, and Roger Nichols. They are legendary keyboardist Al Kooper, who gives his unique views of the audio industry, and musical Web expert Jon Luini, who reveals how to discover and use audio on the internet.

To be a part of this jam-packed issue, contact: Kathleen A. Mackay; Associate Publisher (ext. 460) Matt Charles (ext. 458), Andrea Berrie (ext. 471), Christine Cali (ext. 454), Pete Seidel (ext. 457); Advertising Sales

Tel: 212-378-0400 Fax: 212-378-0484

The IOBE AUDIO ENCINEERING SOCIETY CONVENTION

November 8-11, 1996 Los Angeles, California

fter six years, the Audio Engineering Society Convention returns to Los Angeles! Technology is exploding to keep up with the ever expanding role of audio in all aspects of entertainment and communications. The extensive program of Exhibits, Demonstrations, Workshops, Technical Papers, Tours, and Special Events offered at the AES Convention is your connection to this world of audio - present and future!

and join us in Los Angeles. Don't miss your on-ramp to the next century.



AES

For more information contact: AUDIO ENGINEERING SOCIETY 60 East 42nd Street, New York, NY 10165 U.S.A. Tel: 212-661-8528 0r 800-541-7299 (N. America except NY) Fax: 212-682-0477 e-mail: HQ@aes.org Check out the AES Website: http://www.aes.org

World Radio History


Los Angeles Convention

Center

rttt

Miscellaneous Notes

Straight from my back pocket to the back page of this magazine BY ROGER NICHOLS



n A Gum Wrapper: "Run For President." Campaign promises used to be: "A chicken in every pot and a car in every driveway." As the millennium approaches, we have attained that goal, sort of. There is a Kentucky Fried Chicken on every corner and there is a car in every driveway. The car might not be yours, though. It could be the police or the IRS. For this year, my slogan is going to be: "I promise 3 dB more headroom and a quieter noise floor for everyone." I think that just about sums up what we all need. Write me in and send me all of your campaign contributions.

While I'm at it, I think that everyone should own a computer. You guys are thinking, "I have a computer, so everyone else must have one too." Not quite, CPU breath. I talk to a lot of project studio owners who don't own any computers at all. They insist on going in to the next century completely ignorant of web sites like hotsex.com and whatever else there is.

A Post-It-Note Stuck To Forehead: "Buy More Computers." Computers are getting so inexpensive that they are basically free. I just upgraded an old PC motherboard to something that would do a better job of running Windows for \$30. At Sam's Club I bought a 2.1 GB IDE hard disk for \$239. A hard-disk controller with built-in parallel port and two serial ports was \$49. I bought an 8x CD-ROM drive for \$123. Then I thought, "As long as I have all of this new stuff. I can't put it in the old case," so I picked up a case with a big power supply and tons of space for everything you could imagine for another \$45. And to top it all off, since I basically replaced everything on my old computer, I still have the untouched original (8 MHz 286 that cost \$4000 new). Maybe I should just get it a new motherboard.

The same thing happens in my studio. I keep replacing gear until eventually I have replaced everything in my original studio. This means that I have a complete working studio's worth of gear just sitting in a corner.

On The Refrigerator Door: "Return John Denver's Call." I engineered and produced John Denver records from 1980 until 1990. John then changed record companies a few times and they supplied the producers and engineers, so I was free at last. A couple of weeks ago he called me and said that he needed to cut four or five tunes and remix two previous recordings for an album to be released in Scandinavian countries. The problem was time. He had to start on Tuesday after Labor Day Weekend and be finished by Thursday night. I was supposed to be in Banff, Canada that Tuesday and wouldn't get home until midnight. John said he would send a Lear Jet to get me, but that it would cost \$10,000 that would eat into my piece of the budget. I said I would hitchhike if I had to, but I would get to Nashville by 3 PM so we could cut the tracks in the afternoon and evening. We agreed that it could be done, and the studios and musicians were booked.

The race was on. I had to rent a car

in Banff, get up at 3 AM, drive about 100 miles to Calgary, and change to an early flight back to Nashville. Since American Airlines dissolved its hub operation in Nashville, you can't get there from anywhere, so I had to fly to Dallas and change planes to get to Nashville.

As is usual when you are in a hurry, everything happens to slow you down. The flight from Calgary was late leaving because two trucks ran into each other right behind our plane and we couldn't push back out of the gate until they got all of the pieces cleared out of the way. Then, just as we were about to touch the runway in Dallas, all of a sudden the pilot switched on the power, raised the landing gear and executed a missed approach. The pilot got on the intercom and said that there was another plane still on our runway and there wasn't room for both of us. Good choice. It took 40 minutes for us to go around, get back in line, and finally get on the ground.

Instead of an hour between flights, I now had only eight minutes to get to the other side of the Dallas terminal complex (this should have been an Olympic event). The only reason I made it is because the door was stuck on the flight to Nashville and the maintenance crew was working on it when I got there. They closed the door and we were on our way. The winds were in our favor and we got to Nashville on time, taxied up to the gate, and just sat there. The newly repaired door would not open. It took over an hour for them to fix it so we could get off of the plane.

I got to the studio at 4:30. As I walked in the door, all of the musicians were in position eagerly awaiting my arrival. I had another engineer I work with go in and get everything set up, get cue mixes, and be ready to go when I got there. Sort of "tag-team engineering." I went into the studio and checked some mic positioning, then into the control room, where I scooted up to the SSL 4000G and, "Ah one, ah two, ah one, two, tres, quattro." We were waxing.

This is the good news. As it turned out, John was a little off on the amount of work that needed to be done. We endcontinued on page 160

A Legacy of Great Performance Semnheiser and the Hollywood Bowl

Joseph Magee, a sound designer for the Hollywood Bowl, insists upon the precision German engineering of the MD 421 II. "It's faster, more open and transparent, yet it retains the timbre of the MD 421."

The superb directionality and freedom from distortion to more than 175dB SPL provide the versatility and control to capture every performance. And its renown rugged construction secures your investment. The MD 421 II is built to even closer tolerances to consistently deliver the classic Sennheiser sound.

Contact your dealer for a personal demonstration or call us directly.

er for the Hollywood e records and mixes for film, and in 1995



SENNHEISER ELECTRONIC CORPORATION

6 VISTA DRIVE, P.O. BOX 987, OLD LYME, CT 06371 • TEL: 860-434-9190 FAX: 860-434-1759 • CALIFORNIA: 4116 WEST MAGNOLIA BLVD., SUITE 100, BURBANK, CA 91505 • TEL: 818-845-7366 FAX: 818-845-7140 MEXICO: PALENQUE NO. 663, COL. NARVARTE, 03600 MEXICO, D.F. MEXICO - TEL: 525-605-7686 FAX: 525-605-6473 - CANADA: 221 LABROSSE AVE., PTE-CLAIRE, PQ H9R 1A3 - TEL: 514-426-3013 FAX: 514-426-3953 World Wide Web: http://www.sennheiserusa.com

Manufacturing Plant: Am Labor 1, 30900 Wedemark, Germany

CIRCLE 73 ON FREE INFO CARD

Two built-in amplifiers-one for the woofer and one for the tweeter. The result-while the bass is pouncing, the high frequencies and vocals are crisp and clear.

Passive crossovers waste as much as half of the amplifier power by generating heat. EON Powerec Speakers have built-in active crossovers that use the amplifier power to produce more of what you want-SOUND.

Heat is the #1 enemy of loudspeakers. EON has a die-cast aluminum baffle that absorbs heat away from the woofer and amps and quickly dissipates it to keep them running cool. The more you crank it, the better the system works.

The highly durable and versatile EON polypropylene enclosure allows the speaker to stand upright, tilt back for stage monitor use, hang on a wall or mount on a tripod speaker stand.

EON's flattened voice coil wire allows for 22% more wire in the magnetic gap than most speakers using round wire. More wire = higher efficiency = plays louder.

Patented Differential Drive™ results in a woofer that weighs less than 3 lbs, yet plays louder than similar woofers weighing in at more than 16 lbs! More power, more punch less weight

EON

SOUND

ТНАТ

Need more? Every EON Powered Speaker has features such as an XLR input for easy connection...a peak indicator that alerts the operator before a problem starts...a button that gives you instant PA when you plug in your microphone...a daisy chain output jack that gives your sound system room to grow...and an ergonomic carrying handle mounted at the center of gravity.

JBL Professional's low mass titanium diaphragm provides extended high frequency for sharper transients. Lighter mass = higher efficiency = You can play louder.

> New, low-distortion Bi-Radial[®] horn provides smooth high frequency coverage so you'll sound as good in the cheap seats as you do up front.

Built-in thermal protection. If the amplifiers overheat, they shut themselves off before any damage can be done-and we guarantee it!

Aluminum fins cast into the ports provide active cooling to the whole system. The louder you play, the more it cools!!

EON woofer cones are computer-designed using Finite Element Analysis techniques to develop a lightweight cone without sacrificing strength.

Neodymium magnets are ten times lighter yet yield the same strength as the conventional ferrite magnets used by our competitors.

Tcrroidal transformer powers the amplifiers without adding excessive weight. EON Powered Speakers - the lightest in their class.

THE MOST INPORTANT THING TO LOOK FOR



©1996 JBL Professional

A Harman International Company

EVEN AN EON POWERED SPEAKER

CARRIES

CAN'T GET BY ON GOOD LOOKS ALONE.